



STATE OF CONNECTICUT
CONNECTICUT SITING COUNCIL

Ten Franklin Square, New Britain, CT 06051

Phone: (860) 827-2935 Fax: (860) 827-2950

E-Mail: siting.council@ct.gov

Web Site: www.ct.gov/csc

VIA ELECTRONIC MAIL

September 21, 2020

Jennifer Iliades
Site Acquisition Consultant
Centerline Communications LLC
750 West Center Street, Suite 301
West Bridgewater, MA 02379

RE: **EM-CING-104-200814** – New Cingular Wireless PCS, LLC (AT&T) notice of intent to modify an existing telecommunications facility located at 223 Rogers Road, Norwich, Connecticut.

Dear Ms. Iliades:

The Connecticut Siting Council (Council) is in receipt of your correspondence of September 16, 2020 submitted in response to the Council's August 31, 2020 notification of an incomplete request for exempt modification with regard to the above-referenced matter.

The submission renders the request for exempt modification complete and the Council will process the request in accordance with the Federal Communications Commission 60-day timeframe.

Thank you for your attention and cooperation.

Sincerely,

s/ Melanie A. Bachman

Melanie A. Bachman
Executive Director

MAB/IN/emr

September 16, 2020

Melanie A. Bachman
Executive Director
Connecticut Siting Council
10 Franklin Square
New Britain, CT 06051

Regarding: EM-CING-104-200814 Notice of Incompletion
Address: Notice of Intent to Modify an Existing Telecommunications Facility at 223
Rogers Road, Norwich, CT (AT&T Site #: CT2028)

Dear Ms. Bachman:

Pursuant to your correspondence dated August 31, 2020, your staff had identified deficiencies in the radio frequency emissions report and proof of proper notice to the underlying property owner. Accordingly, enclosed herewith please find both the revised report and delivery confirmation per your request.

Please do not hesitate to contact me should you have any questions, concerns or require additional information. Thank you for your assistance to this matter.

Sincerely,



Jennifer Iliades
Site Acquisition Consultant
Centerline Communications, LLC
750 West Center Street, Suite 301
West Bridgewater, MA 02379
jiliades@clinellc.com

Enclosures



STATE OF CONNECTICUT
CONNECTICUT SITING COUNCIL

Ten Franklin Square, New Britain, CT 06051

Phone: (860) 827-2935 Fax: (860) 827-2950

E-Mail: siting.council@ct.gov

Web Site: portal.ct.gov/csc

VIA ELECTRONIC MAIL

August 31, 2020

Jennifer Iliades
Site Acquisition Consultant
Centerline Communications LLC
750 West Center Street, Suite 301
West Bridgewater, MA 02379

RE: **EM-CING-104-200814** – New Cingular Wireless PCS, LLC (AT&T) notice of intent to modify an existing telecommunications facility located at 223 Rogers Road, Norwich, Connecticut.

Dear Ms. Iliades:

The Connecticut Siting Council (Council) received a notice of intent to modify the above-referenced facility on August 14, 2020.

According to Section 16-50j-71 of the Regulations of Connecticut State Agencies, "...any modification, as defined in Section 16-50j-2a of the Regulations of Connecticut State Agencies, to an existing tower site, except as specified in Sections 16-50j-72 and 16-50j-88 of the Regulations of Connecticut State Agencies, may have a substantial adverse environmental effect."

Staff has reviewed this exempt modification request for completeness and has identified a deficiency in the request. The radio frequency emissions report dated July 17, 2020 and provided with the request does not include certain required values used in calculating the maximum permissible exposure in accordance with the standards adopted by the Federal Communications Commission (FCC) pursuant to Section 704 of the Telecommunications Act of 1996, as amended, and the State Department of Energy and Environmental Protection, pursuant to Section 22a-162 of the Connecticut General Statutes. The missing values include:

1. Effective Radiated Power; and
2. Number of channels being used by the proposed equipment.

Also, the above referenced request for exempt modification lacks proof that the entire request for exempt modification was physically mailed to the underlying property owner listed on the property card as Michael J. Coleman Trust.

Therefore, the exempt modification request is incomplete at this time. The Council recommends that Centerline Communications provide a radio frequency emissions report that includes the above referenced information for the proposed modification and proof of proper notice of this exempt modification request to the underlying property owner, on or before September 30, 2020. If additional time is needed to gather the requested information, please submit a written request for an extension of time prior to September 28, 2020. **Please provide an electronic version of the requested information for the incomplete exempt modification to be rendered complete and processed. Please include the Council's exempt modification identification number referenced above with the submittal.**

This notice of incompleteness shall have the effect of tolling the FCC 60-day timeframe in accordance with Paragraph 217 of the FCC Wireless Infrastructure Report and Order issued on October 21, 2014 (FCC 14-153).

Thank you for your attention to this matter. Should you have any questions, please feel free to contact me at 860-827-2951.

Sincerely,

s/Melanie Bachman

Melanie Bachman
Executive Director

MAB/IN/emr



**Lawrence Behr
Associates** INC
www.lbagroup.com

Radio Frequency Emissions Report

SITE NAME:

302493 Nrwc-Norwich

LOCATION:

Norwich, Connecticut

COMPANY:

**American Tower Corporation
Woburn, Massachusetts**

September 14th, 2020

Contents

DISCLAIMER NOTICE	2
INTRODUCTION	3
SITE AND FACILITY CONSIDERATIONS.....	3
POWER DENSITY CALCULATIONS.....	4
APPENDIX 1 LOAD LIST.....	4
APPENDIX 2 AT&T CHANNELS USED.....	5
APPENDIX 3 AT&T ANTENNA INFORMATION	6
APPENDIX 4 FCC OET-65 MPE LIMIT STUDY.....	7
APPENDIX 5 SUMMARY OF POWER DENSITY	8
APPENDIX 6 INFORMATION PERTAINING TO MPE STUDIES.....	9
APPENDIX 7 MPE STANDARDS METHODOLOGY	11



DISCLAIMER NOTICE

This work is based upon our best interpretation of available information. However, these data and their interpretation are constantly changing. Therefore, we do not warrant that any undertaking based on this report will be successful, or that others will not require further research or actions in support of this proposal or future undertaking. In the event of errors, our liability is strictly limited to replacement of this document with a corrected one. Liability for consequential damages is specifically disclaimed. Any use of this document constitutes an agreement to hold Lawrence Behr Associates, Inc. and its employees harmless and indemnify it for any and all liability, claims, demands, and litigation expenses and attorney's fees arising out of such use.

Work product documents released prior to account settlement remain the sole property of Lawrence Behr Associates, Inc. and must be returned on demand. Underlying work notes and data relating to this document remain the property of Lawrence Behr Associates, Inc. This document shall not be reproduced in whole or part without permission of Lawrence Behr Associates, Inc. Any dispute hereunder shall be adjudicated in North Carolina. Any use or retention of this document constitutes acceptance of these terms, the entire work product, and all charges associated therewith.

COPYRIGHT © 2020 BY
LAWRENCE BEHR ASSOCIATES, INC.
GREENVILLE, NORTH CAROLINA

RADIO FREQUENCY EMISSIONS REPORT

302493 Nrwc-Norwich

Norwich, Connecticut

INTRODUCTION

Lawrence Behr Associates, Inc. (LBA) has been retained by American Tower Corporation (ATC) of Woburn, Massachusetts to evaluate the RF emissions of an existing tower at this location. AT&T is adding emitters to this site and the purpose of this study is to determine if, after the addition of the AT&T emitters, the site is in Compliance with FCC Regulations. This study determined that THIS SITE IS IN COMPLIANCE with Federal Regulations.

Details regarding the FCC Rules and the methodology used to determine compliance may be seen below.

SITE AND FACILITY CONSIDERATIONS

Site 302493 Nrwc-Norwich is located at 225 Rogers Road in Norwich, Connecticut at coordinates 41.53366, -72.135. The support structure is a 155' monopole.

All data used in this study was provided by one or more of the following sources:

1. ATC furnished data
2. Compiled from carrier and manufacturer standard configurations
3. Empirical data collected by LBA

AT&T proposes to add antennas to the tower at the 156' level. The structure already supports several antennas, but only AT&T has transmit antennas. This study considers the AT&T facility in detail.


The load list may be seen in Appendix 1. Appendix 2 contains the AT&T channel counts, frequency bands, and power levels. AT&T Antenna information may be seen in Appendix 3.

POWER DENSITY CALCULATIONS

Based upon the provided information and the FCC limits for exposure as outlined in 47 CFR 1.1307(b)(1) - (b)(3), the power levels and percentages of the FCC's allowable general population limit are shown in Appendix 4. Calculations were done at industry standard average head height of six feet above ground level.

A summary of the power density from all emitters may be seen in Appendix 5.

These limits are based upon the Information Relating to MPE Standards found in Appendix 6. Study methodology may be seen in Appendix 7, which describes the Non-Ionizing Radiation Prediction Models. Approximate radiation patterns may be found in Appendix 5. This site ***IS*** in compliance with FCC OET-65 MPE limits.



September 14th, 2020

Kathryn G. Tesh
Wireless Services Manager



APPENDIX 1 *Load List*

Proposed	Customer	RAD Height (ft)	Equipment Quantity	Equipment Type	Manufacturer	Model Number	Line Quantity	Line size	Mount Type	Azimuths	TX Frequency	RX Frequency
Yes	AT&T MOBILITY	156	1	PANEL	CCI	OPA65R-BU4DA-K			Platform with Handrails	0	1745-1755, 1770-1780, 1850-1865, 1885-1910, 704-716, 758-763, 824-845, 869-890	1930-1945, 1965-1990, 2145-2155, 2170-2180, 728-746, 788-793, 845-849-890, 890-894
Yes	AT&T MOBILITY	156	2	PANEL	CCI	OPA65R-BU8D			Platform with Handrails	0/115	1745-1755, 1770-1780, 1850-1865, 1885-1910, 704-716, 758-763, 824-845, 869-890	1930-1945, 1965-1990, 2145-2155, 2170-2180, 728-746, 788-793, 845-849-890, 890-894
Yes	AT&T MOBILITY	156	3	PANEL	Powerwave Allgon	7770.00	12	1 1/4" Coax	Platform with Handrails	23/143/263	1930-1935, 1945-1950, 1965-1970, 1982-1990, 891-894	1930-1945, 1965-1990, 2145-2155, 1982-1990, 891-894
Yes	AT&T MOBILITY	156	2	PANEL	CCI	DMP65R-BU8D			Platform with Handrails	0/115	1745-1755, 1770-1780, 1850-1865, 1885-1910, 704-716, 758-763, 824-845, 869-890	1930-1945, 1965-1990, 2145-2155, 2170-2180, 728-746, 788-793, 845-849-890, 890-894
Yes	AT&T MOBILITY	156	1	PANEL	CCI	DMP65R-BU4D			Platform with Handrails	0	1745-1755, 1770-1780, 1850-1865, 1885-1910, 704-716, 758-763, 824-845, 869-890	1930-1945, 1965-1990, 2145-2155, 2170-2180, 728-746, 788-793, 845-849-890, 890-894
No	AT&T MOBILITY	156	6	PANEL	Powerwave Allgon	7770.00	12	1 1/4" Coax	Platform with Handrails	23/143/263	1930-1935, 1945-1950, 1965-1970, 1982-1990, 891-894	1930-1935, 1945-1950, 1965-1970, 1982-1990, 891-894
No	AT&T MOBILITY	156	1	PANEL	Andrew	SBNHH-1D65A (33.5 lbs)			Platform with Handrails	0	1900, 700	19002100, 700
No	AT&T MOBILITY	156	2	PANEL	CCI	HPA-65R-BU-U-H8			Platform with Handrails	115/235	1900, 700	19002100, 700
No	T-MOBILE	143	3	PANEL	Ericsson	AIR 21, 1.3M, B4A 82P			T-Arm	40/160/280		
No	T-MOBILE	143	3	PANEL	Ericsson	AIR 21, 1.3 M, B2A B4P			T-Arm	40/160/280		

APPENDIX 2

AT&T Channels Used

Antenna	Technology	Frequency Band	Channel Count	Transmitter Power per Channel (W)
AT&T A1	LTE	1700	1	40
AT&T A2	LTE	1700	1	40
AT&T A3	LTE	1800	1	40
AT&T A4	LTE	1900	1	40
AT&T A5	LTE	700	1	40
AT&T A6	LTE	700	1	40
AT&T A7	UMTS	850	1	40
AT&T A8	UMTS	850	1	40
AT&T A9	LTE	1700	1	40
AT&T A10	LTE	1700	1	40
AT&T A11	LTE	1800	1	40
AT&T A12	LTE	1900	1	40
AT&T A13	LTE	700	1	40
AT&T A14	LTE	700	1	40
AT&T A15	UMTS	850	1	40
AT&T A16	UMTS	850	1	40
AT&T A17	LTE	1900	1	40
AT&T A18	LTE	1900	1	40
AT&T A19	LTE	1900	1	40
AT&T A20	LTE	1900	1	40
AT&T A21	UMTS	850	1	40
AT&T A22	LTE	1700	1	40
AT&T A23	LTE	1700	1	40
AT&T A24	LTE	1800	1	40
AT&T A25	LTE	1900	1	40
AT&T A26	LTE	700	1	40
AT&T A27	LTE	700	1	40
AT&T A28	UMTS	850	1	40
AT&T A29	UMTS	850	1	40
AT&T A30	LTE	1700	1	40
AT&T A31	LTE	1700	1	40
AT&T A32	LTE	1800	1	40
AT&T A33	LTE	1900	1	40
AT&T A34	LTE	700	1	40
AT&T A35	LTE	700	1	40
AT&T A36	UMTS	850	1	40
AT&T A37	UMTS	850	1	40
AT&T A38	LTE	1900	1	40
AT&T A39	LTE	1900	1	40
AT&T A40	LTE	1900	1	40
AT&T A41	UMTS	850	1	40
AT&T A42	UMTS	850	1	40
AT&T A43	LTE	1900	1	40
AT&T A44	LTE	700	1	40
AT&T B1	LTE	1900	1	40
AT&T B2	LTE	700	1	40
AT&T B3	LTE	1700	1	40
AT&T B4	LTE	1700	1	40
AT&T B5	LTE	1800	1	40
AT&T B6	LTE	1900	1	40
AT&T B7	LTE	700	1	40
AT&T B8	LTE	700	1	40
AT&T B9	UMTS	850	1	40
AT&T B10	UMTS	850	1	40
AT&T B11	LTE	1900	1	40
AT&T B12	LTE	1900	1	40
AT&T B13	LTE	1900	1	40
AT&T B14	LTE	1900	1	40
AT&T B15	UMTS	850	1	40
AT&T B16	LTE	1700	1	40
AT&T B17	LTE	1700	1	40
AT&T B18	LTE	1800	1	40
AT&T B19	LTE	1900	1	40
AT&T B20	LTE	700	1	40
AT&T B21	LTE	700	1	40
AT&T B22	UMTS	850	1	40
AT&T B23	UMTS	850	1	40
AT&T B24	LTE	1900	1	40
AT&T B25	LTE	1900	1	40
AT&T B26	LTE	1900	1	40
AT&T B27	UMTS	850	1	40
AT&T B28	UMTS	850	1	40
AT&T C1	LTE	1900	1	40
AT&T C2	LTE	1900	1	40
AT&T C3	LTE	1900	1	40
AT&T C4	LTE	1900	1	40
AT&T C5	UMTS	850	1	40
AT&T C6	LTE	1900	1	40
AT&T C7	LTE	1900	1	40
AT&T C8	LTE	1900	1	40
AT&T C9	UMTS	850	1	40
AT&T C10	UMTS	850	1	40
AT&T C11	LTE	1900	1	40
AT&T C12	LTE	700	1	40

APPENDIX 3

AT&T Antenna Information

Sector	Antenna Number	Antenna Make / Model	Antenna Centerline (ft)
A	AT&T A1	CCI OPA65R-BU4DA-K	156
A	AT&T A2	CCI OPA65R-BU4DA-K	156
A	AT&T A3	CCI OPA65R-BU4DA-K	156
A	AT&T A4	CCI OPA65R-BU4DA-K	156
A	AT&T A5	CCI OPA65R-BU4DA-K	156
A	AT&T A6	CCI OPA65R-BU4DA-K	156
A	AT&T A7	CCI OPA65R-BU4DA-K	156
A	AT&T A8	CCI OPA65R-BU4DA-K	156
A	AT&T A9	CCI OPA65R-BU8D	156
A	AT&T A10	CCI OPA65R-BU8D	156
A	AT&T A11	CCI OPA65R-BU8D	156
A	AT&T A12	CCI OPA65R-BU8D	156
A	AT&T A13	CCI OPA65R-BU8D	156
A	AT&T A14	CCI OPA65R-BU8D	156
A	AT&T A15	CCI OPA65R-BU8D	156
A	AT&T A16	CCI OPA65R-BU8D	156
A	AT&T A17	Powerwave Allgon 7770.00	156
A	AT&T A18	Powerwave Allgon 7770.00	156
A	AT&T A19	Powerwave Allgon 7770.00	156
A	AT&T A20	Powerwave Allgon 7770.00	156
A	AT&T A21	Powerwave Allgon 7770.00	156
A	AT&T A22	CCI DMP65R-BU8D	156
A	AT&T A23	CCI DMP65R-BU8D	156
A	AT&T A24	CCI DMP65R-BU8D	156
A	AT&T A25	CCI DMP65R-BU8D	156
A	AT&T A26	CCI DMP65R-BU8D	156
A	AT&T A27	CCI DMP65R-BU8D	156
A	AT&T A28	CCI DMP65R-BU8D	156
A	AT&T A29	CCI DMP65R-BU8D	156
A	AT&T A30	CCI DMP65R-BU4D	156
A	AT&T A31	CCI DMP65R-BU4D	156
A	AT&T A32	CCI DMP65R-BU4D	156
A	AT&T A33	CCI DMP65R-BU4D	156
A	AT&T A34	CCI DMP65R-BU4D	156
A	AT&T A35	CCI DMP65R-BU4D	156
A	AT&T A36	CCI DMP65R-BU4D	156
A	AT&T A37	CCI DMP65R-BU4D	156
A	AT&T A38	Powerwave Allgon 7770.00	156
A	AT&T A39	Powerwave Allgon 7770.00	156
A	AT&T A40	Powerwave Allgon 7770.00	156
A	AT&T A41	Powerwave Allgon 7770.00	156
A	AT&T A42	Powerwave Allgon 7770.00	156
A	AT&T A43	Andrew SBNHH-1D65A	156
A	AT&T A44	Andrew SBNHH-1D65A	156
B	AT&T B1	CCI HPA-65R-BUU-H8	156
B	AT&T B2	CCI HPA-65R-BUU-H8	156
B	AT&T B3	CCI OPA65R-BU8D	156
B	AT&T B4	CCI OPA65R-BU8D	156
B	AT&T B5	CCI OPA65R-BU8D	156
B	AT&T B6	CCI OPA65R-BU8D	156
B	AT&T B7	CCI OPA65R-BU8D	156
B	AT&T B8	CCI OPA65R-BU8D	156
B	AT&T B9	CCI OPA65R-BU8D	156
B	AT&T B10	CCI OPA65R-BU8D	156
B	AT&T B11	Powerwave Allgon 7770.00	156
B	AT&T B12	Powerwave Allgon 7770.00	156
B	AT&T B13	Powerwave Allgon 7770.00	156
B	AT&T B14	Powerwave Allgon 7770.00	156
B	AT&T B15	Powerwave Allgon 7770.00	156
B	AT&T B16	CCI DMP65R-BU8D	156
B	AT&T B17	CCI DMP65R-BU8D	156
B	AT&T B18	CCI DMP65R-BU8D	156
B	AT&T B19	CCI DMP65R-BU8D	156
B	AT&T B20	CCI DMP65R-BU8D	156
B	AT&T B21	CCI DMP65R-BU8D	156
B	AT&T B22	CCI DMP65R-BU8D	156
B	AT&T B23	CCI DMP65R-BU8D	156
B	AT&T B24	Powerwave Allgon 7770.00	156
B	AT&T B25	Powerwave Allgon 7770.00	156
B	AT&T B26	Powerwave Allgon 7770.00	156
B	AT&T B27	Powerwave Allgon 7770.00	156
B	AT&T B28	Powerwave Allgon 7770.00	156
C	AT&T C1	Powerwave Allgon 7770.00	156
C	AT&T C2	Powerwave Allgon 7770.00	156
C	AT&T C3	Powerwave Allgon 7770.00	156
C	AT&T C4	Powerwave Allgon 7770.00	156
C	AT&T C5	Powerwave Allgon 7770.00	156
C	AT&T C6	Powerwave Allgon 7770.00	156
C	AT&T C7	Powerwave Allgon 7770.00	156
C	AT&T C8	Powerwave Allgon 7770.00	156
C	AT&T C9	Powerwave Allgon 7770.00	156
C	AT&T C10	Powerwave Allgon 7770.00	156
C	AT&T C11	CCI HPA-65R-BUU-H8	156
C	AT&T C12	CCI HPA-65R-BUU-H8	156

APPENDIX 4

FCC OET-65 MPE Limit Study

Antenna ID	Antenna Make / Model	Frequency Band	Antenna Gain (dBd)	Antenna Height (ft)	Channel Count	TX Power (W)	ERP (W) (All Channels)	Total Power Density (µW/cm²)	Allowable Public MPE (µW/cm²)	Public MPE%
AT&T A1	CCI OPA65R-BU4DA-K	1700	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T A2	CCI OPA65R-BU4DA-K	1700	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T A3	CCI OPA65R-BU4DA-K	1800	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T A4	CCI OPA65R-BU4DA-K	1900	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T A5	CCI OPA65R-BU4DA-K	700	12.15	156	1	40	1076.61	0.0633167	466.67	0.013568%
AT&T A6	CCI OPA65R-BU4DA-K	700	12.15	156	1	40	1076.61	0.0633167	466.67	0.013568%
AT&T A7	CCI OPA65R-BU4DA-K	850	13.05	156	1	40	1324.52	0.1017268	566.67	0.017952%
AT&T A8	CCI OPA65R-BU4DA-K	850	13.05	156	1	40	1324.52	0.1017268	566.67	0.017952%
AT&T A9	CCI OPA65R-BUSD	1700	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T A10	CCI OPA65R-BUSD	1700	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T A11	CCI OPA65R-BUSD	1800	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T A12	CCI OPA65R-BUSD	1900	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T A13	CCI OPA65R-BUSD	700	12.15	156	1	40	1076.61	0.0633167	466.67	0.013568%
AT&T A14	CCI OPA65R-BUSD	700	12.15	156	1	40	1076.61	0.0633167	466.67	0.013568%
AT&T A15	CCI OPA65R-BUSD	850	13.05	156	1	40	1324.52	0.1017268	566.67	0.017952%
AT&T A16	CCI OPA65R-BUSD	850	13.05	156	1	40	1324.52	0.1017268	566.67	0.017952%
AT&T A17	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T A18	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T A19	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T A20	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T A21	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T A22	CCI DMP65R-BUSD	1700	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T A23	CCI DMP65R-BUSD	1700	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T A24	CCI DMP65R-BUSD	1800	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T A25	CCI DMP65R-BUSD	1900	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T A26	CCI DMP65R-BUSD	700	11.85	156	1	40	1004.75	0.1801904	466.67	0.038612%
AT&T A27	CCI DMP65R-BUSD	700	11.85	156	1	40	1004.75	0.1801904	466.67	0.038612%
AT&T A28	CCI DMP65R-BUSD	850	12.45	156	1	40	1153.61	0.0678451	566.67	0.011973%
AT&T A29	CCI DMP65R-BUSD	850	12.45	156	1	40	1153.61	0.0678451	566.67	0.011973%
AT&T A30	CCI DMP65R-BU4D	1700	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T A31	CCI DMP65R-BU4D	1700	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T A32	CCI DMP65R-BU4D	1800	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T A33	CCI DMP65R-BU4D	1900	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T A34	CCI DMP65R-BU4D	700	11.85	156	1	40	1004.75	0.1801904	466.67	0.038612%
AT&T A35	CCI DMP65R-BU4D	700	11.85	156	1	40	1004.75	0.1801904	466.67	0.038612%
AT&T A36	CCI DMP65R-BU4D	850	12.45	156	1	40	1153.61	0.0678451	566.67	0.011973%
AT&T A37	CCI DMP65R-BU4D	850	12.45	156	1	40	1153.61	0.0678451	566.67	0.011973%
AT&T A38	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T A39	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T A40	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T A41	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T A42	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T A43	Andrew SBHHH-1D65A	1900	15.85	156	1	40	2523.83	0.175288	1000.00	0.017529%
AT&T A44	Andrew SBHHH-1D65A	700	13.65	156	1	40	1520.76	0.4129171	466.67	0.088482%
AT&T B1	CCI HPA-65R-BUU-H8	1900	14.75	156	1	40	1959.12	1.633286	1000.00	0.163329%
AT&T B2	CCI HPA-65R-BUU-H8	700	11.95	156	1	40	1028.16	0.060467	466.67	0.012957%
AT&T B3	CCI OPA65R-BUSD	1700	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T B4	CCI OPA65R-BUSD	1700	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T B5	CCI OPA65R-BUSD	1800	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T B6	CCI OPA65R-BUSD	1900	15.95	156	1	40	2582.62	0.179371	1000.00	0.017937%
AT&T B7	CCI OPA65R-BUSD	700	12.15	156	1	40	1076.61	0.0633167	466.67	0.013568%
AT&T B8	CCI OPA65R-BUSD	700	12.15	156	1	40	1076.61	0.0633167	466.67	0.013568%
AT&T B9	CCI OPA65R-BUSD	850	13.05	156	1	40	1324.52	0.1017268	566.67	0.017952%
AT&T B10	CCI OPA65R-BUSD	850	13.05	156	1	40	1324.52	0.1017268	566.67	0.017952%
AT&T B11	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T B12	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T B13	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T B14	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T B15	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T B16	CCI DMP65R-BUSD	1700	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T B17	CCI DMP65R-BUSD	1700	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T B18	CCI DMP65R-BUSD	1800	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T B19	CCI DMP65R-BUSD	1900	15.55	156	1	40	2355.37	1.1022503	1000.00	0.110225%
AT&T B20	CCI DMP65R-BUSD	700	11.85	156	1	40	1004.75	0.1801904	466.67	0.038612%
AT&T B21	CCI DMP65R-BUSD	700	11.85	156	1	40	1004.75	0.1801904	466.67	0.038612%
AT&T B22	CCI DMP65R-BUSD	850	12.45	156	1	40	1153.61	0.0678451	566.67	0.011973%
AT&T B23	CCI DMP65R-BUSD	850	12.45	156	1	40	1153.61	0.0678451	566.67	0.011973%
AT&T B24	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.0235014	1000.00	0.002350%
AT&T B25	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.0235014	1000.00	0.002350%
AT&T B26	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.0235014	1000.00	0.002350%
AT&T B27	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T B28	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T C1	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T C2	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T C3	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T C4	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.6961633	1000.00	0.069616%
AT&T C5	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T C6	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.0235014	1000.00	0.002350%
AT&T C7	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.0235014	1000.00	0.002350%
AT&T C8	Powerwave Alligon 7700.00	1900	13.35	156	1	40	1419.25	0.0235014	1000.00	0.002350%
AT&T C9	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T C10	Powerwave Alligon 7700.00	850	11.45	156	1	40	916.35	0.1643356	566.67	0.029000%
AT&T C11	CCI HPA-65R-BUU-H8	1900	14.75	156	1	40	1959.12	1.633286	1000.00	0.163329%
AT&T C12	CCI HPA-65R-BUU-H8	700	11.95	156	1	40	1028.16	0.060467	466.67	0.012957%
AT&T All Sectors									Total:	3.8085%

APPENDIX 5

Summary of Power Density

Carriers	Power Density Value (% of General Population)
AT&T All Sectors:	3.8085%
Other Carriers:	0.0000%
Site Total:	3.8085%
Site Compliance Status:	Compliant



APPENDIX 6

Information Pertaining to MPE Studies

In 1985, the FCC first adopted guidelines to be used for evaluating human exposure to RF emissions. The FCC revised and updated these guidelines on August 1, 1996, as a result of a rule-making proceeding initiated in 1993. The new guidelines incorporate limits for Maximum Permissible Exposure (MPE) in terms of electric and magnetic field strength and power density for transmitters operating at frequencies between 300 kHz and 100 GHz.

The FCC's MPE limits are based on exposure limits recommended by the National Council on Radiation Protection and Measurements (NCRP) and, over a wide range of frequencies, the exposure limits were developed by the Institute of Electrical and Electronics Engineers, Inc., (IEEE) and adopted by the American National Standards Institute (ANSI) to replace the 1982 ANSI guidelines. Limits for localized absorption are based on recommendations of both ANSI/IEEE and NCRP.

The FCC's limits, and the NCRP and ANSI/IEEE limits on which they are based, are derived from exposure criteria quantified in terms of specific absorption rate (SAR). The basis for these limits is a whole-body averaged SAR threshold level of 4 watts per kilogram (4 W/kg), as averaged over the entire mass of the body, above which expert organizations have determined that potentially hazardous exposures may occur. The MPE limits are derived by incorporating safety factors that lead, in some cases, to limits that are more conservative than the limits originally adopted by the FCC in 1985. Where more conservative limits exist, they do not arise from a fundamental change in the RF safety criteria for whole-body averaged SAR, but from a precautionary desire to protect subgroups of the general population who, potentially, may be more at risk.

The FCC exposure limits are also based on data showing that the human body absorbs RF energy at some frequencies more efficiently than at others. The most restrictive limits occur in the frequency range of 30-300 MHz where whole-body absorption of RF energy by human beings is most efficient. At other frequencies, whole-body absorption is less efficient, and consequently, the MPE limits are less restrictive.

MPE limits are defined in terms of power density (units of milliwatts per centimeter squared: mW/cm²), electric field strength (units of volts per meter: V/m) and magnetic field strength (units of amperes per meter: A/m). The far-field of a transmitting antenna is where the electric field vector (E), the

magnetic field vector (H), and the direction of propagation can be considered to be all mutually orthogonal ("plane-wave" conditions).

The FCC guidelines define two separate tiers of exposure limits. As defined by the FCC, these limits are:

Occupational/controlled exposure limits apply to situations in which persons are exposed as a consequence of their employment and in which those persons who are exposed have been made fully aware of the potential for exposure and can exercise control over their exposure. Occupational/controlled exposure limits also apply where exposure is of a transient nature as a result of incidental passage through a location where exposure levels may be above general population/uncontrolled limits (see below), as long as the exposed person has been made fully aware of the potential for exposure and can exercise control over his or her exposure by leaving the area or by some other appropriate means.

General population/uncontrolled exposure limits apply to situations in which the general public may be exposed or in which persons who are exposed as a consequence of their employment may not be made fully aware of the potential for exposure or cannot exercise control over their exposure. Therefore, members of the general public would always be considered under this category when exposure is not employment-related, for example, in the case of a telecommunications tower that exposes persons in a nearby residential area. Additional details can be found in FCC OET 65.

For the purposes of this study, only General population/uncontrolled exposure limits were studied.

APPENDIX 7

MPE Standards Methodology

This study predicts RF field strength and power density levels that emanate from communications system antennae. It considers all transmitter power levels (less filter and line losses) delivered to each active transmitting antenna at the communications site. Calculations are performed to determine power density and MPE levels for each antenna as well as composite levels from all antennas. The calculated levels are based on where a human (Observer) would be standing at various locations at the site. The point of interest where the MPE level is predicted is based on the height of the Observer.

Compliance with the FCC limits on RF emissions are determined by spatially averaging a person's exposure over the projected area of an adult human body, that is approximately six-feet or two-meters, as defined in the ANSI/IEEE C95.1 standard. The MPE limits are specified as time-averaged exposure limits. This means that exposure is averaged over an identifiable time interval. It is 30 minutes for the general population/uncontrolled RF environment and 6 minutes for the occupational/controlled RF environment. However, in the case of the general public, time averaging should not be applied because the general public is typically not aware of RF exposure and they do not have control of their exposure time. Therefore, it should be assumed that any RF exposure to the general public will be continuous.

The FCC's limits for exposure at different frequencies are shown in the following Tables.

Limits for Occupational/Controlled Exposure				
Frequency Range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm ²)	Averaging Time E ² , H ² or S (minutes)
0.3 - 3.0	614	1.63	100*	6
3.0 - 30	1842/f	4.89/f	900/F ²	6
30 - 300	61.4	0.163	1.0	6
300 - 1500	--	--	f/300	6
1500 - 100,000	--	--	5	6



Where:

f = frequency

* = Plane-wave equivalent power density

Occupational/controlled limits apply in situations in which persons are exposed as a consequence of their employment provided those persons are fully aware of the potential for exposure and can exercise control over their exposure. Limits for occupational/controlled exposure also apply in situations when an individual is transient through a location where occupational/controlled limits apply provided he or she is made aware of the potential for exposure.

Limits for General Population/Uncontrolled Exposure				
Frequency Range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm ²)	Averaging Time E ² , H ² or S (minutes)
0.3 - 1.34	614	1.63	100*	30
1.34 - 30	824/f	2.19/f	180/F ²	30
30 -300	27.5	0.073	0.2	30
300 -1500	--	--	f/1500	30
1500 -100,000	--	--	1.0	30

Where:

f = frequency

* = Plane-wave equivalent power density

General population/uncontrolled exposures apply in situations in which the general public may be exposed or in which persons that are exposed as a consequence of their employment may not be fully aware of the potential for exposure or cannot exercise control over their exposure.

It is important to understand that these limits apply cumulatively to all sources of RF emissions affecting a given area. For example, if several different communications system antennas occupy a shared facility such as a tower or rooftop, then the total exposure from all systems at the facility must be within compliance of the FCC guidelines.

The field strength emanating from an antenna can be estimated based on the characteristics of an antenna radiating in free space. There are basically two field areas associated with a radiating antenna. When close to the antenna, the region is known as the Near Field. Within this region, the characteristics of the RF fields are very complex and the wave front is extremely curved. As you move further from the antenna, the wave front has less curvature and becomes planar. The wave front still

has a curvature but it appears to occupy a flat plane in space (plane-wave radiation). This region is known as the Far Field.

Two models are utilized to predict Near and Far field power densities. They are based on the formulae in FCC OET 65. As this study is concerned only with Near Field calculations, we will only describe the model used for this study. For additional details, refer to FCC OET Bulletin 65.

Cylindrical Model (Near Field Predictions)

Spatially averaged plane-wave equivalent power densities parallel to the antenna may be estimated by dividing the antenna input power by the surface area of an imaginary cylinder surrounding the length of the radiating antenna. While the actual power density will vary along the height of the antenna, the average value along its length will closely follow the relation given by the following equation:

$$S = P \div 2\pi RL$$

Where:

S = Power Density

P = Total Power into antenna

R = Distance from the antenna

L = Antenna aperture length

For directional-type antennas, power densities can be estimated by dividing the input power by that portion of a cylindrical surface area corresponding to the angular beam width of the antenna. For example, for the case of a 120-degree azimuthal beam width, the surface area should correspond to 1/3 that of a full cylinder. This would increase the power density near the antenna by a factor of three over that for a purely omni-directional antenna. Mathematically, this can be represented by the following formula:

$$S = (180 / \theta_{BW}) P \div \pi RL$$

Where:

S = Power Density

θ_{BW} = Beam width of antenna in degrees (3 dB half-power point)

P = Total Power into antenna

R = Distance from the antenna

L = Antenna aperture length

If the antenna is a 360-degree omni-directional antenna, this formula would be equivalent to the previous formula.

Spherical Model (Far Field Predictions)

Spatially averaged plane-wave power densities in the Far Field of an antenna may be estimated by considering the additional factors of antenna gain and reflective waves that would contribute to exposure.

The radiation pattern of an antenna has developed in the Far Field region and the power gain needs to be considered in exposure predictions. Also, if the vertical radiation pattern of the antenna is considered, the exposure predictions would most likely be reduced significantly at ground level, resulting in a more realistic estimate of the actual exposure levels.

Additionally, to model a truly "worst case" prediction of exposure levels at or near a surface, such as at ground-level or on a rooftop, reflection off the surface of antenna radiation power can be assumed, resulting in a potential four-fold increase in power density.

These additional factors are considered and the Far Field prediction model is determined by the following equation:

$$S = EIRP \times Rc \div 4\pi R^2$$

Where:

S = Power Density

EIRP = Effective Radiated Power from antenna

Rc = Reflection Coefficient (2.56)

R = Distance from the antenna

The EIRP includes the antenna gain. If the antenna pattern is considered, the antenna gain is relative based on the horizontal and vertical pattern gain values at that particular location in space, on a rooftop or on the ground. However, it is recommended that the antenna radiation pattern characteristics not be considered to provide a conservative "worst case" prediction. This is the equation is utilized for the Far Field exposure predictions herein.

Jennifer Iliades

From: UPS Quantum View <pkginfo@ups.com>
Sent: Thursday, September 3, 2020 10:59 AM
To: Jennifer Iliades
Subject: UPS Delivery Notification, Tracking Number 1Z9Y45030334936216



Hello, your package has been delivered.

Delivery Date: Thursday, 09/03/2020

Delivery Time: 10:57 AM

Left At: FRONT DESK

Signed by: ANCRI

CENTERLINE SITE ACQUISITION

Tracking Number: [1Z9Y45030334936216](#)

Ship To: MICHAEL J. COLEMAN, TRUSTEE
10 PRESIDENTIAL WAY
CRAIG CORBETT, PM, SITE DEVELOPMENT
WOBURN, MA 018011053
US

Number of Packages: 1

UPS Service: UPS Ground

Package Weight: 0.2 LBS

Reference Number: CT2028 - CSC TO PROPERTY OWNER



[Download the UPS mobile app](#)

© 2020 United Parcel Service of America, Inc. UPS, the UPS brandmark, and the color brown are trademarks of United Parcel Service of America, Inc. All rights reserved.

All trademarks, trade names, or service marks that appear in connection with UPS's services are the property of their respective owners.

Please do not reply directly to this email. UPS will not receive any reply message.

[Review the UPS Privacy Notice](#)

[For Questions, Visit Our Help and Support Center](#)