

445 Hamilton Avenue, 14th Floor White Plains, New York 10601 T 914 761 1300 F 914 761 5372 cuddyfeder.com

Lucia Chiocchio lchiocchio@cuddyfeder.com

3/31/20

BY ELECTRONIC MAIL

Melanie A. Bachman Executive Director Connecticut Siting Council 10 Franklin Square New Britain, CT 06051

Re: New Cingular Wireless PCS, LLC ("AT&T")

Notice of Exempt Modification Emergency Back-up Generator

719 George Washington Turnpike, Burlington, CT 06013

Lat.: 41.76681690° Long.: -72.96150690°

Dear Ms. Bachman:

This letter and enclosures are respectfully submitted on behalf of New Cingular Wireless PCS, LLC ("AT&T"). AT&T currently maintains its wireless telecommunications facility at 719 George Washington Turnpike in the Town of Burlington, Connecticut. The Town of Burlington Fire Department is the owner of the underlying property and the tower owner. AT&T submits this letter and enclosures to the Connecticut Siting Council ("Council") to notify the Council of AT&T's intent to perform modifications to the existing facility that do not have substantial adverse environmental effects and thus do not require a certificate pursuant to Section 16-50k of the Connecticut General Statutes.

AT&T intends to install one (1) new Generac 30kW Diesel Generator within the existing grade-level fenced equipment compound as demonstrated on the plans enclosed as Attachment 1. AT&T's existing facility supports its FirstNet program which provides first responders with priority access to AT&T's network to ensure adequate communication capabilities in the event of emergency. AT&T's proposed generator will ensure that critical communication capability for first responders and the public are not lost in the event of a loss of power.

AT&T's proposed generator will also advance the State's goal of natural disaster and emergency preparedness. As discussed in the Council's Docket 432 Findings and Report and Docket 440 proceedings and Findings of Fact (Nos. 76-77), in response to two significant storm events in 2011, the State formed a Two Storm Panel (the "Panel") that evaluated Connecticut's approach to

planning and mitigation of impacts associated with emergencies and natural disasters. The Panel found that "wireless telecommunications service providers were not prepared to serve residential and business customers during a power outage" because certain companies had limited backup generator capacity. The Panel also noted that "[t]he failure of a large portion of Connecticut's telecommunications system during the two storms is a life safety issue." The Panel recommended that State regulatory bodies review "telecommunications services currently in place to verify that the vendors have sufficient generator and backhaul capacity to meet the emergency needs of consumers and businesses" and that the "Connecticut Siting Council should require continuity of service plans for any cellular tower to be erected."2 The planned modifications will ensure continuity of services by reinforcing AT&T's back-up power and backhaul capacity to meet the emergency needs of first responders, consumers and businesses in the event of a power outage.

The planned modifications to the facility fall squarely within the activities explicitly provided for in R.C.S.A. § 16-50j-72(b)(2) as the planned modifications:

- Will not result in an increase in the height of the existing structure;
- Will not require the extension of the site boundary;
- Will not increase noise levels at the facility by more than six decibels or more, or to levels that exceed state or local criteria since emergency backup generators are exempt from noise regulations as "noise created as a result of, or relating to, an emergency";3
- Will not increase radio frequency emission at the facility to a level at or above the Federal Communications Commission safety standards:
- Will not cause a change or alteration in the physical or environmental characteristics of the site; and
- Will not impair the structural integrity of the facility.

This facility was originally approved by the Town of Burlington on August 9, 2005 as illustrated in the decision enclosed as Attachment 2. This modification complies with the conditions of the aforementioned approval. A copy of AT&T's most recent Exempt Modification approval for upgrades to its wireless facility is also included in Attachment 2.

The proposed modifications will have no impact on the existing tower structure itself or the radiofrequency emissions as the proposed modifications only consist of the addition of one new generator within the grade-level fenced equipment compound. Thus, AT&T respectfully requests a waiver from submission of information relating to the existing tower structure or the radiofrequency emissions.

Please accept this letter as notification pursuant to R.C.S.A. § 16-50j-73 for construction that constitutes an exempt modification pursuant to R.C.S.A. § 16-50j-73. In accordance with R.C.S.A. § 16-50j-73, a copy of this letter and enclosure are being sent by email to the Town First Selectman

¹ See Council Administrative Notice Item No. 39

² See Council Administrative Notice Item No. 39.

³ R.C.S.A. § 22a-69-1.8.

Theodore Shafer and the Planning & Zoning Department as well as by first class mail to the property owner and structure owner identified above. Certificate of mailing is enclosed as Attachment 3.

For the foregoing reasons, AT&T respectfully submits that the proposed modification to the above referenced wireless telecommunications facility constitutes an exempt modification under R.C.S.A. § 16-50j-72(b)(2).

Very truly yours,

Lucia Chrocchio

Lucia Chiocchio

Attachments

cc: First Selectman Theodore Shafer - First Selectman, Town of Burlington Jerry Burns, Zoning Enforcement Officer Town of Burlington Fire Department, Property Owner and Tower Owner AT&T

General Dynamics Information Technology Daniel Patrick, Esq. & Julie Durkin, Cuddy & Feder, LLP

ATTACHMENT 1



at&t Mobility

SITE NAME: BURLINGTON FIRE DEPARTMENT FA LOCATION CODE: 10042310

GENERATOR PROJECT 30KW GENERAC DIESEL GENERATOR 200A GENERAC ATS

719 GEORGE WASHINGTON TURNPIKE **BURLINGTON, CT 06013**

VICINITY MAP BURLINGTON Spielman Hwy

SCOPE OF WORK

ADD STANDBY GENERATOR, ASSOCIATED CONCRETE PAD, AND UTILITY EQUIPMENT TO EXISTING AT&T EQUIPMENT AREA. THERE WILL BE NO CHANGE IN THE SIZE OR HEIGHT OF THE TOWER OR ANTENNAS.

TO OBTAIN LOCATION OF PARTICIPANTS' UNDERGROUND FACILITIES BEFORE YOU DIG IN CONNECTICUT

CALL BEFORE YOU DIG 811 OR 1-800-922-4455

CONNECTICUT PUBLIC ACT 87-71 REQUIRES MIN, 2 WORKING DAYS NOTICE BEFORE YOU EXCAVATE.

APPLICABLE BUILDING CODE \$ STANDARDS

ALL WORK AND MATERIALS SHALL BE PERFORMED AND INSTALLED IN ACCORDANCE WITH THE CURREN' EDITION OF THE FOLLOWING CODES AS ADOPTED BY THE GOVERNING LOCAL AUTHORITIES. NOTHING NITHESE PLANS ARE TO BE CONSTRUCTED TO PERMIT WORK NOT CONFORMING TO THESE CODES:

- INTERNATIONAL BUILDING CODE 2015
- . NATIONAL ELECTRIC CODE 2017
- 3. AMERICAN CONCRETE INSTITUTE (ACI) 3 | 8. BUILDING CODE REQUIREMENTS FOR STRUCTURAL
- 4. AMERICAN INSTITUTE OF STEEL CONSTRUCTION (AISC), MANUAL OF STEEL CONSTRUCTION
- . TELECOMMUNICATIONS INDUSTRY ASSOCIATION (TIA) 222-G, STRUCTURAL STANDARDS FOR STEEL OWER AND ANTENNA SUPPORTING STRUCTURES
- . TIA 607, COMMERCIAL BUILDING GROUNDING AND BONDING REQUIREMENTS FOR

AERIAL VIEW OF SITE



PROJECT INFORMATION

PROJECT MANAGER:

JOF JARVIS MARKET LEAD

1

GENERAL DYNAMICS WIRELESS SERVICES

661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

joseph.jarvis@gdit.com

ENGINEER:

855 COMMUNITY DRIVE SAUK CITY, WI 53583 PH.: (608) 643-4100 FAX: (608) 643-7999 CONTACT: TYLER BEATTY tbeatty@ramaker.com

RAMAKER \$ ASSOCIATES, INC.

APPLICANT INFORMATION: 150 STANDARD DR HANOVER, MD 21076

SITE NAME: BURLINGTON FIRE DEPARTMENT FA NUMBER: 10042310

PROPERTY OWNER: BURLINGTON FIRE DEPARTMENT 7 | 9 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

ADDRESS

7 19 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

COUNTY: HARTFORD

41.76681690° -72.96150690°

GROUND ELEVATION: 775 FT AMSL

DO NOT SCALE DRAWINGS CONTRACTOR SHALL VERIFY ALL PLANS & EXISTIN DIMENSIONS & CONDITIONS ON THE JOB SITE & SHALL IMMEDIATELY NOTIFY THE ENGINEER IN WRITING OF ANY DISCREPANCIES BEFORE PROCEEDING WITH THE WORK OR BE RESPONSIBLE FOR SAME

THE INFORMATION CONTAINED IN THIS SET OF DOCUMENTS IS PROPRIETARY BY NATURE. ANY USE OR DISCLOSURE OTHER THAN THAT WHICH RELATES TO THE CLIENT IS STRICTLY PROHIBITED.

SHEET INDEX

GENERAL:

T-I TITLE SHEET

NOTES:

N-I GENERAL NOTES

A-I SITE PLAN
A-2 SITE PLAN & EQUIPMENT LAYOUT
S-I FOUNDATION DETAILS

ELECTRICAL & GROUNDING:

- E- I WIRING DETAILS
- PANEL AND PENETRATION DETAILS

 ATS, CONDUIT # GROUND ROD DETAILS
- GENERAC GENERATOR SPECIFICATIONS
- E-4. I GENERAC GENERATOR SPECIFICATIONS E-4.2 GENERAC GENERATOR SPECIFICATIONS
- GENERAC ATS SPECIFICATIONS
- E-5. I GENERAC ATS SPECIFICATIONS

SIGNATURE BLOCK

AT¢T MGR. DATE

GENERAL DYNAMICS DATE

CONSTRUCTION MGR.

SITE ACQUISITION

BURLINGTON FIRE DEPARTMENT FA ID # 10042310

DATE 3/23/2020

7 I 9 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

TITLE SHEET

SCALE: NONE

45831

CONSULTANT: GENERAL DYNAMICS Information Technology, Inc. GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406 hereby certify that this plan, specification, or

855 Community Dr, Sauk City, WI 53583 608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN Woodcliff Lake, NJ · Bayamon, PR

PREPARED FOR:

NOTES TO SUBCONTRACTOR:

ACCORDANCE WITH LOCAL CODES.

OF THE WORK

ERECTION OF TOWER.

THE EVENT OF A PROBLEM.

LIMITS PRIOR TO CONSTRUCTION.

. THE GENERAL SUBCONTRACTOR MUST VERIFY ALL DIMENSIONS. CONDITIONS AND ELEVATIONS

SUBCONTRACTOR SHALL BE RESPONSIBLE FOR ALL TEMPORARY BRACING, SHORING, TIES, FORM

THOROUGHLY TRAINED AND EXPERIENCED IN THE NECESSARY CRAFTS AND WHO ARE COMPLETELY

FAMILIAR WITH THE SPECIFIED REQUIREMENTS AND METHOD NEEDED FOR PROPER PERFORMANCE

4 CONSTRUCTION SUBCONTRACTOR AGREES THAT IN ACCORDANCE WITH GENERALLY ACCEPTED

CONSTRUCTION OF THE PROJECT, INCLUDING THE SAFETY OF ALL PERSONS AND PROPERTY, THAT

THIS REQUIREMENT SHALL BE MADE TO APPLY CONTINUOUSLY AND NOT BE LIMITED TO NORMAL

. SITE GROUNDING SHALL COMPLY WITH AT\$T WIRELESS SERVICES TECHNICAL SPECIFICATIONS

FOR FACILITY GROUNDING FOR CELL SITE STANDARDS, LATEST EDITION, AND COMPLY WITH AT&T

6. ALL WORK SHALL COMPLY WITH OSHA AND STATE SAFETY REQUIREMENTS. PROCEDURES FOR

ESTABLISHED PRIOR TO FOUNDATION INSTALLATION, IF TEMPORARY LIGHTING AND MARKING IS

RESPONSIBILITY TO MAINTAIN THE NECESSARY LIGHTS AND NOTIFY THE PROPER AUTHORITIES IN

7. ALL WORK SHALL BE ACCOMPLISHED IN ACCORDANCE WITH ALL LOCAL, STATE, AND FEDERAL

8. ANY DAMAGE TO THE ADJACENT PROPERTIES WILL BE CORRECTED AT THE SUBCONTRACTOR'S

9. THE COMPLETE BID PACKAGE INCLUDES THESE CONSTRUCTION DRAWINGS ALONG WITH THE

SPECIFICATIONS. SUBCONTRACTOR IS RESPONSIBLE FOR REVIEW OF TOTAL BID PACKAGE PRIOR

IO. SUBCONTRACTOR SHALL VERIFY LOCATION OF ALL EXISTING UTILITIES WITHIN CONSTRUCTION

REQUIRED BY THE FEDERAL AVIATION ADMINISTRATION (FAA), IT IS THE SUBCONTRACTOR'S

TOWERS GROUNDING CHECKLIST, LATEST VERSION. WHEN NATIONAL AND LOCAL GROUNDING CODES ARE MORE STRINGENT THEY SHALL GOVERN. GROUNDING SHALL BE COMPLETED BEFORE

WORKING HOURS AND CONSTRUCTION SUBCONTRACTOR FURTHER AGREES TO INDEMNIFY AND

CONSTRUCTION PRACTICES, CONSTRUCTION SUBCONTRACTOR WILL BE REQUIRED TO ASSUME

SOLE AND COMPLETE RESPONSIBILITY FOR JOB SITE CONDITIONS DURING THE COURSE OF

HOLD DESIGN ENGINEER HARMLESS FROM ANY AND ALL LIABILITY, REAL OR ALLEGED, IN

THE PROTECTION OF EXCAVATIONS, EXISTING CONSTRUCTION AND UTILITIES SHALL BE

CODES OR ORDINANCES. THE MOST STRINGENT CODE WILL APPLY IN THE CASE OF

CONNECTION WITH PERFORMANCE OF WORK ON THIS PROJECT

DISCREPANCIES OR DIFFERENCES IN THE CODE REQUIREMENTS.

EXPENSE TO THE SATISFACTION OF THE LANDOWNER AND THE ENGINEER

WORK, ETC. IN ACCORDANCE WITH ALL NATIONAL, STATE, AND LOCAL ORDINANCES, TO SAFELY

BEFORE PROCEEDING WITH THE WORK. ALL WORK SHALL BE PERFORMED IN A WORKMANLIKE

2. IT IS THE INTENTION OF THESE DRAWINGS TO SHOW THE COMPLETED INSTALLATION. THE

3. THE SUBCONTRACTOR SHALL USE ADEQUATE NUMBER OF SKILLED WORKMAN WHO ARE

EXECUTE ALL WORK AND SHALL BE RESPONSIBLE FOR SAME. ALL WORK SHALL BE IN

MANNER IN ACCORDANCE WITH ACCEPTED CONSTRUCTION PRACTICES.

DRAWINGS WHICH SHALL BE TURNED OVER TO THE CONSTRUCTION MANAGER UPON COMPLETION

15. PERMITS: THE SUBCONTRACTOR SHALL BE RESPONSIBLE FOR OBTAINING AND INCURRING

I 6. RECORD DRAWINGS: MAINTAIN A RECORD OF ALL CHANGES, SUBSTITUTIONS BETWEEN

WORK AS SPECIFIED AND INSTALLED. RECORD CHANGES ON A CLEAN SET OF CONTRACT

THE COST OF ALL REQUIRED PERMITS. INSPECTIONS, CERTIFICATES, ETC.

GENERAL NOTES

OF THE PROJECT

- . THIS PROPOSAL IS FOR THE ADDITION OF A NEW GENERATOR ON A CONCRETE PAD TO AN EXISTING UNMANNED TELECOMMUNICATIONS FACILITY CONSISTING OF AN EQUIPMENT SHELTER AND TOWER
- 2. THE PROPOSED FACILITY WILL BE LINMANNED AND DOES NOT REQUIRE POTABLE WATER OR SEWER SERVICE
- 3. THE PROPOSED FACILITY IS UNMANNED AND IS NOT FOR HUMAN HABITAT. (NO HANDICAP

ACCESS IS REQUIRED)

CONSTRUCTION OPERATION

- 4. OCCUPANCY IS LIMITED TO PERIODIC MAINTENANCE AND INSPECTION. APPROXIMATELY 2 TIMES PER MONTH BY AT&T TECHNICIANS.
- 5. OUTDOOR STORAGE AND SOLID WASTE CONTAINERS ARE NOT PROPOSED.
- G. ALL MATERIAL SHALL BE FURNISHED AND WORK SHALL BE PERFORMED IN ACCORDANCE WITH THE PROJECT SPECIFICATIONS.
- 7. SUBCONTRACTOR SHALL BE RESPONSIBLE FOR REPAIRING ANY DAMAGE CAUSED BY THE
- 8. SUBCONTRACTOR SHALL BE RESPONSIBLE FOR OBTAINING ALL PERMITS AND INSPECTION REQUIRED FOR CONSTRUCTION.
- 9. SUBCONTRACTOR SHALL REMOVE ALL TRASH AND DEBRIS FROM THE SITE ON A DAILY BASIS.

ELECTRICAL NOTES A. GENERAL

- I. COORDINATE LOCATION AND POWER REQUIREMENTS OF ALL EQUIPMENT WITH AT\$T AND EQUIPMENT SUPPLIER PRIOR TO INSTALLATION.
- 2 COORDINATE LOCATION AND REQUIREMENTS FOR ELECTRICAL AND TELEPHONE SERVICES WITH THE PROPERTY REPRESENTATIVE. AT&T AND UTILITY COMPANIES. ROUTING OF CONDUITS MAY BE MODIFIED TO MEET SITE REQUIREMENTS. EXACT CONDUIT ROUTING TO
- 3. ALL WIRING AND EQUIPMENT SHOWN ON ELECTRICAL SHEETS SHALL BE FURNISHED AND INSTALLED UNDER ELECTRICAL PORTION OF CONTRACT UNLESS OTHERWISE NOTED
- 4. UNINTERRUPTED ELECTRICAL SERVICE FOR EXISTING EQUIPMENT SHALL BE MAINTAINED DURING THE INSTALLATION OF THE WORK DESCRIBED UNDER THESE DOCUMENTS TEMPORARY EQUIPMENT, CABLES AND WHATEVER ELSE IS NECESSARY SHALL BE PROVIDED AS REQUIRED TO MAINTAIN ELECTRICAL SERVICE. TEMPORARY SERVICE FACILITIES, IF REQUIRED AT ANY TIME, SHALL NOT BE DISCONNECTED OR REMOVED UNTIL NEW SERVICE EQUIPMENT IS IN PROPER OPERATION. IF ANY SERVICE OR SYSTEM MUST BE INTERRUPTED, THE CONTRACTOR SHALL REQUEST PERMISSION IN WRITING STATING THE DATE. TIME. ETC. THE SERVICE WILL BE INTERRUPTED AND THE AREAS AFFECTED. THIS REQUEST SHALL BE MADE IN SUFFICIENT TIME FOR PROPER ARRANGEMENTS TO BE MADE. WRITTEN PERMISSION SHALL BE OBTAINED FROM THE OWNER BEFORE INTERRUPTING ELECTRICAL SERVICE
- 5. COORDINATE NEW WORK WITH OTHER TRADES AND VERIFY EXISTING CONDITIONS TO AVOID INTERFERENCE. IN CASE OF INTERFERENCE, AT&T'S REPRESENTATIVE WILL DECIDE WHICH WORK IS TO BE RELOCATED. REGARDLESS OF WHICH WAS FIRST INSTALLED
- 6. THE INSTALLATION MUST COMPLY WITH NEC AND ALL FEDERAL, STATE AND LOCAL RULES AND REGULATIONS.
- 7. THE DRAWINGS ARE DIAGRAMMATIC AND INDICATE THE GENERAL ARRANGEMENT OF SYSTEMS AND FOLIPMENT UNLESS OTHERWISE DEFINED BY DIMENSIONS OR DETAILS EXACT EQUIPMENT LOCATIONS AND RACEWAY ROUTING SHALL BE GOVERNED BY ACTUAL FIELD CONDITIONS AND/OR DIRECTIONS FROM AT&T'S REPRESENTATIVE.
- 8. CONTRACTOR SHALL PAY ALL PERMITS AND FEES REQUIRED.
- 9. ALL MATERIALS SHALL BE FURNISHED AND WORK SHALL BE PERFORMED IN ACCORDANCE WITH THE APPLICABLE SECTIONS OF THE STANDARDS REFERENCED BELOW:
 - ANSI (AMERICAN NATIONAL STANDARDS INSTITUTE) ASTIM (AMERICAN SOCIETY FOR TESTING MATERIALS)
 - ETL (ELECTRICAL TESTING LABORATORY)
 - ICEA (INSULATED CABLE ENGINEERS ASSOCIATION)
 - IEEE (INSTITUTE OF ELECTRICAL AND ELECTRONIC ENGINEERS)
 - MBFI (NATIONAL BOARD OF FIRE UNDERWRITERS)
 - NESC (NATIONAL ELECTRICAL SAFETY CODE)
 - NEMA (NATIONAL ELECTRICAL MANUFACTURER'S ASSOCIATION)
 - NFPA (NATIONAL FIRE PROTECTION ASSOCIATION)
 - UL (UNDERWRITER'S LABORATORY)
- IO. CONTRACTOR SHALL REVIEW PLANS, DETAILS AND SPECIFICATIONS IN DETAIL AND ADJUST WORK TO CONFORM WITH ACTUAL SITE CONDITIONS SO THAT ELECTRICAL DEVICES AND FOLIPMENT WILL BE LOCATED AND READILY ACCESSIBLE. QUANTITIES LISTED IN MATERIAL LISTS ON THE DRAWINGS ARE FOR INFORMATION ONLY. THE CONTRACTOR SHALL PROVIDE HIS OWN TAKEOFF FOR MATERIAL QUANTITY AND TYPES BASED ON ACTUAL SITE CONDITIONS, IN ADDITION, CONTRACTOR SHALL PROVIDE ALL NECESSARY MATERIALS TO INSTALL EQUIPMENT FURNISHED BY AT&T OR ITS SUPPLIERS. ALL ITEMS NOT SPECIFICALLY MENTIONED HEREIN OR SHOWN ON THE DRAWINGS, BUT WHICH ARE OBVIOUSLY NECESSARY TO MAKE A COMPLETE WORKING INSTALLATION, SHALL BE INCLUDED.
- II. THE CONTRACTOR OR BIDDER SHALL BEAR THE RESPONSIBILITY OF NOTIFYING (IN WRITING) AT&T'S REPRESENTATIVE OF ANY CONFLICTS PRIOR TO THE SUBMISSION OF CONTRACTOR'S PROPOSAL OR PERFORMANCE OF WORK, IN THE EVENT OF DISCREPANCIES THE CONTRACTOR SHALL PRICE THE MORE COSTLY OR EXTENSIVE WORK, UNLESS DIRECTED IN WRITING OTHERWISE.
- 12 ALL FLOORS WHERE PENETRATIONS ARE REQUIRED IN BUILDING ARE TO BE CORE DRILLED AND THEN FIREPROOFED

- I. PROVIDE PULL BOXES AND JUNCTION BOXES WHERE SHOWN OR AS REQUIRED BY CODE SUCH THAT NO MORE THAN THE EQUIVALENT OF FOUR QUARTER BENDS (380 DEGREES TOTAL) FXIST IN A CONDUIT RUN
- 2. ALL POWER AND CONTROL/INDICATION WIRING SHALL BE TYPE THHN/THWN 800V RATED 75 DEGREES CELSIUS, UNLESS NOTED OTHERWISE

- 3. SCHEDULE 80 PVC CONDUIT SHALL BE USED ABOVE GROUND, WHERE ABOVE GRADE IS DEFINED AS THE GROUND OF THE TURN-UP
- 4. BELL END OR TERMINAL ADAPTER MUST BE INSTALLED ON END OF PVC CONDUIT PER NEC 352.46, 300.4 F. (3)
- CONDUIT BENDS SHALL BE MADE IN ACCORDANCE WITH NEC TABLE 346-10. NO RIGHT ANGLE DEVICE OTHER THAN STANDARD CONDUIT ELBOWS WITH 12" MINIMUM INSIDE SWEEPS FOR ALL CONDUITS 2" OR LARGER.
- 6. POWER WIRING SIZE SHALL NOT BE SMALLER THAN #12 AWG
- 7. ALL WIRING SHALL BE COPPER. ALUMINUM WILL NOT BE ACCEPTABLE ALL POWER CIRCUITS SHALL CONTAIN A GROUND WIRE
- 8. PHASE MARKINGS TO BE USED AT POWER CONDUCTOR TERMINATIONS.
- 9. CONTRACTOR SHALL ENSURE INTEGRITY IS MAINTAINED WHEN INSTALLING CONDUIT AND WIRING.
- 10. INSTALL PULL STRING IN ALL CONDUIT
- I I . FOR ROOFTOP INSTALLS AND BUILD-OUTS, CONDUITS INSIDE BUILDING AND ON ROOF SHALL BE RGS, UNLESS OTHERWISE NOTED. FOR RAW LAND SITES AND CO-LOCATES, PVC SCHEDULE 80 SHALL BE UTILIZED UNLESS NOTED OTHERWISE.
- 12. MAINTAIN MINIMUM I'-O" VERTICAL AND I'-O" HORIZONTAL SEPARATIONS FROM ANY MECHANICAL GAS PIPING.
- 13. ALL WIRING ROUTED IN PLENUM TO BE RATED OR IN METALLIC FLEX (LIQUIDITE) CONDUIT.

C. EQUIPMENT

- EQUIPMENT/PARTS CONNECTED TO EXISTING PANELS, DUCTS, ETC. SHALL MATCH THE CHARACTERISTICS (A/C, V, A) OF THAT EQUIPMENT.
- 2. ALL ELECTRICAL EQUIPMENT OUTSIDE SHALL BE NEMA OR 3R RATED.

D. GROUNDING

- ALL GROUND CONNECTIONS TO BUILDING SHALL BE MADE USING TWO-HOLE CONNECTORS PROVIDE STAINLESS STEEL BOLTS AND LOCK WASHERS ON ALL MECHANICAL GROUND CONNECTIONS
- 2 ALL FOUIPMENT SURFACES TO BE BONDED TO GROUNDING SYSTEM SHALL BE STRIPPED OF ALL PAINT AND DIRT. CONNECTIONS TO VARIOUS METALS SHALL BE OF A TYPE AS TO CAUSE A GALVANIC OR CORROSIVE REACTION. AREA SHALL BE REPAINTED FOLLOWING
- 3. ANY METALLIC ITEM WITHIN 6' OF GROUND CONDUCTORS MUST BE CONNECTED TO THE GROUNDING SYSTEM.
- 4. EXTERIOR, ABOVE GRADE GROUND CONNECTIONS SHALL BE FURNISHED WITH A LIBERAL PROTECTIVE COATING OF ANTI-OXIDE COMPOUND.
- ALL MATERIALS AND LABOR REQUIRED FOR THE GROUNDING SYSTEM AS INDICATED ON THE PLANS AND DETAILS, AND AS DESCRIBED HEREIN SHALL BE FURNISHED BY THIS CONTRACTOR LINIESS OTHERWISE NOTED
- 6 EXACT LOCATION OF GROUND CONNECTION POINTS SHALL BE DETERMINED IN FIELD. ADJUST LOCATIONS INDICATED ON PLANS ACCORDING TO ACTUAL EQUIPMENT LOCATIONS TO KEEP THE GROUND CONNECTION CABLES AS SHORT AS PRACTICAL.
- 7. PROVIDE ALL ELECTRICAL SYSTEM AND EQUIPMENT GROUNDS AS REQUIRED BY THE CURRENT EDITION OF THE NATIONAL ELECTRIC CODE (1999) AND THE CURRENT EDITION O THE NATIONAL FLECTRICAL SAFETY CODE. BONDING JUMPERS WITH APPROVED GROUND FITTINGS SHALL BE INSTALLED AT ALL RACEWAYS, EQUIPMENT ENCLOSURES, PULL BOXES, ETC. TO MAINTAIN GROUND CONTINUITY WHERE REQUIRED BY CODE
- 8. ALL EQUIPMENT GROUND CONDUCTORS SHALL BE TIN COATED, #2 AWG COPPER UNLESS NOTED OTHERWISE ON THE DRAWINGS.
- PROVIDE PRE AND POST GROUND TEST RESULTS. USING CLAMP-ON TESTER. TEST RESULTS SHALL BE PHOTOS WITH DIGITAL TIME AND GPS STAMPED/EMBEDDED.

E. INSPECTION/DOCUMENTATION

- I. THE CONTRACTOR, UPON COMPLETION OF HIS WORK, SHALL PROVIDE AS-BUILT DRAWINGS INFORMATION SHOULD BE GIVEN TO THE GENERAL CONTRACTOR FOR INCLUSION IN FINAL AS-BUILT SURVEY DOCUMENTS TO BE GIVEN TO THE OWNER.
- 2. CONTRACTOR SHALL SUPPLY DOCUMENTATION ATTESTING TO THE COMPLETE GROUND SYSTEM'S RECEPTIVITY (MAX. 5 OHMS).
- 3. AN ELECTRICAL INSPECTION SHALL BE MADE BY AND INSPECTING AGENCY APPROVED BY AT&T'S REPRESENTATIVE. CONTRACTOR SHALL COORDINATE ALL INSPECTIONS AND OBTAIN POWER COMPANY APPROVAL.
- 4. CONTRACTOR SHALL HAVE ATS AND GENERATOR RELAY INSTALLATION AND CONNECTIONS INSPECTED BY OTHERS TO ENSURE THAT UL LISTING FOR THAT EQUIPMENT IS NOT VOIDED



855 Community Dr, Sauk City, WI 53583 608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN Woodcliff Lake, NJ · Bayamon, PR

PREPARED FOR:



CONSULTANT:


GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

ertification \$ Seal

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



DATE 3/23/2020

BURLINGTON FIRE DEPARTMENT FA ID # 10042310


19 GEORGE WASHINGTON TURNPIKE

BURLINGTON, CT 06013

GENERAL NOTES

SCALE: NONE

4583 N- I SHEET



SCOPE OF WORK DETAILS

GENERAL:


- NEW GENERAC DIESEL GENERATOR PROVIDED BY GENERAL
- DYNAMICS & INSTALLED BY GENERAL CONTRACTOR, SEE E-4.

 NEW 4'-0" X I 0'-0" CONCRETE PAD PROVIDED & INSTALLED BY GENERAL CONTRACTOR (AS REQUIRED) SEE 5-1
- NEW GENERAC AUTOMATIC TRANSFER SWITCH PROVIDED BY GENERAL DYNAMICS & INSTALLED BY CONTRACTOR (AS REQUIRED)
- CONTRACTOR TO VERIFY ALL EXISTING UTILITIES PRIOR TO CONSTRUCTION
- CONTRACTOR SHALL RESTORE ¢ REPAIR ANY DAMAGED AREAS CAUSED BY CONSTRUCTION TO ORIGINAL OR BETTER CONDITION

- INSTALL PULL STRING IN EACH CONDUIT
- (1) NEW 2" AND (1) NEW 1" ELECTRICAL CONDUITS WITH CONDUCTORS TO RUN FROM NEW GENERATOR TO NEW ATS. CONDUIT PROVIDED AND INSTALLED BY GENERAL CONTRACTOR. SEE E-1, E-2 \$ E-3.
- (2) NEW I" ELECTRICAL CONDUIT WITH CONDUCTORS TO RUN FROM NEW GENERATOR TO AC PANEL. CONDUIT PROVIDED \$ INSTALLED BY GENERAL CONTRACTOR. SEE E-1, E-2 & E-3.
- (I) NEW I" ALARM CONDUIT & CABLING PROVIDED & INSTALLED BY GENERAL CONTRACTOR. SEE E-1, E-2 & E-3.

NEW EXOTHERMIC CONNECTION FROM EXISTING GROUND RING TO NEW MECHANICAL CONNECTION AT GENERATOR CHASSIS GENERAL CONTRACTOR TO VERIFY LOCATION IN FIELD. LOCATE GROUND RODS NO MORE THAN 8'-O" APART.

PROVIDE NEW H-FRAME IF REQUIRED. MATCH EXISTING H-FRAME MATERIAL FOR CONSTRUCTION OF NEW H-FRAME. USE ALL GALVANIZED COMPONENTS, WHITE PLASTIC END CAPS ON UNISTRUTS, WEATHER CAPS ON TOPS OF PIPE AND CONCRETE SUPPORTS BELOW FROST LINE. TOP OF FOOTING SHOULD BE AT LEAST 2" ABOVE EXISTING GROUND LEVEL. SLOPE THE GROUND AWAY FROM THE H-FRAME FOR POSITIVE WATER DRAINAGE OFF







855 Community Dr, Sauk City, WI 53583 608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN Woodcliff Lake, NJ · Bayamon, PR

PREPARED FOR:



CONSULTANT:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



FINAL

BURLINGTON FIRE **DEPARTMENT**

DATE 3/23/2020

FA ID # 10042310

7 | 9 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

SITE PLAN & EQUIPMENT LAYOUT

| 0 : | 2.5' I | 5' | 10' |
|-----------------------|-----------|----------------|-----|
| | | | |
| 11" x 17" 22" x 34 | | = 5' = 2.5' | |
| PROJECT NUMBER | | 45831 | |
| SHEET NUMBER | | A-2 | |





(C)

ANCHORS MINIMUM (4) @ 5/8" FOR GEN-SET MOUNTING

FUEL FILL: 5 GALLON SPILL CONTAINMENT WITH ALARM

BASIN LEAK DETECTOR SWITCH SHALL BE PROVIDED

PER UL-142 STANDARDS

40% REMAINING FOR ALARM


20% REMAINING FOR SHUT-DOWN

FACTORY PRE-SET AT 95% FULL FOR ALARM

SUB BASE TANK TESTING: PRIMARY TANK \$ SECONDARY CONTAINMENT BASIN SECTIONS

PRESSURIZED AT 3-5 PSI AND LEAK-CHECKED TO ENSURE INTEGRITY OF SUB BASE WELD

FUEL CONTAINMENT BASIN: SUB BASE TANK SHALL INCLUDE A WELDED STEEL CONTAINMENT BASIN, SIZED AT A MINIMUM OF 1 I 0% OF THE TANK CAPACITY TO PREVENT ESCAPE OF FUEL INTO THE ENVIRONMENT IN THE EVENT OF A TANK RUPTURE. A FUEL CONTAINMENT



CONDUIT ELBOW -

SLIPJOINT DETAIL

SCALE: NTS

PROPOSED

CONDUIT

NOTE: VERIFY WIRE AND CONDUIT QUANTITY ≰ SIZES WITH GENERATOR MAKE & MODEL # PRIOR TO INSTALLATION. VERIFY ELECTRICAL REQUIREMENTS WITH LOCAL UTILITY PROVIDER. RESTORE SURFACE TO MATCH ORIGINAL CONDITION - UNDISTURBED SOIL COMPACTED BACKFILL (SUITABLE ON SITE MATERIAL) 6" WARNING TAPE ELECTRICAL CONDUIT(S) WHERE APPLICABLE *

> * SEPARATION DIMENSION TO BE VERIFIED WITH LOCAL UTILITY COMPANY REQUIREMENTS

6"

I. PROVIDE PVC CONDUIT BELOW GRADE EXCEPT AS NOTED BELOW. 2. PROVIDE RGS CONDUIT AND ELBOWS AT STUB UP LOCATIONS (I.E. SERVICE POLE, BTS EQUIPMENT, ETC.) 3. INSTALL UTILITY PULLBOXES PER NEC

6" TYP

UTILITY CONDUIT TRENCH SCALE: NTS

STRUCTURAL GENERAL NOTES

LO GENERAL CONDITIONS

1.1 DESIGN & CONSTRUCTION OF ALL WORK SHALL CONFORM TO LOCAL BUILDING CODES, ACI 318-11. IN CASE OF CONFLICT BETWEEN THE CODES, STANDARDS, REGULATIONS, SPECIFICATIONS, GENERAL NOTES AND/OR MANUFACTURER'S REQUIREMENTS USE THE MOST STRINGENT PROVISIONS.

USE THE EXPRESS INTENT OF PARTIES INVOLVED IN THIS PROJECT THAT THE CONTRACTOR OR SUBCONTRACTOR OR INDEPENDENT CONTRACTOR OR THE RESPECTIVE EMPLOYEES SHALL EXCULPATE THE ARCHITECT, THE ENGINEER, TECH. CONSTRUCTION MANAGER, THE OWNER, \$ THEIR AGENTS FROM ANY LIABILITY WHATSOEVER \$ HOLD THEM HARMLESS AGAINST LOSS, DAMAGES, LIABILITY OR ANY EXPENSE ARISING IN ANY MATTER FROM THE WRONGFUL OR NEGLIGENT ACT, OR FAILURE TO CARRY METHODS, TECHNIQUES OR PROCEDURES OR FAILURE TO CONFORM TO THE STATE SCAFFOLDING ACT IN CONNECTIONS WITH THE WORK.

1.3 DO NOT SCALE DRAWINGS

1.4 VERIFY ALL EQUIPMENT MOUNTING DIMENSIONS PER MANUFACTURER DRAWINGS

1.5 DESIGN LOADS ARE (GENERAC):

LIVE LOAD EQUIPMENT SIZE

: 889.1" H, 106" W, 38" D

WEIGHT WITH WOODEN SHIPPING SKID

ENCLOSED GENERATOR : 3974 LBS 2.0 FOR DESIGN & ANALYSIS OF THE FOUNDATION, THE MINIMUM NET SOIL BEARING CAPACITY SHALL BE ASSUMED TO BE 2000 PSF.

3.1 MEET OR EXCEED THE FOLLOWING CODES & STANDARDS:

DESIGN : ACI318-11

CONSTRUCTION : ACI301

: CRSI MANUAL OF STANDARD PRACTICE DETAILING REINF. STEEL : ASTM A 615 GRADE 60, DEFORMED MIXING : ASTM C 94. READY MIX CONCRETE

AIR ENTRAINMENT : ACI 3 | 8 AND ASTM C-260 AGGREGATE ASTM C 33 AND C 330 (FOR LIGHT WEIGHT)

3.2 CONCRETE STRENGTH AT 28 DAYS SHALL BE 4000 PSI MINIMUM 3.3 DO NOT FIELD BEND OR WELD TO GRADE 60 REINFORCED STEEL

3.4 PROVIDE AIR ENTRAINED CONCRETE WITH AIR CONTENT OF 5 TO 7% FOR ALL CONCRETE EXPOSED TO EARTH OR WEATHER.

3.5 MAXIMUM AGGREGATE SIZE: 3/4" 3.6 DO NOT USE IN ADMIXTURE, WATER OR OTHER CONSTITUENTS OF CONCRETE WHICH HAS CALCIUM CHLORIDE.

3.7 MINIMUM COVER FOR REINFORCING STEEL SHALL BE AS SHOWN ON PLAN.

4.0 FOUNDATION \$ EXCAVATION NOTES

4.1 SLAB SHALL BE CONSTRUCTED UPON UNDISTURBED, NATURAL SUBGRADE OR COMPACTED GRANULAR FILL WITH AN ASSUMED MINIMUM NET ALLOWABLE BEARING CAPACITY OF 1800 PSF.

4.2 ALL ORGANIC AND/OR OTHER UNSUITABLE MATERIAL SHALL BE REMOVED FRO FOUNDATION \$ SLAB SUBGRADE \$ BACKFILL AREAS

\$ THEN BACKFILLED WITH ACCEPTABLE GRANULAR FILL COMPACTED TO 95% OF MAXIMUM DENSITY AT OPTIMUM MOISTURE

4.3 THE CONTRACTOR SHALL PROVIDE ALL NECESSARY MEASURES TO PREVENT ANY WATER, FROST, OR ICE FROM PENETRATING ANY FOOTING OR STRUCTURAL SUBGRADE BEFORE & AFTER PLACING OF CONCRETE, AND UNTIL SUCH CONCRETE HAS FULLY CURED.



608-643-4100 www.Ramaker.com Sauk City, WI • Willmar, MN Woodcliff Lake, NJ · Bayamon, PR

PREPARED FOR:



CONSULTANT:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



FINAL DATE 3/23/2020

BURLINGTON FIRE DEPARTMENT FA ID # 10042310

7 I 9 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

FOUNDATION DETAILS

SCALE: NONE

4583 SHEET S-

DIAGRAM CIRCUIT SCHEDULE


| | 5 // O. V. W. O. V. O. S. 125 522 | | | | | |
|-----|--------------------------------------|------------------------------|--|--------------------|-----------------|--|
| NO. | FROM | ТО | WIRES | GROUND | CONDUIT SIZE | FUNCTION |
| | NORMAL POWER SOURCE | AUTOMATIC TRANSFER SWITCH | (3) 3/0 | (1) #4 | 2" | NORMAL POWER FEEDER TO ATS (CUT BACK EXISTING) |
| 2 | AUTOMATIC TRANSFER SWITCH | LOAD CENTER | (3) 3/0 | (1) #4 | 2" | POWER FEEDER FROM ATS TO PANEL |
| 3 | GENERATOR | AUTOMATIC TRANSFER SWITCH | (3) 3/0 | (1) #4 | 2" | EMERGENCY POWER FEEDER TO ATS |
| 4 | AUTOMATIC TRANSFER SWITCH | GENERATOR | (2) #10 | (1) #10 | 1" | START CIRCUIT |
| 5 | LOAD CENTER (DISTRIBUTION CENTER) | GENERATOR, ATS | (2) #12 | (I) #I2 (I) #I2 | " " | CIRCUIT FOR GENERATOR BLOCK HEATER \$ BATTERY HEATER CIRCUIT FOR BATTERY CHARGER |
| 6 | GENERATOR | AUTOMATIC TRANSFER SWITCH | I 2-PAIR 24 AWG OR 2EA G-PAIR CAT5 | N/A | 1" | ALARM CABLES (I) I 2 PAIR 24 AWG. PROVIDE 24" OF SLACK CABLE. FINAL PUNCH DOWN IS BY AT\$T TECH. LABEL ALL WIRES |
| 7 | AUTOMATIC TRANSFER SWITCH | ALARM BLOCK | I 2-PAIR 24 AWG OR 2EA G-PAIR CAT5 | N/A | 1" | ALARM CABLES (I) I 2 PAIR 24 AWG (RUN TO PURCELL CABINET & INTO ALARM BOX). PROVIDE 24" OF SLACK CABLE. FINAL PUNCH DOWN IS BY AT&T TECH. LABEL ALL WIRES |

ALARM WIRE IDENTIFICATION CHART

| WIRE | ALARM |
|---------------------------------------|-------------------|
| BROWN BROWN / WHITE | GENERATOR RUNNING |
| GREEN GREEN / WHITE | CRITICAL FAULT |
| BLUE BLUE / WHITE | MINOR FAULT |
| ORANGE ORANGE / WHITE | LOW FUEL |
| BROWN * BROWN / WHITE * | FUEL LEAK |
| *CAT5 CABLE ONLY, FROM 2ND CAT5 CABLE | |

ALARM WIRING IDENTIFICATION CHART

SCALE: NTS





855 Community Dr, Sauk City, WI 53583 608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN Woodcliff Lake, NJ • Bayamon, PR

PREPARED FOR:



CONSULTANT:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



SSUE FINAL

DATE 3/23/2020

BURLINGTON FIRE DEPARTMENT FA ID # 10042310

7 19 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

SHEET TITLE:

WIRING DETAILS

SCALE: NONE

45831 SHEET E- 1

Breaker

Position

Breaker

Type

1P

1P

1P

2P

2P

2P

2P

2P

1P

1P

1P

1P

1P

13

21

31

33

35

37

39

41

On/Off

ON

ON

ON

ON

ON

ON

OFF

OFF

OFF

ON

OFF

ON

ON

ON

Size

50

20

20

20

30

30

30

30

30


20

20

120

20

20



- IF EXISTING CONSTRUCTION VARIES FROM THIS DETAIL, AN EQUAL 3-HR U.L. PENETRATION APPROPRIATE FOR THE EXISTING WALL TYPE SHALL BE CONSTRUCTED
- GC SHALL USE NON-SHRINKING CAULK TO WEATHERSEAL ALL PENETRATIONS INTO OR THRU SHELTER WALL

U.L. SYSTEM NO. C-AJ- I 150 CONDUIT THROUGH BEARING WALL SIMILAR TO U.L. DESIGN NO. U902 FRATING = 3 HRT RATING = O HR

- FLOOR OR WALL ASSEMBLY: MINIMUM 4-1/2" THICK REINFORCED LIGHTWEIGHT OR NORMAL WEIGHT (100-150 PCF) CONCRETE. WALL MAY ALSO BE CONSTRUCTED OF ANY UL CLASSIFIED CONCRETE BLOCKS*. MAX DIAMETER OF OPENING IS 4". SEE CONCRETE BLOCKS 9CATZ) CATEGORY IN THE FIRE RESISTANCE DIRECTORY FOR NAMES OF MANUFACTURERS.
- THROUGH PENETRATIONS: ONE METALLIC PIPE OR CONDUIT TO BE RIGIDLY SUPPORTED ON BOTH SIDES OF FLOOR OR WALL ASSEMBLY. THE ANNULAR SPACE SHALL BE MINIMUM O". (POINT CONTACT) TO MAXIMUM 1-3/8". THE FOLLOWING TYPES AND SIZES OF METALLIC PIPES OR CONDUITS MAY BE USED:
 - A. STEEL PIPE-NOMINAL 6" DIAMETER (OR SMALLER) SCHEDULE 40 (OR HEAVIER) STEEL PIPE.
 - B. IRON PIPE-NOMINAL 6" DIAMETER (OR SMALLER) CAST OR DUCTILE IRON PIPE. C. CONDUIT - NOMINAL 4" DIAMETER (OR SMALLER) STEEL ELECTRICAL METALLIC TUBING OR NOMINAL 3-1/2" DIAMETER (OR SMALLER) STEEL CONDUIT
- PACKING MATERIAL: MINIMUM 6" THICKNESS OF MIN 4.0 PCF MINERAL WOOL BATTING INSULATION FIRMLY PACKED INTO OPENING AS A PERMANENT FORM. PACKING MATERIAL TO BE RECESSED FROM TOP SURFACE OF FLOOR OR FROM BOTH SURFACES OF WALL AS REQUIRED TO ACCOMMODATE THE REQUIRED THICKNESS OF FILL MATERIAL.
- FILL, VOID, OR CAVITY MATERIAL*: SEALANT: MINIMUM 1/4" THICKNESS OF FILL MATERIAL APPLIED WITHIN THE ANNULUS, FLUSH WITH TOP SURFACE OF FLOOR AND WITH BOTH SURFACES OF WALL. AT THE POINT CONTACT LOCATION BETWEEN PIPE AND CONCRETE, A MINIMUM 1/2" DIAMETER BEAD OF FILL MATERIAL SHALL BE APPLIED AT THE CONCRETE/PIPE INTERFACE ON THE TOP SURFACE OF FLOOR AND ON BOTH SURFACES OF WALL. W RATING APPLIES ONLY WHEN CPGO IS OR CPGO4 SEALANT IS

HILTI CONSTRUCTION CHEMICALS, DIV OF HILTI INC. : CP6015, CP604, CP606, OR FS-ONE

* BEARING THE UL CLASSIFICATION MARK

OUTER WALL PENETRATION DETAIL (IF APPLICABLE)



PROPOSED 20A BREAKERS FOR BLOCK HEATER BATTERY CHARGER AND ATS ON NEW AT&T GENERATOR

AC Distribution Panel - Layout Diagram

Circuit Label

HVAC #1

INT. LIGHTS

GFCI

EXT. LIGHTS

RECT #1

RECT #3

RECT #5

RECT #7

RECT #9

TELCO

SPARE

BATTERY CHARGER

BLOCK HEATER

ATS

BLANK

Breaker

Position

Breaker

Type

1P

1P

1P

2P

2P

2P

2P

2P

1P

1P

1P

10

12

14

16

18

20

22

24

26

28

30

32

34

36

38

40

42

On/Off

OFF

ON

ON

ON

ON

ON

OFF

OFF

ON

OFF

ON

Size

20

20

20

50

30

30

30

30

20

20

20

Circuit Label

SPARE

TELCO RECEPT.

RECEPT. LEFT

HVAC#2

RECT #2

RECT #4

RECT#6

RECT #8

RECEPT. RIGHT

SPARE

SMOKE ALARM

BLANK

BLANK

BLANK

BLANK

BLANK

EXISTING PANEL SCHEDULE SCALE: NTS



TOP OF GROUND



THROUGH CABLE THROUGH CABLE TO SIDE OF GROUND ROD. GROUND ROD



Type VV THROUGH VERTICAL CABLE TO VERTICAL STEEL SURFACE OR TO THE

SIDE OF EITHER HORIZONTAL OR



HORIZONTAL CABLE HORIZONTAL STEEL CABLE OFF SURFACE TFF OF

ORIZONTAL RUN

AND TAP CABLES





HORIZONTAL CABLE TAP TO VERTICAL STEEL SURFACE OR THE SIDE OF HORIZONTAL PIPE



Type VS CABLE TAP DOWN AT 45°TO VERTICAL STEEL SURFACE OR SIDE OF HORIZONTAL OR VERTICAL PIPE.



GROUND ROD

CONTRACTOR TO LABEL WIRES WITH P-TOUCH OR SIMILAR LABELS ONLY. ABSOLUTELY NO HANDWRITTEN LABELS.

*CONTRACTOR TO UTILIZE NEXT AVAILABLE IN SEQUENCE SINGLE BREAKER POSITION FOR GENERATOR BATTERY CHARGER BATTERY HEATER AND BLOCK HEATER

> CADWELD DETAILS SCALE: NTS





855 Community Dr, Sauk City, WI 53583 608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN Woodcliff Lake, NJ · Bayamon, PR

PREPARED FOR:



CONSULTANT:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



| 4 | mangk descuran | 3/23/2020 |
|---|----------------|-----------|
|) | Signature: | Date: |
| J | | |
| | | |

FINAL

BURLINGTON FIRE DEPARTMENT FA ID # 10042310

DATE 3/23/2020

7 | 9 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

SHEET TITLE:

PANEL AND PENETRATION DETAILS

SCALE: NONE

45831 SHEET E-2

CONDUIT (TYP)

(2) (3)


EXISTING WALL/CEILING

BUTTERFLY CLAMP AS REQUIRED

VERTICAL "UNISTRUT" PI 000 'T' SERIES LENGTH BASED ON NUMBER OF CONDUIT TO BE MOUNTED

| WALL CONSTRUCTION TYPE | USE |
|------------------------------|--|
| HOLLOW | 3/8" DIA. TOGGLE BOLT |
| HOLLOW, AT STUD | 3/8" DIA. LAG SCREW |
| CONCRETE BLOCK (HOLLOW) | 3/8" DIA. HILTI HY-20 WITH SCREEN, MINIMUM EMBEDMENT 2-1/2" |
| CONCRETE (SOLID) | 3/8" DIA. HILTI HY-150 WITH SCREEN MINIMUM EMBEDMENT 2-1/2" |

NOTE: USE GALVANIZED OR STAINLESS STEEL HARDWARE FOR WALL MOUNT & CONNECTIONS OF CHANNELS SPACE UNITS @ 5'-O" O.C. LENGTH OF RUN



- CADWELD - GRADE #2 AWG BCW GROUND RING GROUND ROD COPPERWELD 5/8"Ø x 8'-0" LONG (MAX)

GROUND ROD DETAIL

- GROUND RODS MAY BE: - COPPER CLAD STEEL
- SOLID COPPER GROUND RODS SHALL HAVE A MAXIMUM SPACING TWICE THE LENGTH OF ROD
- SEE RESISTIVITY REPORT FOR VERIFICATION AS AVAILABLE
- A LARGER CONDUCTOR SHALL BE REQUIRED IN AREAS HIGHLY PRONE TO LIGHTNING AND/OR AREAS WITH HIGHLY ACIDIC SOIL
- GROUND RODS INSTALLED WITHIN CLOSE PROXIMITY TO TOWER OR WHEN SOIL IS AT OR BELOW 2,000 OHM-CM, SHALL BE GALVANIZED TO PREVENT GALVANIC CORROSION OF TOWER, (SEE ANSI/TIA-EIA-222-G)
- PROVIDE (I) GROUND LEAD TO EACH SIDE OF THE GENERATOR

Mobility

100% EMPLOYEE-OWNED

855 Community Dr, Sauk City, WI 53583

608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN

Woodcliff Lake, NJ · Bayamon, PR

CONSULTANT:

PREPARED FOR:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



| V | | | | |
|---|--|--|--|--|
| | | | | |
| | | | | |
| | | | | |
| | | | | |
| | | | | |
| | | | | |

ARK DATE DESCRIPTION SSUE FINAL

DATE 3/23/2020

BURLINGTON FIRE DEPARTMENT FA ID # 10042310

7 19 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

SHEET TITLE:

ATS, CONDUIT & GROUND ROD DETAILS


SCALE: NONE


45831 SHEET E-3

WALL CONSTRUCTION USE TYPE HOLLOW 3/8" DIA. TOGGLE BOLT

3/8" DIA. LAG SCREW HOLLOW, AT STUD CONCRETE BLOCK 7/16" DIA. HILTI HY-20 WITH SCREEN (HOLLOW) 7/16" DIA. HILTI HY-150 WITH SCREEN CONCRETE (SOLID) MINIMUM EMBEDMENT 2-1/2"

- USE GALVANIZED OR STAINLESS STEEL HARDWARE FOR WALL MOUNT AND CONNECTION OF CHANNELS
- 2. GC SHALL USE NON-SHRINKING CAULK TO WEATHER SEAL ALL PENETRATIONS INTO OR THROUGH SHELTER WALL





2'-6"

GENERAC ATS MOUNTING DETAIL

SD030 | 2.2L | 30 kW INDUSTRIAL DIESEL GENERATOR SET GENERAC* INDUSTRIAL

EPA Certified Stationary Emergency

Standby Power Rating 30 kW, 38 kVA, 60 Hz

Prime Power Rating* 27 kW, 34 kVA, 60 Hz



Image used for illustration purposes only

Codes and Standards

Not all codes and standards apply to all configurations. Contact factory for details.



UL2200, UL508, UL489, UL142



CSA C22.2



BS5514 and DIN 6271



SAE J1349



NFPA 37, 70, 99, 110



NEC700, 701, 702, 708



ISO 3046, 7637, 8528, 9001



NEMA ICS10, MG1, 250, ICS6, AB1



ANSI C62.41

Powering Ahead

For over 50 years, Generac has provided innovative design and superior manufacturing.

Generac ensures superior quality by designing and manufacturing most of its generator components, including alternators, enclosures and base tanks, control systems and communications software.

Generac gensets utilize a wide variety of options, configurations and arrangements, allowing us to meet the standby power needs of practically every application.

Generac searched globally to ensure the most reliable engines power our generators. We choose only engines that have already been proven in heavy-duty industrial applications under adverse conditions.

Generac is committed to ensuring our customers' service support continues after their generator purchase.

SD030 | 2.2L | 30 kW

INDUSTRIAL DIESEL GENERATOR SET

EPA Certified Stationary Emergency

STANDARD FEATURES

ENGINE SYSTEM

- Oil Drain Extension Air Cleaner
- Fan Guard
- Stainless Steel Flexible Exhaust Connectio
- · Factory Filled Oil and Coolant
- · Radiator Duct Adapter (Open Set Only)
- Critical Silencer (Enclosed Unit Only) · Engine Coolant Heater

Fuel System

- Fuel Lockoff Solenoid
- Primary Fuel Filter

Cooling System

- Closed Coolant Recovery System
- UV/Ozone Resistant Hoses · Factory-Installed Radiator
- Radiator Drain Extension
- 50/50 Ethylene Glycol Antifreeze

Electrical System

· Battery Charging Alternator Battery Cables

CONTROL SYSTEM

Program Functions

· Programmable Crank Limiter

• 7-Day Programmable Exerciser

• RS-232/485 Communications

Date/Time Fault History (Event Log)

Isochronous Governor Control

Waterproof/Sealed Connectors

· 2-Wire Start Capability

- Battery Tray
- Rubber-Booted Engine Electrical Connections

Digital H Control Panel- Dual 4x20 Display

Special Applications Programmable Logic Controller

· All Phase Sensing Digital Voltage Regulator

· Solenoid Activated Starter Motor

ALTERNATOR SYSTEM

- UL2200 GENprotect[™]
- Class H Insulation Material
- 2/3 Pitch
- Skewed Stator
- Brushless Excitation
- Sealed Bearing
- · Rotor Dynamically Spin Balanced Amortisseur Winding (3-Phase Only)
- Full Load Capacity Alternator
- · Protective Thermal Switch

GENERATOR SET

- Internal Genset Vibration Isolation
- Separation of Circuits High/Low Voltage
- Separation of Circuits Multiple Breakers
- Wrapped Exhaust Piping
- · Standard Factory Testing
- 2 Year Limited Warranty (Standby Rated Units)
- 1 Year Limited Warranty (Prime Rated Units)
- Silencer Mounted in the Discharge Hood (Enclosed Unit Only)

ENCLOSURE (If Selected)

Rust-Proof Fasteners with Nylon Washers to

GENERAC INDUSTRIAL

- High Performance Sound-Absorbing Material (Sound Attenuation Enclosures)
- Gasketed Doors
- · Stamped Air-Intake Louvers
- Upward Facing Discharge Hoods (Radiator and Exhaust

FUEL TANKS (If Selected)

- Stainless Steel Lift Off Door Hinges
- Stainless Steel Lockable Handles

RhinoCoat™ - Textured Polyester Powder Coat Paint

- UL 142/ULC S601
- Double Wall
- · Normal and Emergency Vents
- Sloped Top
- Sloped Bottom
- Factory Pressure Tested Rupture Basin Alarm
- Fuel Level
- Check Valve In Supply and Return Lines
- RhinoCoat™ Textured Polvester Powder Coat Paint
- Stainless Steel Hardware
- Oil Pressure
- Coolant Temperature
- Battery Voltage
- Modbus[®] Protocol

· Audible Alarms and Shutdowns

Not in Auto (Flashing Light)

Auto/Off/Manual Switch

- Single Point Ground
- 16 Channel Remote Trending
- 0.2 msec High Speed Remote Trending
- on the Display

- Power Factor
- Real/Reactive/Apparent Power
- All Phase AC Voltage All Phase Currents

- E-Stop (Red Mushroom-Type)
- NFPA110 Level I and II (Programmable) · Customizable Alarms, Warnings, and Events
- · Predictive Maintenance Algorithm
- Sealed Boards
- Password Parameter Adjustment Protection
- · Alarm Information Automatically Annunciated

Full System Status Display

- Power Output (kW)
- · kW Hours, Total, and Last Run

- Coolant Level
- Engine Speed
- Frequency

Alarms and Warnings

- Oil Pressure
- Coolant Temperature Coolant Level
- Engine Overspeed Battery Voltage
- Alarms and Warnings Time and Date Stamped
- Snap Shots of Key Operation Parameters During Alarms and Warnings
- Alarms and Warnings Spelled Out (No Alarm Codes)



855 Community Dr, Sauk City, WI 53583 608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN Woodcliff Lake, NJ · Bayamon, PR

CONSULTANT:

PREPARED FOR:

GENERAL DYNAMICS Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110

KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepar by me or under my direct supervision and that I am a duly License Professional Engineer under the laws of the State of Connecticut



BURLINGTON FIRE DEPARTMENT FA ID # 10042310

DATE 3/23/2020

19 GEORGE WASHINGTON TURNPIKE 2 of 6 BURLINGTON, CT 060 | 3

GENERAC 30KW GENERATOR **SPECIFICATIONS**

SCALE: NONE

45831 SHEET E-4

GENERAC 30KW GENERATOR SPECIFICATIONS SCALE: NTS

SD030 | 2.2L | 30 kW

INDUSTRIAL DIESEL GENERATOR SET

EPA Certified Stationary Emergency

CONFIGURABLE OPTIONS

ENGINE SYSTEM

- Oil Heater
- O Critical Silencer (Open Set Only)
- O Radiator Stone Guard
- O Level 1 Fan and Belt Guards (Open Set Only)

FUEL SYSTEM

O NPT Flexible Fuel Line

ELECTRICAL SYSTEM

- O 10A UL Listed Battery Charger
- O Battery Warmer

ALTERNATOR SYSTEM

- Alternator Upsizing
- O Anti-Condensation Heater
- Tropical Coating
- O Permanent Magnet Excitation

GENERATOR SET

- Extended Factory Testing O 8 Position Load Center
- O Pad Vibration Isolation

ENGINEERED OPTIONS

ENGINE SYSTEM

- Coolant Heater Isolation Ball Valves
- O Fluid Containment Pan

CONTROL SYSTEM

CIRCUIT BREAKER OPTIONS

- O Main Line Circuit Breaker
- O 2nd Main Line Circuit Breaker
- O Shunt Trip and Auxiliary Contact Electronic Trip Breakers

ENCLOSURE

- Weather Protected Enclosure
- Level 1 Sound Attenuation
- Level 2 Sound Attenuation
- Level 2 Sound Attenuation with Motorized Dampers
- Steel Enclosure
- Aluminum Enclosure O Up to 200 MPH Wind Load Rating (Contact Factory
- for Availability) AC/DC Enclosure Lighting Kit
- O Door Alarm Switch
- Enclosure Heater
- O Damper Alarm Contacts

WARRANTY (Standby Gensets Only)

- 2 Year Extended Limited Warranty
- O 5 Year Limited Warranty
- O 5 Year Extended Limited Warranty O 7 Year Extended Limited Warranty
- O 10 Year Extended Limited Warranty

- ALTERNATOR SYSTEM O 3rd Breaker System
- **GENERATOR SET**
- Special Testing

- **FUEL TANKS** O UL2085 Tank
- Stainless Steel Tanks
- O Special Fuel Tanks Vent Extensions

GENERAC* | INDUSTRIAL

O NFPA 110 Compliant 21-Light Remote Annunciator

O Remote E-Stop (Break Glass-Type, Surface Mount) O Remote E-Stop (Red Mushroom-Type,

Remote E-Stop (Red Mushroom-Type, Flush Mount)

O Remote Relay Assembly (8 or 16)

Oil Temperature Indication and Alarm

CONTROL SYSTEM

Surface Mount)

O 100 dB Alarm Horn

Ground Fault Annunciation

O 10A Engine Run Relay

O 120V GFCI and 240V Outlets

O 8 in (203.2 mm) Fill Extension

O 13 in (330.2 mm) Fill Extension

O 19 in (482.6 mm) Fill Extension

O 5 Gallon Spill Box Return Hose

O Fuel Level Switch and Alarm

O Fire Rated Stainless Steel Fuel Hose

Overfill Protection Valve

O 5 Gallon Spill Box

Tank Risers

12' Vent System

O Remote Communication - Modem

FUEL TANKS (Size On Last Page)

SD030 | 2.2L | 30 kW INDUSTRIAL DIESEL GENERATOR SET

EPA Certified Stationary Emergency

APPLICATION AND ENGINEERING DATA

ENGINE SPECIFICATIONS

| 0 | _ | |
|---|---|--|
| | | |

| Make | Perkins |
|------------------------------------|-------------------------|
| EPA Emissions Compliance | Stationary Emergency |
| EPA Emissions Reference | See Emission Data Sheet |
| Cylinder # | 4 |
| Туре | In-Line |
| Displacement - in ³ (L) | 135 (2.22) |
| Bore - in (mm) | 3.3 (84) |
| Stroke - in (mm) | 3.9 (100) |
| Compression Ratio | 23.3:1 |
| Intake Air Method | Turbocharged |
| Cylinder Head | Cast Iron |
| Piston Type | Aluminum |
| Crankshaft Type | Forged Steel |

Engine Governing

| Governor | Electronic Isochronous |
|-------------------------------------|------------------------|
| Frequency Regulation (Steady State) | ±0.5% |

Lubrication System

| Eddinodion Oyotom | | |
|-----------------------------|-------------|--|
| Oil Pump Type | Gear | |
| Oil Filter Type | Full-Flow | |
| Crankcase Capacity - qt (L) | 11.2 (10.6) | |

Cooling System

| Cooling System Type | Closed Recovery |
|------------------------|-------------------------|
| Water Pump Type | Pre-Lubed, Self Sealing |
| Fan Type | Pusher |
| Fan Speed - RPM | 1,980 |
| Fan Diameter - in (mm) | 18 (457) |

GENERAC | INDUSTRIAL

Fuel System

| Fuel Type | Ultra Low Sulfur Diesel Fuel #2 |
|----------------------------|---------------------------------|
| Fuel Specifications | ASTM |
| Fuel Filtering (Microns) | 5 |
| Fuel Inject Pump | Distribution Injection Pump |
| Fuel Pump Type | Engine Driven Gear |
| Injector Type | Mechanical |
| Fuel Supply Line - in (mm) | 0.31 (7.9) ID |
| Fuel Return Line - in (mm) | 0.2 (4.8) ID |

Engine Electrical System

| System Voltage | 12 VDC |
|----------------------------|------------------------------|
| Battery Charger Alternator | Standard |
| Battery Size | See Battery Index 0161970SBY |
| Battery Voltage | 12 VDC |
| Ground Polarity | Negative |

ALTERNATOR SPECIFICATIONS

| Standard Model | K0035124Y21 | |
|-------------------------------------|---------------|--|
| Poles | 4 | |
| Field Type | Revolving | |
| Insulation Class - Rotor | Н | |
| Insulation Class - Stator | Н | |
| Total Harmonic Distortion | <5% (3-Phase) | |
| Telephone Interference Factor (TIF) | < 50 | |

| Standard Excitation | Brushless | | |
|------------------------------------|--------------------------|--|--|
| Bearings | Single Sealed | | |
| Coupling | Direct via Flexible Disc | | |
| Load Capacity - Standby | 100% | | |
| Prototype Short Circuit Test | Yes | | |
| Voltage Regulator Type | Digital | | |
| Number of Sensed Phases | All | | |
| Regulation Accuracy (Steady State) | ±0.25% | | |

100% EMPLOYEE-OWNED

855 Community Dr, Sauk City, WI 53583 608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN Woodcliff Lake, NJ · Bayamon, PR

PREPARED FOR:



CONSULTANT:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



BURLINGTON FIRE DEPARTMENT FA ID # 10042310

DATE 3/23/2020

19 GEORGE WASHINGTON TURNPIKE 4 of 6 BURLINGTON, CT 060 | 3

GENERAC 30KW GENERATOR **SPECIFICATIONS**

SCALE: NONE

45831 E-4. SHEET

GENERAC 30KW GENERATOR SPECIFICATIONS SCALE: NTS

SD030 | 2.2L | 30 kW INDUSTRIAL DIESEL GENERATOR SET GENERAC INDUSTRIAL

EPA Certified Stationary Emergency

OPERATING DATA

POWER RATINGS

| | Standby | | |
|---------------------------------|---------|-----------|--|
| Single-Phase 120/240 VAC @1.0pf | 30 kW | Amps: 125 | |
| Three-Phase 120/208 VAC @0.8pf | 30 kW | Amps: 104 | |
| Three-Phase 120/240 VAC @0.8pf | 30 kW | Amps: 90 | |
| Three-Phase 277/480 VAC @0.8pf | 30 kW | Amps: 45 | |
| Three-Phase 346/600 VAC @0.8pf | 30 kW | Amps: 36 | |

MOTOR STARTING CAPABILITIES (skVA)

skVA vs. Voltage Dip

| 277/480 VAC | 30% | 208/240 VAC | 30% |
|-------------|-----|-------------|-----|
| K0035124Y21 | 61 | K0035124Y21 | 46 |
| K0040124Y21 | 76 | K0040124Y21 | 58 |
| K0050124V21 | Q2 | K0050124V21 | 75 |

FUEL CONSUMPTION RATES*

| | Diesel - gph (Lph) | | |
|--|---|------------|--|
| Fuel Pump Lift- ft (m) | Percent Load | Standby | |
| 3 (1) | 25% | 1.0 (3.7) | |
| | 50% | 1.4 (5.2) | |
| Total Fuel Pump Flow (Combustion + Return) - gph (Lph) | 75% | 2.0 (7.5) | |
| 16.6 (63) | 100% | 2.8 (10.5) | |
| | * Fuel supply installation must accommodate fuel consumption rates at 100% load. | | |

COOLING

| | | Standby |
|---|---------------------------|----------------|
| Coolant Flow | gpm (Lpm) | 14.9 (56.2) |
| Coolant System Capacity | gal (L) | 2.5 (9.5) |
| Heat Rejection to Coolant | BTU/hr (kW) | 128,638 (136) |
| Inlet Air | scfm (m³/hr) | 2,800 (4,757) |
| Maximum Operating Ambient Temperature | °F (°C) | 122 (50) |
| Maximum Operating Ambient Temperature (Before Derate) | See Bulletin | No. 0199280SSD |
| Maximum Radiator Backpressure | in H ₂ O (kPa) | 0.5 (0.12) |
| | | |

EXHAUST

Exhaust Flow (Rated Output)

Exhaust Temp (Rated Output)

Max. Allowable Backpressure (Post Turbocharger)

COMBUSTION AIR REQUIREMENTS

| | | Stariuby |
|-----|---------------------------------|----------|
| Flo | ow at Rated Power scfm (m³/min) | 88 (2.5) |

| NGIN | F | |
|------|---|--|
| u | _ | |

| | | Standby |
|--------------------------|----------------|-------------|
| Rated Engine Speed | RPM | 1,800 |
| Horsepower at Rated kW** | hp | 49 |
| Piston Speed | ft/min (m/min) | 1,181 (360) |
| BMEP | psi (kPa) | 159 (1,096) |

^{**} Refer to "Emissions Data Sheet" for maximum bHP for EPA and SCAQMD permitting purposes.


Deration – Operational characteristics consider maximum ambient conditions. Derate factors may apply under atypical site conditions. Please contact a Generac Power Systems Industrial Dealer for additional details. All performance ratings in accordance with ISO3046, BS5514, ISO8528, and DIN6271 standards. Prime - See Bulletin 0187510SSB

SD030 | 2.2L | 30 kW

INDUSTRIAL DIESEL GENERATOR SET

EPA Certified Stationary Emergency

DIMENSIONS AND WEIGHTS*






OPEN SET (Includes Exhaust Flex)

GENERAC INDUSTRIAL


| Time - Hours | Capacity - Gal (L) | LxWxH-in (mm) | Weight - Ibs (kg) |
|-----------------|-----------------------|--|----------------------|
| No Tank | - | 76.0 (1,930) x 37.4 (950) x 44.8 (1,138) | 1,641 (745) |
| 19 | 54 (204) | 76.0 (1,930) x 37.4 (950) x 57.8 (1,468) | 2,121 (963) |
| 47 | 132 (501) | 76.0 (1,930) x 37.4 (950) x 69.8 (1,773) | 2,351 (1,067) |
| 75 | 211 (799) | 76.0 (1,930) x 37.4 (950) x 81.8 (2,078) | 2,560 (1,162) |
| 107 | 300 (1,136) | 92.9 (2,360) x 37.4 (950) x 81.8 (2,078) | 2,623 (1,190) |





WEATHER PROTECTED ENCLOSURE Weight - lbs (kg) LxWxH-in (mm) Enclosure Only Capacity


| - Hours | - Gal (L) | | Steel | Aluminum |
|---------|-------------|--|-------|--------------|
| No Tank | - | 94.8 (2,409) x 38.0 (965) x 49.5 (1,258) | | |
| 19 | 54 (204) | 94.8 (2,409) x 38.0 (965) x 62.5 (1,588) | 070 | 0.44 |
| 47 | 132 (501) | 94.8 (2,409) x 38.0 (965) x 74.5 (1,893) | 372 | 241 (110) |
| 75 | 211 (799) | 94.8 (2,409) x 38.0 (965) x 86.5 (2,198) | (170) | (110) |
| 107 | 300 (1,136) | 94.8 (2,409) x 38.0 (965) x 86.5 (2,198) | | |
| | | | | |





LEVEL 1 ACOUSTIC ENCLOSURE

| LLVLL ! | AUUUUIIU | LINGLOGGIIL | | |
|----------|--------------------|---|-------------------------------------|--------------|
| Run Time | Usable Capacity | L x W x H - in (mm) | Weight - Ibs (kg) Enclosure Only | |
| - 110013 | - Gal (L) | | Steel | Aluminum |
| No Tank | - | 112.5 (2,857) x 38.0 (965) x 49.5 (1,258) | | |
| 19 | 54 (204) | 112.5 (2,857) x 38.0 (965) x 62.5 (1,582) | - | |
| 47 | 132 (501) | 112.5 (2,857) x 38.0 (965) x 74.5 (1,893) | 505 (230) | 338 (154) |
| 75 | 211 (799) | 112.5 (2,857) x 38.0 (965) x 86.5 (2,198) | (200) | (134) |
| 107 | 300 (1,136) | 112.5 (2,857) x 38.0 (965) x 86.5 (2,198) | | |
| | | | | |





LEVEL 2 ACOUSTIC ENCLOSURE

| Run Time | Usable Capacity | LxWxH-in (mm) | Weight - Ibs (kg) Enclosure Only | |
|----------|--------------------|--|-------------------------------------|--------------|
| - Hours | - Gal (L) | , | Steel | Aluminum |
| No Tank | - | 94.8 (2,407) x 38.0 (965) x 61.1 (1,551) | | |
| 19 | 54 (204) | 94.8 (2,407) x 38.0 (965) x 74.1 (1,881) | 540 | 0.44 |
| 47 | 132 (501) | 94.8 (2,407) x 38.0 (965) x 86.1 (2,186) | 510 (232) | 341 (155) |
| 75 | 211 (799) | 94.8 (2,407) x 38.0 (965) x 98.1 (2,491) | (202) | (100) |
| 107 | 300 (1,136) | 94.8 (2,407) x 38.0 (965) x 98.1 (2,491) | | |

* All measurements are approximate and for estimation purposes only. Specification characteristics may change without notice. Please contact a Generac Power Systems Industrial Dealer for detailed installation drawings

Generac Power Systems, Inc. | P.O. Box 8 | Waukesha, WI 53189

P: (262) 544-4811 ©2018 Generac Power Systems, Inc. All rights reserved. All specifications are subject to change without notice.

Part No. 10000024842 Rev. B 08/27/18

855 Community Dr, Sauk City, WI 53583 608-643-4100 www.Ramaker.com

Sauk City, WI • Willmar, MN Woodcliff Lake, NJ · Bayamon, PR

PREPARED FOR:



CONSULTANT:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



DATE 3/23/2020

BURLINGTON FIRE DEPARTMENT FA ID # 10042310

7 I 9 GEORGE WASHINGTON TURNPIKE 6 of 6 BURLINGTON, CT 060 | 3

GENERAC 30KW GENERATOR SPECIFICATIONS

SCALE: NONE

45831 E-4.2

Standby 296.6 (8.4)

1.5 (5.1)

892 (478)

scfm (m3/min)

inHg (kPa)

TTS Series Switches

200 Amps 600 VAC



TAS200 TAS200

TAS200

200A Automatic Transfer Switch

1 of 3 2 of 3

The Generac TAS200 Automatic Transfer Switch

Flexibility for multiple application installations

Multiple generator support with 3 source panel

Designed with a 6 inch touch screen controller for improved user interface

Camlock functionality for mobile generator sources



Image used for illustration purposes only.

Features

- STEEL CONSTRUCTION
- NEMA 3R ENCLOSURE WITH HINGED "PADLOCKING" DOORS
- STAINLESS STEEL HARDWARE
- CAMLOCK "QUICK CONNECT" CAPABILITY
- OPERATIONAL STATUS VIEW VIA **6 INCH TOUCH SCREEN**
- TEST FUNCTION FAST TEST & NORMAL TEST
- UL1008 LISTED FOR EMERGENCY SYSTEMS

Optional Features

- EXTENDED WARRANTY
- THREE-PHASE VOLTAGE CONFIGURATIONS

Codes and Standards

Generac products are designed to the following



UL1008, UL508, UL50. CSA C22.2 No. 178



NEC 700, 701 and 702



NEMA 250

Application and Engineering Data

| Dimensions | 24"W x 12"D x 48"H |
|------------------|---|
| Veight | 210 lbs. |
| | Single Chamber with Main Door |
| | Steel |
| | UL Type / NEMA 3R Rated |
| Construction | Powder Coat Finish for Corrosion Resistance |
| | C-UL-US Listed - Automatic Transfer Switch |
| | Stainless Steel Hardware |
| | 3-Point Latching System with Pad-Lockable Handles |
| Maunting Options | Wall |
| Mounting Options | H-frame |
| Installed | Pre-wired alarm terminal strip |

| Electrical Specifications | | | |
|---|--|--|--|
| Voltage/Phase/Amps | 120/240 Single-Phase, 200A 120/208 3-Phase, 200A 120/240 3-Phase, 200A | | |
| Breaker | Eaton 200 amp Utility Breaker | | |
| Dieakei | Eaton 200 amp Generator Breaker | | |
| Maximum RMS Symmetrical Fault Current - Amps | 25k AIC Rated | | |
| Protective Device Continuous Rating (Max) Amp | 200 | | |
| Input to Generator | 350MCM - #6 AWG 350MCM - #6 AWG | | |
| Output to Site | | | |
| Generator Annunciator Connector | Deutsch DTM04-12PA-L012 | | |
| | Generator Run Alarm | | |
| | Generator Fail — Shutdown Alarm | | |
| Alarm Tarminal Doord | Generator Fail – Non Shutdown Alarm | | |
| Alarm Terminal Board | Low Fuel Alarm | | |
| | Generator Theft Alarm | | |
| | AC Utility Fail Alarm | | |

| Camlock Component | | | | | |
|-------------------------------------|---|---------|--|--|--|
| Camlock Component | Shipped loose for multiple installation options | | | | |
| Dimensions | 9" W x 9.4" D x 24.25" H | GENERAC | | | |
| | Single-Phase: Black L1, Red L2, White-Neutral, Green-Ground | | | | |
| 200A Camlock Generator Connection | 3-Phase: Black L1, Red L2, Blue L3, White-Neutral, Green-Ground | | | | |
| 200A Callifock Generator Connection | Uses 4 CH E1016 Male Connectors | | | | |
| | Mating Connector – CH E1016 Female | | | | |







CONSULTANT:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was by me or under my direct supervision and that I am a duly I Professional Engineer under the laws of the State of <u>Conn</u>



| MARK | DATE | DESCRIPTION |
|------|------|-------------|

BURLINGTON FIRE DEPARTMENT FA ID # 10042310

DATE 3/23/2020

7 1 9 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

GENERAC ATS SPECIFICATIONS

SCALE: NONE

45831 E-5 SHEET





INDICATORS AND BUTTONS

- · System Ready indicator
- Standby Operating indicator
- Utility Available indicator
- GEN/UTIL Switch Position indicator
- · TVSS status

- Normal Test button
- Fast Test button
- Return to Normal button
- Reset button
- · Exercising indicator

DETAILS SCREEN

System Settings:

- · System Voltage/Phases:
- 120/240V single phase (standard)
- 120/208V three phase (optional)
- 120/240V three phase (optional)
- Utility Fail Monitor:
- Under Voltage: 75-95% of nominal voltage
- Over Voltage: 105%-125% of nominal voltage
- Pickup (hysteresis): fixed at 5 volts
- Delay time: 0-60s
- Utility Interrupt Delay: 0-60s
- Return to Utility Timer: 1-30 minutes
- Transfer:
- In-phase, or
- Time-Delay-Neutral at 0.0-10.0s in 1 second increments

Engine Settings:

- Engine Warm-up timer: 0-20 minutes
- Generator Load Accept:
- Time-Delay-Neutral at 0.0-10.0s in 1 second increments
- Voltage: 85-95% of nominal
- Frequency: 85-95% of nominal
- Engine Minimum Run Timer: 5-30 minutes
- Engine Cooldown Timer: 0-20 minutes

Exercise Settings:

- Time of day
- · Day of week
- Exercise:
- Exercise with/without load
- Exercise once every 1, 2, or 4 weeks.
- Exercise time-of-day
- Exercise day of week
- Exercise duration: 15-30 minutes

Screen Settings:

- · Brightness & Contrast button
- Screen Calibration button
- Startup/Clean screen

Diagnostics:

- Digital I/O bits status
- Voltage A/D readings

Mimic Diagram:

- System Ready
- Transfer switch position
- Utility available
- Standby available
- Maintenance/Auto switch position
- Generator source TS position
- TVSS status

Generac Power Systems, Inc. • S45 W29290 HWY. 59, Waukesha, WI 53189 • generac.com @2013 Generac Power Systems, Inc. All rights reserved. All specifications are subject to change without notice. Bulletin 0195670SBY-B / Printed in U.S.A. 03/13/13

608-643-4100 www.Ramaker.com Sauk City, WI • Willmar, MN Woodcliff Lake, NJ • Bayamon, PR

855 Community Dr, Sauk City, WI 53583

PREPARED FOR:



CONSULTANT:

GENERAL DYNAMICS

Information Technology, Inc.

GENERAL DYNAMICS 661 MOORE RD STE 110 KING OF PRUSSIA, PA 19406

hereby certify that this plan, specification, or report was prepare by me or under my direct supervision and that I am a duly Licensec Professional Engineer under the laws of the State of <u>Connecticut</u>.



DATE 3/23/2020

BURLINGTON FIRE DEPARTMENT FA ID # 10042310

7 1 9 GEORGE WASHINGTON TURNPIKE BURLINGTON, CT 06013

GENERAC ATS SPECIFICATIONS

SCALE: NONE

45831 E-5. SHEET

Map Block Lot

4-08-73-1

Building #

Section #

1 Account

00037000

Property Information


| Property Location | 719 GEO W | ASHING1 | ON TP | KE |
|-------------------|------------|----------|-------|-------|
| Owner | BURLINGT | ON TOW | N OF | |
| Co-Owner | | | | |
| Mailing Address | 200 SPIELM | IAN HWY | , | |
| | BURLINGT | ON | СТ | 06013 |
| Land Use | 9032 | Mun Fire | е | |
| Land Class | E | | | |
| Zoning Code | СВ | | | |
| Census Tract | | | | |

| Street Index | 4500 |
|------------------|-------------|
| Acreage | 1.88 |
| Utilities | Well,Septic |
| Lot Setting/Desc | Rural Level |
| Additional Info | |

Photo



Sketch




Primary Construction Details

| Year Built | 1987 |
|--------------------|--------------|
| Stories | 1 |
| Building Style | Fire Station |
| Building Use | Ind/Com |
| Building Condition | VG |
| Occupancy | 1.00 |
| Extra Fixtures | 0 |
| Bath Style | NA |
| Kitchen Style | NA |
| AC Type | |
| Heating Type | Hot Water |
| Heating Fuel | Oil |

| Bedrooms | 0 |
|-------------------|--------------|
| Full Bathrooms | 0 |
| Half Bathrooms | 0 |
| Total Rooms | 0 |
| Roof Style | Wood Truss |
| Roof Cover | Asphalt |
| Interior Floors 1 | Concrete |
| Interior Floors 2 | Vinyl |
| Exterior Walls | Vinyl Siding |
| Exterior Walls 2 | Brick Veneer |
| Interior Walls | Drywall |
| Interior Walls 2 | NA |

(*Industrial / Commercial Details)

| (*Industrial / | Commercial Details) |
|------------------|---------------------|
| Building Desc. | Mun Fire |
| Building Grade | Average +20 |
| Heat / AC | HEAT/AC SPLIT |
| Frame Type | MASONRY |
| Baths / Plumbing | AVERAGE |
| Ceiling / Wall | SUS-CEIL/MN WL |
| Rooms / Prtns | AVERAGE |
| Wall Height | 14.00 |
| First Floor Use | NA |
| | |
| | |
| - | |
| | |



Property Listing Report

BURLINGTON TOWN OF

Map Block Lot

4-08-73-1

Building #

Section #


1 Account

00037000

| Valuation Summary (Assessed value = 70% of Appraised Value) | | | Sub Areas | | | |
|---|-------------|-------------|-----------|--------------------|--------------------|---------------------|
| Item | Appraised | | Assessed | Subarea Type | Gross Area (sq ft) | Living Area (sq ft) |
| Buildings | 1003500 | | 702450 | First Floor | 9880 | 9880 |
| Extras | 27100 | | 18970 | Cathedral | 5968 | 0 |
| Improvements | | | | Basement, Finished | 3912 | 0 |
| Outbuildings | 40700 | | 28490 | Porch, Enclosed | 160 | 0 |
| Land | 157100 | | 109970 | | | |
| Total | 1228400 | | 859880 | | | |
| Outbuilding ar | nd Extra Fe | eatures | | | | |
| Туре | | Description | | | | |
| Paving-Asphalt | | 10000 S.F. | | | | |
| Light w/Pole | | 5 UNITS | | | | |
| Air Condition | | 8500 UNITS | | | | |
| Shed Good | | 400 S.F. | | | | |
| Open Porch | | 1040 S.F. | | | | |
| | | | | | | |
| | | | | | | |
| | | | | | | |
| | | | | Total Area | 19920 | 9880 |
| Sales History | | | | | | |
| Owner of Record | | | | Book/ Page Sale | Date Sale Price | ce |

00091/0528

0



ATTACHMENT 2



Town of Burlington



Theodore C. Scheidel
First Selectman

Mary Ann Schwarzmann James A. Chard Robert R. Sheriffs Theodore C. Shafer

Board of Selectmen

TO:

Michael Vollono, Chairman,

Planning & Zoning Commission

FROM:

Theodore C. Scheidel, Jr., First Selectr

DATE:

August 9, 2005

RE:

New Cingular Wireless PCS, LLC

Application - Replacement Tower - Fire Station Property

Please find below a Statement of Consensus of the Board of Selectmen arrived at on August 8, 2005 concerning the above-referenced application.

The Board strongly recommends that the Planning & Zoning Commission give favorable consideration to this matter as it continues an existing critical use of the Property for municipal purposes, exchanges an old, weaker tower structure with a newer, safer and longer lasting tower of forty additional feet, surmounted by new municipal fire, police and highway antennas at no cost to the Town. This exchange will have a positive effect on the emergency radio reception in Burlington. Also attached is a suggested "Report" for your consideration.

TCS/ejp Attachment

BOARD OF SELECTMEN STATEMENT OF CONSENSUS AUGUST 8, 2005



WHEREAS, the Town of Burlington ("Town") owns certain property located at 719 George Washington Turnpike also known as Lot No. 73-1 on Assessor's Map 4-8 (the "Property"); and

WHEREAS, the Property is currently used for municipal purposes, is the site of the Burlington Fire Department headquarters which maintains a communications tower and associated municipal antennas and equipment with Verizon Wireless as a tenant; and

WHEREAS, New Cingular Wireless PCS, LLC, a telecommunications company licensed to provide cellular telephone service throughout most of Connecticut, including the Town of Burlington, is desirous of replacing the existing municipal communications tower by: constructing for (and at no cost to) the Town a 180 ft. monopole tower adjacent to the existing tower site; installing new equipment and antennas thereon for the Town's police, fire and public works; moving Verizon Wireless's antennas to the replacement tower; installing its own antenna; dismantling the lattice tower (leaving it for the Volunteer Fire Department); and, entering into a lease with the Town for utilization of a portion of the replacement tower and a portion of the Property to establish a cellular telecommunications facility; and

WHEREAS, the installation of a replacement tower at the Property will fulfill the Town's needs including additional space for rental of antenna space for other communications company equipment, will enhance the public safety through improved emergency service communications and will improve cellular telephone service to the residents of the Town, all of which constitutes a continuing use of the Property for municipal purposes deemed in the best interest of the community of the Town of Burlington; and

IT IS A UNANIMOUS CONSENSUS, That the Board of Selectmen approves the proposed application by New Cingular Wireless PCS, LLC to replace the existing municipal lattice tower with a monopole on the same Property with new municipal antennas and equipment and the lease agreement for rental of space on the municipal tower for New Cingular's antennas. The First Selectman may sign said lease agreement on behalf of the Town, as approved by the Town attorney, provided, however, that the Board of Selectmen receive a favorable report from the Burlington Planning and Zoning Commission pursuant to Section 8-24 of the Connecticut General Statutes and Department of Public Health permits necessary for this activity.

Dated this Pth day of August, 2005.

Theodore C. Scheidel, First Selectman

Accounting Office 860.675.4960

Town Clerk 860.673.2108

Assessor 860.673.3901

Tax Collector 860.673.0717

Building Inspector 860.673.1000

Highway Department 860.673.2439

Parks + Recreation 860.673.7361 fax 860.675.5038

> Town Fax 860.675.9312

Bristol Press Classified Department 99 Main Street Bristol, CT 06010

To Whom It May Concern:

Please publish the following legal notice once upon receipt. Thank you.

NOTICE OF VOTES/NOTICE OF DECISIONS

The Burlington Planning & Zoning Commission made the following decisions at the meeting of August 25, 2005:

A motion was made by Alden and seconded by Dumais to approve Application No. 1870, for Modification of Site Plan submitted by The Town of Burlington subject to the following conditions:

That the Applicant secure all necessary permits from the Department of Health; and

That a risk assessment of the property be performed by the Town or its insurer to determine if any fencing around the Tower or the Site is required.

IN FAVOR, Vollono, Alden, Dumais, Halpin, Fanning, Perkins and van Noordennen. ABSTAINED – None. OPPOSED – None.

A motion was made by Alden and seconded by Dumais to approve Application No. 1870 for Modification of Site Plan submitted by the Town of Burlington pursuant to Connecticut General Statues Section 8-24.

IN FAVOR, Vollono, Alden, Fanning, Dumais, Perkins, Halpin and van Noordennen. ABSTAINED – None. OPPOSED – None.

The Burlington Planning and Zoning Commission, by Michael Vollono, Chairman, dated this 25th day of August, 2005.

200 Spielman Highway Burlington, Connecticut 06013-1735

Cc: Town Clerk File No. 1870





CONNECTICUT SITING COUNCIL

Ten Franklin Square, New Britain, CT 06051

Phone: (860) 827-2935 Fax: (860) 827-2950

E-Mail: siting.council@ct.gov

www.ct.gov/csc

November 18, 2019

Aidan Griffin Site Acquisition Consultant Centerline Communications, LLC 750 W. Center Street, Suite 301 West Bridgewater, MA 02379

RE: EM-CING-020-191015 - New Cingular Wireless PCS, LLC (AT&T) notice of intent to modify an existing telecommunications facility located at 719 George Washington Turnpike, Burlington, Connecticut.

Dear Mr. Griffin:

The Connecticut Siting Council (Council) hereby acknowledges your notice to modify this existing telecommunications facility, pursuant to Section 16-50j-73 of the Regulations of Connecticut State Agencies with the following conditions:

- Prior to AT&T's antenna installation, the antenna mount modifications shall be installed in accordance with the Mount Analysis prepared by Hudson Design Group, LLC dated April 1, 2019 and stamped and signed by Daniel Hamm;
- Within 45 days following the completion of equipment installation, AT&T shall provide documentation certified by a Professional Engineer that its installation complied with the Mount Analysis;
- 3. Any deviation from the proposed modification as specified in this notice and supporting materials with the Council shall render this acknowledgement invalid;
- 4. Any material changes to this modification as proposed shall require the filing of a new notice with the Council;
- 5. Within 45 days after completion of construction, the Council shall be notified in writing that construction has been completed;
- Any nonfunctioning antenna and associated antenna mounting equipment on this facility owned and operated by AT&T shall be removed within 60 days of the date the antenna ceased to function;
- 7. The validity of this action shall expire one year from the date of this letter; and
- 8. The applicant may file a request for an extension of time beyond the one year deadline provided that such request is submitted to the Council not less than 60 days prior to the expiration.



The proposed modifications including the placement of all necessary equipment and shelters within the tower compound are to be implemented as specified here and in your notice dated October 10, 2019 and additional information received on October 30, 2019. The modifications are in compliance with the exception criteria in Section 16-50j-72 (b) of the Regulations of Connecticut State Agencies as changes to an existing facility site that would not increase tower height, extend the boundaries of the tower site by any dimension, increase noise levels at the tower site boundary by six decibels or more, and increase the total radio frequencies electromagnetic radiation power density measured at the tower site boundary to or above the standards adopted by the Federal Communications Commission pursuant to Section 704 of the Telecommunications Act of 1996 and by the state Department of Energy and Environmental Protection pursuant to Connecticut General Statutes § 22a-162. This facility has also been carefully modeled to ensure that radio frequency emissions are conservatively below state and federal standards applicable to the frequencies now used on this tower.

This decision is under the exclusive jurisdiction of the Council. Please be advised that the validity of this action shall expire one year from the date of this letter. Any additional change to this facility will require explicit notice to this agency pursuant to Regulations of Connecticut State Agencies Section 16-50j-73. Such notice shall include all relevant information regarding the proposed change with cumulative worst-case modeling of radio frequency exposure at the closest point of uncontrolled access to the tower base, consistent with Federal Communications Commission, Office of Engineering and Technology, Bulletin 65. Thank you for your attention and cooperation.

Sincerely,

Melanie A. Bachman Executive Director

Whithere !-

MAB/IN/lm

c: The Honorable Theodore C. Shafer, First Selectman, Town of Burlington Gerald Burns, Zoning Enforcement Officer, Town of Burlington

ATTACHMENT 3

CERTIFICATION

I hereby certify that on the 31st day of March 2020, a copy of AT&T's Exempt Modification Request to the Connecticut Siting Council was sent by electronic mail to the chief elected official and the planning and zoning department of the municipality in which the facility is located as well as by first class mail to the property owner and tower/facility owner.

Dated: March 31, 2020

Cuddy & Feder LLP 445 Hamilton Ave, 14th Floor White Plains, NY 10601 Attorneys for: New Cingular Wireless PCS, LLC (AT&T)

Lucia Chrocchio