

STATE OF CONNECTICUT

CONNECTICUT SITING COUNCIL

Ten Franklin Square New Britain, Connecticut 06051 Phone: (860) 827-2935 Fax: (860) 827-2950

August 6, 2002

Michele G. Briggs Manager of Real Estate SNET Mobility LLC 500 Enterprise Drive, 3rd Floor Rocky Hill, CT 06067

RE:

EM-CING-033-020722 - Southwestern Bell Mobile Systems, LLC notice of intent to modify an existing telecommunications facility located at 179 Shunpike Road, Cromwell, Connecticut.

Dear Ms. Briggs:

At a public meeting held on August 1, 2002, the Connecticut Siting Council (Council) acknowledged your notice to modify this existing telecommunications facility, pursuant to Section 16-50j-73 of the Regulations of Connecticut State Agencies.

The proposed modifications are to be implemented as specified here and in your notice dated July 22, 2002. The modifications are in compliance with the exception criteria in Section 16-50j-72 (b) of the Regulations of Connecticut State Agencies as changes to an existing facility site that would not increase tower height, extend the boundaries of the tower site, increase noise levels at the tower site boundary by six decibels, and increase the total radio frequencies electromagnetic radiation power density measured at the tower site boundary to or above the standard adopted by the State Department of Environmental Protection pursuant to General Statutes § 22a-162. This facility has also been carefully modeled to ensure that radio frequency emissions are conservatively below State and federal standards applicable to the frequencies now used on this tower.

This decision is under the exclusive jurisdiction of the Council. Any additional change to this facility will require explicit notice to this agency pursuant to Regulations of Connecticut State Agencies Section 16-50j-73. Such notice shall include all relevant information regarding the proposed change with cumulative worst-case modeling of radio frequency exposure at the closest point of uncontrolled access to the tower base, consistent with Federal Communications Commission, Office of Engineering and Technology, Bulletin 65. Any deviation from this format may result in the Council implementing enforcement proceedings pursuant to General Statutes § 16-50u including, without limitation, imposition of expenses resulting from such failure and of civil penalties in an amount not less than one thousand dollars per day for each day of construction or operation in material violation.

Thank you for your attention and cooperation.

Very truly yours.

Mortimor A Galata

Chairman

MAG/laf

c: Honorable Stanley A. Terry, Jr., First Selectman, Town of Cromwell Frederic Curtin, Zoning Enforcement Officer, Town of Cromwell Cromwell Fire District Christopher B. Fisher, Esq, Cuddy & Feder & Worby LLP Stephen J. Humes, Esq., LeBoeuf, Lamb, Greene & MacRae

Town of Cromwell

AUG 0 2 2002

CONNECTICUT

SITING COUNCIL

Memo

To:

Stan Terry, First Selectman

From:

Craig Minor, Town Planner

Date:

07/25/02

Re:

Southwestern Bell Mobile Proposal to Modify Cromwell Fire District

Telecommunications Tower at 179 Shunpike Road

Thank you for forwarding to me the letter from Southwestern Bell Mobile (SBC) of July 22, 2002 regarding the Cromwell Fire District's tower at 179 Shunpike Road. My comments are as follows.


As you know, the Connecticut Siting Council has near-total jurisdiction over approving the construction and modification of telecommunication towers. Local municipalities are given the opportunity to comment and request modifications to plans.


This is a proposal for SBC to add its antennae to the existing tower. These new antennae would be located approximately 2/3 of the way up the tower. The proposal also involves SBC constructing an additional equipment room 12' x 38' in size, and a new generator on a pad set into (excavated from) the side of the hill. See attached drawings submitted by SBC.

The additional antennas will be no more noticeable than the existing "Voicestream" and "AT&T" antennas, so I don't have any concern there. However, the new equipment room will be only 20' from the back of Lot 12 on Black Birch Drive, and the excavated generator pad will be about 40' from the back of Lots 9 and 10 on Twin Oaks Drive. The plan doesn't indicate any plantings or other screening and I am not familiar with how dense the existing vegetation is on Lots 9, 10 and 12...

If they haven't already done so, I recommend SBC be directed by either the Connecticut Siting Council or the Cromwell Fire District to discuss this plan with the owners of these lots and to discuss the need, if any, for screening.

CC: P&Z Cromwell Fire District file









Southwestern Bell Mobile Systems, LLC

500 Enterprise Drive

Rocky Hill, Connecticut 06067-3900

Phone: (860) 513-7700 Fax: (860) 513-7190

Michele G. Briggs Manager of Real Estate

July 22, 2002

Honorable Stanley A. Terry, Jr., First Selectman Cromwell Town Hall 41 West Street Cromwell, Connecticut 06416

Re: Notice of Exempt Modification – Existing Telecommunications Tower Facility at 179 Shunpike Road, Cromwell, Connecticut

Dear Mr. Terry:

Southwestern Bell Mobile Systems, LLC ("SBMS") (formerly SNET Mobility, LLC formerly Springwich Cellular Limited Partnership) intends to install telecommunications antennas and associated equipment at an existing multicarrier telecommunications tower at 179 Shunpike Road in Cromwell, Connecticut.

The facility is owned and operated by the Cromwell Fire District ("Fire District"), with offices at 322 Main Street, Cromwell, CT 06416. The Fire District and SBMS have entered into an agreement concerning the modification and sharing of the facility.

A Notice of Exempt Modification has been filed with the Connecticut Siting Council as required by Regulations of Connecticut State Agencies ("R.C.S.A.") Section 16-50j-73. Please accept this letter as notification to the Town of Cromwell under Section 16-50j-73 of construction which constitutes an exempt modification pursuant to R.C.S.A. Section 16-50j-72(b)(2).

The attached letter fully sets forth the SBMS proposal. However, if you have any questions or require any further information on the plans for the site or the Siting Council's procedures, please contact the undersigned or Mr. Derek Phelps, Executive Director of the Connecticut Siting Council, at (860) 827-2935.

Sincerely, Michele D. Bruggs / She

Michele G. Briggs Manager of Real Estate

Enclosure

EM-CING-033-020722





Southwestern Bell Mobile Systems, LLC

500 Enterprise Drive Rocky Hill, Connecticut 06067-3900

Phone: (860) 513-7700 Fax: (860) 513-7190

Michele G. Briggs Manager of Real Estate

July 22, 2002



Mr. Mortimer A. Gelston, Chairman Connecticut Siting Council 10 Franklin Square New Britain, Connecticut 06051 CONNECTICUT SITING COUNCIL

Re: Notice of Exempt Modification – Existing Telecommunications Tower Facility at 179 Shunpike Road, Cromwell, Connecticut

Dear Chairman Gelston:

Southwestern Bell Mobile Systems, LLC ("SBMS") (formerly SNET Mobility, LLC; formerly Springwich Cellular Limited Partnership) intends to install telecommunications antennas and associated equipment at an existing multicarrier telecommunications tower at 179 Shunpike Road in Cromwell, Connecticut.

The facility is owned and operated by the Cromwell Fire District ("Fire District"), with a principal address of 322 Main Street, Cromwell, CT 06416. The Fire District erected the 170-foot high, self-supporting lattice tower in 1999 for the purpose of meeting its and the Town's communications needs as well as generating revenue from co-located commercial carriers.

The Fire District and SBMS have agreed to the proposed shared use of this tower pursuant to mutually acceptable terms and conditions. The Fire District has authorized SBMS to apply for all necessary permits, approvals, and authorizations which may be required for the proposed shared use of this facility.

SBMS is licensed by the Federal Communications Commission ("FCC") to provide cellular mobile telephone service in the Hartford, CT Metropolitan Statistical Area, which includes the area to be served by SBMS' proposed installation. The public need for cellular service has been predetermined by the FCC.

Please accept this letter as notification to the Council, pursuant to R.C.S.A. Section 16-50j-73, of construction which constitutes an exempt modification pursuant to R.C.S.A. Section 16-50j-72(b)(2). In compliance with R.C.S.A. Section 16-50j-73, a copy of this letter is being sent to the First Selectman of the Town of Cromwell.

Attached to this notice are a site location map, a proposed site plan, the proposed tower profile, and structural information.

The existing facility is located west of Shunpike Road (Route 3), with coordinates of 41° 37' 23.6" N and 72° 40' 44.5" W (NAD 83). The site is a wooded hilltop with a clearing for a large, buried water storage tank owned by the Fire District. The tower and associated equipment buildings lie immediately north of the water tank. The entire Fire District parcel is surrounded by a chain link security fence topped with barbed wire; however, the Tower facility is not separately fenced.

The 170 foot tower was designed to support multiple antenna arrays. At the present time, the Tower is shared by the Town of Cromwell (fire, police, ambulance), AT&T Wireless ("AT&T"), and VoiceStream Wireless ("VoiceStream").

- The Town of Cromwell operates redundant whip antenna arrays with centerlines at 180 feet above ground level ("AGL") and 142 feet AGL. The lower array is held in reserve should there be a failure of the upper array, and there is no reason to expect that they would ever operate simultaneously.
- AT&T operates 12 panel antennas with centerlines at 160 feet AGL.
- VoiceStream operates six panel antennas with centerlines at 125 feet AGL.

On January 25, 2001, the Council approved tower sharing application TS-SCLP-033-010104 in which SBMS' predecessor-in-interest presented a plan for additional shared use of the Fire District's tower. The original plan called for the existing equipment building to accommodate our telecommunications equipment and for an existing indoor power generator to be replaced by an outdoor generator. Although no construction took place pursuant to the approved TS-SCLP-033-010104, it was subsequently determined that the existing building was, in reality, inadequate to accommodate anticipated telecommunications development at the site.

As shown on the attached site plan, SBMS now proposes to construct an additional 12' x 38' equipment building just west of the existing building for equipment belonging to SBMS and future carrier(s). It will be a prefabricated structure designed to match the existing building.

As before, a power generator presently occupying the westernmost room of the original building, as well as an outdoor propane tank used to fuel the existing generator, will be removed from the facility. SBMS will install a replacement electric power generator (Kohler diesel-powered) on a concrete pad to be built just west of the new building.

For its antenna array, SBMS proposes to install up to twelve CSS DUO4-8670 panel antennas, approximately 48 inches in height, with the center of radiation approximately 114 feet above ground level AGL. Associated equipment to be installed on the tower are up to six ADC Co. dual-band tower top amplifiers ("TTA's"; small metal boxes approximately 26 pounds apiece) immediately behind the antennas, and one Nokia Emergency-911 location measurement unit antenna ("LMU"; approximately 9 inches high and 9 ounces in weight). A small GPS antenna will be mounted to the top of the equipment building.

With the "GSM" configuration, SBMS will broadcast up to:

- 2 channels, 296 Watts ERP, 880 894 MHz;
- 2 channels, 427 Watts ERP, 1930 -1935 MHz.

A structural analysis report (attached) shows that the tower currently is not structurally capable of supporting the proposed SBMS telecommunications equipment. However, a plan for strengthening the tower has been developed (attached), and SBMS will not install its equipment on the tower until it has been re-enforced in accordance with these specifications.

Statutory Considerations

5 , t

The changes to the Cromwell tower facility do not constitute a modification as defined in Connecticut General Statutes ("C.G.S.") Section 16-50i(d) because the general physical characteristics of the facility will not be significantly changed or altered. Rather, the planned changes to the facility fall squarely within those activities explicitly provided for in R.C.S.A. Section 16-50j-72(b)(2) because they will not result in any substantial adverse environmental effect.

- 1. The height of the overall structure will be unaffected.
- 2. The proposed changes will not affect the property boundaries. All new construction will take place on property owned by Fire District and within the existing fence.
- 3. The proposed additions will not increase the noise level at the existing facility by six decibels or more. Except for noise resulting from construction, the only additional sound will be from equipment cooling systems.
- 4. Operation of the additional antennas will not increase the total radio frequency electromagnetic radiation power density, measured at the tower base, to or above the standard adopted by the State of Connecticut and the FCC. The "worst-case" exposure calculation in accordance with FCC OET Bulletin No. 65 (1997) for a point of

interest at the base of the tower in relation to the operation of the currently proposed antenna array is as follows:

Company	Centerline Height (feet)	Frequency (MHz)	Number of Channels	Power Per Channel (Watts)	Power Density [†] (mW/cm ²)	Standard Limits (mW/cm²)	Percent of Limit
AT&T *	160	D: 1945 E: 1985	8	100	0.0112	1.0000	1.12
Town of Cromwell *	142 ±		Cumulative				1.30
VoiceStream *	125	1930 - 1950	4	268	0.0247	1.0000	2.47
SBMS GSM	114	881 - 894	2	296	0.0164	1.5867	1.03
SBMS GSM	114	1931 - 1935	2	427	0.0236	1.0000	2.36
Total							8.29%

^{*} Power density parameters taken from VoiceStream's application to the Council in TS-VoiceStream-033-000609, approved June 20, 2000. Town data utilize lower set of redundant antennas for worst-case analysis. Note for VoiceStream calculation that ERP = EIRP / 1.64.

As the table demonstrates, the cumulative "worst-case" exposure would be approximately 8.3 % of the ANSI/IEEE standard, as calculated for mixed frequency sites. Total power density levels resulting from SBMS' use of the tower facility would thus remain well within applicable standards.

For the foregoing reasons, SBMS respectfully submits that proposed changes to implement expanded shared use at the Cromwell site constitute an exempt modification under R.C.S.A. Section 16-50j-72(b)(2).

Please feel free to call me at (860) 513-7700 with questions concerning this application. Thank you for your consideration in this matter.

Respectfully yours,

Michele G. Briggs 5LL

1 1


Michele G. Briggs


Manager of Real Estate


Enclosures


cc: Honorable Stanley A. Terry, Jr., First Selectman, Town of Cromwell


[†] Please note that the standard power density equation provided by the Council in its memo of January 22, 2001 incorporates a ground reflection factor of 2.56 (i.e., the square of 1.6) as described in FCC OET Bulletin No. 65.













PARTIAL ELEVATION


SCALE: 1/4'' = 1'-0''






	ELESS CROMWELL COMMUNORCEMENT OF DIAGONAL I			SA
BE	Maguine			
MGCI No: 15364	DATE: July 22, 2002	DRAWN BY: JAM	MAGUIRE	
CONTRACT No:	DESIGNED BY: JAM	CHK'D BY: KAT	<u>Qroot</u>	
		<u></u>		1251

Structural Analysis Report For Cingular Wireless





170' Communications Tower Cromwell, Connecticut

MGI 15364.1251

July 15, 2002



Maguire Group Inc.
Architects/Engineers/Planners

One Court Street New Britain, Connecticut 06051 Maguire Group Inc. Architects, Engineers, Planners One Court Street New Britain, Connecticut 06051 (860) 224-9141

STRUCTURAL ANALYSIS REPORT Of 170' COMMUNICATIONS TOWER CROMWELL, CONNECTICUT

EXECUTIVE SUMMARY:

Maguire Group performed a structural analysis of the 170 foot tall self supporting tower located in Cromwell, Connecticut. The analysis was performed to determine the effect of installing 12 Cingular DOU4-8670 Cellular antennas and 6 ADC Cleargain amplifiers mounted on a low-profile platform at an elevation of 115 feet.

The proposed installation is intended to replace the original design set of 12 Allgon 7184 antennas at elevation 115 feet. Our analysis indicates the tower and its foundation are not capable of supporting the proposed antenna/amplifier system at elevation 115 feet, in addition to the antenna installations at the four other antenna elevations, as originally designed. However, the tower can be reinforced to carry the additional loading.

INTRODUCTION:

The tower is a 3 sided, self supporting lattice truss on a drilled pier foundation. The analysis was based on information included in a letter from Paul J. Ford and Company to ARCNET, including a sketch (Appendix "A") of the tower as built, together with antennas, platforms and cables proposed as of May 4, 2000. We were also provided with cut sheets of the newly proposed antennas and amplifiers. Maguire engineers did not visit the tower site. The cut sheets of the proposed antennas and amplifiers are shown in Appendix "B".

This analysis was conducted with the following antenna loads:

Elevation	115 ft	125 ft	135 ft	160 ft	170 ft
	12 CSS DOU4	6 RR90-12	1 TXRX	12 Allgon 7184	1 TXRX
			1 PD201-7		1 PD201-7
			2 PD1142		2 PD1142
			3 PD620		3 PD620
Cables	(12) - 1-5/8"	(6) - 1-5/8"	7 various dia.	(12) - 1-5/8"	7 various dia.

- Platforms were located at the same elevations as the antennas.
- Cables were not modified from the revised design. Forty four cables of various diameters were evenly distributed on the three faces of the tower.
- (12) DOU4-8679 panel antennas and 6 amplifiers were located at elevation 115'.

TOWER ANALYSIS:

The structural analysis was done according to TIA/EIA-222-F (EIA), Structural Standards for Steel Antenna Towers and Antenna Supporting Structures. EIA requires two loading conditions to be evaluated to determine the tower's capacity. The higher stresses resulting from the two cases is used to calculate the tower capacity:

- Case I = Wind Load (without ice) + Tower Dead Load (controls)
- Case 2 = 0.75 Wind Load (with ice) + Ice Load + Tower Dead Load

Allowable stresses of tower members were increased by one-third according to TIA/EIA Paragraph 3.1.1.1.

Dead weights, ice loads, and wind load of the truss, antennas, platforms and cables were "hand calculated" on Mathcad sheets. These modeling calculations are shown in Appendix "C". An 85 mile per hour wind was applied according to section 16 of the TIA/EIA Standard for Middlesex County, Connecticut. For load case 2, one-half inch of radial ice covered the entire structure and all appurtenances, according to Annex A, 2.3.1.2 C.

Member properties and loads generated on the Mathcad sheets were input into a general purpose frame analysis program, RISA 3D, distributed by RISA Technologies. Results from the RISA 3D stiffness analysis are shown in Appendix "D".

Axial and bending forces were determined for each member of the model. These forces were fed back to the Mathcad sheet (Appendix "C", sheets 16 through 20) to compute axial stresses. The axial stresses were compared to allowable stresses, taking local buckling into account according to Paragraph 3.1.15.1 of TIA/EIA.

TOWER ANALYSIS RESULTS:

Our analysis determined the tower cannot support the proposed antenna/amplifier loads in addition to the loading proposed at the four other antenna elevations.

The following table summarizes the capacity of the tower legs and diagonals based on axial stresses. Note that the diagonals between 0 and 20 feet have a C/D ratio of 0.97 and the diagonals between 80 and 120 feet have a C/D ratio of 0.90.

	Capacity/Demand			
Elevation	Leg Members	Diagonal Members		
150' – 170'	2.32			
120' – 150'	1.75	1.54		
80' – 120'	1.08	0.90		
60' - 80'	1.16	1.09		
20' – 60'	1.07	1.05		
0' – 20'	1.19	0.97		

FOUNDATION ANALYSIS

As no soils information is available, the foundation is not analyzed.

CONCLUSIONS AND SUGGESTIONS:

As detailed above, our analysis indicates that the existing tower is not capable of supporting the antenna loading proposed by Cingular. We recommend reinforcing the six diagonal members located between elevations 80' and 90'.

LIMITATIONS:

This report is based on the following assumptions:

- 1. Tower is properly installed and maintained.
- 2. All members are in new condition.
- 3. All required members are in place.
- 4. All bolts are in place and are properly tightened.
- 5. Tower is in plumb condition.
- 6. All members are galvanized.
- 7. All tower members were properly designed, detailed, fabricated, and installed and have been properly maintained since erection.
- 8. Record sketches accurately reflect tower dimensions and height.

Maguire Group is not responsible for any modifications completed prior to or hereafter which Maguire is not or was not directly involved. Modifications include but are not limited to:

- 1. Adding or relocating antennas.
- 2. Installing antenna mounting gates or side arms.
- 3. Extending tower.

Maguire hereby states that this document represents the entire report and that it assumes no liability for any factual changes that may occur after the date of this report. All representations, recommendations, and conclusions are based upon the information contained and set forth herein. If you are aware of any information which conflicts with that which is contained herein, or you are aware of any defects arising from original design, material, fabrication, or erection deficiencies, you should disregard this report and immediately contact Maguire. Maguire Group disclaims all liability for any representation, recommendation, or conclusion not expressly stated


Structural Analysis Report

For

Cingular Wireless

IUL 22 2002

CONNECTICUT SITING COUNCIL





170' Communications Tower Cromwell, Connecticut

MGI 15364.1251

July 15, 2002



Maguire Group Inc.
Architects/Engineers/Planners

One Court Street New Britain, Connecticut 06051 Maguire Group Inc. Architects, Engineers, Planners One Court Street New Britain, Connecticut 06051 (860) 224-9141

STRUCTURAL ANALYSIS REPORT Of 170' COMMUNICATIONS TOWER CROMWELL, CONNECTICUT

EXECUTIVE SUMMARY:

Maguire Group performed a structural analysis of the 170 foot tall self supporting tower located in Cromwell, Connecticut. The analysis was performed to determine the effect of installing 12 Cingular DOU4-8670 Cellular antennas and 6 ADC Cleargain amplifiers mounted on a low-profile platform at an elevation of 115 feet.

The proposed installation is intended to replace the original design set of 12 Allgon 7184 antennas at elevation 115 feet. Our analysis indicates the tower and its foundation are not capable of supporting the proposed antenna/amplifier system at elevation 115 feet, in addition to the antenna installations at the four other antenna elevations, as originally designed. However, the tower can be reinforced to carry the additional loading.

INTRODUCTION:

The tower is a 3 sided, self supporting lattice truss on a drilled pier foundation. The analysis was based on information included in a letter from Paul J. Ford and Company to ARCNET, including a sketch (Appendix "A") of the tower as built, together with antennas, platforms and cables proposed as of May 4, 2000. We were also provided with cut sheets of the newly proposed antennas and amplifiers. Maguire engineers did not visit the tower site. The cut sheets of the proposed antennas and amplifiers are shown in Appendix "B".

This analysis was conducted with the following antenna loads:

Elevation	115 ft	125 ft	135 ft	160 ft	170 ft
	12 CSS DOU4	6 RR90-12	1 TXRX	12 Allgon 7184	1 TXRX
			1 PD201-7		1 PD201-7
			2 PD1142		2 PD1142
			3 PD620		3 PD620
Cables	(12) - 1-5/8"	(6) - 1-5/8"	7 various dia.	(12) - 1-5/8"	7 various dia.

- Platforms were located at the same elevations as the antennas.
- Cables were not modified from the revised design. Forty four cables of various diameters were evenly distributed on the three faces of the tower.
- (12) DOU4-8679 panel antennas and 6 amplifiers were located at elevation 115'.

TOWER ANALYSIS:

The structural analysis was done according to TIA/EIA-222-F (EIA), Structural Standards for Steel Antenna Towers and Antenna Supporting Structures. EIA requires two loading conditions to be evaluated to determine the tower's capacity. The higher stresses resulting from the two cases is used to calculate the tower capacity:

- Case I = Wind Load (without ice) + Tower Dead Load (controls)
- Case 2 = 0.75 Wind Load (with ice) + Ice Load + Tower Dead Load

Allowable stresses of tower members were increased by one-third according to TIA/EIA Paragraph 3.1.1.1.

Dead weights, ice loads, and wind load of the truss, antennas, platforms and cables were "hand calculated" on Mathcad sheets. These modeling calculations are shown in Appendix "C". An 85 mile per hour wind was applied according to section 16 of the TIA/EIA Standard for Middlesex County, Connecticut. For load case 2, one-half inch of radial ice covered the entire structure and all appurtenances, according to Annex A, 2.3.1.2 C.

Member properties and loads generated on the Mathcad sheets were input into a general purpose frame analysis program, RISA 3D, distributed by RISA Technologies. Results from the RISA 3D stiffness analysis are shown in Appendix "D".

Axial and bending forces were determined for each member of the model. These forces were fed back to the Mathcad sheet (Appendix "C", sheets 16 through 20) to compute axial stresses. The axial stresses were compared to allowable stresses, taking local buckling into account according to Paragraph 3.1.15.1 of TIA/EIA.

TOWER ANALYSIS RESULTS:

Our analysis determined the tower cannot support the proposed antenna/amplifier loads in addition to the loading proposed at the four other antenna elevations.

The following table summarizes the capacity of the tower legs and diagonals based on axial stresses. Note that the diagonals between 0 and 20 feet have a C/D ratio of 0.97 and the diagonals between 80 and 120 feet have a C/D ratio of 0.90.

	Capacity/Demand			
Elevation	Leg Members	Diagonal Members		
150' — 170'	2.32			
120' – 150'	1.75	1.54		
80' - 120'	1.08	0.90		
60' - 80'	1.16	1.09		
20' – 60'	1.07	1.05		
0' – 20'	1.19	0.97		

FOUNDATION ANALYSIS

As no soils information is available, the foundation is not analyzed.

CONCLUSIONS AND SUGGESTIONS:

As detailed above, our analysis indicates that the existing tower is not capable of supporting the antenna loading proposed by Cingular. We recommend reinforcing the six diagonal members located between elevations 80' and 90'.

LIMITATIONS:

This report is based on the following assumptions:

- 1. Tower is properly installed and maintained.
- 2. All members are in new condition.
- 3. All required members are in place.
- 4. All bolts are in place and are properly tightened.
- 5. Tower is in plumb condition.
- 6. All members are galvanized.
- 7. All tower members were properly designed, detailed, fabricated, and installed and have been properly maintained since erection.
- 8. Record sketches accurately reflect tower dimensions and height.


Maguire Group is not responsible for any modifications completed prior to or hereafter which Maguire is not or was not directly involved. Modifications include but are not limited to:

- 1. Adding or relocating antennas.
- 2. Installing antenna mounting gates or side arms.
- 3. Extending tower.

Maguire hereby states that this document represents the entire report and that it assumes no liability for any factual changes that may occur after the date of this report. All representations, recommendations, and conclusions are based upon the information contained and set forth herein. If you are aware of any information which conflicts with that which is contained herein, or you are aware of any defects arising from original design, material, fabrication, or erection deficiencies, you should disregard this report and immediately contact Maguire. Maguire Group disclaims all liability for any representation, recommendation, or conclusion not expressly stated

APPENDIX "A"

Tower Sections
And
Revised Design



BY PIROD INCORPORATED IN 1999

PAUL J. FORD AND COMPANY
S I R U C T U R A L E N G I N E E R S
250 East Brood Stroot State 500 Columbus, Oxio 43215
PH (614)-221-6679
FAX (614)-221-0166

Paga	1	Of	3
ву	KRH	Dala	5-5-2000
Job No	3430	00-4	
Revision No	'	Data _	
Tower	EXISTING 1	70 FT SE	LF SUPPORT
Location	CROMWEUL,	CONNEC	ПСИТ
Sīta	ROCKY HIL	L - ∦ 059	С
EIA Min	85 MPH/74	MPH +	1/2" RADIAL ICE
Copacily	100 MPH/8	3 MPH +	1/2" RADIAL ICE
	According to	ANSI/EI/	1-222-F 1996

COAX 1 1/4" (2)-7/8" (2)-7/8"

7/8

1 5/8"

7/8"

(2)-1/2* (2)-1/2* 1/2*

(6)-1 5/8"

(12)-15/8

1 1/4"

(12)-15/8

ASTM 5'-0" <u>%</u> A36 A325 ANTENNA LIST 170 ANTENNA NO. 2,3 TOP PD620 (2) PD620 (2) PD1142 STRAIGHT TOP 1/80 TOP 7/8 TOP PD201-7 (1) TX/RX ANTENNA 9-ARM HALO MOUNT TOP 150' TOP (12) ALLGON 7184
(3) PIROD T-FRAMES 菱 8-19 160 160 á 135' PD820 20 140 135' (2) PD620 135' (2) PD1142 21,22 9 23,24 135' P0201-7 25 2 135' (1) TX/RX ANTENNA 26 135' ANTENNA PLATFORM n 125' (6) EMS RR90-17 125' (6) EMS RR90-17 125' 16' LOW PROFILE PLATFORM 115' (12) ALLGON 7184 115' (3) PIROD T-FRAMES 120 27-32 \mathbb{C} (6)-176 33-44 n 3/4" STEP RUNGS ONE FACE ONLY FROM 150" TO 170" 2 100 - COAX ASSUMED TO BE EQUALLY DISTRIBUTED TO ALL THREE TOWER FACES 3 80' 3/4.0 13x3x5/16 -14 3/16 (C) SOLID ROO LEG 60' REDUIRED 5/16 5/8"¢ SUB-GIRT 1/2 (J)-2"a 40 1/2" P OR 5/8" # ~ SUB DIAGONAL 1 × MPICAL (6)-1 **LEGS** <u>`</u> C (EL 150' TO 0') 20 20 <u>.</u> ~ 9 INTERIOR BRACING ×× (3)-2- NONE REQUIRED - Σ 0 BOLTS **BOL19**

LEGS DIAGONALS

TRUSS

20'-0

BOLT

ANCHOR

BRACE 1 SPLICE

GIRTS

FOUNDATION REACTIONS

UPLIFT: 220 KIPS HAX ONE LEG

COMP: KIPS MAX ONE LEG

KIPS MAX ONE LEG HORIZ: . 24

APPENDIX "B"

Proposed Antennas And Amplifiers

RAD. CENTER: 114± FT. (AGL) Top Of Existing Town ____188' A.G.L Antennas (Typ.) Top Of Existing AT&T Antennos (Typ.) —163' A.G.L <u>Top Of Existing Town</u> — 153' A.G.L Whip Antennas (Typ.) Top Of Existing Support Poles 127' A.G.L PROPOSED CINGULAR PANEL ANTENNAS W/ 6 AMPLIFIERS - 114'± A.G.L Existing Lattice -Tower Existing Police/Fire Ice Bridge (Typ.) Existing Modular Shelter Existing Voicestream Wireless Power/Telco-PROPOSED 8' SUPPORT Cabinet FRAME W/ (3) AUTOMATIC TRANSFER SWITCHES Existing Meter Panel-Existing Transformer -PROPOSED EQUIPMENT SHELTER Existing Retaining Wall **PROPOSED GENERATOR** Top Of Existing Access Road NORTH SITE NAME: CROMWELL FIRE DEPARTMENT

DESIGN

Maguire Group Inc.

Architects Engineers Planners

One Court Street New Britoin, Connecticut 06051

ADDRESS:

179 SHUNPIKE ROAD CROMWELL, CT 06416

DRAWN: MDJ | CHECKED: GMP | SCALE: N.T.S.

THIS DRAWING AND ALL DATA CONTAINED HEREIN IS FOR INFORMATIONAL PURPOSES ONLY, NOT INTENDED FOR DESIGN OR CONSTRUCTION USE. ALL DATA SHOULD BE VERIFIED

x cingular

MGI#: 15364

TASK #: 1244

DATE: 4/02/02



Directing our energies for you

Dual Band Antenna DUO4-8670

Electrical Specifications

Frequency Range
Gain
Electrical Downtilt Options
VSWR
Front-to-Back at Horizon
Upper Side Lobe Suppression
Elevation Beam (3-dB Points)
Azimuth Beam (3-dB Points)
Polarization
Impedance
Power Input Rating
Intermodulation Specification

Cellular

806-900 MHz
12.2 dBd ±0.5 dB
0, 2 or 6 Degrees
1.35:1 Maximum
> 25 dB
<-16 dB
15 Degrees (±1 Degree)
86 Degrees (±4 Degrees)
Vertical
50 Ohms
500 Watts

PCS

250 Watts

<153dBc (<-110dBm at 2x20W) <153dBc (<-110dBm at 2x20W)

1850-1990 MHz
17.0 dBi ±0.5 dB
0 or 4 Degrees
1.35:1 Maximum
> 30 dB
<-18 dB
7 Degrees (±1 Degree)
70 Degrees (±4 Degrees)
Vertical
50 Ohms

Mechanical Specifications

Input Connectors
Antenna Dimensions
Weight
Lightning Protection
RF Distribution

Radome
Weatherability
Radome Water Absorption
Environmental
Wind Survival
Wind Loading (at 120 mph)
Mounting Brackets
Mechanical Downtilt Range
Clamps/Bolts


Two 7/16 DIN Connectors (Silver Finish)
48 x 14 x 9 Inches (LxWxD)
31.4 lbs Maximum (Includes Brackets)
Direct Ground
Cellular: Silver Plated Copper Alloy
PCS: Printed Microstrip Substrate
Ultra High-Strength Luran
UV Stabilized, ASTM D1925
ASTM D570, 0.45%
MIL-STD-810E
Tested to 150 mph

180 Front, 110 Side, 237 Rear (lbs)
Fits 2.5 to 3 Inch Schedule 40 Pipe
0-12 Degrees in 1 Degree Increments
Hot Dip Galvanized Steel/Stainless Steel

Ordering Information

Model DUO4- 8670-xy Options

x=Electrical Downtilt at 800 MHz in Degrees (0, 2 or 6) y=Electrical Downtilt at 1900 MHz in Degrees (0 or 4)



APPENDIX "C"

Proposed Tower
Analysis



Project: <u>Cinqular Wireless</u> Subject: <u>Cromwell, Connecticut</u>

170' Lattice Tower

CROUP Comp:

Description:

170 foot Self Supporting Tower, on spead footing foundation.

Design Code:

TIA/EIA-222-F

Material properties:

Legs: A500 Gr.B Steel: $F_y := 50 \text{ksi}$ Bracing Steel: A36 $F_{yx} := 36 \text{ksi}$

Ice Density (2.1.2.2): $\gamma_{ice} := 56pcf$ $E_s = 29000 \, ksi$

Design Criteria:

Overstress Factor for structures under 700 ft (3.1.1.1): $K_0 := \frac{7}{7}$

Ice Thickness (Annex A 2.3.1.2C): Ti := .5in

Allowable Combined Bending and Axial Stress for Compact Sections: $F_B := .6F_y$

Geometry:

(Input sections from bottom to top)

 $F_B = 30 \, \text{ksi}$

Elevation at the top of the pier or footing: $El_D := Oin$

Elevation at Top of Section: $EL_t := (20 60 80 120 150 170)^T$ ft

Elevation at Bottom of Section: $EL_{b} := EL_{t} \\ k2 \\ k2-1$ $EL_{b}^{T} = (0.00 \ 20.00 \ 60.00 \ 80.00 \ 120.00 \ 150.00)$ ft

Top of Sloped section elevation: $EL_{ss} := 150 \text{ft}$ $ind_{ss} := if \left(EL_{ss} = EL_{t}, k, 0\right)$ $ind_{ss}^{T} = (0 \ 0 \ 0 \ 5 \ 0)$

Number of sloped sections: $n := max(ind_{ss})$ n = 5

Mid-point elevation of each section: $z := .5 \cdot \left(EL_t + EL_b \right)$ $z^T = (10 \ 40 \ 70 \ 100 \ 135 \ 160) ft$

Leg spread at the base: Sp1:= 20ft

Joint coordinates at the base:

 $x_1 := -.5 \cdot Sp_1$ $x_1 = -10.000 \text{ ft}$ $y_1 := x_1 \cdot tan(30 \text{ deg})$ $y_1 = -5.774 \text{ ft}$

 $x_2 := .5 \cdot Sp_1$ $x_2 = 10.000 \, ft$ $y_2 := x_1 \cdot tan(30 deg)$ $y_2 = -5.774 \, ft$

 $x_3 := Oft$

уз:= x₂·tan(60deg) + y₁

 $y_3 = 11.547 ft$

Leg spread at the top of sloped section: $Sp_{n+1} := 5ft$

$$x'_1 := -.5 \cdot Sp_{n+1}$$
 $x'_1 = -2.500 \text{ ft}$ $y'_1 := x'_1 \cdot tan(30 \text{ deg})$ $y'_1 = -1.443 \text{ ft}$

$$y_1' = -1.443 \, ft$$

$$x'_2 := .5 \cdot Sp_{n+1}$$
 $x'_2 = 2.500 \, ft$ $y'_2 := x'_1 \cdot tan(30 deg)$ $y'_2 = -1.443 \, ft$

$$y_2' = -1.443 f$$

$$x'_3 := Oft$$

$$y'_3 = 2.887 \text{ ft}$$

 $Sp_i := Sp_1 - \frac{EL_b}{EL_t} \cdot (Sp_1 - Sp_{n+1})$ Intermediate leg spreads:

Straight Sections: $Sp_{i+1} := Sp_{n+1}$

 $Sp^{T} = (20.0 18.0 14.0 12.0 8.0 5.0 5.0) ft$

(3)2-1/4" ϕ , (3)2" ϕ , $(3)1-3/4\phi$ ", $(3)1-1/2\phi$ ", $(3)1-1/4\phi$ ", 1-3/4" ϕ

Width of sub leg to wind: $B_L := (2.25 \ 2 \ 1.75 \ 1.5 \ 1.25 \ 1.75)^T$ in

Number of sub legs in the section: $N_L := (3 \ 3 \ 3 \ 3 \ 1)^T$

Sub Girt Length: $L_{sq} := (12 \ 12 \ 12 \ 12 \ 12 \ \epsilon)^{1}$ in

 $y_{sg} := \frac{1}{3} \cdot L_{sg} \cdot sin(60 deg)$ $y_{sg}^{T} = (3.46 \ 3.46 \ 3.46 \ 3.46 \ 3.46 \ 0.00) in$

Gross Section Area: $G_{N_k} := \overline{\left(\frac{EL_t - EL_b}{k}\right) \cdot \left(\frac{Sp_k + Sp_{k+1}}{.5} + L_{sg_k}\right)} \quad G_{N_k} = (400 680 280 440 225 100) \text{ ft}$

With Ice: $G_{N_i} := \overline{\left(EL_{t_k} - EL_{b_k} \right) \cdot \left[\left(Sp_k + Sp_{k+1} \right) \cdot .5 + L_{sg_k} + 2T_i \right]}$ $G_{N_i}^T = (402\ 683\ 282\ 443\ 228\ 102) \, \mathrm{ft}^2$

Straight leg length: $L_{L_i} := EL_{t_i} - EL_{b_i}$

Sloped Legs: $L_{L_i} := \left(EL_{t_i} - EL_{b_i}\right) \cdot sec\left(\frac{y_3 - y_3}{EL_{t_i}}\right)$ $L_{L_i}^T = (20.03 \ 40.07 \ 20.03 \ 40.07 \ 30.05 \ 20.00) \text{ ft}$

Leg sub-girt diameter : B_{sq}:= .625in

Sub girt spacing: $S_{sq} := (14.1 \ 14.1 \ 14.1 \ 14.1 \ 14.1 \ \epsilon)^{\dagger}$ in

Number of sub girts per section: $N_{sg_k} := if \left[L_{sg_k} = \epsilon \cdot in, 0, floor \left(\frac{L_k}{S_{sg}} \right) \right]$ $N_{sg}^{T} = (17 \ 34 \ 17 \ 34 \ 25 \ 0)$

Leg sub diagonal: $B_{sd} := (.625 .625 .5 .5 .5 .5 0.)^T$ in

Length of sub-diagonal: $L_{sd} := \sqrt{L_{sq}^2 + S_{sq}^2}$

 $L_{sd}^{T} = (18.5 \ 18.5 \ 18.5 \ 18.5 \ 18.5 \ 0.0) ir$

Leg wind area: $A_L := \overline{\left[N_L \cdot \left[L_L \cdot B_L + N_{sg} \cdot \left(L_{sg} \cdot B_{sg} + L_{sd} \cdot B_{sd}\right)\right]\right]}$ $A_L^T = (2595 \ 4830 \ 2117 \ 3873 \ 2609 \ 420) in^2$

 $\text{Leg wind area with ice: } A_{L.i} := \boxed{ N_L \cdot \left(B_L + 2T_i \right) + N_{sg} \cdot \left(B_{sg} + 2T_i \right) + L_{sd} \cdot \left(B_{sd} + 2T_i \right) \right) }$

 $A_{L,i}^{T} = (4873 9385 4394 8428 5980 660) in'$

Leg x-section Area: $A_{Lx} := (N_L \cdot .25 \cdot \pi \cdot B_L^2)$ $A_{Lx}^T = (11.93 \ 9.42 \ 7.22 \ 5.30 \ 3.68 \ 2.41) \text{ in}^2$

Sub Girt:
$$A_{sgx} := \overline{\left(N_L \cdot .25 \cdot \pi \cdot B_{sg}^2\right)}$$
 Diagonal: $A_{sdx} := \overline{\left(N_L \cdot .25 \cdot \pi \cdot B_{sd}^2\right)}$

Leg wt: $Wt_L := \gamma_s \cdot \overline{\left[\left[A_{Lx} \cdot L_L + N_{sg} \cdot \left(A_{sgx} \cdot L_{sg} + A_{sdx} \cdot L_{sd}\right)\right]\right]}$
 $Wt_L^T = (949 \ 1556 \ 598 \ 934 \ 532 \ 164) \ Ibs$
 $wt_L := \overline{Wt_L + L_L}$
 $wt_L^T = (47 \ 39 \ 30 \ 23 \ 18 \ 8) \ plf$

lce per foot to sub legs:
$$ice_{sl} := \frac{\pi}{4} \cdot \left[\left(B_L + 2T_i \right)^2 - B_L^2 \right] \cdot \gamma_{ice}$$
 $ice_{sl}^T = (1.68 \ 1.53 \ 1.37 \ 1.22 \ 1.07 \ 1.37) \, plf$

lce per foot to sub girts:
$$ice_{sg} := \frac{\pi}{4} \cdot \left[\left(B_{sg} + 2T_i \right)^2 - B_{sg}^2 \right] \cdot \gamma_{ice}$$
 $ice_{sg} = 0.69 \, pH$

lce per foot to sub diags:
$$ice_{sd} := \frac{\pi}{4} \cdot \left(\left[\left(\left(B_{sd} + 2T_i \right) \right)^2 - B_{sd}^2 \right] \right) \cdot \gamma_{ice}$$
 $ice_{sd}^T = (0.69 \ 0.69 \ 0.61 \ 0.61 \ 0.61 \ 0.31) \, ph$

$$\text{Leg Ice Wt: Ice}_{L} := \underbrace{\left(\overrightarrow{\text{lice}_{\text{SI}} \cdot \text{L}_{L}}\right) + \left(\overrightarrow{\text{N}_{\text{Sg}} \cdot \text{ice}_{\text{Sg}} \cdot \text{L}_{\text{Sg}}}\right) + \left(\overrightarrow{\text{N}_{\text{Sg}} \cdot \text{ice}_{\text{Sd}} \cdot \text{L}_{\text{Sd}}}\right)}_{\text{Ice}_{L}} \cdot 362 \quad \text{Ice}_{L} \cdot \text{Ice$$

Number of Cross Braces per Section: $N_x := (2 \ 4 \ 2 \ 4 \ 3 \ 8)^T$

Leg sections unbraced lengths:
$$L_u := L_L \div N_x$$

$$L_{\rm u}^{\rm T}$$
 = (120.2 120.2 120.2 120.2 30.0) in

Leg moment of inertia:
$$I_{Lx} := \left(\frac{N_L \cdot \pi}{64} \cdot B_L^4 + \frac{6 \cdot \pi}{4} \cdot B_L^2 \cdot y_{sg}^2 \right)$$

$$I_{Lx}^T = (290 \ 229 \ 175 \ 128 \ 89 \ 0) \text{ in}^4$$

$$I_{\rm l,x}^{\rm T} = (290\ 229\ 175\ 128\ 89\ 0) {\rm in}^4$$

$$x_{sg} := \frac{L_{sg}}{2}$$
 $x_{sg}^{T} = (6.00 \ 6.00 \ 6.00 \ 6.00 \ 6.00 \ 0.00)$ in

$$I_{Ly} := \left(\frac{N_L \cdot \pi}{64} \cdot B_L^4 + \frac{2 \cdot \pi}{4} \cdot B_L^2 \cdot x_{sg}^2 \right)$$

$$I_{Ly} = \left(\frac{1}{290} \cdot B_L^4 + \frac{2 \cdot \pi}{4} \cdot B_L^2 \cdot x_{sg}^2 \right)$$

$$I_{Ly} = \left(\frac{1}{290} \cdot B_L^4 + \frac{2 \cdot \pi}{4} \cdot B_L^2 \cdot x_{sg}^2 \right)$$

$$I_{Ly}^{T} = (290 \ 229 \ 175 \ 128 \ 89 \ 0) in^{4}$$

Leg radius of gyration:
$$r_L := \sqrt{I_{Lx} + A_{Lx}}$$

$$r_L^T = (4.93 \ 4.92 \ 4.92 \ 4.91 \ 4.91 \ 0.44)$$
 in

Global slenderness ratio:
$$KL_{-G} := L_{II} \div r_{I}$$

Global slenderness ratio:
$$KL_r_G := L_u + r_L$$
 $KL_r_G = (24.4 \ 24.4 \ 24.4 \ 24.5 \ 24.5 \ 68.6)$

Element radius of gyration:
$$r_e := .25B_l$$

Element radius of gyration:
$$r_e := .25B_L$$
 $r_e^T = (0.56 \ 0.50 \ 0.44 \ 0.38 \ 0.31 \ 0.44)$ in

Local slenderness ratio:
$$KL_{r_l} := S_{sg} \div r_e$$
 $KL_{r_l} = (25.1 \ 28.2 \ 32.2 \ 37.6 \ 45.1 \ 0.0)$

$$KL_{-1}^{T} = (25.1 \ 28.2 \ 32.2 \ 37.6 \ 45.1 \ 0.0)$$

Governing slenderness ratio:
$$KL_r_L := max \left(KL_r_L , KL_r_G \right)$$
 $KL_r_L ^T = (25.1 \ 28.2 \ 32.2 \ 37.6 \ 45.1 \ 68.6)$
Effective K-Factor to convert global to local slenderness ratio: $K_{eff} := \frac{KL_r_L}{KL_r_G}$

$$K_{eff}^{T} = (1.03 \ 1.16 \ 1.32 \ 1.54 \ 1.84 \ 1.00)$$

Diagonals:

Diagonal sections: L4x4x1/4", L3.5x3.5x5/16, L3x3x5/16, L3x3x3/16, L3x3x3/16, T/8" rod

Sections with angle diagonals: $LD := (1 \ 1 \ 1 \ 1 \ 1 \ 0)^T$ $Id_k := if(LD_k = 1, k, 0)$ Ld := max(Id) jd := Ld + 1..nn

Width of diagonal to wind: $B_D := (4 \ 3.5 \ 3 \ 3 \ 3 \ .875)^{1}$ in

Thickness of diagonal section: Tp:= (.25 .3125 .3125 .1875 .1875 .1875) in

Diagonal x-sectional area: $A_{Dx} := (1.94 \ 2.09 \ 1.78 \ 1.09 \ 1.09 \ .601)^T \text{ in}^2$

Diagonal weight per foot: $wt_d := (6.6 7.2 6.1 3.71 3.71 2.05)^T$ plf

Radius of gyration: $r_x := \begin{pmatrix} 1.25^{"} & 1.08^{"} & .922^{"} & .939^{"} & .939^{"} & .25 B_{D_6} \end{pmatrix}^T$

Radius of gyration: $r_z := (.795^{\circ} .69^{\circ} .589^{\circ} .596^{\circ} .596^{\circ} .25 B_{D_g})^{T}$

Length of diagonal:
$$L_{D_i} := cos \left(\frac{y_3 - y_3'}{EL_{t_n}} \right)^{-1} \cdot \sqrt{\left[\left(\frac{L_{t_i}}{N_{x_i}} \right)^2 + \left(Sp_i - \frac{Sp_i - Sp_{i+1}}{2 \cdot N_{x_i}} - L_{Sg_i} \right)^2} \right]}$$

$$L_{D_{j}} := \sqrt{\left(L_{L_{j}} \div N_{X_{j}}\right)^{2} + \left(Sp_{j} - B_{L_{j}}\right)^{2}}$$

 $L_D^T = (21.1 19.3 16.0 14.5 12.0 5.5) ft$

Angle with Horizontal: $\alpha_{D_k} := asin \left[L_k + \left(N_x \cdot L_{D_k} \right) \right]$

α_D = (28.4 31.2 38.6 43.6 56.9 27.2)deg

Member Offsets: Offset := $L_{sq} \div (2 \cdot cos(\alpha_D))$

 $Offset^{T} = (6.8 \ 7.0 \ 7.7 \ 8.3 \ 11.0 \ 0.0) in$

$$LD_{1_{k}} := \frac{Sp_{k} - L_{Sg_{k}} - B_{L_{k}}}{\left(LD_{k} + 1\right) \cdot cos\left(\alpha_{D_{k}}\right)}$$

$$KL_{r_{Z_{k}}} := LD_{1_{k}} + r_{Z_{k}}$$

$$KL_{r_z}^{\mathsf{T}} = (161 \ 171 \ 168 \ 151 \ 127 \ 300)$$

$$LD_{x} := .5 \cdot \left(LD_{1} + L_{D} \right)$$

$$KL_{r_{x_k}} := LD_{x_k} + r_{x_k}$$

$$KL_{-r_{x}}^{T} = (152 \ 162 \ 158 \ 141 \ 117 \ 300)$$

Total diagonal wind area of section: $A_D := 2 \cdot (N_x \cdot L_D \cdot B_D)$

$$A_D^T = (28.1 \ 45.1 \ 16.0 \ 29.1 \ 17.9 \ 6.4) \, \text{ft}^2$$

With ice:
$$A_{D,i} := 2 \cdot \overline{\left[N_x \cdot L_D \cdot \left(B_D + 2T_i \right) \right]}$$
 $A_{D,i}^T = (35.1 \ 58.0 \ 21.4 \ 38.8 \ 23.9 \ 13.7) \, \text{ft}^2$

Total weight of diagonals:

$$Wt_D := 6 \cdot (wt_d \cdot N_x \cdot L_D)$$

$$Wt_D := 6 \cdot (wt_d \cdot N_x \cdot L_D)$$
 $Wt_D^T = (1669 \ 3341 \ 1174 \ 1294 \ 799 \ 537) lbs$

Ice per ft for L sections: $ice_D := \gamma_{ice} \cdot \left(4 \cdot B_D \cdot T_i + \pi \cdot T_i^2 + 2T_i \cdot T_D \right)$

for Round sections:
$$ice_{D_{jd}} := \frac{\pi}{4} \cdot \overline{\left(\left(\frac{\beta_{D_j} + 2T_i}{jd} \right)^2 - \left(\frac{\beta_{D_j}}{jd} \right)^2 \right)} \cdot \gamma_{ice}$$
 $ice_{D}^T = (3.51 \ 3.15 \ 2.76 \ 2.71 \ 2.71 \ 0.84) plf$

$$ice_D^T = (3.51 \ 3.15 \ 2.76 \ 2.71 \ 2.71 \ 0.84) pl$$

Total ice weight in a section: $lce_D := 2.3 (N_x \cdot ice_D \cdot L_D)$

$$lce_D^T = (889 \ 1461 \ 531 \ 946 \ 584 \ 220) lbs$$

Horizontals:

Horzontal Sections: L3"x3"x3/16"
$$B_H := (0\ 0\ 0\ 0\ 3\ .875)^T$$
 in $T_H := .1875$ in $r_h := .296$ in

$$wt_h := (0 \ 0 \ 0 \ 3.71 \ 2.05)^T plf$$

Length of Horizontals:
$$L_H := (0 \ 0 \ 0 \ Sp_5 \ Sp_6)^T$$
 $L_H^T = (0 \ 0 \ 0 \ 8 \ 5) \text{ ft}$

$$N_{H} := \begin{pmatrix} 0 & 0 & 0 & 0 & N_{x_{5}} & N_{x_{6}} \end{pmatrix}^{T}$$
 $N_{H}^{T} = \begin{pmatrix} 0 & 0 & 0 & 0 & 3 & 8 \end{pmatrix}$

Total horizontal wind area of section:
$$A_H := (N_H \cdot B_H \cdot L_H)$$

with ice:
$$A_{H,i} := \overline{\left[N_{H} \cdot \left(B_{H} + 2T_{i}\right) \cdot L_{H}\right]}$$
 $A_{H,i}^{T} = (0.0 \ 0.0 \ 0.0 \ 0.0 \ 8.0 \ 6.2) \text{ ft}^{2}$

 $A_{H}^{T} = (0.0 \ 0.0 \ 0.0 \ 0.0 \ 6.0 \ 2.9) ft^{2}$

Total Weight:
$$Wt_H := 3 \cdot (wt_h \cdot N_H \cdot L_H)$$
 $Wt_H^T = (0 \ 0 \ 0 \ 267 \ 246) \text{ lbs}$

lce per ft for L sections:
$$ice_H := \gamma_{ice} \cdot \underbrace{\left(4 \cdot B_H \cdot T_i + \pi \cdot T_i^2 + 2 T_i \cdot T_H\right)}_{\text{T}} \quad \text{ice}_H = (0.38 \ 0.38 \ 0.38 \ 0.38 \ 2.71 \ 1.06) \, plf$$

for Round sections:
$$ice_{H_{6}} := \frac{\pi}{4} \cdot \left[\left(B_{D_{6}} + 2T_{i} \right)^{2} - \left(B_{D_{6}} \right)^{2} \right] \cdot \gamma_{ice}$$
 $ice_{H}^{T} = (0.38 \ 0.38$

Total ice weight in a section:
$$lce_H := 3 \overline{\left(N_H \cdot lce_H \cdot l_H\right)}$$
 lce_H = (0 0 0 0 195 101) lbs

Cable and Linear Appurtenance Gravity Loads

Nominal Size	1/2"	7/8"	1-1/4"	1-5/8"
diameter	$D_4 := 0.58$ "	D ₇ := 1.11"	D ₁₀ := 1.55"	D ₁₃ := 1.98"
wt/ft	w ₄ := .25plf	w7 := .54plf	w ₁₀ := .66plf	w ₁₃ := 1.04pif

At elev. 170, we have five 7/8", one 1-1/4", and one 1-5/8" cable.

At elev. 160, we add twelve 1-5/8" cables

At Elev 135, we add five 1/2" cables, one 7/8", and one 1-1/4".

At elev. 125, we add six 1-5/8" cables

$$W_{cbl_{6}} := L_{L_{2}} \cdot (5 \cdot w_{7} + w_{10} + w_{13}) + 10' \cdot 12 \cdot w_{13}$$

$$W_{cbl_{2}} := L_{L_{2}} \cdot (6 \cdot w_{7} + 5 w_{4} + 2 \cdot w_{10} + 31 \cdot w_{13})$$

$$W_{cbl_{5}} := L_{L_{5}} \cdot \left(5 \cdot w_{7} + w_{10} + 13 \cdot w_{13}\right) + 15' \cdot \left(w_{10} + w_{7} + 5w_{4}\right) + 5' \cdot 6 \cdot w_{13} \qquad W_{cbl_{5}} := L_{L_{5}} \cdot \left(6 \cdot w_{7} + 5w_{4} + 2 \cdot w_{10} + 31 \cdot w_{13}\right)$$

$$W_{cbl}_{4} := L_{L_{4}} \cdot \left(6 \cdot w_{7} + 5w_{4} + 2 \cdot w_{10} + 19 \cdot w_{13}\right) + 35' \cdot 12w_{13}$$

$$W_{cbl}_{4} := (762 \ 1525 \ 762 \ 1461 \ 575 \ 213) I$$

Dead loads (3) applied to the top of each section:
$$\left(\frac{1}{3} \cdot W_{cbl} \right)^{l} = (254 \ 508 \ 254 \ 487 \ 192 \ 71) \text{ lbs}$$

 $W_{cbl_3} := L_{L_3} \cdot (6 \cdot w_7 + 5w_4 + 2 \cdot w_{10} + 31 \cdot w_{13})$

$$v_4 := \frac{\pi}{4} \cdot \left[\left(D_4 + 2 \cdot T_i \right)^2 - D_4^2 \right]$$

$$v_7 := \frac{\pi}{4} \cdot \left[\left(D_7 + 2 \cdot T_i \right)^2 - D_7^2 \right]$$

$$v_{10} := \frac{\pi}{4} \cdot \left[\left(D_{10} + 2 \cdot T_i \right)^2 - D_{10}^2 \right]$$

$$v_{10} := \frac{\pi}{4} \cdot \left[\left(D_{10} + 2 \cdot T_i \right)^2 - D_{10}^2 \right]$$

$$v_{13} := \frac{\pi}{4} \cdot \left[\left(D_{13} + 2 \cdot T_i \right)^2 - D_{13}^2 \right]$$

$$|ce_{cbl}_{6} := \left[L_{L_{6}} \cdot \left(5v_{7} + v_{10} + v_{13} \right) + 10' \cdot 12 \cdot v_{13} \right] \cdot \gamma_{ice}$$

$$|ce_{cbl_5} := \left[L_{L_5} \cdot \left(5v_7 + v_{10} + 13 \cdot v_{13} \right) + 15' \cdot \left(v_{10} + v_7 + 5v_4 \right) + 5' \cdot 6 \cdot v_{13} \right] \cdot \gamma_{ice}$$

$$|ce_{cbl}|_4 := \left[L_4 \cdot \left(6 \cdot v_7 + 5 v_4 + 2 \cdot v_{10} + 19 \cdot v_{13} \right) + 35' \cdot 12 v_{13} \right] \cdot \gamma_{ice}$$

$$|ce_{cbl_3} := L_{L_3} \cdot (6 \cdot v_7 + 5v_4 + 2 \cdot v_{10} + 31 \cdot v_{13}) \cdot \gamma_{ice}$$

$$lce_{cbl_2} := L_{L_2} \cdot (6 \cdot v_7 + 5v_4 + 2 \cdot v_{10} + 31 \cdot v_{13}) \cdot \gamma_{ice}$$

$$|ce_{cbl_1}| := L_{L_1} \cdot (6 \cdot v_7 + 5v_4 + 2 \cdot v_{10} + 31 \cdot v_{13}) \cdot \gamma_{ice}$$

$$|ce_{cb}|^{\mathsf{T}} = (1175 \ 2351 \ 1175 \ 2259 \ 906 \ 335)|bs$$

lce loads (3) applied to the top of each section: $\frac{|ce_{cbl}|^T}{3} = (392 784 392 753 302 112) \text{ lbs}$

Platform Gravity Loads:

Platform Elevations: $EL_{plat} := (115 \ 125 \ 135 \ 160 \ 170)^T$ ft

Node Loads:
$$\frac{W_{PL}'}{3}$$
 = (117 230 230 117 757) lbs

lce Node Loads:
$$\frac{\left(W_{PLI} - W_{PL}\right)^{T}}{3} = (50 \ 113 \ 113 \ 50 \ 353) \, lbs$$

Antenna Gravity Loads:

<u>Antenna Elevs:</u>	<u>Antenna</u>	Number:	Weight:	Dead Load	Weight wlice	Antenna Ice
EL _{ant} := 115ft 1	CSS DOU4	N ₁ := 12	W ₁ := 32lbs	$N_1 \cdot W_1 = 384 \text{lbs}$	W' ₁ := 53lbs	$N_1 \cdot (W_1 - W_1) = -252 \text{lbs}$
EL _{ant} := 125ft	EMS RR90-12	N ₂ := 6	W ₂ := 211bs	$N_2 \cdot W_2 = 126 \text{lbs}$	W'2:= 551bs	$N_2 \cdot (W_2 - W_2) = -204 \text{ lbs}$
EL _{ant} := 135ft 3	TXRX(1142)	N ₃ := 1	W ₃ := 10lbs		$W_3 := 20$ lbs	
	PD201-7	$N_{3_2} := 1$	$W_3 := 4lbs$		W'32 := 81bs	
	PD1142	N ₃ := 2	W ₃ := 10lbs		W'33 := 201bs	
	PD620	N ₃ := 3	W ₃ := 53lbs	$N_3 \cdot W_3 = 193 \text{lbs}$	W'3 ₄ := 106lbs	$N_3 \cdot (W_3 - W_3) = -193 \text{ lbs}$
EL _{ant} := 160ft	Allgon 7184	$N_4 := 12$	$W_4 := 10lbs$	$N_4 \cdot W_4 = 120 \text{lbs}$	W' ₄ := 20lbs	$N_4 \cdot (W_4 - W_4) = -120 \text{ lbs}$
EL _{ant} := 170ft	TXRX(1142)	N ₅ := 1	W ₅ := 10lbs		W'5 := 20lbs	
	PD201-7	N ₅₂ := 1	$W_{\frac{5}{2}} := 4 \text{lbs}$		W'52 := 81bs	
	PD1142	N ₅₃ := 2	$W_{5_3} := 10 lbs$		W'53 := 20lbs	
	PD620	N ₅ := 3	W ₅ := 53lbs	$N_5 \cdot W_5 = 193 \text{lbs}$	W'5 ₄ := 106lbs	$N_5 \cdot (W_5 - W_5) = -193 \text{lbs}$
Wt _{ant} := N	1·W1 + N2·W2 +	N3·W3 + N4	W4 + N5·W5	Wta	_{int} = 1016 lbs	
Wt _{ant.i} := N	N1·W'1 + N2·W'2	+ Nz·W'z + N	1 ₄ ·W' ₄ + N ₅ ·W' ₅	Wta	_{nnt.i} = 1978 lbs	

Tower Member Wind Loads:

Wind Velocity (Section 16): V:= 85mph

To account for shielding of the cables by the diagonals,

Shield := 1 -
$$\left[\frac{N_x}{L_L} \cdot \left(\frac{2 \cdot B_D}{\cos(\alpha_D)} \right) \right]$$
 Shield₆ := 1 Shield^T = (92 93 94 93 91 100)%

Cable area per side, assuming 1/3 of the area to each side:

$$\begin{split} & A_{C_{6}} \coloneqq \frac{\text{Shield}_{6}}{3} \cdot \left[L_{L_{6}} \cdot \left(5D_{7} + D_{10} + D_{13} \right) + 10^{!} \cdot 12 \cdot D_{13} \right] \\ & A_{C_{5}} \coloneqq \frac{\text{Shield}_{5}}{3} \cdot \left[L_{L_{5}} \cdot \left(5D_{7} + D_{10} + 13 \cdot D_{13} \right) + 15^{!} \cdot \left(D_{10} + D_{7} + 5D_{4} \right) + 5^{!} \cdot 6 \cdot D_{13} \right] \\ & A_{C_{4}} \coloneqq \frac{\text{Shield}_{4}}{3} \cdot \left[L_{L_{4}} \cdot \left(6 \cdot D_{7} + 5D_{4} + 2 \cdot D_{10} + 19 \cdot D_{13} \right) + 35^{!} \cdot 12D_{13} \right] \\ & A_{C_{3}} \coloneqq \frac{\text{Shield}_{3}}{3} \cdot \left[L_{L_{3}} \cdot \left(6 \cdot D_{7} + 5D_{4} + 2 \cdot D_{10} + 31 \cdot D_{13} \right) \right] \\ & A_{C_{2}} \coloneqq \frac{\text{Shield}_{2}}{3} \cdot \left[L_{L_{2}} \cdot \left(6 \cdot D_{7} + 5D_{4} + 2 \cdot D_{10} + 31 \cdot D_{13} \right) \right] \\ & A_{C_{1}} \coloneqq \frac{\text{Shield}_{1}}{3} \cdot \left[L_{L_{1}} \cdot \left(6 \cdot D_{7} + 5D_{4} + 2 \cdot D_{10} + 31 \cdot D_{13} \right) \right] \end{split}$$

$$A_{C}^{T} = (38.1 \ 76.8 \ 38.6 \ 73.7 \ 28.7 \ 11.6) \, \text{ft}^{2}$$

 $D_{E90} := .85$

Solidity ratio:
$$e := \frac{\overline{(2A_L + A_D + A_H + A_C)}}{G_N}$$
 $e^T = (0.26 \ 0.28 \ 0.30 \ 0.36 \ 0.40 \ 0.27)$

Round Component reduction factors: $R_{RA} := .51e^2 + .57$ $R_{RA}^T = (0.60 \ 0.61 \ 0.62 \ 0.64 \ 0.65 \ 0.61)$

For the legs: $R_{LA} := 1$ $R_{LA} := R_{RA} = R_{RA}$

Effective projected area of structural components on each face:

Wind Direction Factors (Table 2): $D_R := 1$ $D_{FN} := 1$ $D_{F60} := .80$

Normal Wind:

Legs:
$$A_{LN} := \overline{\left(D_R \cdot A_L \cdot R_{LA}\right)}$$
 $A_{LN}^T = (18.02 \ 33.54 \ 14.70 \ 26.89 \ 18.12 \ 1.77) \, \mathrm{ft}^2$ $A_{LN}^T = (18.02 \ 33.54 \ 14.70 \ 26.89 \ 18.12 \ 1.77) \, \mathrm{ft}^2$ $A_{DN}^T = (28.69 \ 46.12 \ 16.44 \ 29.81 \ 18.36 \ 3.86) \, \mathrm{ft}^2$ $A_{DN}^T = (0.00 \ 0.00 \ 0.00 \ 0.00 \ 6.00 \ 1.77) \, \mathrm{ft}^2$ $A_{HN}^T = (0.00 \ 0.00 \ 0.00 \ 0.00 \ 6.00 \ 1.77) \, \mathrm{ft}^2$ $A_{CN}^T = (23.00 \ 46.86 \ 23.80 \ 46.83 \ 18.63 \ 7.06) \, \mathrm{ft}^2$

90° Wind:

Legs:
$$A_{L90} := \overline{\left(D_{R} \cdot A_{L} \cdot R_{LA}\right)}$$
 $A_{L90}^{T} = (18.02 \ 33.54 \ 14.70 \ 26.89 \ 18.12 \ 1.77) \, \mathrm{ft}^{2}$

Diagonals: $A_{D90} := \overline{\left(D_{F90} \cdot A_{D} \cdot R_{DA}\right)}$ $A_{D90}^{T} = (24.38 \ 39.20 \ 13.97 \ 25.34 \ 15.61 \ 3.28) \, \mathrm{ft}^{2}$

Horizontals: $A_{H90} := \overline{\left(D_{F90} \cdot A_{H} \cdot R_{HA}\right)}$ $A_{H90}^{T} = (0.00 \ 0.00 \ 0.00 \ 0.00 \ 5.10 \ 1.50) \, \mathrm{ft}^{2}$

Cables: $A_{C90} := \overline{\left(A_{C} \cdot R_{RA}\right)}$ $A_{C90}^{T} = (23.00 \ 46.86 \ 23.80 \ 46.83 \ 18.63 \ 7.06) \, \mathrm{ft}^{2}$

60° Wind:

Legs:
$$A_{L60} := \overline{\left(D_{R} \cdot A_{L} \cdot R_{LA}\right)}$$
 $A_{L60}^{T} = (18.02 \ 33.54 \ 14.70 \ 26.89 \ 18.12 \ 1.77) \, \mathrm{ft}^{2}$

Diagonals: $A_{D60} := \overline{\left(D_{F60} \cdot A_{D} \cdot R_{DA}\right)}$ $A_{D60}^{T} = (22.95 \ 36.90 \ 13.15 \ 23.85 \ 14.69 \ 3.09) \, \mathrm{ft}^{2}$

Horizontals: $A_{H60} := \overline{\left(D_{F60} \cdot A_{H} \cdot R_{HA}\right)}$ $A_{H60}^{T} = (0.00 \ 0.00 \ 0.00 \ 0.00 \ 4.80 \ 1.42) \, \mathrm{ft}^{2}$

Cables: $A_{C60} := \overline{\left(A_{C} \cdot R_{RA}\right)}$ $A_{C60}^{T} = (23.00 \ 46.86 \ 23.80 \ 46.83 \ 18.63 \ 7.06) \, \mathrm{ft}^{2}$

$$C_{FA} := 3.4e^2 - 4.7e + 3.4$$

$$C_{FA}^{T} = (2.42 \ 2.35 \ 2.29 \ 2.15 \ 2.07 \ 2.39)$$

For latticed structures, the Gust Response Factor (2.3.4.1): $G_H := .65 + \frac{.6}{\left[EL_{t_{nh}} \div (33ft)\right]^{1 \div 7}}$ $G_H = 1.12$

Exposure coeffficient (2.3.3): $K'_{z_k} := \min \left[\max \left(\frac{z_k + El_p}{33 \text{ft}} \right)^{2 \div 7}, 1 \right], 2.58 \right]$ $K'_{z_k} = (1.00 \ 1.06 \ 1.24 \ 1.37 \ 1.50 \ 1.57)$

 $\text{Velocity pressure(2.3.3): } \ q := 0.00256 \text{psf-K'}_{z} \cdot (\text{V} \div \text{mph})^2 \qquad \left(\overrightarrow{\left(\text{q} \cdot \text{G}_{\text{H}} \right)} \right)^T = (20.8 \ 22.0 \ 25.8 \ 28.6 \ 31.1 \ 32.7) \, \text{psf}$

Structural Components and Linear Appurtenances: $\left(\overrightarrow{\left(q \cdot G_{H} \cdot C_{FA} \right)} \right)^T = (50.3 \ 51.7 \ 59.1 \ 61.5 \ 64.4 \ 77.9) \, \text{psf}$

Normal wind direction w/o ice:

Uniform wind to each leg: $w_{LN} := G_H \cdot \left[C_{FA} \cdot q \cdot \left[A_{LN} \div \left(3 \cdot L_L \right) \right] \right]$

Uniform wind to each diagonal: $w_{DN} := G_H \cdot \overline{\left(C_{FA} \cdot B_D \cdot D_{FN} \cdot R_{DA} \right) \cdot q}$

Uniform wind to each horizontal: $w_{HN} := G_H \cdot \overline{\left[\left(C_{FA} \cdot B_H \cdot D_{FN} \cdot R_{HA}\right) \cdot q\right]}$

Uniform wind to the cables(2.3.2): $w_{CN} := G_H \cdot \left[C_{FA} \cdot \left(A_{CN} + L_L \right) \cdot q \right]$

90° direction:

Uniform wind to each leg: $w_{L90} := G_H \cdot \left[C_{FA} \cdot q \cdot \left[A_{L90} \div \left(3 \cdot L_L \right) \right] \right]$

Uniform wind to each diagonal: $w_{D90} := G_H \cdot \overline{\left(C_{FA} \cdot B_D \cdot D_{F90} \cdot R_{DA} \right) \cdot q}$

Uniform wind to each horizontal: $w_{H90} := G_H \cdot \left[\left(C_{FA} \cdot B_H \cdot D_{F90} \cdot R_{HA} \right) \cdot q \right]$

Uniform wind to the cables(2.3.2): $w_{C90} := G_H \cdot \left[C_{FA} \cdot \left(A_{C90} \div L_L \right) \cdot q \right]$

60° direction:

Uniform wind to each leg: $w_{L60} := G_H \cdot \left[C_{FA} \cdot q \cdot \left[A_{L60} \div \left(3 \cdot L_L \right) \right] \right]$

Uniform wind to each diagonal: $w_{D60} := G_H \cdot \overline{\left(C_{FA} \cdot B_D \cdot D_{F60} \cdot R_{DA} \right) \cdot q}$

 $\text{Uniform wind to each horizontal: } w_{H60} := G_{H^*} \overline{\left[\left(C_{FA} \cdot B_H \cdot D_{F60} \cdot R_{HA} \right) \cdot q \right] }$

Uniform wind to the cables(2.3.2): $w_{C60} := G_H \cdot \boxed{C_{FA} \cdot \left(A_{C60} + L_L\right) \cdot q}$

 $w_{LN}^{T} = (15 \ 14 \ 14 \ 14 \ 13 \ 2) plf$

 $w_{DN}^{T} = (17 \ 15 \ 15 \ 15 \ 16 \ 3) plf$

 $w_{HN}^{T} = (0 \ 0 \ 0 \ 0 \ 16 \ 3) plf$

 $w_{CN}^{T} = (58 60 70 72 40 28) plf$

 $W_{L90}^{T} = (15 \ 14 \ 14 \ 14 \ 13 \ 2) plf$

 $w_{D90}^{T} = (14 \ 13 \ 13 \ 13 \ 14 \ 3) plf$

 $w_{H90}^{T} = (0 \ 0 \ 0 \ 0 \ 14 \ 3) plf$

 $w_{C90}^{T} = (58 60 70 72 40 28) plf$

 $w_{L60}^{T} = (15 \ 14 \ 14 \ 14 \ 13 \ 2) plf$

 $w_{D60}^{T} = (13 \ 12 \ 12 \ 13 \ 3) plf$

 $w_{H60}^{T} = (0 \ 0 \ 0 \ 0 \ 13 \ 3) plf$

 $w_{C60}^{T} = (58 60 70 72 40 28) pi$

Width of Linear Appurtenances with ice:

$$\begin{aligned} \text{DI}_4 &:= \text{D}_4 + 2\text{T}_i & \text{DI}_7 &:= \text{D}_7 + 2\text{T}_i & \text{DI}_{10} &:= \text{D}_{10} + 2\text{T}_i & \text{DI}_{13} &:= \text{D}_{13} + 2\text{T}_i \\ \text{DI}_4 &= 1.58 \text{ in} & \text{DI}_7 &= 2.11 \text{ in} & \text{DI}_{10} &= 2.55 \text{ in} & \text{DI}_{13} &= 2.98 \text{ in} \end{aligned}$$

$$\text{Shield}:= 1 - \overline{\left[\frac{\text{N}_x}{\text{L}} \left[\frac{2 \cdot \left(8\text{D} + 2\text{T}_i\right)}{\text{cos}\left(\alpha_D\right)}\right]\right]} \qquad \text{Shield}_6 := 1 \qquad \text{Shield}^T = \left(91 \ 91 \ 92 \ 91 \ 88 \ 100\right)\%$$

$$\text{Ac.}_i &:= \frac{\text{Shield}_6}{3} \cdot \left[\text{L}_{\text{L}_6} \cdot \left(5\text{DI}_7 + \text{DI}_{10} + \text{DI}_{13}\right) + 10^{\circ} \cdot 12 \cdot \text{DI}_{13}\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_5}{3} \cdot \left[\text{L}_{\text{L}_4} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 19 \cdot \text{DI}_{13}\right) + 35^{\circ} \cdot 12 \text{DI}_{13}\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_3}{3} \cdot \left[\text{L}_{\text{L}_3} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_2} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_2}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_3}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10} + 31 \cdot \text{DI}_{13}\right)\right] \\ \text{Ac.}_i &:= \frac{\text{Shield}_3}{3} \cdot \left[\text{L}_{\text{L}_1} \cdot \left(6 \cdot \text{DI}_7 + 5\text{DI}_4 + 2 \cdot \text{DI}_{10}$$

Solidity ratio w/ice:
$$e_i := \frac{\overbrace{(2A_{L,i} + A_{D,i} + A_{H,i} + A_{C,i})}^{T}}{G_{N_i}}$$
 $e_i^T = (0.41 \ 0.45 \ 0.51 \ 0.61 \ 0.71 \ 0.47)$

Round Component reduction factors:

$$R_{RAi} := .51e_i^2 + .57$$
 $R_{RAi}^T = (0.65 \ 0.67 \ 0.70 \ 0.76 \ 0.82 \ 0.68)$

For the legs:
$$R_{LA_{i_k}} := 1$$
 $R_{LA_{i_k}} := R_{RA_{i_k}}$ $R_{LA}^T = (1.00 \ 1.00 \ 1.00 \ 1.00 \ 0.61)$

For the diagonals:
$$R_{DA_i} := 1$$
 $R_{DA_i} := R_{RA}$ $R_{DA_i} = (1.00 \ 1.00 \ 1.00 \ 1.00 \ 1.00 \ 0.61)$

For the horizontals:
$$R_{HAi} := 1$$
 $R_{HAi} := R_{RAi}$ $R_{HAi} := R_{RAi}$ $R_{HAi} := (1.00 \ 1.00 \ 1.00 \ 1.00 \ 1.00 \ 0.68)$

Effective projected area of structural components on each face:

Normal Wind:

Legs:
$$A_{LNi} := \overline{\left(D_{R} \cdot A_{L,i} \cdot R_{LAi}\right)}$$
 $A_{LNi}^{T} = (33.84 \ 65.17 \ 30.52 \ 58.53 \ 41.52 \ 3.13) \, \mathrm{ft}^2$

Diagonals: $A_{DNi} := \overline{\left(D_{FN} \cdot A_{D,i} \cdot R_{DAi}\right)}$ $A_{DNi}^{T} = (35.86 \ 59.30 \ 21.92 \ 39.74 \ 24.49 \ 8.28) \, \mathrm{ft}^2$

Horizontals: $A_{HNi} := \overline{\left(D_{FN} \cdot A_{H,i} \cdot R_{HAi}\right)}$ $A_{HNi}^{T} = (0.00 \ 0.00 \ 0.00 \ 0.00 \ 8.00 \ 4.27) \, \mathrm{ft}^2$

Cables: $A_{CNi} := \overline{\left(A_{C,i} \cdot R_{RAi}\right)}$ $A_{CNi}^{T} = (38.92 \ 80.94 \ 42.22 \ 87.58 \ 37.16 \ 12.89) \, \mathrm{ft}^2$

90° Wind:

Legs:
$$A_{L90i} := \overline{\left(D_R \cdot A_{L,i} \cdot R_{LAi}\right)}$$

Diagonals: $A_{D90i} := \overline{\left(D_{F90} \cdot A_{D,i} \cdot R_{DAi}\right)}$

Horizontals: $A_{H90i} := \overline{\left(D_{F90} \cdot A_{H,i} \cdot R_{HAi}\right)}$

Cables: $A_{C90i} := \overline{\left(A_{C,i} \cdot R_{RAi}\right)}$

Legs:
$$A_{L90i} := \overline{\left(D_{R} \cdot A_{L,i} \cdot R_{LAi}\right)}$$
 $A_{L90i} = (33.84 \ 65.17 \ 30.52 \ 58.53 \ 41.52 \ 3.13) \, ft^2$

Diagonals: $A_{D90i} := \overline{\left(D_{F90} \cdot A_{D,i} \cdot R_{DAi}\right)}$ $A_{D90i} = (30.48 \ 50.40 \ 18.63 \ 33.78 \ 20.81 \ 7.04) \, ft^2$

Horizontals: $A_{H90i} := \overline{\left(D_{F90} \cdot A_{H,i} \cdot R_{HAi}\right)}$ $A_{H90i} = (0.00 \ 0.00 \ 0.00 \ 0.00 \ 6.80 \ 3.63) \, ft^2$

 $A_{C90i}^{T} = (38.92 \ 80.94 \ 42.22 \ 87.58 \ 37.16 \ 12.89) \text{ ft}^{2}$

60° Wind:

Legs:
$$A_{L60i} := \overline{\left(D_R \cdot A_{L,i} \cdot R_{LAi}\right)}$$

Diagonals: $A_{D60i} := \overline{\left(D_{F60} \cdot A_{D,i} \cdot R_{DAi}\right)}$

Horizontals: $A_{H60i} := \overline{\left(D_{F60} \cdot A_{H,i} \cdot R_{HA}\right)}$

Cables: $A_{C60i} := \overline{\left(A_{C,i} \cdot R_{RAi}\right)}$
 $C_{F,i} := 3.4e_i^2 - 4.7e_i + 3.4$

Legs:
$$A_{L60i} := \overline{\left(D_{R} \cdot A_{L,i} \cdot R_{LAi}\right)}$$
 $A_{L60i}^{T} = (33.84 \ 65.17 \ 30.52 \ 58.53 \ 41.52 \ 3.13) \, \mathrm{ft}^2$

Diagonals: $A_{D60i} := \overline{\left(D_{F60} \cdot A_{D,i} \cdot R_{DAi}\right)}$ $A_{D60i}^{T} = (28.69 \ 47.44 \ 17.54 \ 31.80 \ 19.59 \ 6.62) \, \mathrm{ft}^2$

Horizontals: $A_{H60i} := \overline{\left(D_{F60} \cdot A_{H,i} \cdot R_{HAi}\right)}$ $A_{H60i}^{T} = (0.00 \ 0.00 \ 0.00 \ 0.00 \ 0.00 \ 6.40 \ 3.42) \, \mathrm{ft}^2$

Cables: $A_{C60i} := \overline{\left(A_{C,i} \cdot R_{RAi}\right)}$ $A_{C60i}^{T} = (38.92 \ 80.94 \ 42.22 \ 87.58 \ 37.16 \ 12.89) \, \mathrm{ft}^2$
 $C_{F,i} := 3.4 \, \mathrm{e}_{i}^{2} - 4.7 \, \mathrm{e}_{i} + 3.4$ $C_{F,i}^{T} = (2.05 \ 1.97 \ 1.89 \ 1.80 \ 1.78 \ 1.94)$

Normal wind direction wlice:

Uniform wind to each leg: $w_{LNi} := G_H \cdot \bigcap_{C_{F,i}} q \cdot \bigcap_{A_{LNi}} A_{LNi} + (3 \cdot L_L)$ w_{LNi} = (24 23 25 25 25 3)plf Uniform wind to each diagonal: $w_{DNi} := G_H \cdot \overline{||C_{F,i}(B_D + 2T_i) \cdot D_{FN} \cdot R_{DA}| \cdot q||}$ $w_{DNi}^T = (18 \ 16 \ 16 \ 17 \ 18 \ 6) plf$ Uniform wind to each horizontal: $w_{HNi} := G_H \cdot \overline{\left[C_{F,i} \left[A_{H,i} \div \left(N_H \cdot L_H \right) \right] \cdot D_{FN} \cdot R_{HA} \right] \cdot q}$ $w_{HNi}^T = (0 \ 0 \ 0 \ 18 \ 6) \, p \, \text{If}$ Uniform wind to the cables(2.3.2): $w_{CNi} := G_H \cdot \overline{\left[C_{F,i} \left(A_{CNi} \div L_L \right) \cdot q \right]}$ $w_{CNi} = (83 \ 87 \ 103 \ 112 \ 68 \ 41) \, plf$

90° direction:

Uniform wind to each leg:
$$w_{L90i} := G_H \cdot \overline{\left[C_{F,i'} q \cdot \left[A_{L90i} + \left(3 \cdot L_L \right) \right] \right]}$$
 $w_{L90i}^T = (24 \ 23 \ 25 \ 25 \ 25 \ 3) \, plf$ Uniform wind to each diagonal: $w_{D90i} := G_H \cdot \overline{\left[C_{F,i'} \left(B_D + 2T_i \right) \cdot D_{F90} \cdot R_{DA} \right] \cdot q \right]}$ $w_{D90i}^T = (15 \ 14 \ 14 \ 15 \ 16 \ 5) \, plf$ Uniform wind to each horizontal: $w_{H90i} := G_H \cdot \overline{\left[C_{F,i'} \left(A_{H,i} + \left(N_H \cdot L_H \right) \right) \cdot D_{F90} \cdot R_{HA} \right] \cdot q \right]}$ $w_{H90i}^T = (0 \ 0 \ 0 \ 16 \ 5) \, plf$ Uniform wind to the cables(2.3.2): $w_{C90i} := G_H \cdot \overline{\left[C_{F,i'} \left(A_{C90i} + L_L \right) \cdot q \right]}$ $w_{C90i}^T = (83 \ 87 \ 103 \ 112 \ 68 \ 41) \, plf$

60° direction:

Uniform wind to each leg:
$$w_{L60i} := G_H \cdot \left[C_{F,i} \cdot q \cdot \left[A_{L60i} + \left(3 \cdot L_L \right) \right] \right]$$
 $w_{L60i} = (24 \ 23 \ 25 \ 25 \ 3) \, p \, \text{If}$

Uniform wind to each diagonal:
$$w_{D60i} := G_H \cdot \overline{\left[C_{F,i'} \left(B_D + 2T_i \right) \cdot D_{F60} \cdot R_{DA} \right] \cdot q}$$
 $w_{D60i} = (14 \ 13 \ 13 \ 14 \ 15 \ 5) \, plf$

$$w_{D60i}^{T} = (14 \ 13 \ 13 \ 14 \ 15 \ 5) plf$$

Uniform wind to each horizontal:
$$w_{H60i} := G_H \cdot \overline{\left[C_{F,i} \left[A_{H,i} + \left(N_H \cdot L_H \right) \right] \cdot D_{F60} \cdot R_{HA} \right] \cdot q} \right]} \quad w_{H60i} = (0 \quad 0 \quad 0 \quad 15 \quad 5) \, plf$$

Uniform wind to the cables(2.3.2):
$$w_{C60i} := G_H \cdot \overline{\left[C_{F,i'} \left(A_{C60i} + L_L \right) \cdot q \right]}$$
 $w_{C60i} = (83 \ 87 \ 103 \ 112 \ 68 \ 41) \, plf$

$$w_{C60i} = (83 \ 87 \ 103 \ 112 \ 68 \ 41) plf$$

Platform and Antenna Wind Loads:

$$jj := 1..rows(EL_{plat})$$

Factored Wind area of the platforms: $C_A_p := (13.9 \ 40.4 \ 40.4 \ 13.9 \ 91.0)^T \ ft^2$

$$K_{z}(z) := \min \left[\max \left(\frac{z + EI_{p}}{33ft} \right)^{2 \div 7}, 1 \right], 2.58 \right]$$

Exposure Coefficient:
$$Kx_{jj} := K_z \left(EL_{plat_{jj}} + El_p \right)$$
 $Kx^T = (1.43 \ 1.46 \ 1.50 \ 1.57 \ 1.60)$

$$K_x^T = (1.43 \ 1.46 \ 1.50 \ 1.57 \ 1.60)$$

Wind Pressure:
$$q := 0.00256 \cdot psf \cdot Kx \cdot (V + mph)$$

$$q^{T} = (26.4 \ 27.1 \ 27.7 \ 29.0 \ 29.5) psf$$

Wind Pressure:
$$q := 0.00256 \cdot psf \cdot Kx \cdot (V \div mph)^2$$
 $q^T = (26.4 \ 27.1 \ 27.7 \ 29.0 \ 29.5) psf$
Platform Wind Force to each leg: $\frac{1}{3} \cdot \left(\overbrace{\left(q \cdot G_H \cdot C_A_p\right)}^T \right)^T = (138 \ 410 \ 419 \ 151 \ 1008) lbs$

Wind area of the platforms with ice: $C_A_{p,i} := (19 57.1 57.1 19 131)^T ft^2$

Wind Force with ice:
$$\frac{1}{3} \cdot \left(\overline{\left(q \cdot G_H \cdot C_A_{p,i} \right)} \right)^T = (188 579 592 207 1451) \text{ lbs}$$

CSS DOU4

Directional Wind Factor: $C_d := 1$

Antenna Height:
$$H_{ant} := 48 \text{in}$$
 Width: $W_{ant} := 14 \text{in} \cdot C_d$ Aspect Ratio: $AR := \frac{H_{ant}}{W_{ant}}$ $AR = 3.43$

$$:= \frac{H_{ant}}{W} \qquad AR = 3.43$$

Antenna Wind Factor:
$$C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$$

$$C_a = 1.40$$

Factored Wind Area:
$$C_A_1 := C_a \cdot H_{ant} \cdot W_{ant}$$

$$C_A_1 = 6.53 \, \text{ft}^2$$

CSS DOU4 wlice

Antenna Height:
$$H'_{ant} := H_{ant} + 2T_i$$
 Width: $W'_{ant} := \left(W_{ant} + 2T_i\right) \cdot C_d$ Aspect Ratio: $AR := \frac{H'_{ant}}{W'_{ant}} = \frac{H'_{ant}}{W$

Aspect Ratio: AR :=
$$\frac{H'_{ant}}{W'_{ant}}$$

Antenna Wind Factor:
$$C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$$
 $C_a = 1.40$

$$C_a = 1.40$$

Factored Wind Area: $C_A'_1 := C_a \cdot H'_{ant} \cdot W'_{ant}$

$$C_A'_1 = 7.15 \, \text{ft}^2$$

EMS-RR90-12

Antenna Height:
$$H_{ant} := 48$$
in Width: $W_{ant} := 12$ in· C_d Aspect Ratio: $AR := \frac{H_{ant}}{W_{ant}}$ • $AR = 4.00$

Antenna Wind Factor:
$$C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$$
 $C_a = 1.40$

Factored Wind Area:
$$C_A_2 := C_a \cdot H_{ant} \cdot W_{ant}$$

$$C_A_2 = 5.60 \, \text{ft}^2$$

EMS-RR90-12 w/ice

Antenna Wind Factor:
$$C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$$
 $C_a = 1.4$

Factored Wind Area:
$$C_A'_2 := C_a \cdot H'_{ant} \cdot W'_{ant}$$

$$C_A'_2 = 6.19 \, \text{ft}^2$$

TXRX(1142)

Antenna Height:
$$H_{ant}$$
:= 192in Width: W_{ant} := .28in· C_d Aspect Ratio: $AR := \frac{H_{ant}}{W_{ant}}$ $AR = 685.71$

Antenna Wind Factor:
$$C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$$
 $C_a = 2.00$

Factored Wind Area:
$$C_A_3 := C_a \cdot H_{ant} \cdot W_{ant}$$

$$C_A_{3_1} = 0.75 \, \text{ft}^2$$

TXRX w/ice

Antenna Height:
$$H'_{ant} := H_{ant} + 2T_i$$
 Width: $W'_{ant} := (.28in + 2T_i) \cdot C_d$ Aspect Ratio: $AR := \frac{H'_{ant}}{W'_{ant}}$

Antenna Wind Factor:
$$C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$$

Factored Wind Area:
$$C_A'_3 := C_a \cdot H'_{ant} \cdot W'_{ant}$$
 $C_A'_3 = 3.43 \text{ ft}^2$

PD201-7

Antenna Height:
$$H_{ant} := 93$$
in Width: $W_{ant} := 29$ in· C_d Aspect Ratio: $AR := \frac{H_{ant}}{W_{ant}}$ $AR = 320.69$

Antenna Wind Factor:
$$C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$$

Factored Wind Area: $C_A = C_a \cdot H_{ant} \cdot W_{ant}$
 $C_A = 0.375 \text{ ft}^2$

PD201-7 w/ice

Antenna Height:
$$H'_{ant} := H_{ant} + 2T_i$$
 Width: $W'_{ant} := (.29in + 2T_i) \cdot C_d$ Aspect Ratio: $AR := \frac{H'_{ant}}{W'_{ant}}$

Antenna Wind Factor: $C_a := \inf \left\{ AR \le 7, 1.4, \inf \left\{ AR \ge 25, 2, 1.4 + 6 \cdot \frac{(AR - 7)}{25 - 7} \right\} \right\}$

$$C_a = 2.00$$

Factored Wind Area:
$$C_A'_3 := C_a \cdot H'_{ant} \cdot W'_{ant}$$
 $C_A'_3 = 1.68 \text{ ft}^2$

PD1142

Antenna Height: H_{ant} := 192in Width: W_{ant} := .28in·C_d Aspect Ratio: AR:= $\frac{H_{ant}}{W_{ant}}$. AR = 685.71 Antenna Wind Factor: C_a := if $AR \le 7, 1.4$, if $AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7}$ C_a = 2.00 Factored Wind Area: $C_A 3_a$:= $C_a \cdot H_{ant} \cdot W_{ant}$ $C_A 3_a$ = 0.75 ft C_a

PD1142 w/ice

Antenna Height: $H'_{ant} := H_{ant} + 2T_i$ Width: $W'_{ant} := \left(.28in + 2T_i\right) \cdot C_d$ Aspect Ratio: $AR := \frac{H'_{ant}}{W'_{ant}}$ Antenna Wind Factor: $C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7}\right]\right]$ $C_a = 2.00$ Factored Wind Area: $C_A'_3 := C_a \cdot H'_{ant} \cdot W'_{ant}$ $C_A'_3 = 3.43 \text{ ft}^2$

PD620

Antenna Height: $H_{ant} := 252 \text{in}$ Width: $W_{ant} := .68 \text{in} \cdot C_d$ Aspect Ratio: $AR := \frac{H_{ant}}{W_{ant}}$ AR = 370.59 Antenna Wind Factor: $C_a := \text{if} \left[AR \le 7, 1.4, \text{if} \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$ $C_a = 2.00$ Factored Wind Area: $C_A = C_a \cdot H_{ant} \cdot W_{ant}$ $C_A = 2.38 \text{ ft}^2$

PD620 w/ice

Antenna Height: $H'_{ant} := H_{ant} + 2T_i$ Width: $W'_{ant} := \left(.68 \text{in} + 2T_i\right) \cdot C_d$ Aspect Ratio: $AR := \frac{H'_{ant}}{W'_{ant}}$ Antenna Wind Factor: $C_a := \text{if} \left[AR \le 7, 1.4, \text{if} \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7}\right]\right]$ $C_a = 2.00$ Factored Wind Area: $C_A'_3 := C_a \cdot H'_{ant} \cdot W'_{ant}$ $C_A'_5 := C_A'_3$ $C_A'_5 := C_A'_3$

Allgon 7184

Directional Wind Factor: $C_d := 1$

Antenna Height: $H_{ant} := 51.3$ in Width: $W_{ant} := 5.4$ in· C_d Aspect Ratio: $AR := \frac{H_{ant}}{W_{ant}}$ AR = 9.50Antenna Wind Factor: $C_a := if \left[AR \le 7, 1.4, if \left[AR \ge 25.2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7} \right] \right]$ $C_a = 1.483$ Factored Wind Area: $C_A = C_a \cdot H_{ant} \cdot W_{ant}$ $C_A = 2.85$ ft

Allgon 7184 w/ice

Antenna Height:
$$H'_{ant} := H_{ant} + 2T_i$$
 Width: $W'_{ant} := \left(W_{ant} + 2T_i\right) \cdot C_d$ Aspect Ratiq: $AR := \frac{H'_{ant}}{W'_{ant}}$

Antenna Wind Factor: $C_a := \inf \left[AR \le 7, 1.4, \inf \left[AR \ge 25, 2, 1.4 + .6 \cdot \frac{(AR - 7)}{25 - 7}\right]\right]$
 $C_a = 1.44$

Factored Wind Area: $C_A'_4 := C_a \cdot H'_{ant} \cdot W'_{ant}$
 $C_A'_4 = 3.35 \, \text{ft}^2$

Antenna Elevs:	<u>Antenna</u>	Number:	Factored Wind Area	<u>Total Area</u>	Factored Wind Area w/ice	Total Area wlice
EL _{ant} = 115.0 ft	CSS DOU4	N ₁ = 12	$A_1 := C_A_1$	$N_1 \cdot A_1 = 78.4 \text{ft}^2$	$Y_1 := C_A'_1$	$N_1 \cdot Y_1 = 85.7 \text{ft}^2$
$EL_{ant}_{2} = 125.0 ft$	RR90-12	N ₂ = 6	$A_2 := C_A_2$	$N_2 \cdot A_2 = 33.6 \text{ft}^2$	Y ₂ := C_A' ₂	$N_2 \cdot Y_2 = 37.2 \text{ft}^2$
EL _{ant} = 135.0 ft	PD1142 PD620	\ /		/	J	$(N_3 \cdot Y_3) = \begin{pmatrix} 3.4 \\ 1.7 \\ 6.9 \\ 17.7 \end{pmatrix} \text{ft}^2$
EL _{ant} = 160.0 ft	Allgon 7184	N ₄ = 12	$A_4 := C_A_4$	$N_4 \cdot A_4 = 34.2 \text{ft}^2$	$Y_4 := C_A'_4$	$N_4 \cdot Y_4 = 40.1 \text{ft}^2$
EL _{ant} = 170.0 ft	TXRX PD201-7 PD1142 PD620	$N_5 = \begin{pmatrix} 1 \\ 1 \\ 2 \\ 3 \end{pmatrix}$	A ₅ := C_A ₅	$ \frac{1}{\left(N_{5}\cdot A_{5}\right)} = \begin{pmatrix} 0.7\\0.4\\1.5\\7.1 \end{pmatrix} \text{ft}^{2} $	Y ₅ := C_A' ₅	$ \frac{N_4 \cdot Y_4 = 40.1 \text{ ft}^2}{\left(N_5 \cdot Y_5\right) = \begin{pmatrix} 3.4 \\ 1.7 \\ 6.9 \\ 17.7 \end{pmatrix} \text{ ft}^2} $
Factored Antenna	a Area w/o ice: '	C_A _{ant} := (N ₁ ·A ₁ N ₂ ·A ₂	$\sum \overline{\left(N_3 \cdot A_3\right)} \ N_4 \cdot A_4 \ \sum$	$\sum (N_5 \cdot A_5)$	$kk := 1rows(EL_{\tilde{\epsilon}})$
Exposure Co	efficient: K'x _{kk}	$:= K_z (EL_{ant})$	t + EI _P)	$K'x^{T} = (1.43)$	1.46 1.50 1.57	1.60)
Antenna Win	d Force: $\frac{1}{3} \cdot \left(\begin{pmatrix} 1 \\ 1 \end{pmatrix} \right)$	q _{ant} ·G _H ·C_/	A_{ant}) $T = (77.$	$A_{ant}^{T} = (26.4 \ 27.1 \ 27)^{T}$) lbs	
				9 377 308 437 32		

Check the tower leg at the base of section 1:

Local

Effective Length Factor

$$K_{v} := 1$$

$$K_{y} := 1$$

Unsupported Length

$$L_x := 10 \cdot ft$$

$$L_y := S_{sg}$$

$$A_x := A_{Lx}$$

$$A_x := A_{Lx}$$
 $A_x = 11.93 \text{ in}^2$

$$\Gamma_{\mathsf{X}} := \Gamma_{\mathsf{L}_{\mathsf{A}}}$$

$$\Gamma_{y} := \Gamma_{e_{1}}$$

$$KL_R := \max \left(\left(\frac{K_x \cdot L_x}{r_x} \cdot \frac{K_y \cdot L_y}{r_y} \right) \right)$$

$$KL_R = 25.1 C_c := \sqrt{\frac{2 \cdot \pi^2 \cdot E_s}{F_y}}$$

$$C_c = 107.00$$

$$F'_{ex} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_x \cdot L_x}{r_x}\right)^2}$$

$$F'_{ex} = 252.17 \text{ ksi}$$

$$F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2}$$

$$F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2}$$

$$F_a = 27.74 \, \text{ksi}$$

$$L_{all_1} := K_o \cdot F_a \cdot A_x$$

$$L_{all_1} = 441 \, \text{kips}$$

$$if\left(P_{L_{1}} \le L_{all_{1}}, OK, NG\right) = "O.K."$$

Check the tower leg at the base of section 2:

Global

Local

$$P_{L_2} := 322 \text{kips}$$

Effective Length Factor

$$K_{v} := 1$$

$$L_{V} := S_{SQ}$$

$$A_x := A_{Lx}$$

$$A_x := A_{Lx}$$
 $A_x = 9.42 \text{ in}^2$

$$r_{x} := r_{L}$$

$$KL_R := max \left(\left(\frac{K_x \cdot L_x}{r_x} \cdot \frac{K_y \cdot L_y}{r_y} \right) \right)$$

$$KL_R = 28.2$$
 $C_c := \sqrt{\frac{2 \cdot \pi^2 \cdot E_s}{F_y}}$ $C_c = 107.00$

$$C_c = 107.00$$

$$F'_{ex} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_x \cdot L_x}{r_x}\right)^2} \qquad F'_{ex} = 251.48 \, \text{ksi} \qquad F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2} \qquad F'_{ey} = 187.78 \, \text{ksi}$$

$$F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2}$$

$$F_a = 27.4 \, \text{ksi}$$

$$L_{all_2} := K_0 \cdot F_a \cdot A_x$$
 $L_{all_2} = 344 \text{ kips}$

$$if\left(P_{L_2} \le L_{all_2}, OK, NG\right) = "O.K."$$

Check the tower leg at the base of section 3:

Global

Local

$$P_{L_z} := 223 \text{kips}$$

Effective Length Factor

 $K_x := 1$

Unsupported Length

 $L_x := 10 \cdot ft$

$$A_{\mathsf{x}} := A_{\mathsf{Lx}_{\mathsf{x}}}$$

$$A_x := A_{Lx_x}$$
 $A_x = 7.22 in^2$

$$KL_R := \max \left(\frac{K_x \cdot L_x}{r_x} \frac{K_y \cdot L_y}{r_y} \right)$$

$$KL_R = 32.2$$

$$C_c := \sqrt{\frac{2 \cdot \pi^2 \cdot E_s}{F_y}}$$

$$C_c = 107.00$$

$$C_c := \sqrt{\frac{2 \cdot \pi^2 \cdot E_s}{F_y}}$$

$$C_C = 107.00$$

$$F'_{ex} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_x \cdot L_x}{r_x}\right)^2}$$

$$F'_{ex} = 250.87 \, \text{ksi}$$

$$F'_{ex} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_x \cdot L_x}{r_x}\right)^2} \qquad F'_{ex} = 250.87 \, \text{ksi} \qquad F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2} \qquad F'_{ey} = 143.77 \, \text{ksi}$$

$$F'_{ey} = 143.77 \, \text{ksi}$$

$$F_{a} := if \left[KL_{R} < C_{c}, \frac{\left[\left(1 - \frac{KL_{R}^{2}}{2 \cdot C_{c}^{2}} \right) \cdot F_{y} \right]}{\frac{5}{3} + \frac{3 \cdot KL_{R}}{8 \cdot C_{c}} - \frac{KL_{R}^{3}}{8 \cdot C_{c}^{3}}}, \frac{12 \cdot \pi^{2} \cdot E_{s}}{23 \cdot KL_{R}^{2}} \right]$$

$$F_{a} = 26.9 \text{ ksi} L_{all_{3}} := K_{o} \cdot F_{a} \cdot A_{x} L_{all_{3}} = 259 \text{ kips}$$

$$if \left(PL_{3} \le L_{all_{3}}, OK, NG \right) = "O.K."$$

$$F_a = 26.9 \, \text{ksi}$$

$$L_{all_3} := K_0 \cdot F_a \cdot A_x$$
 $L_{all_3} = 259 \text{ kip}$

$$if(P_{L_3} \le L_{all_3}, OK, NG) = "O.K."$$

Check the tower leg at the base of section 4:

Global

Local

Effective Length Factor

 $K_x := 1$

Unsupported Length

 $L_x := 10 \cdot ft$

$$A_x := A_{Lx}$$

$$A_x := A_{Lx_A}$$
 $A_x = 5.30 \text{ in}^2$

 $\Gamma_{\mathsf{X}} := \Gamma_{\mathsf{L}_{\mathsf{A}}}$

$$KL_R := max \Biggl(\Biggl(\frac{K_x \cdot L_x}{r_x} - \frac{K_y \cdot L_y}{r_y} \Biggr) \Biggr)$$

KL_R = 37.6
$$C_c := \sqrt{\frac{2 \cdot \pi^2 \cdot E_s}{F_v}}$$
 $C_c = 107.00$

$$C_C = 107.00$$

$$F'_{ex} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_x \cdot L_x}{r_x}\right)^2}$$

$$F'_{ex} = 250.34 \text{ ksi}$$

$$F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2}$$

$$F'_{ex} = 250.34 \, ks$$

$$F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{F_y}\right)^2}$$

$$F_{a} := if \left[KL_{R} < C_{c}, \frac{\left[\left(1 - \frac{KL_{R}^{2}}{2 \cdot C_{c}^{2}} \right) \cdot F_{y} \right]}{\frac{5}{3} + \frac{3 \cdot KL_{R}}{8 \cdot C_{c}} - \frac{KL_{R}^{3}}{8 \cdot C_{c}^{3}}}, \frac{12 \cdot \pi^{2} \cdot E_{s}}{\frac{23 \cdot KL_{R}^{2}}{8 \cdot C_{c}^{3}}} \right]$$

$$F_{a} = 26.2 \text{ ksi} L_{all_{4}} := K_{o} \cdot F_{a} \cdot A_{x} L_{all_{4}} = 185 \text{ kips}$$

$$if \left(P_{L} \le L_{all_{4}}, OK, NG \right) = "O.K."$$

$$F_a = 26.2 \, \text{ksi}$$

$$L_{all_A} := K_0 \cdot F_a \cdot A_x \qquad L_{all_A} = 185 \text{ kips}$$

$$if\left(P_{L_{4}} \le L_{all_{4}}, OK, NG\right) = "O.K."$$

Check the tower leg at the base of section 5:

Local

Effective Length Factor

$$K_{\mathbf{v}} := 1$$

$$L_x := 10 \cdot ft$$

$$y := S_{sg}$$

$$A_x := A_{Lx}$$

$$A_x := A_{Lx}$$
 $A_x = 3.68 \text{ in}^2$

$$\Gamma_{X} := \Gamma_{L_{\underline{6}}}$$

$$r_y := r_{e_{f_5}}$$

$$KL_R := max \left(\left(\frac{K_x \cdot L_x}{r_x} - \frac{K_y \cdot L_y}{r_y} \right) \right)$$

$$C_c = 107.00$$

$$F'_{ex} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_x \cdot L_x}{r_x}\right)^2}$$

$$F'_{ex} = 249.90 \, \text{ksi}$$

$$F'_{ex} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_x \cdot L_x}{r_x}\right)^2} \qquad F'_{ex} = 249.90 \text{ ksi} \qquad F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2} \qquad F'_{ey} = 73.35 \text{ ksi}$$

$$F'_{ey} = 73.35 \, \text{ksi}$$

$$F_{a} := if \left[KL_{R} < C_{c}, \frac{\left[\left(1 - \frac{KL_{R}^{2}}{2 \cdot C_{c}^{2}} \right) \cdot F_{y} \right]}{\frac{5}{3} + \frac{3 \cdot KL_{R}}{8 \cdot C_{c}} - \frac{KL_{R}^{3}}{8 \cdot C_{c}^{3}}, \frac{12 \cdot \pi^{2} \cdot E_{s}}{23 \cdot KL_{R}^{2}} \right]$$

$$F_{a} = 25.1 \text{ ksi}$$

$$L_{all_{5}} := K_{o} \cdot F_{a} \cdot A_{x} \quad L_{all_{5}} = 123 \text{ kips}$$

$$if \left(P_{L_{5}} \le L_{all_{5}}, OK, NG \right) = "O.K."$$

$$F_a = 25.1 \, \text{ksi}$$

$$L_{all_5} := K_0 \cdot F_a \cdot A_x$$
 $L_{all_5} = 123 \text{ kips}$

$$if\left(P_{L_{5}} \le L_{all_{5}}, OK, NG\right) = "O.K."$$

Check the tower leg at the base of section 6:

Global

Local

$$P_{L_6} := 29.3 \text{kips}$$

Effective Length Factor

 $K_x := 1$

 $K_{v} := 1$

Unsupported Length

 $L_x := 2.5 \cdot ft$

 $L_v := 1ft$

$$A_{x} := A_{Lx}$$

$$A_x := A_{Lx} \qquad A_x = 2.41 \text{in}^2$$

 $r_{\mathsf{X}} := r_{\mathsf{L}_{\mathsf{C}}}$

 $r_y := r_e$

$$KL_R := max \left(\left(\frac{K_x \cdot L_x}{r_x} - \frac{K_y \cdot L_y}{r_y} \right) \right)$$

 $C_c = 107.00$

$$F'_{ex} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_x \cdot L_x}{r_x}\right)^2} \qquad F'_{ex} = 31.76 \text{ ksi} \qquad F'_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2} \qquad F'_{ey} = 198.49 \text{ ksi}$$

$$= '_{ey} := \frac{12 \cdot \pi^2 \cdot E_s}{23 \cdot \left(\frac{K_y \cdot L_y}{r_y}\right)^2}$$

$$F_{a} := if \left[KL_{R} < C_{c}, \frac{\left[\left(1 - \frac{KL_{R}^{2}}{2 \cdot C_{c}^{2}} \right) \cdot F_{y} \right]}{\frac{5}{3} + \frac{3 \cdot KL_{R}}{8 \cdot C_{c}} - \frac{KL_{R}^{3}}{8 \cdot C_{c}^{3}}}, \frac{12 \cdot \pi^{2} \cdot E_{s}}{23 \cdot KL_{R}^{2}} \right]$$

$$F_{a} = 21.2 \text{ ksi} L_{all_{6}} := K_{o} \cdot F_{a} \cdot A_{x} L_{all_{6}} = 68 \text{ kip}$$

$$if \left(P_{L_{6}} \le L_{all_{6}}, OK, NG \right) = "O.K."$$

$$F_a = 21.2 \, \text{ksi}$$

$$L_{all_6} := K_0 \cdot F_a \cdot A_x \quad L_{all_6} = 6$$

$$if\left(P_{L_{6}} \le L_{all_{6}}, OK, NG\right) = "O.K."$$

Maximum uplift force due to Moment minus 1/3 Dead and Ice Loads will occur with the wind at 60° to a face.

T := 329kips As this is less than the maximum compressive force, the leg will not fail in tension.

Diagonals $F_V := 36$ ksi

Section 1: maximum compressive force for member 19, load case 20 (90 deg wind) is $P_D := 15.32 \text{kips}$ $A_x := A_{Dx}$

$$KL_R := \max \left(\left(KL_{-r_X} & KL_{-r_{Z_1}} \right) \right) \qquad \qquad KL_R = 161.4 \qquad C_c := \sqrt{\frac{2 \cdot \pi^2 \cdot E_s}{F_y}} \qquad C_c = 126.099$$

$$F_{a} := if \left[KL_{R} < C_{c}, \frac{\left[\left(1 - \frac{KL_{R}^{2}}{2 \cdot C_{c}^{2}} \right) \cdot F_{y} \right]}{\frac{5}{3} + \frac{3 \cdot KL_{R}}{8 \cdot C_{c}} - \frac{KL_{R}^{3}}{8 \cdot C_{c}^{3}}}, \frac{12 \cdot \pi^{2} \cdot E_{s}}{23 \cdot KL_{R}^{2}} \right]$$

$$F_{a} = 5.7 \text{ ksi} \quad D_{all_{1}} := K_{o} \cdot F_{a} \cdot A_{x} \quad D_{all_{1}} = 14.8 \text{ kips}$$

$$if \left(P_{D_{1}} \leq D_{all_{1}}, OK, NG \right) = "N.G."$$

Section 2: maximum compressive force for member 31, load case 20 (90 deg wind) is $P_{D_2} := 13.47 \text{kips } A_x := A_{Dx_2}$

$$KL_{-}R := \max \left(\left(KL_{-}r_{X_{2}} \quad KL_{-}r_{Z_{2}} \right) \right) \qquad KL_{-}R = 171.1$$

$$C_{c} = 126.099$$

$$F_{a} := \inf \left[KL_{-}R < C_{c}, \frac{\left[\left(1 - \frac{KL_{-}R^{2}}{2 \cdot C_{c}^{2}} \right) \cdot F_{y} \right]}{\frac{5}{3} + \frac{3 \cdot KL_{-}R}{8 \cdot C_{c}} - \frac{KL_{-}R^{3}}{8 \cdot C_{c}^{3}}}, \frac{12 \cdot \pi^{2} \cdot E_{s}}{23 \cdot KL_{-}R^{2}} \right]$$

$$F_{a} = 5.1 \text{ ksi} \qquad D_{all_{2}} := K_{0} \cdot F_{a} \cdot A_{x} \qquad D_{all_{2}} = 14.2 \text{ kips}$$

$$\text{if} \left(P_{D_{2}} \leq D_{all_{2}}, OK, NG \right) = \text{"O.K."}$$

Section 3: maximum compressive force for member 55, load case 20 (90 deg wind) is $P_{D_3} := 11.53$ kips $A_x := A_{Dx_3}$

$$KL_R := max((KL_r_x_3 KL_r_z_3))$$
 $KL_R = 167.6$ $C_c = 126.099$

$$F_{a} := if \begin{cases} KL_{R} < C_{c}, \frac{\left[\left(1 - \frac{KL_{R}^{2}}{2 \cdot C_{c}^{2}}\right) \cdot F_{y}\right]}{2 \cdot C_{c}^{2}}, \frac{12 \cdot \pi^{2} \cdot E_{s}}{23 \cdot KL_{R}^{2}} \end{cases}$$

$$F_{a} = 5.3 \text{ ksi} \qquad D_{all_{3}} := K_{o} \cdot F_{a} \cdot A_{x} \qquad D_{all_{3}} = 12.6 \text{ kips}$$

$$if \left(P_{D_{3}} \le D_{all_{3}}, OK, NG\right) = "O.K."$$

Section 4: maximum compressive force for member 67, load case 20 (90 deg wind) is $P_{D_4} := 10.56 \text{kips } A_{\text{X}} := A_{D_{\text{X}}}$

$$KL_{-}R := \max \left(\left(\frac{KL_{-}r_{X_{4}}}{KL_{-}r_{Z_{4}}} \right) \right) \qquad KL_{-}R = 151.1$$

$$C_{c} = 126.099$$

$$F_{a} := \inf \left[KL_{-}R < C_{c}, \frac{\left[\left(1 - \frac{KL_{-}R^{2}}{2 \cdot C_{c}^{2}} \right) \cdot F_{y} \right]}{\frac{5}{3} + \frac{3 \cdot KL_{-}R}{8 \cdot C_{c}} - \frac{KL_{-}R^{3}}{8 \cdot C_{c}^{3}}}, \frac{12 \cdot \pi^{2} \cdot E_{s}}{23 \cdot KL_{-}R^{2}} \right] \qquad F_{a} = 6.5 \text{ ksi} \qquad D_{all_{4}} := K_{o} \cdot F_{a} \cdot A_{x} \qquad D_{all_{4}} = 9.5 \text{ kips}$$

$$\inf \left(P_{D_{4}} \leq D_{all_{4}}, OK, NG \right) = \text{"N.G."}$$

$$if\left(P_{D_{4}} \le D_{AH_{4}}, OK, NG\right) = "N.G."$$

Section 5: maximum compressive force for member 93, load case 20 (90 deg wind) is $P_{D_{\underline{x}}} := 8.71 \text{kips}$ $A_{\underline{x}} := A_{D\underline{x}_{\underline{x}}}$

$$KL_{R} := \max \left(\left(KL_{-}r_{X_{5}} \quad KL_{-}r_{Z_{5}} \right) \right)$$

$$KL_{R} = 127.0$$

$$C_{c} = 126.099$$

$$F_{a} := \inf \left[KL_{R} < C_{c}, \frac{\left[\left(1 - \frac{KL_{R}^{2}}{2 \cdot C_{c}^{2}} \right) \cdot F_{y} \right]}{2 \cdot C_{c}^{2}} , \frac{12 \cdot \pi^{2} \cdot E_{s}}{2 \cdot C_{c}^{3}} \right]$$

$$F_{a} = 9.3 \text{ ksi}$$

$$D_{all_{5}} := K_{o} \cdot F_{a} \cdot A_{x}$$

$$D_{all_{5}} = 13.4 \text{ kips}$$

$$\text{ if } \left(P_{D_{5}} \leq D_{all_{5}}, OK, NG \right) = "O.K."$$

Capacity/Demand Ratios for the Tower Legs: $\left(\frac{L_{all}}{P_{l}}\right)^{l} = (119 \ 107 \ 116 \ 108 \ 175 \ 232)\%$

Capacity/Demand Ratios for the Tower Diagonals $\left(\frac{D_{all}}{P_D}\right)^{l} = (97 \ 105 \ 109 \ 90 \ 154)\%$

The Diagonal at the base of the 4th level has 90% of the required strength. It is only the bottom panel of the 4th evel that is overstressed. These could be reinforced by running a 3/8" bead along the inside of these six angles

APPENDIX "D"

Selected Stiffness Analysis Results

Cromwell Cellphone Tower

July 13, 2002 5:49 PM Checked By:___

Envelope Member Section Forces

Member Label	Section	on	Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	 Lc
M19	1	max	15.327	20	.134	11	.041	11	.044	11	0	11	0	4
		min	-2.411	17	177	4	09	17	056	4	0	4	0	11
	2	max	14.739	20	.175	4	.094	17	.038	11	0	4	0	4
		min	-2.53	17	133	11	048	11	048	4	0	4	0	4
M20	1	max	14.6	17	.087	7	.036	17	.039	11	0	11	0	11
		min	-13.858	24	04	4	024	7	- 049	4	Ō	4	0	4
	2	max	15.215	17	.043	4	.03	7	.054	7	0	4	0	4
		min	-13.874	24	085	7	041	17	001	11	0	4	0	4
M21	1	max	15.215	17	.049	11	.066	20	.054	7	0	4	0	4
		min	-13.874	24	055	7	005	11	001	4	0	7	0	7
	2	max	14.6	17	.058	7	.003	11	.049	4	0	4	0	
		min	-13.858	24	045	11	058	7	039	11	0	4	0	4
M22	1	max	2.439	24	.133	11	048	11	.048	4	0	11	0	11
		min	-14.737	20	175	4	094	17	038	11	0	4		
	2	max	2.805	24	177	4	.09	17	.056	4			0	4
		min	-14.653	20	- 134	11	041	11	044		0	4	0	4
M23	1	max	11,723	24	.106	7	.141			11	0	4	0	4
	··	min	-11.877	17	12	4	042	7	.057	4	0	4	0	4
	2	max	11.336	24	.119	4	.05	4	045	11	0	11	0	11
		min	-11.977	17	105	7		4	0	11	0	4	0	4
M24	1	max	11,336	24	078		142	7	047	7	0	4	0	4
, , , , , , , , , , , , , , , , , , ,		min	-11.977	17		11	.062	24	.001	4	0	17	0	7
	2	max	11.723	24	129	7	104	7	047	7	0	7	0	4
	4-	min	-11.877		.132	7	.1	7	.045	11	0	4	0	4
M25	1	1		17	078	11	058	24	057	4	0	4	0	4
10125		max	13.42	20	.128	11	.038	11	.046	11	0	11	0	11
}	2	min	499	24	17	4	084	17	059	4	0	4	0	4
		max	12.866	20	.168	4	.089	17	.04	11	0	4	0	4
M26	3300 BR000	min	829	24	127	11	045	11	05	4	0	4	0	4
10120	1	max	11.235	17	.079	7	.037	17	.041	11	0	4	0	11
		min	-11	24	+.035	4	- 028	7	+.052	4	0	7	0	4
	2	max	11.805	17	.039	4	.034	7	.058	7	0	4	0	4
MOZ		min	-11.016	24	077	7	043	17	001	11	0	4	0	4
M27	1	max	11.805	17	.045	11	.068	7	.058	7	0	17	0	7
		min	-11.016	24	047	7	008	11	002	4	0	24	0	4
	2	max	11.235	17	.051	7	.006	11	.052	4	0	4	0	4
		min	-11	24	041	11	06	7	041	11	0	4	0	4
M28	1	max	.5	17	.127	11	.045	11	,05	4	0	11	0	4
		min	-13.305	20	+.168	4	089	17	04	11	0	4	0	11
	2	max	619	17	17	4	.084	17	.059	4	0	4	0 i	4
		min l	-13.239	20	128	11		11		11	0	4	0	4
M29	1	max	11.756	24	.101	7	.135	7	.061	4	0	11	0	4
		min	-12.245	17	116	4	041	4	048	11	0	4		11
	2	max		24	.115	4	.049	4		11	0	4	0	4
		min		17	099	7	137	7	05	7	0	4	0	4
M30	1	max		24	The state of the s	11		24	.001	4		24	0	7
		min		17	122	7	- 102	7	05	7	0	7		17
		max		24	.126	7	.097	7	,048					
				17		11		24		11	0	4	0	4
-				e totalodiss	concert I Jesses 4.3	or 1 (3)	-,000000	24	061	4	0	4	0 1	4

Cromwell Cellphone Tower

July 13, 2002 5:52 PM Checked By:_

Envelope Member Section Forces

Member Label	· · · · · · · · · · · · · · · · · · ·	,	Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	 : Lo
M31	1	max	13.471	20	.114	11	.032	11	.08	11		11	0	1
		min	763	4	144	4	074	4	102	4	0	4	0	4
4	2	max	12.986	20	.141	4	.079	4	.068	11	0	4	0	4
		min	806	17	111	11	039	11	086	4	0	4	0	4
M37	1	max	12.745	20	.108	11	.03	11		11	0	11	0	1
3		min	294	4	137	4	07	4	104	4	0	4	0	4
	2	max	12.278	20	.135	4	075	4	07	11	0	4	0	4
		min	342	17	106	11	- 038	11	089	4	0	4	0	4
M33	1	max	12.55	17	.04	11	.063	7	.101	7	0	24		
		min	-11.588	24	037	7	01	11	003	4	0	17	0	7
	2	max	12.058	17	.042	7	.006	11	.089	4	0		0	17
		min	-11.56	24	035	11	055	7	07	-		4	0	4
M32	1	max	12.058	17	.071	7	.034	17	.07	11	0	4	0	4
	i i	min	-11.56	24	024	4	***************************************			11	0	24	0	4
	2	max	12.55	17	.03	4	024	7	089	4	0	7	0	11
			-11.588				.03	7	.101	7	0	4	0	4
M43	1	min		24	069	7	041	17	002	11	0	4	0	4
10143		max	12.349	20	.103	11	.028	11	.083	11	0	11	0	11
	-	min	555	4	131	4	066	4	105	4	0	4	0	4
	2	max	11.907	20	.128	4	.072	4	.072	11	0	4	0	4
1470		min	617	17	101	11	036	11	091	4	0	4	0	4
M49	1	max	12,056	20	.098	11	.027	11	.085	11	0	11	0	24
		min	12	4	125	4	062	4	107	4	0	4	0	17
	711711	max	11.637	20	.122	4	.069	4	.075	11	0	4	0	4
		min	132	4	096	11	036	11	095	4	0	4	0	4
M39	_1	max	11.585	17	.037	11	.063	7	.105	7	0	24	0	17
		min	-10.861	24	033	7	012	11	003	4	0	7	0	7
	2	max	11.125	17	.039	7	.007	11	.091	4	0	4	0	
		min	-10.832	24	031	11	055	7	072	11	0	4	0	4
M38	1	max	11.125	17	.067	7	033	17	072	11	0			4
		min	-10.832	24	021	4	026	7	+.091			11	0	11
	2	max	11.585	17	.027	4	.032	7		4	0	17	0	4
	***************************************	min	-10.861	24	063	7	04		.105	7	0	4	0	4
M44		max	10.942	17	.062		and the same of th	17	002	11	0	4	0 1	4
		min	-10.607	24		7	.031	17	.074	11	0	11	0	4
	2				017	4	028	7	094	4	0	4	0	7
		max	11.371	17	.024	4	.033	7	.107	7	0	4	0	4
M45	<u> </u>	min	-10.638	24	058	7	039	17	003	11	0	4	0	4
IVI40		max į	11.371	17	********************	11	.062	7	.107	7	0	24	0 1	7
į		min		24	+.029	7	013	11	003	4	0	17	0 i	24
ļ	2	max	10.942	17	.036	7	.008	11	.094	4	0	4	0 1	4
		min		24	027	11	054	7	074	11	0	4	0	4
M36	1	max	10.733	24	.066	11	.053	11	.002	4	0	17	0 !	7
		min	-11.324	17	108	7	089	7	087	7	0	7	0	24
	2	max	11.058	24	.114	7	.086	7	.082	11	0	4	0	4
		min l	-11.26	17	064	11	047	24	104	4	0	4	0	4
M35	1	max	A CONTRACTOR OF THE PARTY OF TH	24	.088	7	124	7	104	4	<u>_</u>	11	0	4
		min i		17	099	4	- 031	4	082					
		max		24	.099	4	.04	4		11	0	4		11
Î				17	084	7			.002	11	0	4	0 ;	4
M51		max		17			124	7	087	7 1	<u> </u>	4	0	4
					.032	11	.06	7	.11 -			17	0	
:		min :		24	025	7		11 ;	003	4	0	24	0 .	17
	_ / :I	max '	10.443	17	.034	7 !	.008	11	.098	4	0	A	0	
1				24	024	11	052	7	078	4 :	0	4	0	4

Cromwell Cellphone Tower

July 13, 2002 5:52 PM Cheçked By:_

Envelope Member Section Forces, (continued)

Member Label			Axial (k)	Lc	Shear y-y (k)	Ĺc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z	— <u> </u>
M50	1	max		17	.059	7	,029	17		11) O	17	1 0	4
		min	-10,136	24	-,014	4	-,029	7	-,098	4	0	24	0	11
	2	max	10,846	17	.022	4	,034	7	.11	7	0	4	Ö	4
		min	-10.17	24	+.053	7	+.038	17	- 003	11	0	4	0	4
M41	1	max	10.732	24	.083	7	.119	7	.106	4	0	11	0	4
		min	-11.071	17	095	4	03	4	084	11	0	4	0	11
	2	max	10.42	24	.096	4	.04	4	.002	11	0	4	0	4
		min	-11.114	17	078	7	119	7	09	7	0	4	0	4
M42	1	max	10.42	24	.063	11	.051	11	002	4	0	24	0	7
		min	-11.114	17	101	7	- 086	7	- 09	7	0	7	0	17
	2	max	10.732	24	.108	7	.084	7	.084	11	0	4	Ö	4
		min	+11.071	17	+.062	11	- 045	24	106	4	0	4	0	4
M54	1	max	9.96	24	.058	11	.049	11	.003	4	0	24	0	24
		min	-10.487	17	088	4	081	7	098	7	0	7	0	17
	2	max	10.247	24	.096	7	.079	7	.087	11	0	4	0	4
		min	-10.474	17	056	11	04	24	11	4	0	4	0	4
M53	1	max	10.247	24	.073	7	109	7	11	4	0	11	0	4
		min	-10.474	17	087	4	029	4	087	11	0	4	0	11
	2	max	9.96	24	.088	4	.042	4	.002	11	0	4	***************************************	
		min	-10,487	17	067	7	108	7	098	7	0	4	0	4
M48	1	max	9.943	24	.061	11	.05	11	.003	4	0	24	0	20
		min	-10.515	17	095	7	084	7	093	7	0	7	0	17
	2	max	10.244	24	.103	7	.081	7	.086	11	0	4	0	4
		min	-10.488	17	059	11	043	24	108	4	0	4	0	4
M47	1	max	10.244	24	.078	7	114	7	.108	4	0	71	0	11
		min	-10.488	17	091	4	029	4	086	11	0	4	0	4
	2	max	9.943	24	.092	4	.041	4	.002	11	0	4	0	4
		min	-10.515	17	073	7	- 114	7	093	7	0	4		4
M34	1	max	.71	24	.111	11	.039	11	.086	4	0	11	0 0	
		min	-13.078	20	141	4	079	4	068	11	0	4		4
	2	max	.981	24	.144	4	.074	4	.102	4	0	4	0	11
		min	-13.018	20	114	11	032	11	08	11	0		0	4
M46	1	max	465	24	101	11	.036	11	.091	4	0 1	4 11	0 0	4
		min	-12.077	20	128	4	072	4	072	11	0	4	0	24 17
ļ	2	max	.69	24	131	4	.066	4	.105	4	0	4	0	
		******	-12.051	20	103	11		11	083				<u> </u>	4
M40	1	max	.168	11	.106	11	.038	11	.089			4		4
		min	-12.548	20	135	4	075	4		4	0	11	0	7
ļ	2	max	.372	24	.137	4	.07	4	07 .104	11	0	4	0	17
		min	-12.508	20	108	11	03	11		4	0	4	0	4
M52	1	max	.042	11		11	.036		082	11	0	4	0	4
	*****	min	-11.793	20	122	4		11	.095	4	~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~	11	0	4
Ė	2	max	.214	24	.125		069	4	075	11	0	4	0	11
<u> </u>	****	min	-11.78	20	***************************************	4	.062	4	107	4	0	4	0 [4
<u> </u>	occusional E	or or Hele	711.70	LU j	098	11	027	11	085	11	0	4	0	4

Company : James A. Mieczkowski, P.E. Designer : Jim Mieczkowski Job Number : 15364.1251 Cro **Cromwell Cellphone Tower**

July 13, 2002 5:54 PM Checked By:_

Envelope Member Section Forces

Member Label	Sectio	n	Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	Lc
M55	1	max	11.534	20	.093	11	.026	11	.073	11	0	11	0	20
		min	821	4	117	4	055	4	093	4	0	4	0	17
	2	max	11.163	20	.116	4	.062	4	.067	11	0	4	0	4
		min	885	17	091	11	035	11	084	4	0	4	0	4
M61	1	max	11.188	20	.088	11	.024	11	.077	111	0	20	0	20
		min	075	4	111	4	051	4	096	4	0	24	0	24
	2	max	10.834	20	.11	4	.059	4	.071	11	0	4	Ū	4
		min	091	17	087	11	033	11	09	4	Ō	4	0	4
M57	1	max	10.764	17	.03	11	.057	7	.096	7	0	20	0	20
		min	-10.101	24	024	4	014	11	003	4	0	24	0	24
	2	max	10.409	17	.031	7	.008	11	.087	4	0	4	0	4
		min	-10.057	24	023	11	05	7	069	11	0	4	0	4
M56	1	max	10.409	17	.051	7	025	17	069	11	0	24	0	17
		min	-10.057	24	016	4	033	7	087	4	0	17	0	24
	2	max	10.764	17	.024	4	037	7	.096	7	0	4	0	4
		min	-10.101	24	045	20	033	17	003	11	0	4	0	4
M62	1	max	9.668	17	.047	7	.022	17	.074	11	0	24	0	17
		min	-9.467	24	012	4	035	7	093	4	0	17	0	24
	2	max	10.001	17	.021	4	.038	7	.101	7	0	4	0	4
		min	-9.513	24	041	20	032	17	003	11	0	4	0	
M63	1	max	10.001	17	027	11	.056	7	.101	7	0	7	0	4
		min	-9.513	24	021	4	- 014	11	004	4		24		17
	2	max	9.668	17	.029	7	007	11	.093	4	0 0	**********	0	7
		min	-9.467	24	019	11	051	7	074	11	0	4	0	4
M66	1	max	9.318	24	.055	11	.046	11	.003	4	0		0	4
		min	-9.812	17	08	4	076	7	095	7	0	17 7	0	17
	2	max	9.57	24	.082	7	.075	7	.079	11	0		0	7
·		min	-9.84	17	052	11	035	11	1	4		4	0	4
M65	1	max	9.57	24	.064	7	.096	7	1	4	0	4	0	4
į		min	-9.84	17	078	4	- 028	4	079		0	20	0	20
	2	max	9.318	24	.08	4	.043			11	0	24		24
		min	-9.812	17	058	7	095	7	.003	11	0	4	0	4
M59	1	max	9.415	24	.069	7	.101	**********	095	7	0	4	0	4
		min	-9.57	17	081	4	029	$\frac{7}{4}$.096	4	0	4	0	4
-	2	max	9.154	24	.083			4	076	11	0	24		11
-	-+	min	-9.554	17	064	4	.042	4	.002	11	0	4	0	4
M60	1	max	9.154	24		7	101	7	088	7	0	4	0 !	4
		min	-9.554	17	.056 083	11	.046	11	,003	4	0	17	*******************************	24
		max	9.415	24	.088	4	08	7	088	7	0	20	*********	17
		min I		17		7	.078	7	.076	11	0	4	0	4
M58			.817			11		11	096	4	0	4	0	4
14100		max		24	.091	11		11	.084	4	0	17		24
-			-11.218 .995	20	116	4	062	4	067	11	0	7		17
 		max		24	.117	4	.055	4	.093	4	0	4	0	4
M64	200120-000		-11.234	20		11		11	073	11	0	4	0	4
: INIOH :		max	014	11		11		11	.09	4		24	0	11
5 to 1 to			-11.026	20	11	4	- 059	4		111	0	17	0	7
		max 📒		11	.111	4	.051	4	.096	4	0	4	0	4
<u> </u>		mane o	-11.054	20	-:088	11	024	11	077	11	0	4	0	4

Company Designer

Company : James A. Mieczkowski, P.E. Designer : Jim Mieczkowski Job Number : 15364.1251 Cro **Cromwell Cellphone Tower**

July 13, 2002 5:55 PM Checked By:_

Envelope Member Section Forces

Member Label			Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	Lc
M67	1	max	10.564	20	.083	11	.025	11	.019	111	0	4	0	11
		min	958	17	104	4	044	17	023	4	0	11	0	4
	2	max	10.259	20	.104	4	.051	17	.018	11	0	4	0	4
		min	987	17	082	11	034	11	022	4	0	4	0	4
M73	1	max	10.128	20	.078	11	.023	11	.02	11	0	7	0	24
		min	378	24	099	4	041	17	025	4	0	17	0	4
	2	max	9.834	20	.098	4	.049	4	.018	11	0	4	0	4
		min	501	24	078	11	- 033	11	023	4	0	4	0	4
M68	1	max	9.678	17	.039	20	.021	17	.018	11	0	4	0	4
		min	-9.281	24	019	4	036	7	023	4	0	20	0	20
	2	max	9.962	17	.023	4	.042	7	.025	7	0	4	0	
		min	-9.353	24	034	20	025	17	0	11	0	4	0	4
M69	1	max	9.962	17	.024	24	.051	7	025	7	0	24	0	
		min	-9.353	24	023	4	013	11	0	4	0	17		17
	2	max	9.678	17	.026	7	011	11	.023	4	0	*********	0	24
i		min	-9.281	24	- 02	24	044	7	018	11	0	4	0	4
M80	1	max	9.663	17	.029	20	.02	17	.02			∴4 •	0	4
		min	-9.094	24	012	4	04	7	025	11	0	24	0	4
	2	max	9.921	17	.019	4	.045	7		4	0	17	0 .	24
		min	-9.17	24	024	20	024		.027	7	0	_4	0	4
M81	1	max	9.921	17	019	11	.053	17	0	11	0	4	0	4
		min	-9.17	24	019			7	.027	7	0	17	0	20
	2	max	9.663	17	.017	4	014	11	001	4	0	24	0	17
		min	-9.094	24	013	7 11	.012	11	.025	4	0	4	0	4
M79	1	max	9.838	20	.074		047	7	02	11	0	4	0	4
11110		min	-2.06	17		11	.021	11	.02	11	0	20	0	20
	2	max	9.553	20	093	4	037	4	025	4	0	11	0	11
		min	-2.096		.093	4	.044	4	.019	11	0	4	0	4
M86	1		9.558	17	074	11	029	11	023	4	0	4	0	4
IVIOO	1	max		17	.028	20		17	.02	11	0	17	0]	24
	2	min	+8.841	24	+.014	4	037	7	+,024	4	0	24	0	17
	4	max	9.81	17	.022	4	.041	7	.027	7	0	4	0	4
M87	4	min	-8.922	24	023	20	022	17	0	11	0	4	0	4
10107	1	max	9.81	17	.021	11	.047	7	.027	7	0	17	0	24
-		min	-8.922	24	022	4	014	11	001	4	0	24	0	17
-		max	9.558	17	.019	7	.011	11	.024	4	0	4	0	4
NAGE		min		24	014	11	041	7	02	11	0	4	0	4
M85	1	max	9.12	20	07	11	,022	11	,02	11	0	17	0	24
		min	-2.986	17	+.088	4	037	4	025	4	0	24	0	4
		max i	8.846	20	.088	4	.043	4	.018	11	0	4	0	4
BA777		min	-3.019	17	07	11	029	11	023	4	0	4	0	4
M77	_1	max	8.912	24	.056	7	.083	7	.026	4	0	20	0	20
		min	-9.328	17	069	4	031	4	02	11	0	24	0	24
 	2	max	8.686	24	.066	4	.04	4	0	11	0	4	0	4
		min	-9.241	17	054	7	085	7	025	7	0	4	0	4
M78	1	max		24	.048	11	.038	11	,001	4	0	17	 	20
É		min !	-9.241	17	066	4	076	7	025	7	o l	24		17
	2	max	8.912	24	.069	4	.072	7	.02	111	0	4	0 1	4
		min !	-9.328	17	049	11		24	026	4	0	4	0 :	4
M74	1	max	8.549	17		20		17:		11	0	4	0	4
		min :	-8.534	24	017	4	036	7	024	4		11		$\frac{7}{11}$
	2	max:		17	.021	4	.042	7	.026	7	0	4	0	4
		min:		24	-	20		17		11	0	4	0	4
														_

Cromwell Cellphone Tower

July 13, 2002 5:55 PM Checked By:_

Member Label			Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	
M75	1	max	8.82	17	.022	11	.051	7	.026	7	0	20	0	
	-	min	-8.607	24	021	4	014	11	001	4	0	24	0	
	2	max	8,549	17	.024	7	.011	11	.024	4	0	4	0	
NA74	4	min	+8.534	24	+ 017	24	+.043	7	+.019	11	0	4	0	
M71	1	max	8.522	24	.061	7	.087	7	.024	4	0	24	0	
	<u> </u>	min	-8.588	17	072	4	032	4	019	11	0	20	0	
	2	max	8.288	24	.07	4	.041	4	0	11	0	4	00	1
8.8770		min	-8.506	17	059	7	089	7	024	7	0	4	0	1
M72	1	max	8.288	24	.05	11	.039	24	.001	4	0	17	0	
		min	-8.506	17	07	4	- 079	7	-,024	7	0	7	Q	
	2	max	8.522	24	.072	4	.075	7	.019	11	0	4	0	1
MOO		min	+8.58 8	17	÷.051	11	+ 034	24	+.024	4	0	4	0	1
M90	1	max	7.455	20	.043	11	.034	11	.001	4	0	24	0	1
		min	-5.639	17	06	4	069	7	025	7	0	17	0	
	2	max	7.637	20	.061	4	.068	7	.021	11	0	4	0	1
1100		min	-5.733	17	044	11	027	24	026	4	0	4	0	1
M83	1	max	7.288	24	.052	7	.078	7	.026	4	0	4	0	1
		min	-7.093	17	066	4	029	4	021	11	0	20	0	
	2	max	7.066	24	.064	4	.039	4	0	11	0	4	0	1
1.04		min	-6.995	17	05	7	079	7	025	7	0	4	0	Ì
M84	1	max	7.066	24	.047	11	.037	11	.001	4	0	17	0	Ī
		min	-6.995	17	064	4	071	7	025	7	0	24	0	l
	2	max	7.288	24	.066	4	.068	7	.021	11	0	4	0	
MOO		min	-7.093	17	048	11	03	24	026	4	0	4	0	
M89	1	max	6.159	24	.047	7	.076	7	.026	4	0	24	0	1
		min	-6.887	20	061	4	027	4	-,021	11	0	17	0	k
		max	5.948	24	.06	4	.038	4	.001	11	0	4	0	
1100	4	min	-6.883	20	- 047	7	076	7	-,025	7	0	4	0	
M88	1	max	3.415	24	.07	11	.029	11	.023	4	0	24	0	1
		min	-8.272	20	088	4	043	4	018	11	0	20	0	
	2	max	3.515	24	.088	4	.037	4	.025	4	0	4	0	ĺ
		min	-8.372	20	07	11	022	11	02	11	0	4	0	ĺ
M82	1	max !	2.323	24	.074	11	.029	11	.023	4	0	24	0	
		min j	-9.197	20	093	4	044	4	019	11	0	20	0	
	**********	max	2:429	24	.093	4	.037	4	.025	4	0	4	0	
1470				20		11		11	-,02	11	0	4	0	
M70		max	1.029	24	.082	11	.034	11	.022	4	0	4	0	
		min	-10.168	20	104	4	051	17	018	11	0	11	0	Ĺ
		max	1.166	24	.104	4	.044	17	.023	4	0	4	0	
		min	-10.251	20	083	11	025	11	019	11	0	4	0	
M76		max	.256	4	.078	11	.033	11	.023	4	0	4	0 j	
	~~~	min	-10.166	20	098	4	049	4	018	11	0	11	0	
	2	max	.266	17	.099	4	.041	17	.025	4	0	4	0	
	· · · · · · · · · · · · · · · · · · ·	min	-10.255	20	078	11	023	11	02	11	0	4	0	

Company : James A. Mieczkowski, P.E. Designer : Jim Mieczkowski Job Number : 15364.1251 Cro **Cromwell Cellphone Tower** 

July 13, 2002 5:57 PM Checked By:

**Envelope Member Section Forces** 

Member Label	Section	n	Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	Lc
M93	1	max	8.709	17	.017	11	.05	7	.028	7	0	24	0	17
		min	-7.846	24	017	4	016	11	002	4	0	17	0	20
	2	max	8.456	17	.019	7	.013	11	.025	4	0	4	0	4
		min	-7.747	24	008	11	044	7	02	11	0	4	0	4
M92	1	max		17	.028	20	.019	17	.02	11	0	20	0	24
		min	-7.747	24	007	4	04	7	025	4	0	24	0	17
	2	max	8.709	17	.017	4	.044	7	.028	7	0	4	0	4
		min	-7.846	24	021	20	024	17	001	11	0	4	0	4
M96	1	max	7.312	20	.043	11	.037	11	.002	4	0	20	0	20
		min	-3.672	17	058	4	067	7	026	7	0	17	0	17
	2	max	7.485	20	.06	4	.065	7	.021	11	0	4	0	4
		min	-3.795	17	044	11	027	11	026	4	0	4	0	4
M91	1	max	7.4	20	.07	11	.02	11	.02	11	0	24	0	4
		min	-3,802	17	086	4	033	4	025	4	0	17	0	11
	2	max	7.113	20	.086	4	.041	4	.018	11	0	4	0	4
		min	-3.835	17	-,069	11	03	11	023	4	0	4	0	4
M99	1	max	6.581	17	.018	11	.047	7	.026	7	0	20	0	17
		min	-6.12	24	02	4	016	11	002	4	0	17	0	24
	2	max	6.328	17	.02	7	.013	24	.023	4	0	4	0	4
		min	-6.011	24	008	11	04	7	018	11	0	4	0	4
M98	1	max	6.328	17	.026	20	.016	17	.018	11	0	20	0	20
		min	-6.011	24	009	4	038	7	023	4	0	4	0	4
	2	max	6.581	17	.02	4	.043	7	.026	7	0	4	0	4
		min	-6.12	24	018	11	022	17	001	11	0	4	0 1	4
M97	1	max	6.053	20	.066	11	.02	11	.018	11	0	17	0	17
		min	-2.178	17	082	4	032	4	023	4	0	24	0	24
	2	max	5.771	20	.081	4	.041	4	.017	11	0	4	0	4
	,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,	min	-2.211	17	066	11	031	11	021	4	0	4	0	4
M105	1	max	5.25	17	.016	11	.05	7	.023	7	0	24	0	17
		min i	-4.652	24	017	4	016	11	001	4	0	17	0	20
	2	max	4.986	17	.012	7	.013	11	.019	4	0	4	0	4
		min	-4.527	24	004	17	046	7	016	11	0	4	0	4
M104	1	max	4.986	17	.02	20	.018	17	.016	11	0	17	0	24
		min	-4.527	24	003	4	043	7	019	4	0	20	0	17
_	2	max	5.25	17	.017	4	.046	7	.023	7	0	4	0	4
14400	4	min	-4.652	24	016	11	023	17	001	11	0	4	0	4
M102	1	max		20	.04	11	.035	11	.002	4	0	24	0	20
		min	-3.81	17	054	4	065	7	024	7	0	17	0	11
	~~~~	max	5.15	20	.056	4	.064	7	.02	11	0	4	0	4
M400		min	-3.935	17	042	11	024	11	024	4	0	4	0	4
M108	1	max	4.324	20	.04	11	.034	11	.002	4	0	17	0	17
-	-	min	-2.168	17	052	4	059	7	021	7	0	24	0	20
-		max	4.483	20	.055	4	.06	7	.017	11	0	4	0	4
14402	area, area area	min	-2.317	17	041	11	022	11	021	4	0	4	0	4
M103		max	4 472	20	.063	11	.017	11	.016	11	0	17	0	24
		min !	-2.148	17	078	4	027	4	02	4	0	24	0	20
		max į	4.177	20	.077	4	.036	4	.014	11	0	4	0 1	4
MOA		min !	-2.186	171	062	11	026	11	018	4	0	4	0	4
M94	t	max:	4.237	24	.069	11	.03	11	.023	4	0	17	0	4
-		min	-6.502	20	086	4	041	4	018	11 :	0	24		20_
-		max	4.323	24	.086	4	.033	4	.025	4	0	4	0	4
	i	min!	-6.634	20	07	11	02	11	02	11	0	4	0	4

Cromwell Cellphone Tower

July 13, 2002 5:57 PM Checked By:_

Member Label	Section	n	Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	Lc
M95	1	max	4,268	24	.046	7	.073	7	.026	4	0	24	O O	17
		min	-6.719	20	06	4	028	4	021	11	0	7	0	20
	2	max	4.046	24	.058	4	.041	4	.001	11	0	4	0	4
		min	-6.701	20	+.044	7	072	7	+.026	7	0	4	0	4
M101	1	max	4.067	24	.042	7	.07	7	.024	4	0	17	0	17
		min	-4.812	20	056	4	025	4	02	11	0	24	0	24
	2	max	3.848	24	.054	4	.04	4	.001	11	0	4	0	4
		min	-4.784	20	04	11	069	7	024	7	0	4	0	4
M107	1	max	2.649	24	.041	11	.065	7	.021	4	0	20	0	17
		min	-3.94	20	-,055	4	023	4	017	11	. 0	17	0	24
	2	max	2.42	24	.052	4	.039	4	.001	11	0	4	0	4
		min	-3.912	20	٠.04	11	- 063	7	+.021	7	0	4	0	4
M106	1	max	2.473	24	.062	11	.026	11	.018	4	0	24	0	17
		min	-3.767	20	077	4	036	4	014	11	0	17	0	24
	2	max	2.539	24	.078	4	.027	4	.02	4	0	4	0	4
		min	-3.928	20	063	11	017	11	016	11	0	4	0	4
M100	1	max	2.32	24	.066	11	.031	11	.021	4	0	17	0	24
		min	-5.581	20	081	4	041	4	017	11	0	24	0	17
	2	max	2.399	24	.082	4	.032	4	.023	4	0	4	0	4
		min [-5.718	20	-,066	11	-,02	11	018	11	0	4	0	4

Company : James A. Mieczkowski, P.E. Designer : Jim Mieczkowski Job Number : 15364.1251 Cro **Cromwell Cellphone Tower**

July 13, 2002 5:58 PM Checked By:_


Envelope Member Section Forces

M115	Member Label	Section	1	Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	Lc
Mil	M115	1	max		20		24		7		11		4		1
Part			min	051	17	013	17	008	17					 	
MI09	!	2		2.963	20	.013	17	.008	17	.037			4	 	
M109			min	059	17	01	24	.001	7	046	4	 		<u> </u>	
M121 1 max 2.952 2.01 2.4	M109	1	max	2.978	20	.01	24	001	7	.047	11				
1			min	234	11	013	17	008	17	059	4				
M121		2	max	2.952	20	.013	17	.008	17	.047	11		*****		
M121			min	235	11	01	24	.001	7	059			4	***************************************	
Min	M121	1	max		20	.01	24	001	7	.033	11		4		
Mil			min			013	17	008	17	041		0	4		
Mil		_2_				.013	17	.008	17	.033	11	0			
M127						01	24	.001	7	041	4	0	4		
Min 1.05 17 -013 17 -008 17 -035 4 0 4	M127	1	max		20	.01	24	001	7	028	11	0			
Part			min	105	17	013	17	008	17	035	4				
M117		2	max	2.651	20	.013	17	.008	17	***************************************	11				
M117			min	113	17	01	24	.001	7	035	4				
Min -2-625	M117	1	max	2.67	17	.009	24		20					***************************************	***************************************
M116			min	-2.625	24	003	17								
M116		2	max	2.643	17	.003									
M116			min	-2.613	1										
Min 2.613 24 -003 17 -002 7 -021 4 0 4	M116	1	max	2.643											
Mathematical Program Mathematical Program															
M113		2	max	2.67											
M113			min	-2.625		***************************************									*********
Min	M113	1	max	2.662									**********		***************************************
M114			min			1									
M114	<u> </u>	2	max												
M114															
Min	M114	1													
M120	i	Walter warmen													
M120	i i														
M120				~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~~		~~~~~									
Min	M120	4							* * * * * * * * * * * * * * * * * * * *					on the second se	
M119															
M119															
M119		i													
Min -2.617 17 013 17 0.01 11 035 7 0 4 0	M119	Mark a book of the	33 34 34 54 54 A												
M122 max 2.54 24 013 17 001 11 024 4 0		1	******				*********	T. C.			********				20000000
M122	<u></u>			***************************************							***********		*******		*************
M122	1 <u>0</u> 0			~~~											
min -2.443 24 003 17 002 7 019 4 0	M122									144					
2 max 2.513 17 .003 17 .002 7 .032 7 0 4 0															
M123	-														
M123	-	— i-													
min -2.455 24 -003 17 001 11 -015 11 0 4 0 4 2 max 2.485 17 003 17 -001 11 032 7 0 4 0 4 min -2.443 24 -009 24 -013 20 -015 11 0 4 0 4 M111 1 max 2.478 17 .009 24 .013 20 .048 7 0 4 0 4 min -2.446 24 003 17 .001 11 021 11 0 4 0 4 2 max 2.451 17 .003 17 001 11 .048 7 0 4 0 4	M123	4.1.1.1.1.1.1.1.1.1.1.1.1.1.1.1.1.1.1.1				····							722222		COUNTY OF
2 max 2.485 17 .003 17 -001 11 .032 7 0 4 0 4	1111120														
M111 1 max 2.443 24009 24013 20015 11 0 4 0 4 min -2.446 24003 17 .001 11021 11 0 4 0 4 2 max 2.451 17 .003 17001 11 .048 7 0 4 0 4	<u> </u>														
M111 1 max 2.478 17 .009 24 .013 20 .048 7 0 4 0 4	\$33 333	~~~~~~~													
min -2.446 24003 17 .001 11021 11 0 4 0 4 2 max 2.451 17 .003 17001 11 .048 7 0 4 0 4	M111														
2 max 2.451 17 .003 17001 11 .048 7 0 4 0 4									<u>-</u>			 	i		
	: 														
+ 10001 = 2434 + 241 = 009 + 241 + 012 + 201 + 024 + 441 + 0 + 41 + 0 = 41	: 														4
	-		min i	-2.434	24	009	24	013	20	021	11	0	4	0 -	4

Cromwell Cellphone Tower

July 13, 2002 5:58 PM Checked By:__

Envelope M	<u>lemb</u>	er Se	ection Fo	rces	, (contin	uedj)					ŧ		
Member Label	Sectio	n	Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	Lc
M110	1	max	2.451	17	01	20	.006	17		7	`O	4	0	4
		min	-2.434	24	003	17	002	7	026	4	0	4	0	4
	2	max	2,478	17	.003	17	.002	7	.047	7	Ö	4	0	4
		min	-2.446	24	- 01	20	+.006	17	+.026	4	Ö	4	0	4
M126	1	max	2.424	24	.004	11	.006	17	.017	11	0	4	0	4
	ļ	min	-2.454	17	013	17	002	7	031	7	0	4	0	4
	2	max	2.444	24	.013	17	.002	7	.017	11	0	4	0	4
Managara da		min	-2.466	17	004	11	006	17	031	7	0	4	0	4
M125	1	max	2.444	24	.004	11	.013	20	.022	4	0	4	0	4
		min	-2.466	17	-,013	17	.001	11	-,031	7	0	4	0	4
	2	max	2.424	24	.013	17	- 001	11	,022	4	0	4	0	4
11/00		min	-2.454	17	+.004	11	- 013	20	+.031	7	0	4	0	4
M129	1	max	2.408	17	.009	24	.013	20	.028	7	0	4	0	4
		min	-2.375	24	003	17	.001	11	013	11	0	4	0	4
	2	max	2.381	17	.003	17	001	11	.028	7	0	4	0	4
	***************************************	min	-2.363	24	009	24	013	20	013	11	0	4	0	4
M128	1	max	2.381	17	.01	20	.006	17	.028	7	0	4	0	4
		min	-2.363	24	003	17	002	7	017	4	0	4	O	4
	2	max	2.408	17	.003	17	.002	7	,028	7	0	4	0	4
1404		min	-2.375	24	01	20	006	17	017	4	0	4	0	4
M131	1	max	2.255	24	.004	11	.013	20	.019	4	0	4	0	4
		min	-2.287	17	013	17	.001	11	027	7	0	4	0	4
	2	max	2.235	24	.013	17	001	11	.019	4	0	4	0	4
N.6400	20000210000	min	-2.275	17	004	11	013	20	027	7	0	4	0	4
M132	1	max	2.235	24	.004	11	.006	17	.015	11	0	4	0	4
		min	-2.275	17	013	17	- 002	7	027	7	0	4	0	4
	2	max	2.255	24	013	17	.002	7	.015	11	0	4	0	4
M133	4	min	-2.287	17	-,004	11	006	17	-,027	7	0	4	0	4
101133	1	max	2.025	20	.01	24	001	7	.025	11	0	4	0	4
	2	min	226	4	013	17	008	17	031	4	0	4	0	4
		max	1.998	20	.013	17	.008	17	.025	11	0	4	0	4
M134	4	min	232	4	01	24	.001	7	031	4	0	4	0	4
IVI 154	1	max	1.856	17	.01	20	.006	17	.025	7	0	4	0	4
		min i	-1.836	24	003	17	002	7	015	4	0	4	0	4
	2	max	1.883	17	.003	17		7	.025	7	0	4	0	4
M135	1	min	-1.848	24	- 01	20		17	015	4	0	4	0	4
141122	1	max min	1.883 -1.848	17	.009	24	.013	20	.025	7	0	4	0	4
	2			24	003	17	.001	11	012	11	0	4	0	4_
		max min	1.856 -1.836	17	.003	17	001	11	.025	7	0	4	0	4_
M139	1		1.865	24	009	24	013 <u> </u>	20	012	11	0	4	0 [4_
im io 3	J	max min	068	20	.01	24	001 000	7	.023	11	0	4	0 1	4
	2	max	1.839	20	013	17	008	17	- 029	4	0	4	0	4
	***********	min	07	11	.013	17		17	023	11	0	4	0	4
M145			1.741			24	.001	7	029	4	0	4	0	4
111173	- '	max i	088	20	.01	24	001	7	.022	11	0	4	0	4_
	2	max	1.715	20	013	17	008	17	027	4	0	4	0	4
		min :	093	4	.013	17		17	.022	11	0	4	0	4_
M138		max -		24	01 .004	24	.001	7	027	4	0	4	0	4_
· · · · · · · · · · · · · · · · · · ·		min		17		11 17		17	***************************************	11	0	4	0 !	4
Ì		max	1.657	24			002	7	024	7	0	4	0	4
	22.77	min [*******	17	***************************************	17	.002	7		11	0	4	0 ;	4
M137		max !	1.657	24		11 11		17		7	0	4		4
		4^ !	1.001	47	.004	- 1	.010	20	.017	4	0	4	0 .	4



Cromwell Cellphone Tower

July 13, 2002 5:58 PM Checked By:_


Marther Label Section Main Lo Shear yr Lo Shear	Envelope M	lemb	er Se	ection Fo	rces	, (continu	ued))	=				*		
Min	Member Label	Sectio	n		Lc		Lc		Lc		Lc		Lc		Lc
2 max 1,636 24 0.13 17 -0.01 11 0.17 4 0 4 0 4 0 4 0 1 1 0.164 17 -0.04 11 0.13 20 -0.24 7 0 4 0 4 0 4 2 1 1 1 1 1 1 1 1 1			min		17	013	17		11		7		4	7	4
Mil49		2	max		24	.013	17	001	11			1			+
Mi43	(min		17	004	11	013	20	024			4		
M144	M143	1	max			.004	11	.013	20	.015	4	0	4	0	
M144			min		*****	+.013	17	.001	11	022	7	0	4	0	
M144	1	2	max		24	.013	17	001	11	.015	4	0	4	0	*********
Miss			min		17	004	11	013	20	022	7	0	4	0	4
M141	M144	1	max			.004	11	.006	17	.012	11	0	4	0	4
M141	•						17	002	7	022	7	0	4	0	4
M141		2						.002	1	.012	11	0	4	0	4
M140		<u> </u>		·				006	17	022	7	0	4	0	4
M140	M141	1							20	.023	7	0	4	0	4
M140					****						11	0	4	0	4
M140		2									1	0	4	0	4
Min -1.571 24 -0.03 17 -0.02 7 -0.014 4 0	11446		, , , , , , , , , , , , , , , , , , , 			***					11	0	4	0	4
M151	M140	1						1			1	0	4	0	4
M151									1			0	4	0	4
M151		2	 							· · · · · · · · · · · · · · · · · · ·	7	0	4	0	4
Min -056 17 -013 17 -008 17 -026 4 0 4												0	4		
M146	M151	1									11	0	4	0	4
M146											4	0	4	0	4
M146		2								***********	11	0	4	0	4
Min			min				24		7	026	4	0	4	0	4
M147	M146	1							17	.021	7	0	4	0	4
M147									7		4	0	4	0	4
M147		2									7	0	4	0	4
Min -1.543 24 -0.03 17 0.01 11 -0.01 11 0 4 0 4 4 0 4 4 0 4 4		0000009000000										!···	4	0	4
M150	M147	1									7	0	4	0	4
M150											11	0	4	0	4
M150		2				the state of the s						0	4	0	4
Min	14450										11	0	4	0	4
M149	M150	1									11	0	4	0	4
M149									7	021	7	0	4	0	4
M149 1 max 1.476 24 004 11 .013 20 .014 4 0 4 0 4 min -1.491 17 013 17 .001 11 -021 7 0 4 0 4 2 max 1.455 24 .013 17 001 11 .014 4 0 4 0 4 min -1.479 17 004 11 013 20 021 7 0 4 0 4 min -1.375 24 003 17 002 7 013 4 0 4 0 4 2 max 1.412 17 .003 17 .002 7 .02 7 0 4 0 4 M153 1 max 1.412 17 .009 24 013 20 .02 7 0 <td></td> <td>0</td> <td>4</td> <td>0</td> <td>4</td>												0	4	0	4
Min	\$		min			004		006	17	021	7	0	4	0	4
M152	M149	1					11		20	.014	4	0	4	0 1	4
M152							***			-,021	7	0	4	0	4
M152 1 max 1.385 17 .01 20 .006 17 .02 7 0 4 0 4 min -1.375 24 003 17 002 7 013 4 0 4 0 4 2 max 1.412 17 .003 17 .002 7 .02 7 0 4 0 4 M153 1 max 1.412 17 .009 24 .013 20 .02 7 0 4 0 4 M153 1 max 1.412 17 .009 24 .013 20 .02 7 0 4 0 4 M153 1 max 1.387 24 .003 17 .001 11 .01 4 0 4 M153 1 max 1.335 17 .003 17 .001 11		2		**********************			**********				4	0	4	.0	4
min -1.375 24 003 17 002 7 013 4 0 4 0 4 2 max 1.412 17 .003 17 .002 7 .02 7 0 4 0 4 min -1.387 24 01 20 006 17 013 4 0 4 0 4 M153 1 max 1.412 17 .009 24 .013 20 .02 7 0 4 0 4 min -1.387 24 003 17 .001 11 .01 11 0 4 0 4 2 max 1.385 17 .003 17 .001 11 .02 7 0 4 0 4 min -1.375 24 009 24 013 20 01 11 0 4 0 4 M155 1 max 1.333 24 .004 11 .013 20 .013 4 0 4 0 4 M156 1 max 1.312 24 .013 17 .001 11 .013 20 .013 4 0 4 0 4 M156 1 max 1.312 24 .004 11 .013 20 .02 7 0 4 0 4 M156 1 max 1.312 24 .004 11 .013 20 .02 7 0 4 0 4 M156 1 max 1.312 24 .004 11 .006 17 .01 11 0 4 0 4	14450												4	0 1	
2 max 1.412 17 .003 17 .002 7 .02 7 0 4 0	IVI 152	1									7	0	4	0	4
M153									$\overline{}$				4	0	
M153 1 max 1 412 17 009 24 013 20 02 7 0 4 0 4 min -1.387 24 003 17 001 11 01 11 0 4 0 4 2 max 1.385 17 .003 17 -001 11 02 7 0 4 0 4 min -1.375 24 009 24 013 20 01 11 0 4 0 4 M155 1 max 1.333 24 .004 11 .013 20 .013 4 0 4 0 4 min -1.322 17 013 17 .001 11 02 7 0 4 0 4 min -1.31 17 004 11 0013 20 02 7 0 4 <td></td>															
M156 M158	N. 64 F.O														
Number 1.385 17 .003 17 .001 11 .02 7 0 4 0	[IVI I 53	1										0	4	0	
M155 1 max 1.333 24 .009 24 013 20 01 11 0 4 0 4 M155 1 max 1.333 24 .004 11 .013 20 .013 4 0 4 0 4 min -1.322 17 013 17 .001 11 02 7 0 4 0 4 2 max 1.312 24 .013 17 001 11 .013 4 0 4 0 4 min -1.31 17 004 11 0013 20 02 7 0 4 0 4 M156 1 max 1.312 24 .004 11 .006 17 .01 11 0 4 0 4	, -			1 1411111				4 2 4 1 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4		The state of the s			********		
M155 1 max 1.333 24 .004 11 .013 20 .013 4 0 4 0 4 min -1.322 17 013 17 .001 11 02 7 0 4 0 4 max 1.312 24 .013 17 001 11 .013 4 0 4 0 4 min -1.31 17 004 11 013 20 02 7 0 4 0 4 M156 1 max 1.312 24 .004 11 .006 17 .01 11 0 4 0 4	a de la companya de l	Z								*********		0	4	0	
min -1.322 17 013 17 .001 11 02 7 0 4 0 0	144.55									- 01	11	0	4	0	4
2 max 1.312 24 .013 17 001 11 .013 4 0 4 0 4 min -1.31 17 004 11 013 20 02 7 0 4 0 4 M156 1 max 1.312 24 .004 11 .006 17 .01 11 0 4 0 4	M155								20	<u>-</u>	4	0	4	0 !	4
min -1.31 17 004 11 013 20 02 7 0 4 0 4 M156 1 max 1.312 24 .004 11 .006 17 .01 11 0 4 0 4	! !										7	0	4	0	4
M156 1 max 1.312 24 004 11 006 17 01 11 0 4 0 4								<u></u>			4	C	4	0	4
		******************				·							4	0 i	
min -1.31 17 013 17 002 7 02 7 0 4 0 4											11	0 [4	0	
			min !	-1.31	17	013	17	002	7	-:02	7	0	4	0	4

Cromwell Cellphone Tower

July 13, 2002 5:58 PM Checked By:_

Envelope M			ction Fo	rces	, (contin	ued)								
Member Label			Axial (k)	Lc	Shear y-y (k)	Lc	Shear z-z (k)	Lc	Torque (k-ft)	Lc	Moment y-y (k-ft)	Lc	Moment z-z (k-ft)	Lo
	2	max	1.333	24	.013	17	.002	7	.01	11	0	4	0	4
		min	-1.322	17	-,004	11	006	17	-,02	7	0	4	0	4
M112	1	max	.293	4	.01	24	002	11	.059	4	0	4	0	4
		min	-2.939	20	013	17	012	20	047	11	0	4	0	4
	2	max	.298	4	.013	17	.012	20	.059	4	0	4	0	4
		min	-2.95	20	01	24	.002	11	047	11	0	4	0	4
M136	1	max	211	11	.01	24	002	11	.031	4	0	×4×	0	4
		min	-2.011	20	013	17	012	20	025	11	0	4	0	4
	2	max	.213	11	.013	17	.012	20	.031	4	0	4	0	4
		min	-2.022	20	01	24	.002	11	025	11	0	4	0	4
M130	1	max	.122	24	.01	24	002	11	.035	4	0	4	0	4
		min	-2.656	20	013	17	012	20	028	11	0	4	0	4
	2	max	.126	24	.013	17	.012	20	.035	4	0	4	0	4
		min	-2.667	20	01	24	.002	11	028	11	0	4	0	4
M142	1	max	.08	4	.01	24	002	11	.029	4	0	4	0	4
		min	-1.838	20	013	17	012	20	023	11	0	4	0	4
	2	max	.085	4	.013	17	.012	20	.029	4	0	4	O	4
		min	-1.849	20	01	24	.002	11	023	11	0	4	0	4
M148	1	max	.078	11	.01	24	002	11	.027	4	0	4	0	4
:		min	-1.734	20	013	17	012	20	022	11	0	4	0	4
	2	max	.08	11	.013	17	.012	20	.027	4	0	4	0	4
Francisco Company		min	-1.746	20	01	24	.002	11	022	11	0	4	0	4
M154	1	max	.069	24	.01	24	002	11	.026	4	0	4	0	4
		min ‡	-1.547	20	013	17	012	20	021	11	0	4	0	4
	2	max	.073	24		17	.012	20	.026	4	0	4	0	4
		min	-1.559	20	01	24	.002	11	021	11	0	4	0	4
M118	1	max	.057	24	.01	24	002	11	.046	4	0	4	0	4
		min	-2.978	20	013	17	012	20	037	11	0	4	0	4
	2	max	.061	24	.013	17	.012	20	.046	4	0	4	0	4
	20000 1000	min	-2.99	20	01	24	.002	11	037	11	0	4	0	4
M124	1	max	.022	11	.01	24	002	11	.041	4	0	4	0	4
		min j	-2.814	20	013	17	012	20	033	11	0	4	0	4
	2	maxi	.024	11		17	.012	20	.041	4	0	4	0 1	4
		min	-2.825	20	01	24	.002	11	033	11	0	4	0	4






Results for LC 2, Frame Weight Reaction units are kland k-ft

James A. Mieczkowski, P.E.	Cromwell Cellphone Tower	July 13, 2002
Jim Mieczkowski		4:49 PM
15364.1251	Frame Dead Load	cromsn002.r3d





Loads: DL (Dead Load Results for LC 1, Dead Weight Reaction units are k and k-ft

James A. Mieczkowski, P.E.
Jim Mieczkowski
15364.1251

Cromwell Cellphone Tower

All Dead Loads

July 13, 2002 4:52 PM cromsn002.r3d



1.116k 1.116k 1.116k

Loads: WL (Wind Load Results for LC 3, Wind Normal to a Face leadton units are kland k-f;

James A. Mieczkowski, P.E.
Jim Mieczkowski
15364.1251

Cromwell Cellphone Tower

July 13, 2002

Normal Wind Loads (Wind to Frame not shown)

4:57 PM cromsn002.r3d



Loads: WL (Wind Load Results for LC 4, Dead+Normal Wind Readson units and k-ft

James A. Mieczkowski, P.E. Jim Mieczkowski 15364.1251 Cromwell Cellphone Tower


July 13, 2002

4:57 PM

cromsn002.r3d

Normal Wind Loads (Wind to Frame not shown)





Loads: EL (Earthquake Load Results for LC 7, Dead+90° Wind Reaction units are kland k-ft


James A. Mi	eczkowski, P.E.
Jim Mieczko	wski
15364.1251	

Cromwell Cellphone Tower

July 13, 2002 5:03 PM cromsn002.r3d

Dead + 90 degree Wind Loads






Loads: EL (Earthquake Load Results for LC 11, Dead+60* Wind Reaction units are k and k-ft

James A. Mieczkowski, P.E.	Cromwell Cellphone Tower	July 13, 2002
Jim Mieczkowski		5:04 PM
15364.1251	Dead + 60 degree Wind Loads	cromsn002.r3d





Loads: LC 13, Frame with Ice Results for LC 14, Ice Reaction units are kland k-ft

James A. Mieczkowski, P.E.

Jim Mieczkowski

15364.1251

Cromwell Cellphone Tower


Ice on Frame

July 12, 2002

11:41 AM

cromsn002.r3d






Results for LC 13, Frame with Ice Reaction units are k and k-ft

James A. Mieczkowski, P.E.	Cromwell Cellphone Tower
Jim Mieczkowski	
15364.1251	Frame DL + Ice on Frame

 July 13, 2002	-
5:19 PM	-
cromsn002.r3d	-





Loads; IL (Impact Load Results for LC 15, Dead+Ice leaction units are k and k-ft

James A. Mieczkowski, P.E.
Jim Mieczkowski
15364.1251


Cromwell Cellphone Tower

July 13, 2002 5:20 PM

All Dead Loads + All Ice Loads

cromsn002.r3d





Loads: LC 16, Normal Wind on Ice Results for LC 16, Normal Wind on Ice Reaction units are k and k-ft

James A. Mieczkowski, P.E.
Jim Mieczkowski
15364.1251

Cromwell Cellphone Tower


July 13, 2002

Normal Wind on Ice (Wind to Frame not shown)

5:31 PM

cromsn002.r3d





Loads: LC 17, Dead+ice+.75N Wind Results for LC 17, Dead+ice+.75N Wind leaction units are kiler/dik-ft


James A. Mieczkowski, P.E. Jim Mieczkowski 15364.1251

Cromwell Cellphone Tower

July 13, 2002 5:32 PM cromsn002.r3d

Dead Load + Ice Load + Normal Wind on Ice






Loads: LC 20, Dead+tce+90° Wind Results for LC 20, Dead+tce+90° Wind Reaction units are k and k-ft

James A. Mieczkowski, P.E.	Cromwell Cellphone Tower	July 13, 2002	
Jim Mieczkowski		5:36 PM	
15364.1251	Dead Load + Ice Load + .75 x 90 degree Wind on Ice	cromsn002.r3d	





Loads: LC 20, Dead+Ice+90* Wind Results for LC 24, Dead+Ice+60* Wind reaction units are k and k-ft

	James A. Mieczkowski, P.E.
1	Jim Mieczkowski
	15364.1251

Cromwell	Cellphone	Tower
----------	-----------	-------

July 13, 2002 5:37 PM cromsn002.r3d

 $.33 \times (DL + Ice Load) + .75 \times 60$ degree Wind on Ice