

February 12th, 2018

Melanie Bachman, Executive Director Connecticut Siting Council 10 Franklin Square New Britain, CT 06051

RE: Notice of Exempt Modification – Antenna Swap for wireless facility located at 864 OPENING HILL ROAD, MADISON, CT 06443 – CT03XC164 (lat. 41° 21' 26.33" N, long. -72° 38' 19.51" W)

Dear Ms. Bachman:

Sprint Spectrum, LP ("Sprint") currently maintains wireless telecommunications antennas at the (150-foot level) on an existing (199-foot self-support tower) at the above-referenced address. The property is owned by JAY SHERWOOD, and the tower is owned by American Tower Corporation.

Sprint's proposed work involves antenna replacement and tower work. Sprint intends to replace three (3) antennas and add three (3) new RRHs onto the tower. All the proposed work is contained within the existing fenced area. Please refer to the attached drawings for site plans prepared by Infinigy Engineering.

Please accept this letter as notification pursuant to R.C.S.A. § 16-50j-73, for construction that constitutes an exempt modification pursuant to R.C.S.A. § 16-50j-72(b). In accordance with R.C.S.A. § 16-50j-73, a copy of this letter is being sent to TOM BANISCH, FIRST SELECTMAN, and DAVID ANDERSON, TOWN PLANNER of the Town of MADISON. A copy of this letter is also being sent to JUSTINE PAUL the manager for AMERICAN TOWER CORPORATION who manages the site and to the NO. MADISON VOLUNTEER FIRE DEPARTMENT who owns the land.

The planned modifications to the facility fall squarely within those activities explicitly provided for in R.C.S.A. § 16-50j-72(b).

- The proposed modifications will not result in an increase in the height of the existing tower.
- 2. The antennas work is a one-for-one replacement of facility components.
- The proposed modifications will include the addition of ground base equipment as depicted on the attached drawings; however, the proposed equipment will not require





an extension of the site boundaries.

- The proposed modifications will not increase noise levels at the facility by six decibels or more.
- The additional ground based equipment will not increase radio frequency (RF) emissions at the facility to a level at or above the Federal Communications Commission (FCC) adopted safety standard.

For the foregoing reasons, Sprint respectfully submits that the proposed modifications to the above referenced telecommunications facility constitutes an exempt modification under R.C.S.A. § 16-50j-72(b).

If you have any questions or require any additional information regarding this request, please do not hesitate to give me a call at (518) 350-4222 or email me to <a href="mailto:aperkowski@airosmithdevelopment.com">aperkowski@airosmithdevelopment.com</a>

Kind Regards,

Arthur Perkowski

Airosmith Development Inc.

32 Clinton Street

Saratoga Springs, NY 12866

518-306-1711 desk & fax

518-871-3707 cell

aperkowski@airosmithdevelopment.com

#### Attachment


CC: TOM BANISCH (FIRST SELECTMAN, MADISON, CT)

JUSTINE PAUL (Manager, AMERICAN TOWER CORPORATION)

DAVID ANDERSON (Town Planner / MADISON, CT)

NO. MADISON VOLUNTEER FIRE DEPARTMENT (Land Owner)

# No. Madison Volunteer Fire Co Inc.



## **OPENING HILL RD**

**Location** OPENING HILL RD **Mblu** 134/ 18/ / /

Acct# 00665800 Owner NORTH MADISON

VOLUNTEER FIRE DEPT INC

**Assessment** \$93,800 **Appraisal** \$134,000

PID 7029 Building Count 1

#### **Current Value**

Appraisal					
Valuation Year Improvements Land Total					
2015	\$0	\$134,000	\$134,000		
Assessment					
Valuation Year	Improvements	Land	Total		
2015	\$	0 \$93,800	\$93,800		

#### **Owner of Record**

**Owner** NORTH MADISON VOLUNTEER FIRE DEPT INC **Sale Price** \$0

Co-Owner Certificate

**Book & Page** 196/851

Sale Date

#### **Ownership History**

Ownership History					
Owner Sale Price Certificate Book & Page Sale Date					
NORTH MADISON VOLUNTEER FIRE DEPT INC	\$0		196/ 851		

#### **Building Information**

# **Building 1 : Section 1**

## Year Built:

Living Area: 0

Building Attributes			
Field Description			
Style	Vacant Land		
Model			
Stories:			

Heat Fuel	
Heat Type:	
AC Type:	
Total Bedrooms:	
Total Bthrms:	
Total Half Baths:	
Total Xtra Fixtrs:	
Total Rooms:	
Fireplace(s)	
Xtra FPL Open	

# **Building Photo**



(http://images.vgsi.com/photos/MadisonCTPhotos/\\01\00\72/61

# **Building Layout**

**Building Layout** 

Building Sub-Areas (sq ft)	<u>Legend</u>
No Data for Building Sub-Areas	

**Extra Features** 

Extra Features	<u>Legend</u>
No Data for Extra Features	

#### Land

Land Use		Land Line Valuation	
Use Code	9030	Size (Acres)	4.23
Description	Municipal	Depth	0
Zone	RU-1		

# Outbuildings

Outbuildings	<u>Legend</u>
No Data for Outbuildings	

# **Valuation History**

Appraisal				
Valuation Year Improvements Land Total				
2016	\$0	\$134,000	\$134,000	

Assessment				
Valuation Year Improvements Land Total				
2016	\$0	\$93,800	\$93,800	

(c) 2016 Vision Government Solutions, Inc. All rights reserved.



# RADIO FREQUENCY EMISSIONS ANALYSIS REPORT EVALUATION OF HUMAN EXPOSURE POTENTIAL TO NON-IONIZING EMISSIONS

# **SPRINT Existing Facility**

Site ID: CT03XC164

N. Madison / Vol. Fire Dept.(1173-1245) Durham RoadMadison, CT 06443

August 31, 2017

EBI Project Number: 6217003876

Site Compliance Summary		
Compliance Status:	COMPLIANT	
Site total MPE% of		
FCC general	11.18 %	
population 11.10 /6		
allowable limit:		



August 31, 2017

SPRINT Attn: RF Engineering Manager 1 International Boulevard, Suite 800 Mahwah, NJ 07495

Emissions Analysis for Site: CT03XC164 – N. Madison / Vol. Fire Dept.

EBI Consulting was directed to analyze the proposed SPRINT facility located at (1173-1245) **Durham Road, Madison, CT**, for the purpose of determining whether the emissions from the Proposed SPRINT Antenna Installation located on this property are within specified federal limits.

All information used in this report was analyzed as a percentage of current Maximum Permissible Exposure (% MPE) as listed in the FCC OET Bulletin 65 Edition 97-01and ANSI/IEEE Std C95.1. The FCC regulates Maximum Permissible Exposure in units of microwatts per square centimeter ( $\mu$ W/cm2). The number of  $\mu$ W/cm² calculated at each sample point is called the power density. The exposure limit for power density varies depending upon the frequencies being utilized. Wireless Carriers and Paging Services use different frequency bands each with different exposure limits, therefore it is necessary to report results and limits in terms of percent MPE rather than power density.

All results were compared to the FCC (Federal Communications Commission) radio frequency exposure rules, 47 CFR 1.1307(b)(1) - (b)(3), to determine compliance with the Maximum Permissible Exposure (MPE) limits for General Population/Uncontrolled environments as defined below.

General population/uncontrolled exposure limits apply to situations in which the general population may be exposed or in which persons who are exposed as a consequence of their employment may not be made fully aware of the potential for exposure or cannot exercise control over their exposure. Therefore, members of the general population would always be considered under this category when exposure is not employment related, for example, in the case of a telecommunications tower that exposes persons in a nearby residential area.

Population exposure to radio frequencies is regulated and enforced in units of microwatts per square centimeter ( $\mu$ W/cm²). The general population exposure limits for the 850 MHz Band is approximately 567  $\mu$ W/cm². The general population exposure limit for the 1900 MHz (PCS) and 2500 MHz (BRS) bands is 1000  $\mu$ W/cm². Because each carrier will be using different frequency bands, and each frequency band has different exposure limits, it is necessary to report percent of MPE rather than power density.



Occupational/controlled exposure limits apply to situations in which persons are exposed as a consequence of their employment and in which those persons who are exposed have been made fully aware of the potential for exposure and can exercise control over their exposure. Occupational/controlled exposure limits also apply where exposure is of a transient nature as a result of incidental passage through a location where exposure levels may be above general population/uncontrolled limits (see below), as long as the exposed person has been made fully aware of the potential for exposure and can exercise control over his or her exposure by leaving the area or by some other appropriate means.

Additional details can be found in FCC OET 65.

#### **CALCULATIONS**

Calculations were done for the proposed SPRINT Wireless antenna facility located at (1173-1245) **Durham Road, Madison, CT**, using the equipment information listed below. All calculations were performed per the specifications under FCC OET 65. Since SPRINT is proposing highly focused directional panel antennas, which project most of the emitted energy out toward the horizon, all calculations were performed assuming a lobe representing the maximum gain of the antenna per the antenna manufactures supplied specifications, minus 10 dB, was focused at the base of the tower. For this report the sample point is the top of a 6-foot person standing at the base of the tower.

For all calculations, all equipment was calculated using the following assumptions:

- 1) 1 CDMA channels (850 MHz) were considered for each sector of the proposed installation. These Channels have a transmit power of 20 Watts per Channel.
- 2) 2 LTE channels (850 MHz) were considered for each sector of the proposed installation. These Channels have a transmit power of 20 Watts per Channel.
- 3) 5 CDMA channels (1900 MHz (PCS)) were considered for each sector of the proposed installation. These Channels have a transmit power of 16 Watts per Channel.
- 4) 2 LTE channels (1900 MHz (PCS)) were considered for each sector of the proposed installation. These Channels have a transmit power of 40 Watts per Channel.
- 5) 8 LTE channels (2500 MHz (BRS)) were considered for each sector of the proposed installation. These Channels have a transmit power of 20 Watts per Channel.



- 6) All radios at the proposed installation were considered to be running at full power and were uncombined in their RF transmissions paths per carrier prescribed configuration. Per FCC OET Bulletin No. 65 Edition 97-01 recommendations to achieve the maximum anticipated value at each sample point, all power levels emitting from the proposed antenna installation are increased by a factor of 2.56 to account for possible in-phase reflections from the surrounding environment. This is rarely the case, and if so, is never continuous.
- 7) For the following calculations, the sample point was the top of a 6-foot person standing at the base of the tower. The maximum gain of the antenna per the antenna manufactures supplied specifications minus 10 dB was used in this direction. This value is a very conservative estimate as gain reductions for these particular antennas are typically much higher in this direction.
- 8) The antennas used in this modeling are the RFS APXVSPP18-C-A20 and the RFS APXVTM14-C-I20 for transmission in the 850 MHz, 1900 MHz (PCS) and 2500 MHz (BRS) frequency bands. This is based on feedback from the carrier with regards to anticipated antenna selection. Maximum gain values for all antennas are listed in the Inventory and Power Data table below. The maximum gain of the antenna per the antenna manufactures supplied specifications, minus 10 dB, was used for all calculations. This value is a very conservative estimate as gain reductions for these particular antennas are typically much higher in this direction.
- 9) The antenna mounting height centerlines of the proposed antennas are **150 feet** above ground level (AGL) for **Sector A**, **150 feet** above ground level (AGL) for **Sector B** and **150 feet** above ground level (AGL) for Sector C.
- 10) Emissions values for additional carriers were taken from the Connecticut Siting Council active database. Values in this database are provided by the individual carriers themselves.

All calculations were done with respect to uncontrolled / general population threshold limits.



## SPRINT Site Inventory and Power Data by Antenna

Sector:	A	Sector:	В	Sector:	C
Antenna #:	1	Antenna #:	1	Antenna #:	1
Make / Model:	RFS	Make / Model:	RFS	Make / Model:	RFS
	APXVSPP18-C-A20		APXVSPP18-C-A20		APXVSPP18-C-A20
Gain:	13.4 / 15.9 dBd	Gain:	13.4 / 15.9 dBd	Gain:	13.4 / 15.9 dBd
Height (AGL):	150 feet	Height (AGL):	150 feet	Height (AGL):	150 feet
Frequency Bands	850 MHz /	Frequency Bands	850 MHz /	Frequency Bands	850 MHz /
Trequency Dands	1900 MHz (PCS)	riequency bands	1900 MHz (PCS)	rrequericy bands	1900 MHz (PCS)
Channel Count	10	Channel Count	10	Channel Count	10
Total TX	220 Watts	Total TX	220 Watts	Total TX	220 Watts
Power(W):	220 watts	Power(W):	220 Walls	Power(W):	220 watts
ERP (W):	7,537.38	ERP (W):	7,537.38	ERP (W):	7,537.38
Antenna A1 MPE%	1.48 %	Antenna B1 MPE%	1.48 %	Antenna C1 MPE%	1.48 %
Antenna #:	2	Antenna #:	2	Antenna #:	2
Make / Model:	RFS	Make / Model:	RFS	Make / Model:	RFS
	APXVTM14-C-I20		APXVTM14-C-I20		APXVTM14-C-I20
Gain:	15.9 dBd	Gain:	15.9 dBd	Gain:	15.9 dBd
Height (AGL):	150 feet	Height (AGL):	150 feet	Height (AGL):	150 feet
Frequency Bands	2500 MHz (BRS)	Frequency Bands	2500 MHz (BRS)	Frequency Bands	2500 MHz (BRS)
Channel Count	8	Channel Count	8	Channel Count	8
Total TX	160 Watts	Total TX	160 Watts	Total TX	160 Watts
Power(W):	100 watts	Power(W):	100 watts	Power(W):	100 wans
ERP (W):	6,224.72	ERP (W):	6,224.72	ERP (W):	6,224.72
Antenna A2 MPE%	1.08 %	Antenna B2 MPE%	1.08 %	Antenna C2 MPE%	1.08 %

Site Composite MPE%				
Carrier	MPE%			
SPRINT – Max per sector	2.56 %			
AT&T	2.59 %			
Verizon Wireless	6.03 %			
Site Total MPE %:	11.18 %			

SPRINT Sector A Total:	2.56 %
SPRINT Sector B Total:	2.56 %
SPRINT Sector C Total:	2.56 %
Site Total:	11.18 %

SPRINT _ Max Values per Frequency Band / Technology Per Sector	# Channels	Watts ERP (Per Channel)	Height (feet)	Total Power Density (µW/cm²)	Frequency (MHz)	Allowable MPE (µW/cm²)	Calculated % MPE
Sprint 850 MHz CDMA	1	437.55	150	0.76	850 MHz	567	0.13%
Sprint 850 MHz LTE	2	437.55	150	1.52	850 MHz	567	0.27%
Sprint 1900 MHz (PCS) CDMA	5	622.47	150	5.40	1900 MHz (PCS)	1000	0.54%
Sprint 1900 MHz (PCS) LTE	2	1,556.18	150	5.40	1900 MHz (PCS)	1000	0.54%
Sprint 2500 MHz (BRS) LTE	8	778.09	150	10.79	2500 MHz (BRS)	1000	1.08%
						Total:	2.56%



# **Summary**

All calculations performed for this analysis yielded results that were **within** the allowable limits for general population exposure to RF Emissions.

The anticipated maximum composite contributions from the SPRINT facility as well as the site composite emissions value with regards to compliance with FCC's allowable limits for general population exposure to RF Emissions are shown here:

SPRINT Sector	Power Density Value (%)
Sector A:	2.56 %
Sector B:	2.56 %
Sector C:	2.56 %
SPRINT Maximum	2.56 %
Total (per sector):	
Site Total:	11.18 %
Site Compliance Status:	COMPLIANT

The anticipated composite MPE value for this site assuming all carriers present is **11.18** % of the allowable FCC established general population limit sampled at the ground level. This is based upon values listed in the Connecticut Siting Council database for existing carrier emissions.

FCC guidelines state that if a site is found to be out of compliance (over allowable thresholds), that carriers over a 5% contribution to the composite value will require measures to bring the site into compliance. For this facility, the composite values calculated were well within the allowable 100% threshold standard per the federal government.



# **Structural Analysis Report**

Structure : 180 ft Self Supported Tower

ATC Site Name : North Madison Volunteer FD, CT

ATC Site Number : 383660

Engineering Number : 12163181\_C3\_01

Proposed Carrier : Sprint Nextel

Carrier Site Name : N. Madison / Vol. Fire Dept.

Carrier Site Number : CT03XC164-A

Site Location : 864 Opening Hill Road

Madison, CT 06443-0000

41.356900,-72.640100

County : New Haven

Date : October 26, 2017

Max Usage : 64%

Result : Pass

Prepared By: Reviewed By:

Robert D. Barrett, E.I. Structural Engineer I

Robert D. Barrett

COA: PEC.0001553



# **Table of Contents**

Introduction	1
Supporting Documents	1
Analysis	1
Conclusion	1
Existing and Reserved Equipment	2
Equipment to be Removed	. 2
Proposed Equipment	3
Structure Usages	3
Foundations	3
Deflection, Twist, and Sway	. 3
Standard Conditions	4
Calculations	Attached



#### Introduction

The purpose of this report is to summarize results of a structural analysis performed on the 180 ft self supported tower to reflect the change in loading by Sprint Nextel.

#### **Supporting Documents**

<b>Tower Drawings</b>	Rohn Drawing #C981756, dated December 2, 1998
Foundation Drawing	Rohn Drawing #A992935-1, dated July 21, 1999
Geotechnical Report	Clarence Welti Assoc. Job #35130AE, dated June 9, 1997

#### **Analysis**

The tower was analyzed using American Tower Corporation's tower analysis software. This program considers an elastic three-dimensional model and second-order effects per ANSI/TIA-222.

Basic Wind Speed:	101 mph (3-Second Gust, V <sub>asd</sub> ) / 130 mph (3-Second Gust, V <sub>ult</sub> )
Basic Wind Speed w/ Ice:	50 mph (3-Second Gust) w/ 3/4" radial ice concurrent
Code:	ANSI/TIA-222-G / 2012 IBC / 2016 Connecticut State Building Code
Structure Class:	
<b>Exposure Category:</b>	В
Topographic Category:	1
Spectral Response:	$Ss = 0.17, S_1 = 0.06$
Site Class:	D - Stiff Soil

#### Conclusion

Based on the analysis results, the structure meets the requirements per the applicable codes listed above. The tower and foundation can support the equipment as described in this report.

If you have any questions or require additional information, please contact American Tower via email at Engineering@americantower.com. Please include the American Tower site name, site number, and engineering number in the subject line for any questions.



# **Existing and Reserved Equipment**

Elevation <sup>1</sup> (ft)		<b>~</b> .	Antonia	NA avvet Torra	Lines	Camian				
Mount	RAD	Qty	Antenna	Mount Type	Lines	Carrier				
	190.8	2	RFS PD455		(3) 7/8" Coax					
180.0	80.0 186.0	1	4-Bay Dipole	Side Arms	(1) 1/2" Coax					
	183.0 1 2-Bay Dipole		(1) 2" Conduit (1) 1" Conduit							
		3	Alcatel Lucent RRH ALU 4X45 AWS		(1) 1 Corract					
		3	ALU RRH2X60PCS							
		3	ALU RRH4X60LTE							
		6	Commscope SBNHH-1D65B							
		3	Commscope LNX6514DS-A1M		(12) 1 5/8" Coax					
170.0	170.0	1	Andrew 8' MW Dish	Sector Frames	(2) 1 5/8" Hybrid	Verizon Wireless				
		1	Antel BXA-70063/6CF		(1) 1 1/4" Coax					
		2	Antel BXA-70063/4CF							
		6	RFS FD9R6004/2C-3L							
		2	RFS DB-T1-6Z-8AB-0Z							
160.0	160.0	12	Andrew DB844H90E-XY	Sector Frames	(12) 1 5/8" Coax					
		3	ALU 800MHz 2X50W RRH w/ Filter		(3) 1 1/4" Hybriflex	Sprint Nextel				
150.0	150.0	3	ALU 1900MHz 4X45 RRH	Sector Frames						
		3	RFS APXVSPP18-C-A20							
		1	Raycap DC6-48-60-18-8F							
		6	Ericsson RRUS-11		(12) 1 1/4" Coax	ATO T A 4 1 111				
140.0	140.0	6	KMW AM-X-CD-16-65-00T-RET	Sector Frames						
140.0	140.0	140.0	140.0	140.0	140.0	6	Powerwave LGP21901	Sector Frames	(2) 0.76" 8 AWG 6 (1) 0.39" Fiber	AT&T Mobility
					6	Powerwave LGP21401		(1) 0.59 Fibel		
		6	Powerwave 7770							
		3	RFS ATMAP1412D-1A120							
130.0	130.0	3	Commscope LNX-6515DS-VTM	T-Arms	(12) 1 5/8" Coax	T-Mobile				
	3		EMS RR90_17_02DP							
125.0	125.0	1	Sinclair SC323-HF2LDF	Side Arm	(1) 7/8" Coax					
90.0	90.0	1	RFI FSA10-67-DIN	Side Arms	(2) 7/8" Coax	Town of Madison, CT				
30.0	90.0		Sinclair SC323-HF2LDF							
75.0	75.0	1	PCTEL GPS-TMG-HR-26N	Stand-Off	(1) 1/2" Coax	Sprint Nextel				

# **Equipment to be Removed**

Elevation <sup>1</sup> (ft)		Ot.	Antonno	Mount Tune	Linos	Carrior
Mount	RAD	Qty	Antenna	Mount Type	Lines	Carrier
150.0	150.0	6	Andrew DB980H90E-M	-	(6) 1 5/8" Coax	Sprint Nextel



## **Proposed Equipment**

Elevation	Elevation <sup>1</sup> (ft)		Antenna	Mount Type	Lines	Carrier
Mount	RAD	Qty	Aiteilla	Mount Type	Lines	Carrier
150.0	150.0	3	ALU TD-RRH8X20	Sactor Frames	(1) 1 1/1" Hubrifloy	Cariat Novtal
150.0	150.0   150.0	3	RFS APXVTM14-C-I20	Sector Frames	(1) 1 1/4" Hybriflex	Sprint Nextel

<sup>&</sup>lt;sup>1</sup>Mount elevation is defined as height above bottom of steel structure to the bottom of mount, RAD elevation is defined as center of antenna above ground level (AGL).

Install proposed coax alongside existing Sprint Nextel coax.

#### **Structure Usages**

Structural Component	Controlling Usage	Pass/Fail
Legs	49%	Pass
Diagonals	64%	Pass
Horizontals	51%	Pass
Anchor Bolts	36%	Pass
Leg Bolts	46%	Pass

#### **Foundations**

Reaction Component	Analysis Reactions	% of Usage
Uplift (Kips)	282.3	58%
Axial (Kips)	323.3	26%
Shear (Kips)	38.2	10%

The structure base reactions resulting from this analysis were found to be acceptable through analysis based on geotechnical and foundation information, therefore no modification or reinforcement of the foundation will be required.

## **Deflection, Twist and Sway\***

Antenna Elevation (ft)	Antenna	Carrier	Deflection (ft)	Twist (°)	Sway (Rotation) (°)
170.0	Andrew 8' MW Dish	Verizon Wireless	0.172	0.007	0.118
150.0	ALU TD-RRH8X20	Cariat Novtol	0.122	0.006	0.111
150.0	RFS APXVTM14-C-I20	Sprint Nextel	0.132	0.006	0.111

<sup>\*</sup>Deflection, Twist and Sway was evaluated considering a design wind speed of 60 mph (3-Second Gust) per ANSI/TIA-222-G



#### **Standard Conditions**

All engineering services are performed on the basis that the information used is current and correct. This information may consist of, but is not necessary limited, to:

- -- Information supplied by the client regarding the structure itself, antenna, mounts and feed line loading on the structure and its components, or other relevant information.
- Information from drawings in the possession of American Tower Corporation, or generated by field inspections or measurements of the structure.

It is the responsibility of the client to ensure that the information provided to A.T. Engineering Service, PLLC and used in the performance of our engineering services is correct and complete. In the absence of information to the contrary, we assume that all structures were constructed in accordance with the drawings and specifications and that their capacity has not significantly changed from the "as new" condition.

Unless explicitly agreed by both the client and American Tower Corporation, all services will be performed in accordance with the current revision of ANSI/TIA -222. The design basic wind speed will be determined based on the minimum basic wind speed as prescribed in ANSI/TIA-222. Although every effort is taken to ensure that the loading considered is adequate to meet the requirements of all applicable regulatory entities, we can provide no assurance to meet any other local and state codes or requirements. If wind and ice loads or other relevant parameters are to be different from the minimum values recommended by the codes, the client shall specify the exact requirement.

All services are performed, results obtained, and recommendations made in accordance with generally accepted engineering principles and practices. A.T. Engineering Service, PLLC is not responsible for the conclusions, opinions and recommendations made by others based on the information we supply.

© 2007 - 2017 by ATC IP LLC. All rights reserved. Loads: 101 mph no ice 50 mph w/ 3/4" radial ice Site Class: D Ss: 0.17 S1: 0.06 60 mph Serviceability 180.00 Sect 9 160.00 Sect 8 140.00 Sect 7 120.00 Sect 6 100.00 Sect 5 80.00 Sect 4 60.00 Sect 3 40.00 Sect 2 20.00

Sect 1

#### **Job Information**

Tower: 383660 Location: North Madison Volunteer FD, CT

Code: ANSI/TIA-222-G Shape: Triangle Base Width: 25.33 ft **Client: Sprint Nextel** 

Top Width: 8.54 ft

		S	ections Properties	
Section	Lea Memb	ers	Diagonal Members	Horizontal Members
1	PX 50 ksi	10" DIA PIPE	PX 50 ksi 3-1/2" DIA PIPE	PST 50 ksi 3" DIA PIPE
2	PX 50 ksi	10" DIA PIPE	PST 50 ksi 3" DIA PIPE	PST 50 ksi 2-1/2" DIA PIPE
3	PX 50 ksi	8" DIA PIPE	PST 50 ksi 3" DIA PIPE	PST 50 ksi 2-1/2" DIA PIPE
4	PX 50 ksi	8" DIA PIPE	PST 50 ksi 3" DIA PIPE	PST 50 ksi 2" DIA PIPE
5	PSP 50 ksi	ROHN 8 EHS	PST 50 ksi 3" DIA PIPE	PST 50 ksi 2" DIA PIPE
6	PSP 50 ksi	ROHN 6 EHS	PST 50 ksi 2-1/2" DIA PIPE	PST 50 ksi 2" DIA PIPE
7	PSP 50 ksi	ROHN 5 EH	PX 50 ksi 2" DIA PIPE	PST 50 ksi 1-1/2" DIA PIPE
8	PX 50 ksi	4" DIA PIPE	PX 50 ksi 2" DIA PIPE	PST 50 ksi 1-1/2" DIA PIPE
9	PST 50 ksi	3" DIA PIPE	PST 50 ksi 2" DIA PIPE	PST 50 ksi 1-1/2" DIA PIPE

	D	iscrete Appurtenance
Elev (ft) Type Q	ty	Description
180.00 Whip	1	2-Bay Dipole
180.00 Whip	1	4-Bay Dipole
180.00 Whip	2	RFS PD455
180.00 Straight Arm	3	Flat Side Arm
170.00 Panel 170.00 Panel	3	Alcatel Lucent RRH ALU 4X45 AW ALU RRH2X60PCS
170.00 Panel	3	ALU RRH4X60LTE
170.00 Panel	6	Commscope SBNHH-1D65B
170.00 Panel	3	Commscope LNX6514DS-A1M
170.00 Dish	1	Andrew 8' MW Dish
		Flat Light Sector Frame
170.00 Panel	1	Antel BXA-70063/6CF
170.00 Panel	2	Antel BXA-70063/4CF
170.00 Panel	6 1	RFS FD9R6004/2C-3L
170.00 Panel 170.00 Panel	1	RFS DB-T1-6Z-8AB-0Z RFS DB-T1-6Z-8AB-0Z
	•	Andrew DB844H90E-XY
160.00 Mounting Frame		Flat Light Sector Frame
150.00 Panel	3	ALU 800 MHz 2X50W RRH w/ Filte
150.00 Panel	3	ALU 1900 MHz 4X45 RRH
150.00 Panel	3	ALU TD-RRH8X20
150.00 Panel	3	RFS APXVSPP18-C-A20
150.00 Panel	3	RFS APXVTM14-C-I20
150.00 Mounting Frame 140.00 Panel	ა 1	Flat Light Sector Frame Raycap DC6-48-60-18-8F
140.00 Panel	6	Ericsson RRUS-11
140.00 Panel	6	KMW AM-X-CD-16-65-00T-RET
140.00 Panel	6	Powerwave LGP21901
140.00 Panel	6	Powerwave LGP21401
140.00 Panel	6	Powerwave 7770
140.00 Mounting Frame		Flat Light Sector Frame
130.00 Panel	3	RFS ATMAP1412D-1A120
130.00 Panel 130.00 Panel	3	Commscope LNX-6515DS-VTM EMS RR90 17 02DP
130.00 Straight Arm	3	Flat T-Arm
125.00 Straight Arm	1	Flat Side Arm
125.00 Whip	1	Sinclair SC323-HF2LDF
90.00 Panel	1	RFI FSA10-67-DIN
90.00 Straight Arm	2	Flat Side Arm
90.00 Whip	1	Sinclair SC323-HF2LDF
75.00 Panel	1	PCTEL GPS-TMG-HR-26N
75.00 Straight Arm	1	Stand-Off
	L	inear Appurtenance
Elev (ft)		
	)es	cription
		Coax

© 2007 - 2017 by ATC IP LLC. All rights reserved.

# Job Information Tower: 383660 Location: North Madison Volunteer FD, CT

Shape: Triangle

Code: ANSI/TIA-222-G Client: Sprint Nextel

> 2" Conduit 1/2" Coax 1" Conduit 180.00 0.00 180.00 0.00 180.00 1 Waveguide 1 5/8" Hybrid 1 5/8" Hybrid 1 5/8" Coax 1 1/4" Coax 170.00 170.00 0.00 1 0.00 0.00 170.00 1 170.00 170.00 12 1 0.00 0.00 Waveguide Waveguide 0.00 0.00 160.00 160.00 1 1 Waveguide
> 12 1 5/8" Coax
> 1 Waveguide
> 3 1 1/4" Hybriflex
> 1 1 1/4" Coax
> 1 Waveguide
> 12 1 1/4" Coax
> 2 0.76" 8 AWG 6
> 1 0.39" Fiber
> 1 Waveguide
> 12 1 5/8" Coax
> 1 7/8" Coax 0.00 160.00 0.00 150.00 0.00 150.00 150.00 140.00 0.00 0.00 0.00 140.00 140.00 140.00 130.00 0.00 0.00 0.00 0.00 130.00 0.00 125.00 0.00 0.00 90.00 75.00 2 7/8" Coax 1/2" Coax

Base Width: 25.33 ft

Top Width: 8.54 ft

	Global Base Foundation Design Loads													
Load Case	Moment (k-ft)	Vertical (kip)	Horizontal (kip)											
DL + WL	6,581.62	69.92	61.78											
DL + WL + IL	2,229.24	184.40	22.28											

Indivi	Individual Base Foundation Design Loads											
Vertical (kip)	Uplift (kip)	Horizontal (kip)										
323.30	282.30	38.25										

© 2007 - 2017 by ATC IP LLC. All rights reserved. Site Number: 383660 Code: ANSI/TIA-222-G

Site Name: North Madison Volunteer FD, CT Engineering Number: 12163181\_C3\_01 10/26/2017 3:52:42 PM

Customer: Sprint Nextel

Tower Manufacturer:

1.2D + 1.6W 120 deg

Analysis Parameters

Location: New Haven County, CT Height (ft): 180

Code: ANSI/TIA-222-G Base Elevation (ft): 0.00

Shape: Triangle Bottom Face Width (ft): 25.33

С Tower Type: Self Support Anchor Bolt Detail Type

Ice & Wind Parameters

Top Face Width (ft):

8.54

Structure Class: П Design Windspeed Without Ice: 101 mph

**Exposure Category:** В Design Windspeed With Ice: 50 mph Topographic Category: 1 Operational Windspeed: 60 mph

Design Ice Thickness: 0.75 in Crest Height: 0.0 ft

Seismic Parameters

Analysis Method: Equivalent Modal Analysis & Equivalent Lateral Force Methods

Site Class: D - Stiff Soil

Rohn

Period Based on Rayleigh Method (sec): 0.66

0.048 T<sub>I</sub> (sec): 6 p: 1.3 Cs:

0.173 0.048  $S_S$ :  $S_1$ : 0.060 Cs, Max:

Fa: 1.600 2.400 C<sub>s</sub>, Min: 0.030  $F_{v}$ :

0.096 0.185  $S_{ds}$ :  $S_{d1}$ :

Load Cases

1.2D + 1.6W Normal 101 mph Normal to Face with No Ice

1.2D + 1.6W 60 deg 101 mph 60 degree with No Ice

1.2D + 1.6W 90 deg 101 mph 90 degree with No Ice

101 mph 120 degree with No Ice 1.2D + 1.6W 180 deg 101 mph 180 degree with No Ice

1.2D + 1.6W 210 deg 101 mph 210 degree with No Ice

1.2D + 1.6W 240 deg 101 mph 240 degree with No Ice

1.2D + 1.6W 300 deg 101 mph 300 degree with No Ice

1.2D + 1.6W 330 deg 101 mph 330 degree with No Ice

0.9D + 1.6W Normal 101 mph Normal to Face with No Ice (Reduced DL)

0.9D + 1.6W 60 deg 101 mph 60 deg with No Ice (Reduced DL)

0.9D + 1.6W 90 deg 101 mph 90 deg with No Ice (Reduced DL)

0.9D + 1.6W 120 deg 101 mph 120 deg with No Ice (Reduced DL)

0.9D + 1.6W 180 deg 101 mph 180 deg with No Ice (Reduced DL)

0.9D + 1.6W 210 deg 101 mph 210 deg with No Ice (Reduced DL)

0.9D + 1.6W 240 deg 101 mph 240 deg with No Ice (Reduced DL)

0.9D + 1.6W 300 deg 101 mph 300 deg with No Ice (Reduced DL)

0.9D + 1.6W 330 deg 101 mph 330 deg with No Ice (Reduced DL)

1.2D + 1.0Di + 1.0Wi Normal 50 mph Normal with 0.75 in Radial Ice

1.2D + 1.0Di + 1.0Wi 60 deg 50 mph 60 deg with 0.75 in Radial Ice

1.2D + 1.0Di + 1.0Wi 90 deg 50 mph 90 deg with 0.75 in Radial Ice

Site Name: North Madison Volunteer FD, CT Engineering Number: 12163181\_C3\_01 10/26/2017 3:52:42 PM

Customer: Sprint Nextel

## **Analysis Parameters**

1.2D + 1.0Di + 1.0Wi 120 deg 50 mph 120 deg with 0.75 in Radial Ice 1.2D + 1.0Di + 1.0Wi 180 deg 50 mph 180 deg with 0.75 in Radial Ice 1.2D + 1.0Di + 1.0Wi 210 deg 50 mph 210 deg with 0.75 in Radial Ice 50 mph 240 deg with 0.75 in Radial Ice 1.2D + 1.0Di + 1.0Wi 240 deg 1.2D + 1.0Di + 1.0Wi 300 deg 50 mph 300 deg with 0.75 in Radial Ice 1.2D + 1.0Di + 1.0Wi 330 deg 50 mph 330 deg with 0.75 in Radial Ice (1.2 + 0.2Sds) \* DL + E Normal Seismic Normal (1.2 + 0.2Sds) \* DL + E 60 deg Seismic 60 deg (1.2 + 0.2Sds) \* DL + E 90 deg Seismic 90 deg (1.2 + 0.2Sds) \* DL + E 120 deg Seismic 120 deg (1.2 + 0.2Sds) \* DL + E 180 deg Seismic 180 deg (1.2 + 0.2Sds) \* DL + E 210 deg Seismic 210 deg (1.2 + 0.2Sds) \* DL + E 240 deg Seismic 240 deg (1.2 + 0.2Sds) \* DL + E 300 deg Seismic 300 deg (1.2 + 0.2Sds) \* DL + E 330 deg Seismic 330 deg (0.9 - 0.2Sds) \* DL + E Normal Seismic (Reduced DL) Normal (0.9 - 0.2Sds) \* DL + E 60 deg Seismic (Reduced DL) 60 deg (0.9 - 0.2Sds) \* DL + E 90 deg Seismic (Reduced DL) 90 deg (0.9 - 0.2Sds) \* DL + E 120 deg Seismic (Reduced DL) 120 deg (0.9 - 0.2Sds) \* DL + E 180 deg Seismic (Reduced DL) 180 deg (0.9 - 0.2Sds) \* DL + E 210 deg Seismic (Reduced DL) 210 deg (0.9 - 0.2Sds) \* DL + E 240 deg Seismic (Reduced DL) 240 deg (0.9 - 0.2Sds) \* DL + E 300 deg Seismic (Reduced DL) 300 deg (0.9 - 0.2Sds) \* DL + E 330 deg Seismic (Reduced DL) 330 deg 1.0D + 1.0W Service Normal Serviceability - 60 mph Wind Normal 1.0D + 1.0W Service 60 deg Serviceability - 60 mph Wind 60 deg 1.0D + 1.0W Service 90 deg Serviceability - 60 mph Wind 90 deg 1.0D + 1.0W Service 120 deg Serviceability - 60 mph Wind 120 deg 1.0D + 1.0W Service 180 deg Serviceability - 60 mph Wind 180 deg 1.0D + 1.0W Service 210 deg Serviceability - 60 mph Wind 210 deg 1.0D + 1.0W Service 240 deg Serviceability - 60 mph Wind 240 deg 1.0D + 1.0W Service 300 deg Serviceability - 60 mph Wind 300 deg 1.0D + 1.0W Service 330 deg Serviceability - 60 mph Wind 330 deg

 $^{\mbox{\scriptsize @}}$  2007 - 2017 by ATC IP LLC. All rights reserved. Site Number: 383660 Code: ANSI/TIA-222-G

Site Name: North Madison Volunteer FD, CT Engineering Number: 12163181\_C3\_01 10/26/2017 3:52:42 PM

Sprint Nextel Customer:

# **Tower Loading**

Discrete Appurtenance Properties 1.2D + 1.6W

Elevation Description (ft)	Qty	Wt. (lb)	EPA (sf)	Length (ft)	Width (in)	Depth (in)	K <sub>a</sub>	Orient. Factor	Vert. Ecc.(ft)	M <sub>u</sub> (Ib-ft)	Q <sub>z</sub> I (psf)	-a (WL) F (Ib)	P <sub>a</sub> (DL) (lb)
180.0 2-Bay Dipole	1	18	2.0	6.0	4.0	4.0	0.80	1.00	3.0	165.9	26.07	55	25
180.0 4-Bay Dipole	1	35	3.9	12.0	4.0	4.0	0.80	1.00	6.0	666.8	26.19	111	50
180.0 Flat Side Arm	3	150	6.3	0.0	0.0	0.0	1.00	0.67	0.0	0.0	25.95	447	648
180.0 RFS PD455	2	24	6.0	21.5	2.8	2.8	0.80	1.00	10.8	3715.0	26.38	346	69
170.0 Alcatel Lucent RRH	3	63	2.5	2.2	11.4	5.9	0.80	0.67	0.0	0.0	25.53	138	273
170.0 ALU RRH2X60PCS	3	55	2.2	1.8	12.0	9.4	0.80	0.67	0.0	0.0	25.53	123	238
170.0 ALU RRH4X60LTE	3	53	2.1	1.8	12.0	7.2	0.80	0.67	0.0	0.0	25.53	118	229
170.0 Andrew 8' MW Dish	1	400	83.6	8.0	96.0	0.0	1.00	1.00	0.0	0.0	25.53	2904	576
170.0 Antel BXA-70063/4CF	2	10	4.7	4.0	11.2	5.2	0.80	0.77	0.0	0.0	25.53	202	29
170.0 Antel BXA-70063/6CF	1	17	7.6	5.9	11.2	5.2	0.80	0.77	0.0	0.0	25.53	162	24
170.0 Commscope	3	29	5.1	4.0	11.9	7.1	0.80	0.83	0.0	0.0	25.53	352	124
170.0 Commscope SBNHH-	6	41	8.1 17.9	6.0	11.9	7.1	0.80	0.83	0.0	0.0	25.53	1118	351
170.0 Flat Light Sector	3	400	4.8	0.0	0.0	0.0	0.75	0.67	0.0	0.0	25.53	937	1728
170.0 RFS DB-T1-6Z-8AB- 170.0 RFS DB-T1-6Z-8AB-	1 1	44 44	4.8	2.0 2.0	24.0 24.0	10.0 10.0	0.80	0.67 0.67	0.0 0.0	0.0	25.53 25.53	89 89	63 63
170.0 RFS DB-11-02-0AB-	6	3	0.4	0.5	6.5	1.5	0.80	0.50	0.0	0.0	25.53	31	22
160.0 Andrew DB844H90E-	12	3 14	3.6	4.0	8.0	4.5	0.80	0.82	0.0	0.0	25.09	970	242
160.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.32	0.0	0.0	25.09	1031	1728
150.0 ALU 1900 MHz 4X45	3	60	2.3	2.1	11.1	10.7	0.73	0.73	0.0	0.0	24.63	125	259
150.0 ALU 800 MHz 2X50W	3	64	2.1	1.6	13.0	12.2	0.80	0.67	0.0	0.0	24.63	111	276
150.0 ALU TD-RRH8X20	3	66	3.7	2.1	17.5	5.7	0.80	0.67	0.0	0.0	24.63	199	286
150.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	24.63	1012	1728
150.0 RFS APXVSPP18-C-	3	57	8.0	6.0	11.8	7.0	0.80	0.83	0.0	0.0	24.63	535	246
150.0 RFS APXVTM14-C-I20		53	6.3	4.7	12.6	6.3	0.80	0.78	0.0	0.0	24.63	398	229
140.0 Ericsson RRUS-11	6	55	3.8	2.1	18.2	6.7	0.80	0.67	0.0	0.0	24.15	400	475
140.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	24.15	992	1728
140.0 KMW AM-X-CD-16-	6	49	8.0	6.0	11.8	5.9	0.80	0.79	0.0	0.0	24.15	999	419
140.0 Powerwave 7770	6	35	5.5	4.6	11.0	5.0	0.80	0.77	0.0	0.0	24.15	669	302
140.0 Powerwave	6	18	0.9	1.2	7.0	2.7	0.80	0.50	0.0	0.0	24.15	75	151
140.0 Powerwave	6	6	0.2	0.3	6.0	3.0	0.80	0.50	0.0	0.0	24.15	18	48
140.0 Raycap DC6-48-60-	1	19	1.3	2.0	11.0	11.0	0.80	1.00	0.0	0.0	24.15	34	27
130.0 Commscope LNX-	3	50	11.4	8.0	11.9	7.1	0.80	0.84	0.0	0.0	23.64	742	217
130.0 EMS RR90_17_02DP	3	14	4.4	4.7	8.0	2.8	0.80	0.73	0.0	0.0	23.64	246	58
130.0 Flat T-Arm	3	250	12.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	23.64	700	1080
130.0 RFS ATMAP1412D-	3	13	1.0	1.0	10.0	4.0	0.80	0.50	0.0	0.0	23.64	39	56
125.0 Flat Side Arm	1	150	6.3	0.0	0.0	0.0	1.00	1.00	0.0	0.0	23.38	200	216
125.0 Sinclair SC323-	1	6 150	1.1	5.6	2.0	2.0	1.00	1.00	0.0	0.0	23.38	36	9
90.00 Flat Side Arm	2	150	6.3 1.4	0.0	0.0	0.0	0.90	0.90	0.0	0.0	21.29	295	432
90.00 RFI FSA10-67-DIN 90.00 Sinclair SC323-	1 1	9 6	1.4	1.7 5.6	23.5	10.0 2.0	1.00	1.00 1.00	0.0 0.0	0.0	21.29 21.29	41 33	13 9
75.00 PCTEL GPS-TMG-HR-	•	6 1	0.2	0.4	3.2	3.2	1.00	1.00	0.0	0.0	20.21	33 4	9 1
75.00 PCTEL GPS-TMG-HR-	1	75	2.5	0.4	0.0	0.0	1.00	1.00	0.0	0.0	20.21	4 69	108
73.00 Stariu-Oii	'	73	2.3	0.0	0.0	0.0	1.00	1.00	0.0	0.0	2U.Z I	09	100

Totals

127

10318 785.4

Discrete Appurtenance Properties 0.9D + 1.6W

Elevation Description (ft)	Qty	Wt. (Ib)	EPA (sf)	Length (ft)	Width (in)	Depth (in)	$K_{a}$	Orient. Factor	Vert. Ecc.(ft)	M <sub>u</sub> (Ib-ft)	Q <sub>z</sub> F (psf)	F <sub>a</sub> (WL) F (lb)	P <sub>a</sub> (DL) (lb)
180.0 2-Bay Dipole	1	18	2.0	6.0	4.0	4.0	0.80	1.00	3.0	165.9	26.07	55	14
180.0 4-Bay Dipole	1	35	3.9	12.0	4.0	4.0	0.80	1.00	6.0	666.8	26.19	111	28
180.0 Flat Side Arm	3	150	6.3	0.0	0.0	0.0	1.00	0.67	0.0	0.0	25.95	447	365
180.0 RFS PD455	2	24	6.0	21.5	2.8	2.8	0.80	1.00	10.8	3715.0	26.38	346	39

Site Name: North Madison Volunteer FD, CT Engineering Number: 12163181\_C3\_01 10/26/2017 3:52:42 PM

Customer: Sprint Nextel

# **Tower Loading**

170.0 Alcatel Lucent RRH	3	63	2.5	2.2	11.4	5.9	0.80	0.67	0.0	0.0	25.53	138	154
170.0 ALU RRH2X60PCS	3	55	2.2	1.8	12.0	9.4	0.80	0.67	0.0	0.0	25.53	123	134
170.0 ALU RRH4X60LTE	3	53	2.1	1.8	12.0	7.2	0.80	0.67	0.0	0.0	25.53	118	129
170.0 Andrew 8' MW Dish	1	400	83.6	8.0	96.0	0.0	1.00	1.00	0.0	0.0	25.53	2904	324
170.0 Antel BXA-70063/4CF	2	10	4.7	4.0	11.2	5.2	0.80	0.77	0.0	0.0	25.53	202	16
170.0 Antel BXA-70063/6CF	1	17	7.6	5.9	11.2	5.2	0.80	0.77	0.0	0.0	25.53	162	14
170.0 Commscope	3	29	5.1	4.0	11.9	7.1	0.80	0.83	0.0	0.0	25.53	352	70
170.0 Commscope SBNHH-	6	41	8.1	6.0	11.9	7.1	0.80	0.83	0.0	0.0	25.53	1118	197
170.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.67	0.0	0.0	25.53	937	972
170.0 RFS DB-T1-6Z-8AB-	1	44	4.8	2.0	24.0	10.0	0.80	0.67	0.0	0.0	25.53	89	36
170.0 RFS DB-T1-6Z-8AB-	1	44	4.8	2.0	24.0	10.0	0.80	0.67	0.0	0.0	25.53	89	36
170.0 RFS FD9R6004/2C-3L	6	3	0.4	0.5	6.5	1.5	0.80	0.50	0.0	0.0	25.53	31	13
160.0 Andrew DB844H90E-	12	14	3.6	4.0	8.0	4.5	0.80	0.82	0.0	0.0	25.09	970	136
160.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	25.09	1031	972
150.0 ALU 1900 MHz 4X45	3	60	2.3	2.1	11.1	10.7	0.80	0.67	0.0	0.0	24.63	125	146
150.0 ALU 800 MHz 2X50W	3	64	2.1	1.6	13.0	12.2	0.80	0.67	0.0	0.0	24.63	111	156
150.0 ALU TD-RRH8X20	3	66	3.7	2.1	17.5	5.7	0.80	0.67	0.0	0.0	24.63	199	161
150.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	24.63	1012	972
150.0 RFS APXVSPP18-C-	3	57	8.0	6.0	11.8	7.0	0.80	0.83	0.0	0.0	24.63	535	139
150.0 RFS APXVTM14-C-I20	3	53	6.3	4.7	12.6	6.3	0.80	0.78	0.0	0.0	24.63	398	129
140.0 Ericsson RRUS-11	6	55	3.8	2.1	18.2	6.7	0.80	0.67	0.0	0.0	24.15	400	267
140.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	24.15	992	972
140.0 KMW AM-X-CD-16-	6	49	8.0	6.0	11.8	5.9	0.80	0.79	0.0	0.0	24.15	999	236
140.0 Powerwave 7770	6	35	5.5	4.6	11.0	5.0	0.80	0.77	0.0	0.0	24.15	669	170
140.0 Powerwave	6	18	0.9	1.2	7.0	2.7	0.80	0.50	0.0	0.0	24.15	75	85
140.0 Powerwave	6	6	0.2	0.3	6.0	3.0	0.80	0.50	0.0	0.0	24.15	18	27
140.0 Raycap DC6-48-60-	1	19	1.3	2.0	11.0	11.0	0.80	1.00	0.0	0.0	24.15	34	15
130.0 Commscope LNX-	3	50	11.4	8.0	11.9	7.1	0.80	0.84	0.0	0.0	23.64	742	122
130.0 EMS RR90_17_02DP	3	14	4.4	4.7	8.0	2.8	0.80	0.73	0.0	0.0	23.64	246	33
130.0 Flat T-Arm	3	250	12.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	23.64	700	608
130.0 RFS ATMAP1412D-	3	13	1.0	1.0	10.0	4.0	0.80	0.50	0.0	0.0	23.64	39	32
125.0 Flat Side Arm	1	150	6.3	0.0	0.0	0.0	1.00	1.00	0.0	0.0	23.38	200	122
125.0 Sinclair SC323-	1	6	1.1	5.6	2.0	2.0	1.00	1.00	0.0	0.0	23.38	36	5
90.00 Flat Side Arm	2	150	6.3	0.0	0.0	0.0	0.90	0.90	0.0	0.0	21.29	295	243
90.00 RFI FSA10-67-DIN	1	9	1.4	1.7	23.5	10.0	1.00	1.00	0.0	0.0	21.29	41	7
90.00 Sinclair SC323-	1	6	1.1	5.6	2.0	2.0	1.00	1.00	0.0	0.0	21.29	33	5
75.00 PCTEL GPS-TMG-HR-	1	1	0.2	0.4	3.2	3.2	1.00	1.00	0.0	0.0	20.21	4	0
75.00 Stand-Off	1	75	2.5	0.0	0.0	0.0	1.00	1.00	0.0	0.0	20.21	69	61

Discrete Appurtenance Properties 1.2D + 1.0Di + 1.0Wi

127

10318

785.4

Totals

Elevation Description (ft)	Qty	Ice Wt (Ib)	Ice EPA (sf)	Length (ft)	Width (in)	Depth (in)	K <sub>a</sub>	Orient. Factor	Vert. Ecc.(ft)	M <sub>u</sub> (Ib-ft)	Q <sub>z</sub> (psf)	F <sub>a</sub> (WL) F (lb)	P <sub>a</sub> (DL) (lb)
180.0 2-Bay Dipole	1	71	4.6	6.0	4.0	4.0	0.80	1.00	3.0	60.1	6.39	20	89
180.0 4-Bay Dipole	1	142	9.2	12.0	4.0	4.0	0.80	1.00	6.0	241.6	6.42	40	178
180.0 Flat Side Arm	3	224	8.8	0.0	0.0	0.0	1.00	0.67	0.0	0.0	6.36	96	915
180.0 RFS PD455	2	299	13.8	21.5	2.8	2.8	0.80	1.00	10.8	1304.9	6.47	121	728
170.0 Alcatel Lucent RRH	3	142	3.2	2.2	11.4	5.9	0.80	0.67	0.0	0.0	6.26	27	555
170.0 ALU RRH2X60PCS	3	127	3.2	1.8	12.0	9.4	0.80	0.67	0.0	0.0	6.26	28	497
170.0 ALU RRH4X60LTE	3	127	2.8	1.8	12.0	7.2	0.80	0.67	0.0	0.0	6.26	24	497
170.0 Andrew 8' MW Dish	1	1396	89.8	8.0	96.0	0.0	1.00	1.00	0.0	0.0	6.26	478	1771
170.0 Antel BXA-70063/4CF	2	133	5.7	4.0	11.2	5.2	0.80	0.77	0.0	0.0	6.26	37	324
170.0 Antel BXA-70063/6CF	1	194	8.9	5.9	11.2	5.2	0.80	0.77	0.0	0.0	6.26	29	237
170.0 Commscope	3	173	6.1	4.0	11.9	7.1	0.80	0.83	0.0	0.0	6.26	65	642
170.0 Commscope SBNHH-	6	245	94	6.0	11 9	7 1	0.80	0.83	0.0	0.0	6.26	199	1824

ANSI/TIA-222-G © 2007 - 2017 by ATC IP LLC. All rights reserved.

Site Name: North Madison Volunteer FD, CT Engineering Number: 12163181\_C3\_01 10/26/2017 3:52:42 PM

Code:

Customer: Sprint Nextel

Site Number: 383660

**Tower Loading** 

				<u> </u>		J CA G	<u>5</u>						
170.0 Flat Light Sector	3	705	33.2	0.0	0.0	0.0	0.75	0.67	0.0	0.0	6.26	266	2827
170.0 RFS DB-T1-6Z-8AB-	1	190	5.7	2.0	24.0	10.0	0.80	0.67	0.0	0.0	6.26	16	238
170.0 RFS DB-T1-6Z-8AB-	1	190	5.7	2.0	24.0	10.0	0.80	0.67	0.0	0.0	6.26	16	238
170.0 RFS FD9R6004/2C-3L	6	16	0.6	0.5	6.5	1.5	0.80	0.50	0.0	0.0	6.26	7	119
160.0 Andrew DB844H90E-	12	111	4.5	4.0	8.0	4.5	0.80	0.82	0.0	0.0	6.15	185	1642
160.0 Flat Light Sector	3	702	33.0	0.0	0.0	0.0	0.75	0.75	0.0	0.0	6.15	291	2814
150.0 ALU 1900 MHz 4X45	3	155	3.0	2.1	11.1	10.7	0.80	0.67	0.0	0.0	6.04	25	602
150.0 ALU 800 MHz 2X50W	3	155	2.7	1.6	13.0	12.2	0.80	0.67	0.0	0.0	6.04	22	603
150.0 ALU TD-RRH8X20	3	156	4.9	2.1	17.5	5.7	0.80	0.67	0.0	0.0	6.04	40	607
150.0 Flat Light Sector	3	702	33.0	0.0	0.0	0.0	0.75	0.75	0.0	0.0	6.04	286	2814
150.0 RFS APXVSPP18-C-	3	257	9.3	6.0	11.8	7.0	0.80	0.83	0.0	0.0	6.04	95	965
150.0 RFS APXVTM14-C-I20	3	191	8.5	4.7	12.6	6.3	0.80	0.78	0.0	0.0	6.04	82	725
140.0 Ericsson RRUS-11	6	158	4.6	2.1	18.2	6.7	0.80	0.67	0.0	0.0	5.92	74	1219
140.0 Flat Light Sector	3	697	32.8	0.0	0.0	0.0	0.75	0.75	0.0	0.0	5.92	278	2798
140.0 KMW AM-X-CD-16-	6	234	9.3	6.0	11.8	5.9	0.80	0.79	0.0	0.0	5.92	177	1755
140.0 Powerwave 7770	6	168	6.5	4.6	11.0	5.0	0.80	0.77	0.0	0.0	5.92	122	1259
140.0 Powerwave	6	45	1.2	1.2	7.0	2.7	0.80	0.50	0.0	0.0	5.92	15	351
140.0 Powerwave	6	18	0.4	0.3	6.0	3.0	0.80	0.50	0.0	0.0	5.92	5	136
140.0 Raycap DC6-48-60-	1	110	2.8	2.0	11.0	11.0	0.80	1.00	0.0	0.0	5.92	11	137
130.0 Commscope LNX-	3	309	13.1	8.0	11.9	7.1	0.80	0.84	0.0	0.0	5.79	130	1150
130.0 EMS RR90_17_02DP	3	110	5.3	4.7	8.0	2.8	0.80	0.73	0.0	0.0	5.79	46	407
130.0 Flat T-Arm	3	456	21.0	0.0	0.0	0.0	0.75	0.75	0.0	0.0	5.79	174	1823
130.0 RFS ATMAP1412D-	3	47	1.4	1.0	10.0	4.0	0.80	0.50	0.0	0.0	5.79	8	180
125.0 Flat Side Arm	1	222	8.7	0.0	0.0	0.0	1.00	1.00	0.0	0.0	5.73	43	303
125.0 Sinclair SC323-	1	66	2.5	5.6	2.0	2.0	1.00	1.00	0.0	0.0	5.73	12	80
90.00 Flat Side Arm	2	220	8.6	0.0	0.0	0.0	0.90	0.90	0.0	0.0	5.22	62	599
90.00 RFI FSA10-67-DIN	1	127	4.7	1.7	23.5	10.0	1.00	1.00	0.0	0.0	5.22	21	154
90.00 Sinclair SC323-	1	62	2.5	5.6	2.0	2.0	1.00	1.00	0.0	0.0	5.22	11	76
75.00 PCTEL GPS-TMG-HR-		10	0.3	0.4	3.2	3.2	1.00	1.00	0.0	0.0	4.95	1	12
75.00 Stand-Off	1	109	3.7	0.0	0.0	0.0	1.00	1.00	0.0	0.0	4.95	16	149
Totals	127	27139 1	127.7										

Discrete Appurtenance Properties 1.0D + 1.0W Service

Elevation Description (ft)	Qty	Wt. (Ib)	EPA (sf)	Length (ft)	Width (in)	Depth (in)	K <sub>a</sub>	Orient. Factor	Vert. Ecc.(ft)	M <sub>u</sub> (lb-ft)	Q <sub>z</sub> F (psf)	F <sub>a</sub> (WL) F (lb)	P <sub>a</sub> (DL) (lb)	
180.0 2-Bay Dipole	1	18	2.0	6.0	4.0	4.0	0.80	1.00	3.0	36.6	9.20	12	18	
180.0 4-Bay Dipole	1	35	3.9	12.0	4.0	4.0	0.80	1.00	6.0	147.1	9.24	25	35	
180.0 Flat Side Arm	3	150	6.3	0.0	0.0	0.0	1.00	0.67	0.0	0.0	9.16	99	450	
180.0 RFS PD455	2	24	6.0	21.5	2.8	2.8	0.80	1.00	10.8	819.4	9.31	76	48	
170.0 Alcatel Lucent RRH	3	63	2.5	2.2	11.4	5.9	0.80	0.67	0.0	0.0	9.01	30	190	
170.0 ALU RRH2X60PCS	3	55	2.2	1.8	12.0	9.4	0.80	0.67	0.0	0.0	9.01	27	165	
170.0 ALU RRH4X60LTE	3	53	2.1	1.8	12.0	7.2	0.80	0.67	0.0	0.0	9.01	26	159	
170.0 Andrew 8' MW Dish	1	400	83.6	8.0	96.0	0.0	1.00	1.00	0.0	0.0	9.01	640	400	
170.0 Antel BXA-70063/4CF	2	10	4.7	4.0	11.2	5.2	0.80	0.77	0.0	0.0	9.01	45	20	
170.0 Antel BXA-70063/6CF	1	17	7.6	5.9	11.2	5.2	0.80	0.77	0.0	0.0	9.01	36	17	
170.0 Commscope	3	29	5.1	4.0	11.9	7.1	0.80	0.83	0.0	0.0	9.01	78	86	
170.0 Commscope SBNHH-	6	41	8.1	6.0	11.9	7.1	0.80	0.83	0.0	0.0	9.01	246	244	
170.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.67	0.0	0.0	9.01	207	1200	
170.0 RFS DB-T1-6Z-8AB-	1	44	4.8	2.0	24.0	10.0	0.80	0.67	0.0	0.0	9.01	20	44	
170.0 RFS DB-T1-6Z-8AB-	1	44	4.8	2.0	24.0	10.0	0.80	0.67	0.0	0.0	9.01	20	44	
170.0 RFS FD9R6004/2C-3L	6	3	0.4	0.5	6.5	1.5	0.80	0.50	0.0	0.0	9.01	7	16	
160.0 Andrew DB844H90E-	12	14	3.6	4.0	8.0	4.5	0.80	0.82	0.0	0.0	8.85	214	168	
160.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	8.85	227	1200	
150.0 ALU 1900 MHz 4X45	3	60	2.3	2.1	11.1	10.7	0.80	0.67	0.0	0.0	8.69	28	180	
150.0 ALU 800 MHz 2X50W	3	64	2.1	1.6	13.0	12.2	0.80	0.67	0.0	0.0	8.69	24	192	

Site Name: North Madison Volunteer FD, CT Engineering Number: 12163181\_C3\_01 10/26/2017 3:52:42 PM

Customer: Sprint Nextel

Totals

127

10318 785.4

# **Tower Loading**

150.0 ALU TD-RRH8X20	3	66	3.7	2.1	17.5	5.7	0.80	0.67	0.0	0.0	8.69	44	198
150.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	8.69	223	1200
150.0 RFS APXVSPP18-C-	3	57	8.0	6.0	11.8	7.0	0.80	0.83	0.0	0.0	8.69	118	171
150.0 RFS APXVTM14-C-I20	3	53	6.3	4.7	12.6	6.3	0.80	0.78	0.0	0.0	8.69	88	159
140.0 Ericsson RRUS-11	6	55	3.8	2.1	18.2	6.7	0.80	0.67	0.0	0.0	8.52	88	330
140.0 Flat Light Sector	3	400	17.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	8.52	219	1200
140.0 KMW AM-X-CD-16-	6	49	8.0	6.0	11.8	5.9	0.80	0.79	0.0	0.0	8.52	220	291
140.0 Powerwave 7770	6	35	5.5	4.6	11.0	5.0	0.80	0.77	0.0	0.0	8.52	148	210
140.0 Powerwave	6	18	0.9	1.2	7.0	2.7	0.80	0.50	0.0	0.0	8.52	17	105
140.0 Powerwave	6	6	0.2	0.3	6.0	3.0	0.80	0.50	0.0	0.0	8.52	4	33
140.0 Raycap DC6-48-60-	1	19	1.3	2.0	11.0	11.0	0.80	1.00	0.0	0.0	8.52	7	19
130.0 Commscope LNX-	3	50	11.4	8.0	11.9	7.1	0.80	0.84	0.0	0.0	8.34	164	151
130.0 EMS RR90_17_02DP	3	14	4.4	4.7	8.0	2.8	0.80	0.73	0.0	0.0	8.34	54	41
130.0 Flat T-Arm	3	250	12.9	0.0	0.0	0.0	0.75	0.75	0.0	0.0	8.34	154	750
130.0 RFS ATMAP1412D-	3	13	1.0	1.0	10.0	4.0	0.80	0.50	0.0	0.0	8.34	9	39
125.0 Flat Side Arm	1	150	6.3	0.0	0.0	0.0	1.00	1.00	0.0	0.0	8.25	44	150
125.0 Sinclair SC323-	1	6	1.1	5.6	2.0	2.0	1.00	1.00	0.0	0.0	8.25	8	6
90.00 Flat Side Arm	2	150	6.3	0.0	0.0	0.0	0.90	0.90	0.0	0.0	7.51	65	300
90.00 RFI FSA10-67-DIN	1	9	1.4	1.7	23.5	10.0	1.00	1.00	0.0	0.0	7.51	9	9
90.00 Sinclair SC323-	1	6	1.1	5.6	2.0	2.0	1.00	1.00	0.0	0.0	7.51	7	6
75.00 PCTEL GPS-TMG-HR-	1	1	0.2	0.4	3.2	3.2	1.00	1.00	0.0	0.0	7.13	1	1
75.00 Stand-Off	1	75	2.5	0.0	0.0	0.0	1.00	1.00	0.0	0.0	7.13	15	75

Site Name: North Madison Volunteer FD, CT Engineering Number: 12163181\_C3\_01 10/26/2017 3:52:42 PM

Customer: Sprint Nextel

# **Tower Loading**

# Linear Appurtenance Properties

Elev	Elev									Out			
From	To			Width	n Weigh	t Pct	Spread On	Bundling	Cluster	Of S	Spacing (	Orientation	n Ka
(ft)	(ft)	Description	Qty	(in)	(lb/ft)	In Block	Faces	Arrangement	Dia (in)	Zone	(in)	Factor	Override
0.00	180.0	1" Conduit	1	1.30	1.68	0	2	Individual	0.00	N	1.00	1.00	0.00
0.00	180.0	1/2" Coax	1	0.63	0.15	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	180.0	2" Conduit	1	2.38	3.65	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	180.0	7/8" Coax	3	1.09	0.33	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	170.0	1 1/4" Coax	1	1.55	0.63	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	170.0	1 5/8" Coax	12	1.98	0.82	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	170.0	1 5/8" Hybrid	1	1.63	1.61	0	2	Individual	0.00	Ν	1.00	1.00	0.01
0.00	170.0	1 5/8" Hybrid	1	1.63	1.61	0	2	Individual	0.00	Ν	1.00	1.00	0.01
0.00	170.0	Waveguide	1	1.50	6.00	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	160.0	1 5/8" Coax	12	1.98	0.82	0	1	Individual	0.00	Ν	1.00	1.00	0.00
0.00	160.0	Waveguide	1	1.50	6.00	0	1	Individual	0.00	Ν	1.00	1.00	0.00
0.00	160.0	Waveguide	1	1.50	6.00	0	1	Individual	0.00	Ν	1.00	1.00	0.00
0.00	150.0	1 1/4" Hybriflex	1	1.54	1.00	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	150.0	1 1/4" Hybriflex	3	1.54	1.00	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	150.0	Waveguide	1	1.50	6.00	0	2	Individual	0.00	Ν	1.00	1.00	0.00
0.00	140.0	0.39" Fiber	1	0.39	0.07	0	3	Individual	0.00	Ν	1.00	1.00	0.00
0.00	140.0	0.76" 8 AWG 6	2	0.76	0.53	0	3	Individual	0.00	Ν	1.00	1.00	0.00
0.00	140.0	1 1/4" Coax	12	1.55	0.63	0	3	Individual	0.00	Ν	1.00	1.00	0.00
0.00	140.0	Waveguide	1	1.50	6.00	0	3	Individual	0.00	Ν	1.00	1.00	0.00
0.00	130.0	1 5/8" Coax	12	1.98	0.82	50	3	Block	0.00	Ν	0.00	1.00	0.00
0.00	130.0	Waveguide	1	1.50	6.00	0	3	Individual	0.00	Ν	1.00	1.00	0.00
0.00	125.0	7/8" Coax	1	1.09	0.33	0	Lin App	Individual	0.00	Ν	1.00	1.00	0.00
0.00	90.00	7/8" Coax	2	1.09	0.33	0	Lin App	Individual	0.00	Ν	1.00	1.00	0.00
0.00	75.00	1/2" Coax	1	0.63	0.15	0	2	Individual	0.00	Ν	1.00	1.00	0.00

© 2007 - 2017 by ATC IP LLC. All rights reserved. Site Number: 383660 Code: ANSI/TIA-222-G

Site Name: North Madison Volunteer FD, CT

Sprint Nextel

Customer:

Engineering Number: 12163181\_C3\_01

10/26/2017 3:52:43 PM

Section: 1 1		Bot Elev (	(ft): 0.0	00	Не	ight (	ft): 20.	.000						
												Bear		
	Pu		Len		cing %		-	Phic Pn				· .		
Max Compression Member	(kip)	Load Case	(ft)	Х	Y Z	KL/R	(ksi)	(kip)	Bolts	Holes	(kip)	(kip)	%	Controls
LEG PX - 10" DIA PIPE HORIZPST - 3" DIA PIPE		1.2D + 1.6W 1.2D + 1.6W 90	10.03			0 33.1 0 124. <i>6</i>			0 2	0	0.00	0.00 40.44		Member X Member X
DIAG PX - 3-1/2" DIA PIPE		1.2D + 1.6W 90				0 147.9				0	0.00	89.29		Member X
										_				
								She	ar	Bear		Shear		
Max Tension Member	Pu (kip) l	_oad Case	Fy (ksi)	Fu (ksi)	Phit F (kip)	n Num Bolts				phiRn (kip)		it Pn kip)	Use %	Controls
LEG PX - 10" DIA PIPE		0.9D + 1.6W 60	50				0		0.00	0.0				Member
HORIZ PST - 3" DIA PIPE		1.2D + 1.6W 90	50				0		0.00	32.4		0.00		Bolt Bear
DIAG PX - 3-1/2" DIA PIPE	12.43	1.2D + 1.6W 90	50	65	165.6	0 3	0	C	0.00	77.5	l	0.00	10	Bolt Bear
	Pu			nhi Di	a+	Use	Num							
Max Splice Forces	(kip)	Load Case		phiRi (kip)		%	Bolts	Bolt Ty	/ре					
Top Tension	256.68	0.9D + 1.6W 18	80	0.0	00	0	0							
Top Compression		1.2D + 1.6W		0.0		0								
Bot Tension	284.55		30	969.		36	16	1" A35	4-BC					
Bot Compression	324.47	1.2D + 1.6W		0.0	)0	0								
Section: 2 2		Bot Elev (	(ft): 20	0.00	Не	eight (	ft): 20	.000						
Section: 2 2	Du	Bot Elev (	,			eight (			Num			Bear (phiPn	Hea	
	Pu (kip)		Len	Bra	cing %		F'y	Phic Pn		Num	ohiRnv	phiRn		Controls
Max Compression Member	(kip)	Load Case	Len (ft)	Bra X	cing % Y Z	KL/R	F'y (ksi)	Phic Pn (kip)	Bolts	Num   Holes	ohiRnv (kip)	phiRn (kip)	%	Controls
Max Compression Member LEG PX - 10" DIA PIPE	(kip) -277.80	Load Case 1.2D + 1.6W	Len (ft) 10.03	Brad X	cing % Y Z	KL/R 0 33.1	F'y (ksi)	Phic Pn (kip) 668.58	Bolts 0	Num   Holes	ohiRnv (kip) 0.00	phiRn (kip) 0.00	% 41	Member X
Max Compression Member	(kip) -277.80 -8.91	Load Case	Len (ft) 10.03 10.79	Brad X 100 100	cing % Y Z 100 10	KL/R	F'y (ksi) 50.0	Phic Pn (kip) 668.58 20.59	Bolts 0 2	Num   Holes	ohiRnv (kip)	phiRn (kip) 0.00 31.67	% 41 43	
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIP	(kip) -277.80 -8.91	Load Case 1.2D + 1.6W 0.9D + 1.6W 90	Len (ft) 10.03 10.79	Brad X 100 100	cing % Y Z 100 10	KL/R 0 33.1 0 136.7	F'y (ksi) 50.0	Phic Pn (kip) 668.58 20.59	Bolts 0 2	Num   Holes 0 0	0.00 0.00	phiRn (kip) 0.00	% 41 43	Member X Member X
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIP	(kip) -277.80 -8.91	Load Case 1.2D + 1.6W 0.9D + 1.6W 90	Len (ft) 10.03 10.79	Brad X 100 100	cing % Y Z 100 10	KL/R 0 33.1 0 136.7	F'y (ksi) 50.0	Phic Pn (kip) 668.58 20.59	Bolts 0 2 3	Num   Holes 0 0	0.00 0.00 0.00 0.00	phiRn (kip) 0.00 31.67	% 41 43	Member X Member X
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIP  DIAG PST - 3" DIA PIPE	-277.80 -8.91 -13.19	Load Case 1.2D + 1.6W 0.9D + 1.6W 90 1.2D + 1.6W 90	Len (ft) 10.03 10.79 15.18	Brad X 100 100 100	2 cing % Y Z 100 10 100 10 100 10 Phit F	KL/R 0 33.1 0 136.7 0 157.0	F'y (ksi) 50.0 50.0 50.0	Phic Pn (kip) 668.58 20.59 20.43 SheaphiR	Bolts 0 2 3	Num   Holes 0 0 0 0 0 Bear phiRn	0.00 0.00 0.00 0.00 0.00	yphiRn (kip) 0.00 31.67 50.54 Shear it Pn	% 41 43 64 Use	Member X Member X Member X
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIP  DIAG PST - 3" DIA PIPE  Max Tension Member	(kip) -277.80 -8.91 -13.19 Pu (kip) L	Load Case  1.2D + 1.6W 0.9D + 1.6W 90 1.2D + 1.6W 90	Len (ft) 10.03 10.79 15.18 Fy (ksi)	Brac X 100 100 100 Fu (ksi)	Phit F (kip)	KL/R 0 33.1 0 136.7 0 157.0	F'y (ksi) 50.0 50.0 50.0 Nums Holes	Phic Pn (kip) 668.58 20.59 20.43 Shea phiR s (kip	Bolts 0 2 3 ar	Num   Holes 0 0 0 8 Bear phiRn (kip)	0.00 0.00 0.00 0.00 0.00	0.00 31.67 50.54	% 41 43 64 Use %	Member X Member X Member X
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 10" DIA PIPE	(kip) -277.80 -8.91 -13.19  Pu (kip) L 239.54	Load Case  1.2D + 1.6W 0.9D + 1.6W 90 1.2D + 1.6W 90  Load Case  1.2D + 1.6W 60	Len (ft)  10.03 10.79 15.18  Fy (ksi)	Brac X 100 100 100 Fu (ksi)	Phit F (kip) 6 724.5	KL/R 0 33.1 0 136.7 0 157.0 n Num Bolts	F'y (ksi) 50.0 50.0 50.0 Nums Holes	Phic Pn (kip) 668.58 20.59 20.43 Shea phiR s (kip	Bolts  0 2 3 err (nv 0)	Num   Holes 0 0 0 0 Bear phiRn (kip)	0.00 0.00 0.00 0.00 0.00 0.00	ophiRn (kip) 0.00 31.67 50.54 Shear it Pn kip)	% 41 43 64 Use %	Member X Member X Member X Controls Member
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 10" DIA PIPE  HORIZ PST - 2-1/2" DIA PIP	(kip) -277.80 -8.91 -13.19  Pu (kip) L 239.54 9.35	Load Case  1.2D + 1.6W 90 0.9D + 1.6W 90 1.2D + 1.6W 90  Load Case 1.2D + 1.6W 60 1.2D + 1.6W 90	Len (ft)  10.03 10.79 15.18  Fy (ksi) 50 50	Brac X 100 100 100 Fu (ksi)	Phit F (kip) 5 724.5 76.6	KL/R 0 33.1 0 136.7 0 157.0 n Num Bolts 0 0 8 2	50.0 50.0 50.0 50.0 Nums Holes	Phic Pn (kip) 668.58 20.59 20.43 Shea phiR s (kip	0 2 3 ar (nv b)	Num   Holes 0 0 0 0 Bear phiRn (kip) 0.00 25.33	0.00 0.00 0.00 0.00 0.00 0.00	yphiRn (kip) 0.00 31.67 50.54 Shear it Pn kip)	% 41 43 64 Use % 33 36	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 10" DIA PIPE	(kip) -277.80 -8.91 -13.19  Pu (kip) L 239.54 9.35	Load Case  1.2D + 1.6W 0.9D + 1.6W 90 1.2D + 1.6W 90  Load Case  1.2D + 1.6W 60	Len (ft)  10.03 10.79 15.18  Fy (ksi)	Brac X 100 100 100 Fu (ksi)	Phit F (kip) 5 724.5 76.6	KL/R 0 33.1 0 136.7 0 157.0 n Num Bolts 0 0 8 2	F'y (ksi) 50.0 50.0 50.0 Nums Holes	Phic Pn (kip) 668.58 20.59 20.43 Shea phiR s (kip	Bolts  0 2 3 err (nv 0)	Num   Holes 0 0 0 0 Bear phiRn (kip)	0.00 0.00 0.00 0.00 0.00 0.00	ophiRn (kip) 0.00 31.67 50.54 Shear it Pn kip)	% 41 43 64 Use % 33 36	Member X Member X Member X Controls Member
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIP  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 10" DIA PIPE  HORIZ PST - 2-1/2" DIA PIP  DIAG PST - 3" DIA PIPE	Pu (kip) L 239.54 9.35 12.32	Load Case  1.2D + 1.6W 90 0.9D + 1.6W 90 1.2D + 1.6W 90  Load Case 1.2D + 1.6W 60 1.2D + 1.6W 90	Len (ft)  10.03 10.79 15.18  Fy (ksi) 50 50	Brack X 100 100 100 Fu (ksi)	Phit F (kip) 5 724.5 76.6 100.3	KL/R 0 33.16.7 0 136.7 0 157.0 n Num Bolts 0 0 8 2 5 3	50.0 50.0 50.0 50.0 Nums Holes	Phic Pn (kip) 668.58 20.59 20.43 Shea phiR s (kip	0 2 3 ar (nv b)	Num   Holes 0 0 0 0 Bear phiRn (kip) 0.00 25.33	0.00 0.00 0.00 0.00 0.00 0.00	yphiRn (kip) 0.00 31.67 50.54 Shear it Pn kip)	% 41 43 64 Use % 33 36	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 10" DIA PIPE  HORIZ PST - 2-1/2" DIA PIP	(kip) -277.80 -8.91 -13.19  Pu (kip) L 239.54 9.35	Load Case  1.2D + 1.6W 90 0.9D + 1.6W 90 1.2D + 1.6W 90  Load Case 1.2D + 1.6W 60 1.2D + 1.6W 90	Len (ft)  10.03 10.79 15.18  Fy (ksi) 50 50	Brac X 100 100 100 Fu (ksi)	Phit F (kip) 5 724.5 76.6 100.3	KL/R 0 33.1 0 136.7 0 157.0 n Num Bolts 0 0 8 2	F'y (ksi) 50.0 50.0 Nums Holes 0 0	Phic Pn (kip) 668.58 20.59 20.43 Shea phiR s (kip	Bolts 0 2 3 ar (nv ) 0.00 0.00 0.00	Num   Holes 0 0 0 0 Bear phiRn (kip) 0.00 25.33	0.00 0.00 0.00 0.00 0.00 0.00	yphiRn (kip) 0.00 31.67 50.54 Shear it Pn kip)	% 41 43 64 Use % 33 36	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 10" DIA PIPE  HORIZ PST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Splice Forces  Top Tension	Pu (kip) L 239.54 9.35 12.32 (kip) 229.61	Load Case  1.2D + 1.6W 0.9D + 1.6W 90 1.2D + 1.6W 90  Load Case 1.2D + 1.6W 60 1.2D + 1.6W 90 0.9D + 1.6W 90  Load Case 0.9D + 1.6W 18	Len (ft)  10.03 10.79 15.18  Fy (ksi) 50 50	Brack X 100 100 100 Fu (ksi) 65 65 65 phiRi (kip) 0.0	Phit F (kip) 5 724.5 5 76.6 6 100.3	KL/R 0 33.1 0 136.7 0 157.0 n Num Bolts 0 0 8 2 5 3 Use % 0	F'y (ksi) 50.0 50.0 Nums Holes 0 0	Phic Pn (kip) 668.58 20.59 20.43 SheaphiRs (kip	Bolts 0 2 3 ar (nv ) 0.00 0.00 0.00	Num   Holes 0 0 0 0 Bear phiRn (kip) 0.00 25.33	0.00 0.00 0.00 0.00 0.00 0.00	yphiRn (kip) 0.00 31.67 50.54 Shear it Pn kip)	% 41 43 64 Use % 33 36	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIP  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 10" DIA PIPE  HORIZ PST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Splice Forces  Top Tension  Top Compression	Pu (kip) L 239.54 9.35 12.32 (kip) 229.61 260.28	Load Case  1.2D + 1.6W 0.9D + 1.6W 90 1.2D + 1.6W 90  Load Case 1.2D + 1.6W 60 1.2D + 1.6W 90 0.9D + 1.6W 90  Load Case 0.9D + 1.6W 18 1.2D + 1.6W 18	Len (ft)  10.03 10.79 15.18  Fy (ksi) 50 50	Brack X 100 100 100 Fu (ksi) 65 65 65 phiRick (kip) 0.0	Phit F (kip)  7 724.5  7 724.5  7 100.3	KL/R 0 33.1 0 136.7 0 157.0 n Num Bolts 0 0 8 2 5 3 Use % 0 0	F'y (ksi) 50.0 50.0 50.0 Num Holes 0 0 Num Bolts	Phic Pn (kip)  668.58 20.59 20.43  Sheaphire (kip)  C C Bolt Ty	90 ar (n)	Num   Holes 0 0 0 0 Bear phiRn (kip) 0.00 25.33	0.00 0.00 0.00 0.00 0.00 0.00	yphiRn (kip) 0.00 31.67 50.54 Shear it Pn kip)	% 41 43 64 Use % 33 36	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 10" DIA PIPE  HORIZPST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 10" DIA PIPE  HORIZ PST - 2-1/2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Splice Forces  Top Tension	Pu (kip) L 239.54 9.35 12.32 (kip) 229.61 260.28 256.68	Load Case  1.2D + 1.6W 0.9D + 1.6W 90 1.2D + 1.6W 90  Load Case 1.2D + 1.6W 60 1.2D + 1.6W 90 0.9D + 1.6W 90  Load Case 0.9D + 1.6W 18	Len (ft)  10.03 10.79 15.18  Fy (ksi) 50 50	Brack X 100 100 100 Fu (ksi) 65 65 65 phiRi (kip) 0.0	Phit F (kip)  7 724.5  7 724.5  7 100.3	KL/R 0 33.1 0 136.7 0 157.0 n Num Bolts 0 0 8 2 5 3 Use % 0	F'y (ksi) 50.0 50.0 Num Hole: 0 0 Num Bolts	Phic Pn (kip) 668.58 20.59 20.43 SheaphiRs (kip	90 ar (n)	Num   Holes 0 0 0 0 Bear phiRn (kip) 0.00 25.33	0.00 0.00 0.00 0.00 0.00 0.00	yphiRn (kip) 0.00 31.67 50.54 Shear it Pn kip)	% 41 43 64 Use % 33 36	Member X Member X Member X  Controls  Member Bolt Bear

Site Name: North Madison Volunteer FD, CT

Customer: Sprint Nextel

Engineering Number: 12163181\_C3\_01

10/26/2017 3:52:43 PM

Section: 3 3		Bot Elev	(ft): 40	0.00	Н	leight	(ft):	: 20.0	000						
							_					Shear			
	Pu		Len		cing %						Num				
Max Compression Member	(kip)	Load Case	(ft)	Х	Υ .	Z KL	R (k	ksi)	(kip)	Bolts	Holes	(kip)	(kip)	%	Controls
LEG PX - 8" DIA PIPE		1.2D + 1.6W				100 41			506.95	0	0	0.00	0.00		Member X
HORIZPST - 2-1/2" DIA PIP DIAG PST - 3" DIA PIPE		1.2D + 1.6W 90 1.2D + 1.6W 90				100 120		50.0 50.0	26.55 23.13	2	0 0	0.00	31.67 50.54		Member X Member X
DIAG PSI - S DIA PIPE	-12.30	1.20 + 1.000 90	14.20	100	100 1	100 14	.0	30.0	23.13	3	U	0.00	30.34	34	Member 7
									Shea	ar	Bear	Blk :	Shear		
	Pu		Fy	Fu		Pn Nu		Num	phiR	nv	phiRn	ph	it Pn	Use	Controls
Max Tension Member	()	_oad Case	(ksi)	(ksi)	(kip	<u> </u>		Holes	· · ·		(kip)		(ip)	%	
LEG PX - 8" DIA PIPE HORIZ PST - 2-1/2" DIA PIP		1.2D + 1.6W 180 1.2D + 1.6W 90	50 50			.00 .68	0 2	0		.00 .00	0.00 25.33		0.00		Member Bolt Bear
DIAG PST - 3" DIA PIPE		1.2D + 1.6W 90 1.2D + 1.6W 90	50				3	0		.00	43.80		0.00		Bolt Bear
DINO 131-3 DIATIFE	11.03	1.2D + 1.0W 70	50	0.	100.	.55	J	U	U	.00	43.00	J	0.00	20	Doit Deal
	Pu			phiR	nt	Use	Νι	um							
Max Splice Forces	(kip)	Load Case		(kip		%		olts	Bolt Ty	pe					
Top Tension		0.9D + 1.6W 18	30		00	0		0							
Top Compression		1.2D + 1.6W	20		00	0		10	1 4205						
Bot Tension Bot Compression		0.9D + 1.6W 18 1.2D + 1.6W	30	654. 0	24 00	35 0		12	1 A325						
Section: 4 4		Bot Elev	(ft): 60	0.00	Н	leight	(ft):	: 20.0	000						
Section: 4 4	Pu	Bot Elev	. ,			Ü	. ,			Num		Shear		llse	
	Pu (kip)	Bot Elev	Len		cing %	,	F	- 'y F	Phic Pn		Num	phiRnv	/phiRn	Use %	Controls
Max Compression Member	(kip)	Load Case	Len (ft)	Bra X	cing %	Z KL	F R (k	-'y F ksi)	Phic Pn (kip)	Bolts	Num   Holes	phiRnv (kip)	phiRn (kip)	%	
	(kip) -210.61	Load Case 1.2D + 1.6W	Len (ft)	Bra X	cing % Y :	Z KL	F R (k	F'y F ksi) 50.0	Phic Pn		Num	phiRnv	/phiRn	% 41	Controls  Member X  Member X
Max Compression Member LEG PX - 8" DIA PIPE	-210.61 -7.91	Load Case	Len (ft) 10.03 8.214	Bra X 100 100	cing % Y :	Z KL	F R (k .8	-'y F ksi)	Phic Pn (kip) 507.00	Bolts 0	Num   Holes	phiRnv (kip) 0.00	phiRn (kip)	% 41 51	Member X
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE	-210.61 -7.91	Load Case 1.2D + 1.6W 1.2D + 1.6W 90	Len (ft) 10.03 8.214	Bra X 100 100	cing % Y :	Z KL 100 41	F R (k .8	50.0 50.0	Phic Pn (kip) 507.00 15.41	Bolts 0 2	Num   Holes	0.00 0.00	(kip) 0.00 24.02	% 41 51	Member X Member X
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE	(kip) -210.61 -7.91 -13.25	Load Case 1.2D + 1.6W 1.2D + 1.6W 90	Len (ft) 10.03 8.214 13.35	Bra X 100 100	cing % Y 100 1 100 1	Z KL 100 4 <sup>2</sup> 100 12!	F R (k .8 5.2 3.1	50.0 50.0 50.0 50.0	Phic Pn (kip) 507.00 15.41 26.41 Shea	Bolts 0 2 3	Num   Holes 0 0 0	0.00 0.00 0.00 0.00	0.00 24.02 50.54 Shear	% 41 51 50	Member X Member X
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE	-210.61 -7.91 -13.25	Load Case 1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90	Len (ft) 10.03 8.214 13.35	Bra X 100 100 100	cing % Y 100 1 100 1 100 1	Z KL 7 KL 100 4 100 12 100 138	FR (k .8 5.2 3.1	50.0 50.0 50.0 50.0	Phic Pn (kip) 507.00 15.41 26.41 Shea phiR	Bolts 0 2 3	Num   Holes 0 0 0 0	0.00 0.00 0.00 0.00 Blk	vphiRn (kip) 0.00 24.02 50.54 Shear it Pn	% 41 51	Member X Member X
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE	(kip) -210.61 -7.91 -13.25  Pu (kip) L	Load Case  1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90	Len (ft) 10.03 8.214 13.35 Fy (ksi)	Bra X 100 100 100 Fu (ksi)	cing % Y : 100 1 100 1 100 1 Phit (kip	Z KL. 100 47 100 129 100 138 Pn Nu	F (k .8 5.2 3.1 m   Its H	50.0 50.0 50.0 50.0 Mum Holes	Phic Pn (kip) 507.00 15.41 26.41 Shea phiR	Bolts 0 2 3 ar nv	Num   Holes 0 0 0 8 Bear phiRn (kip)	phiRnv (kip) 0.00 0.00 0.00 Blk: ph	0.00 24.02 50.54 Shear	% 41 51 50 Use %	Member X Member X Member X
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE	(kip) -210.61 -7.91 -13.25  Pu (kip) L 186.50 (	Load Case 1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90	Len (ft) 10.03 8.214 13.35	Bra X 100 100 100 Fu (ksi)	cing % Y 100 1 100 1 100 1 Phit (kip	Z KL. 100 47 100 129 100 138 Pn Nu	FR (k .8 5.2 3.1	50.0 50.0 50.0 50.0	Phic Pn (kip) 507.00 15.41 26.41 Shea phiR 5 (kip	Bolts 0 2 3	Num   Holes 0 0 0 0	phiRnv (kip) 0.00 0.00 0.00 Blk: phi (k	vphiRn (kip) 0.00 24.02 50.54 Shear it Pn	% 41 51 50 Use %	Member X Member X Member X
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 8" DIA PIPE	(kip) -210.61 -7.91 -13.25  Pu (kip) L 186.50 ( 8.15	Load Case  1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90  Load Case 0.9D + 1.6W 60	Len (ft)  10.03 8.214 13.35  Fy (ksi)	Bra X 100 100 100 Fu (ksi) 65 6	cing % Y 100 1 100 1 100 1 Phit (kip	Z KL, 100 41 100 129 100 138 Pn Nu D) Bo .00	F (k .8 5.2 3.1 m   lts H	50.0 50.0 50.0 50.0 Mum Holes	Phic Pn (kip) 507.00 15.41 26.41 Shea phiR s (kip	Bolts 0 2 3 ar nv )	Num   Holes 0 0 0 Bear phiRn (kip)	phiRnv (kip) 0.00 0.00 0.00 8lk: ph (k	yphiRn (kip) 0.00 24.02 50.54 Shear it Pn kip)	% 41 51 50 Use %	Member X Member X Member X Controls Member
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 8" DIA PIPE  HORIZ PST - 2" DIA PIPE	(kip) -210.61 -7.91 -13.25  Pu (kip) L 186.50 ( 8.15	Load Case  1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90  Load Case 0.9D + 1.6W 60 1.2D + 1.6W 90	Len (ft)  10.03 8.214 13.35  Fy (ksi) 50 50	Bra X 100 100 100 Fu (ksi) 65 6	cing % Y 100 1 100 1 100 1 Phit (kip	Z KL, 100 41 100 129 100 138 Pn Nu D) Bo .00	F (k .8 5.2 3.1 m   lts H 0	50.0 50.0 50.0 50.0 Mum Holes	Phic Pn (kip) 507.00 15.41 26.41 Shea phiR s (kip	0 2 3 arrnv )	Num   Holes 0 0 0 0 0 0 Bear phiRn (kip) 0.00 19.22	phiRnv (kip) 0.00 0.00 0.00 8lk: ph (k	yphiRn (kip) 0.00 24.02 50.54 Shear it Pn kip)	% 41 51 50 Use %	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 8" DIA PIPE  HORIZ PST - 2" DIA PIPE	(kip) -210.61 -7.91 -13.25  Pu (kip) L  186.50 ( 8.15 1  12.43 1	Load Case  1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90  Load Case 0.9D + 1.6W 60 1.2D + 1.6W 90 1.2D + 1.6W 90	Len (ft)  10.03 8.214 13.35  Fy (ksi) 50 50	Bra X 100 100 100   Fu (ksi) 6! 6! phiR	Cing % Y 100 1 100 1 100 1 Phit (kip 5 576. 5 48 5 100.	Z KL. 100 4 <sup>2</sup> 100 129 100 138 Pn Nu b) Bo .00 .15 .35	F R (k) .8 .8 .3.1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .	50.0 50.0 50.0 50.0 0 0 0	Phic Pn (kip) 507.00 15.41 26.41 SheaphiR (kip) 0	0 2 3 arrnv ) .00 .00	Num   Holes 0 0 0 0 0 0 Bear phiRn (kip) 0.00 19.22	phiRnv (kip) 0.00 0.00 0.00 8lk: ph (k	yphiRn (kip) 0.00 24.02 50.54 Shear it Pn kip)	% 41 51 50 Use %	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 8" DIA PIPE  HORIZ PST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Splice Forces	Pu (kip) L 186.50 (8.15 12.43 1	Load Case  1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90  Load Case  0.9D + 1.6W 60 1.2D + 1.6W 90  1.2D + 1.6W 90  Load Case	Len (ft)  10.03 8.214 13.35  Fy (ksi)  50 50	Bra X 100 100 100 Fu (ksi) 6! 6! phiR (kip	Cing % Y  100 1 100 1 100 1  Phit (kip 5 576. 5 48 5 100.  nt )	Z KL 100 41 100 129 100 138 Pn Nu b) Bo .00 .15 .35	F R (k) .8 .8 .3.1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .	50.0 50.0 50.0 50.0 Mum Holes 0 0	Phic Pn (kip) 507.00 15.41 26.41 Shea phiR s (kip	0 2 3 arrnv ) .00 .00	Num   Holes 0 0 0 0 0 0 Bear phiRn (kip) 0.00 19.22	phiRnv (kip) 0.00 0.00 0.00 8lk: ph (k	yphiRn (kip) 0.00 24.02 50.54 Shear it Pn kip)	% 41 51 50 Use %	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 8" DIA PIPE  HORIZPST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 8" DIA PIPE  HORIZ PST - 2" DIA PIPE  DIAG PST - 3" DIA PIPE	Pu (kip) L 186.50 (kip) L 12.43 1 Pu (kip) L 169.83	Load Case  1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90  Load Case 0.9D + 1.6W 60 1.2D + 1.6W 90 1.2D + 1.6W 90	Len (ft)  10.03 8.214 13.35  Fy (ksi)  50 50	Bra X 100 100 100   Fu (ksi) 6! 6! 6! phiR (kip 0.	Cing % Y 100 1 100 1 100 1 Phit (kip 5 576. 5 48 5 100.	Z KL. 100 4 <sup>2</sup> 100 129 100 138 Pn Nu b) Bo .00 .15 .35	F R (k) .8 .8 .3.1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .	50.0 50.0 50.0 50.0 0 0 0	Phic Pn (kip) 507.00 15.41 26.41 SheaphiR (kip) 0	0 2 3 arrnv ) .00 .00	Num   Holes 0 0 0 0 0 0 Bear phiRn (kip) 0.00 19.22	phiRnv (kip) 0.00 0.00 0.00 8lk: ph (k	yphiRn (kip) 0.00 24.02 50.54 Shear it Pn kip)	% 41 51 50 Use %	Member X Member X Member X  Controls  Member Bolt Bear
Max Compression Member  LEG PX - 8" DIA PIPE HORIZPST - 2" DIA PIPE DIAG PST - 3" DIA PIPE  Max Tension Member  LEG PX - 8" DIA PIPE HORIZ PST - 2" DIA PIPE DIAG PST - 3" DIA PIPE  Max Splice Forces  Top Tension	Pu (kip) L 186.50 (kip) L 12.43 1 Pu (kip) L 191.24	Load Case  1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90  Load Case  0.9D + 1.6W 60 1.2D + 1.6W 90  Load Case  0.9D + 1.6W 90	Len (ft)  10.03 8.214 13.35  Fy (ksi)  50 50 50	Bra X 100 100 100   Fu (ksi) 6! 6! 6! phiR (kip 0.	cing % Y 100 1 100 1 100 1 Phit (kip 5 576 5 48 5 100 00 00	Pn Nu Nu Nu Nu Nu Nu Nu Nu Nu Nu	F R (k) .8 .8 .3.1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .1 .	50.0 50.0 50.0 50.0 Mum Holes 0 0	Phic Pn (kip) 507.00 15.41 26.41 SheaphiR (kip) 0	0 2 3 arrnv ) .00 .00	Num   Holes 0 0 0 0 0 0 Bear phiRn (kip) 0.00 19.22	phiRnv (kip) 0.00 0.00 0.00 8lk: ph (k	yphiRn (kip) 0.00 24.02 50.54 Shear it Pn kip)	% 41 51 50 Use %	Member X Member X Member X  Controls  Member Bolt Bear

Site Name: North Madison Volunteer FD, CT

Customer: Sprint Nextel

Engineering Number: 12163181\_C3\_01

81\_C3\_01 10/26/2017 3:52:43 PM

Section: 5 5	Bot Elev (ft): 80.00 Height (ft): 20.000
Max Compression Member	Shear Bear Pu Len Bracing % F'y Phic Pn Num Num phiRnv phiRn Use (kip) Load Case (ft) X Y Z KL/R (ksi) (kip) Bolts Holes (kip) (kip) % Controls
LEG PSP - ROHN 8 EHS HORIZPST - 2" DIA PIPE DIAG PST - 3" DIA PIPE	-171.23 1.2D + 1.6W 10.02 100 100 100 41.2 50.0 386.39 0 0 0.00 0.00 44 Member X -8.03 1.2D + 1.6W 90 7.026 100 100 100 107.1 50.0 20.80 2 0 0.00 24.02 38 Member X -14.53 1.2D + 1.6W 90 12.55 100 100 100 129.9 50.0 29.85 3 0 0.00 50.54 48 Member X
Max Tension Member	Shear Bear Blk Shear Pu Fy Fu Phit Pn Num Num phiRnv phiRn phit Pn Use (kip) Load Case (ksi) (ksi) (kip) Bolts Holes (kip) (kip) (kip) % Controls
LEG PSP - ROHN 8 EHS HORIZ PST - 2" DIA PIPE DIAG PST - 3" DIA PIPE	148.74       1.2D + 1.6W 60       50       65       437.40       0       0       0.00       0.00       34 Member         8.15       1.2D + 1.6W 90       50       65       48.15       2       0       0.00       19.22       0.00       42 Bolt Bear         13.86       1.2D + 1.6W 90       50       65       100.35       3       0       0.00       43.80       0.00       31 Bolt Bear
Max Splice Forces	Pu phiRnt Use Num (kip) Load Case (kip) % Bolts Bolt Type
Top Tension Top Compression Bot Tension Bot Compression	132.16  0.9D + 1.6W 180
Section: 6 6	Bot Elev (ft): 100.0 Height (ft): 20.000
Max Compression Member	Shear Bear Pu Len Bracing % F'y Phic Pn Num Num phiRnv phiRn Use (kip) Load Case (ft) X Y Z KL/R (ksi) (kip) Bolts Holes (kip) (kip) % Controls
LEG PSP - ROHN 6 EHS HORIZPST - 2" DIA PIPE DIAG PST - 2-1/2" DIA PIP	-135.44 1.2D + 1.6W 6.68 100 100 100 36.0 50.0 274.62 0 0 0.00 0.00 49 Member X -7.33 1.2D + 1.6W 90 6.108 100 100 100 93.1 50.0 25.54 2 0 0.00 24.02 28 Member X -11.34 1.2D + 1.6W 90 9.288 100 100 100 117.7 50.0 27.79 3 0 0.00 47.50 40 Member X
Max Tension Member	Shear Bear Blk Shear Pu Fy Fu Phit Pn Num Num phiRnv phiRn phit Pn Use (kip) Load Case (ksi) (ksi) (kip) Bolts Holes (kip) (kip) (kip) % Controls
LEG PSP - ROHN 6 EHS HORIZ PST - 2" DIA PIPE DIAG PST - 2-1/2" DIA PIP	119.05     0.9D + 1.6W 60     50     65     301.95     0     0.00     0.00     0.00     39 Member       7.46     1.2D + 1.6W 90     50     65     48.15     2     0     0.00     19.22     0.00     38 Bolt Bear       10.90     1.2D + 1.6W 90     50     65     76.68     3     0     0.00     41.17     0.00     26 Bolt Bear
Max Splice Forces	Pu phiRnt Use Num (kip) Load Case (kip) % Bolts Bolt Type
Top Tension Top Compression	91.10 0.9D + 1.6W 180 0.00 0 0 104.62 1.2D + 1.6W 0.00 0

Site Name: North Madison Volunteer FD, CT

Customer: Sprint Nextel

Engineering Number: 12163181\_C3\_01

Section: 7 7		Bot Elev	(ft): 12	20.0	Не	eight (	(ft): 20	.000					
	Pu (kip)	Load Case	Len (ft)		cing % Y Z		,	Phic Pn Num (kip) Bolts	Num p	Shear hiRnv (kip)		Use %	Controls
Max Compression Member							. ,	. 17		` ' '	` ' '		
LEG PSP - ROHN 5 EH HORIZPST - 1-1/2" DIA PIP DIAG PX - 2" DIA PIPE	-6.76	1.2D + 1.6W 1.2D + 1.6W 90 1.2D + 1.6W 90	5.049		100 10 100 10 99 9		2 50.0		0	0.00 0.00 0.00	0.00 22.62 51.01	37	Member X Member X Member X
Max Tension Member	Pu (kip)	Load Case	Fy (ksi)	Fu (ksi)	Phit F (kip)	Pn Num Bolt			Bear phiRn (kip)	phi	Shear t Pn ip)	Use %	Controls
LEG PSP - ROHN 5 EH		0.9D + 1.6W 180						0.00	0.00				Member
HORIZ PST - 1-1/2" DIA PIP DIAG PX - 2" DIA PIPE		1.2D + 1.6W 90 1.2D + 1.6W 90	50 50					0.00 0.00	18.10 44.21		0.00		Bolt Bear Bolt Bear
Max Splice Forces	Pu (kip)	Load Case		phiRr (kip)		Use %	Num Bolts	Bolt Type					
Top Tension		0.9D + 1.6W 18	30	0.0		0	0						
Top Compression		1.2D + 1.6W	00	0.0		0	,	1 4 2 2 5					
Bot Tension Bot Compression		0.9D + 1.6W 1 1.2D + 1.6W	80	327.1 0.0		28 0	6	1 A325					
Section: 8 8		Bot Elev	(ft): 14	0.0	Н	eight (	(ft): 20	.000					
	Pu		Len	Bra	cing %		F'y	Phic Pn Num		Shear		Use	
Max Compression Member	(kip)	Load Case	(ft)	Х	_	KL/R		(kip) Bolts	-	(kip)	(kip)	%	Controls
LEG PX - 4" DIA PIPE		1.2D + 1.6W			100 10			160.28 0		0.00	0.00		Member X
HORIZPST - 1-1/2" DIA PIP DIAG PX - 2" DIA PIPE		1.2D + 1.6W 90 1.2D + 1.6W 90			100 10	00 83.6 00 124.1		21.57 2 21.49 3		0.00	22.62 51.01		Member X Member X
DIAG TX-2 DIATTIL	-11.04	7 1.2D 1 1.0VV 70	7.703	100	100 10	00 124.	7 30.0	21.47 3	O	0.00	31.01	31	WEITIBEL X
Max Tension Member	Pu (kip)	Load Case	Fy (ksi)	Fu (ksi)	Phit F (kip)	Pn Num Bolt	n Num s Hole		Bear phiRn (kip)	phi	Shear t Pn ip)	Use %	Controls
LEG PX - 4" DIA PIPE		0.9D + 1.6W 180						0.00	0.00				Member
HORIZ PST - 1-1/2" DIA PIP		1.2D + 1.6W 90	50					0.00	18.10		0.00		Bolt Bear
DIAG PX - 2" DIA PIPE	10.81	1.2D + 1.6W 90	50	65	66.6	00 3	0	0.00	44.21		0.00	24	Bolt Bear
							Nicona						
Max Splice Forces	Pu (kip)	Load Case		phiRr (kip)		Use %	Num Bolts	Bolt Type					
Top Tension	(kip) 10.92	2 0.9D + 1.6W 18	30	(kip)	00	0		Bolt Type					
	(kip) 10.92 15.50			(kip)	00	%	Bolts	Bolt Type					

Site Name: North Madison Volunteer FD, CT

Customer: Sprint Nextel

Engineering Number: 12163181\_C3\_01

3181\_C3\_01 10/26/2017 3:52:43 PM

Section: 9 9	Bot Elev	(ft): 160.C	Heigl	ht (ft): 20.	000		
	Pu	Len B	racing %	F'y ı	Phic Pn Num		r Bear nyphiRn Use
Max Compression Member	(kip) Load Case	(ft) X	•	KL/R (ksi)		Holes (kip)	•
LEG PST - 3" DIA PIPE	-6.69 1.2D + 1.0Di +	6.67 10	0 100 100	69.0 50.0	70.87 0	0 0.00	0.00 9 Member X
HORIZPST - 1-1/2" DIA PIP	-3.27 1.2D + 1.6W	4.299 10	0 100 100	82.8 50.0	21.78 2	0 0.00	22.62 15 Member X
DIAG PST - 2" DIA PIPE	-5.85 1.2D + 1.6W 90	7.940 10	0 100 100 1	121.1 50.0	16.49 3	0 0.00	36.04 35 Member X
Max Tension Member	Pu (kip) Load Case	Fy Fı (ksi) (ks		Num Num Bolts Holes	Tr.	phiRn ph	s Shear hit Pn Use (kip) % Controls
LEG PST - 3" DIA PIPE	3.05 0.9D + 1.6W 180	50	65 100.35	0 0	0.00	0.00	3 Member
HORIZ PST - 1-1/2" DIA PIP	3.30 1.2D + 1.6W 60	50	65 35.96	2 0	0.00	18.10	0.00 18 Bolt Bear
DIAG PST - 2" DIA PIPE	5.73 1.2D + 1.6W 90	50	65 48.15	3 0	0.00	31.23	0.00 18 Bolt Bear
Max Splice Forces	Pu (kip) Load Case		Rnt Use		Bolt Type		
Top Tension	0.00		0.00 0	0			
Top Compression	0.91 1.2D + 1.0Di +		0.00 0	)			
Bot Tension	10.92 0.9D + 1.6W 1		6.24 7	4	7/8 A325		
Bot Compression	15.50 1.2D + 1.6W		0.00 0	)			

North Madison Volunteer FD, CT

Site Number: 383660 Engineer: **Engineering Number:** 

RDB 12163181\_C3\_01 10/26/17

#### Design Base Loads (Factored) - Analysis per TIA-222-G Standards

Analyze or Design a Foundation? Analyze Foundation Mapped: Ν 0.0 k-ft Moment (M): Shear/Leg (V): 38.3 k Compression/Leg (P): 323.3 k Uplift/Leg (U): 282.3 k Tower Type (GT / SST / MP): SST

Diameter of Caisson (d): Caisson Embedment (L-h):

Caisson Height Above Ground (h):

Depth Below Ground Surface to Water Table (w):

Unit Weight of Concrete: Unit Weight of Water:


Tension Skin Friction/Compression Skin Friction:


Pullout Angle:

Site Name:

Date:

## Program Last Updated: American Tower Corporation





5/13/2014

6.0	ft
18.0	ft
0.5	ft
2.5	ft
150.0	pcf
62.4	pcf
1.00	
30.0	degrees

# **Engineer Notes**

#### **Soil Mechanical Properties**

Dept	:h (ft)	$\gamma_{Soil}$	Cohesion	ф	Ultimate Skin	Ultimate Bearing
Тор	Bottom	(pcf)	(psf)	(degree)	Friction (psf)	Pressure (psf)
0.0	2.0	125	0	0	0	0
2.0	10.0	125	625	0	313	0
10.0	14.0	135	6250	0	3125	0
14.0	19.0	145	8000	0	5000	36719


Volume of Concrete:	$523.1 \text{ ft}^3 = 19.4 \text{ yd}^3$
Weight of Concrete (Buoyancy Effect Considered):	51.1 k
Average Soil Unit Weight:	77.9 pcf
Skin Friction Resistance:	659.8 k
Compressive Bearing Resistance:	1038.2 k
Pullout Weight (Minus Concrete Weight):	647.7 k
Nominal Uplift Capacity per Leg ( $\phi_s T_n$ ):	485.8 k
Nominal Compressive Capacity per Leg ( $\phi_s P_n$ ):	1273.5 k
$P_u$ :	334.5 k
$T_u/\phi_sT_n$ :	0.58 Result: OK
$P_{u}/\phi_{s}P_{n}$ :	0.26 Result: OK
Total Lateral Resistance:	2347.2 k
Inflection Point (Below Ground Surface):	14.3 ft
Design Overturning Moment At Inflection Point (M <sub>D</sub> ):	567.6 k-ft
Nominal Moment Capacity $(\phi_s M_n)$ :	4527.1 k-ft
$M_D/\phi_s M_n$ :	0.13 Result: OK
$\phi_s$ :	0.75


#### **Caisson Strength Capacity**


<u>Caisson Strength Capacity</u>	
Concrete Compressive Strength (f'c):	4500 psi
Vertical Steel Rebar Size #:	9
Vertical Steel Rebar Area:	1.00 in <sup>2</sup>
# of Vertical Steel Rebars:	26
Vertical Steel Rebar Yield Strength (F <sub>y</sub> ):	60 ksi
Horizontal Tie / Stirrup Size #:	5
Horizontal Tie / Stirrup Area:	0.31 in <sup>2</sup>
Design Horizontal Tie / Stirrup Spacing:	12.0 in
Horizontal Tie / Stirrup Steel Yield Strength (F <sub>y</sub> ):	60 ksi
Rebar Cage Diameter:	64.0 in
Strength Bending/Tension Reduction Factor ( $\phi_B$ ):	0.90 ACI318-05 - 9.3.2.1
Strength Shear Reduction Factor ( $\phi_V$ ):	0.75 ACI318-05 - 9.3.2.3
Strength Compression Reduction Factor ( $\phi_V$ ):	0.65 ACI318-05 - 9.3.2.2
Steel Elastic Modulus:	29000 ksi
Design Moment (M <sub>u</sub> ):	191.3 k-ft
Nominal Moment Capacity ( $\phi_B M_n$ ):	3662.7 k-ft - ACI318-005 - 10.2
$M_u/\phi_BM_n$ :	0.05 Result: OK
Design Shear (V <sub>u</sub> ):	38.3 k
Nominal Shear Capacity $(\phi_v V_n)$ :	395.5 k - ACI318-05 - 11.3.1.1 or 11.5.7.2
$V_u/\phi_V V_n$ :	0.10 Result: OK
Design Tension (T <sub>u</sub> ):	282.3 k
Nominal Tension Capacity $(\phi_T T_n)$ :	1404.0 k - ACI318-05 - 10.2
$T_{\rm u}/\phi_{\rm T}T_{\rm n}$ :	0.20 Result: OK
Design Compression (P <sub>u</sub> ):	334.5 k
Nominal Compression Capacity $(\phi_P P_n)$ :	8046.5 k - ACI318-05 - 10.3.6.2
$P_{\rm u}/\phi_{\rm P}P_{\rm n}$ :	0.04 Result: OK
Bending Reinforcement Ratio:	0.006 ACI318-05 - 10.8.4 & 10.9.1
$M_u/\phi_B M_n + T_u/\phi_T T_n$ :	0.25 Result: OK


## Design Factored Shear / Depth

## Design Factored Moment / Depth









SITE INFORMATION

**TOWER OWNER:** 

LATITUDE (NAD83):

LONGITUDE (NAD83):

**ZONING JURISDICTION:** 

ZONING DISTRICT:

**POWER COMPANY:** 

**AAV PROVIDER:** 

NATIONAL GRID PHONE: (800) 642-4272

PHONE: (800) 837-4966

PROJECT MANAGER:
AIROSMITH DEVELOPMENT
TERRI BURKHOLDER

(315)719-2928
TBURKHOLDER AIROSMITHDEVELOPMENT.COM

CONNECTICUT SITING COUNCIL

41° 21′ 26.33″ N 41.35731388

72° 38′ 19.51″ W -72.63875277

COUNTY:

NEW HAVEN

AMERICAN TOWER CORPORATION 10 PRESIDENTIAL WAY WOBURN, MA 01801 PROJECT:

DO MACRO UPGRADE

SITE NAME:

N. MADISON/ VOL. FIRE DEPT.

SITE CASCADE:

CT03XC164

SITE ADDRESS:

864 OPENING HILL RD.


MADISON, CT 06443

SITE TYPE:

SELF SUPPORT TOWER

MARKET:

SOUTHERN CONNECTICUT





FROM ZERO TO INFINIGY
the solutions are endless
1033 Watervilet Shaker Rd | Albany, NY 1220:
Phone: 518-690-0790 | rax: 518-690-0793
www.lnfinigy.com

JOB NUMBER 526-104





- DRAWING NOTICE: -

THESE DOCUMENTS ARE CONFIDENTIAL AND ARE THE SOLE PROPERTY OF SPRINT AND MAY NOT BE REPRODUCED, DISSEMINATED OR REDISTRIBUTED WITHOUT THE EXPRESS WRITTEN CONSENT OF SPRINT.

REVISIONS:			
DESCRIPTION	DATE	BY	RE
			-
ISSUED FOR REVIEW	01/25/18	SKB	0

SITE NAME:

N. MADISON/ VOL. FIRE DEPT.

SITE NUMBER

CT03XC164

- SITE ADDRESS:

864 OPENING HILL RD. MADISON, CT 06443

- SHEET DESCRIPTION: -

TITLE SHEET & PROJECT DATA

SHEET NUMBER

T-1

#### SECTION 01 100 - SCOPE OF WORK

PART 1 - GENERAL

- 1.1 THE WORK: THESE STANDARD CONSTRUCTION SPECIFICATIONS IN CONJUNCTION WITH THE SPRINT CONSTRUCTION STANDARDS FOR WIRELESS SITES, CONTRACT DOCUMENTS AND THE CONSTRUCTION DRAWINGS DESCRIBE THE WORK TO BE PERFORMED BY THE CONTRACTOR.
- 1.2 RELATED DOCUMENTS:
- A. THE REQUIREMENTS OF THIS SECTION APPLY TO ALL SECTIONS IN THIS SPECIFICATION.
- B. SPRINT "STANDARD CONSTRUCTION DETAILS FOR WIRELESS SITES" ARE INCLUDED IN AND MADE A PART OF THESE SPECIFICATIONS HEREWITH.
- 1.3 PRECEDENCE: SHOULD CONFLICTS OCCUR BETWEEN THE STANDARD CONSTRUCTION SPECIFICATIONS FOR WIRELESS SITES INCLUDING THE STANDARD CONSTRUCTION DETAILS FOR WIRELESS SITES AND THE CONSTRUCTION DRAWINGS, INFORMATION ON THE CONSTRUCTION DRAWINGS SHALL TAKE PRECEDENCE. NOTIFY SPRINT CONSTRUCTION MANAGER IF THIS OCCURS,
- 1.4 NATIONALLY RECOGNIZED CODES AND STANDARDS:
- A. THE WORK SHALL COMPLY WITH APPLICABLE NATIONAL AND LOCAL CODES AND STANDARDS, LATEST EDITION, AND PORTIONS THEREOF, INCLUDED BUT NOT LIMITED TO THE FOLLOWING:
- 1. GR-63-CORE NEBS REQUIREMENTS: PHYSICAL PROTECTION
- 5. GR-78-CORE GENERIC REQUIREMENTS FOR THE PHYSICAL DESIGN AND MANUFACTURE OF TELECOMMUNICATIONS EQUIPMENT.
- 3. GR-1089 CORE, ELECTROMAGNETIC COMPATIBILITY AND ELECTRICAL SAFETY -GENERIC CRITERIA FOR NETWORK TELECOMMUNICATIONS EQUIPMENT.
- NATIONAL FIRE PROTECTION ASSOCIATION CODES AND STANDARDS (NFPA) INCLUDING NFPA 70 (NATIONAL ELECTRICAL CODE — "NEC") AND NFPA 101 (LIFE SAFETY CODE).
- 5. AMERICAN SOCIETY FOR TESTING OF MATERIALS (ASTM)
- 6. INSTITUTE OF ELECTRONIC AND ELECTRICAL ENGINEERS (IEEE)
- 7. AMERICAN CONCRETE INSTITUTE (ACI)
- 8. AMERICAN WIRE PRODUCERS ASSOCIATION (AWPA)
- 9. CONCRETE REINFORCING STEEL INSTITUTE (CRSI)
- AMERICAN ASSOCIATION OF STATE HIGHWAY AND TRANSPORTATION OFFICIALS (AASHTO)
- 11. PORTLAND CEMENT ASSOCIATION (PCA)
- 12. NATIONAL CONCRETE MASONRY ASSOCIATION (NCMA)
- 13. BRICK INDUSTRY ASSOCIATION (BIA)
- 14. AMERICAN WELDING SOCIETY (AWS)
- 15. NATIONAL ROOFING CONTRACTORS ASSOCIATION (NRCA)
- 16. SHEET METAL AND AIR CONDITIONING CONTRACTORS' NATIONAL ASSOCIATION (SMACNA)
- 17. DOOR AND HARDWARE INSTITUTE (DHI)
- 18. OCCUPATIONAL SAFETY AND HEALTH ACT (OSHA)
- 19. APPLICABLE BUILDING CODES INCLUDING UNIFORM BUILDING CODE, SOUTHERN BUILDING CODE, BOCA, AND THE INTERNATIONAL BUILDING CODE.

#### 1.5 DEFINITIONS:

- A. WORK: THE SUM OF TASKS AND RESPONSIBILITIES IDENTIFIED IN THE CONTRACT DOCUMENTS.
- B. COMPANY: SPRINT CORPORATION
- C. ENGINEER: SYNONYMOUS WITH ARCHITECT & ENGINEER AND "A&E". THE DESIGN PROFESSIONAL HAVING PROFESSIONAL RESPONSIBILITY FOR DESIGN OF THE PROJECT.
- D. CONTRACTOR: CONSTRUCTION CONTRACTOR; CONSTRUCTION VENDOR; INDIMIDUAL OR ENTITY WHO AFTER EXECUTION OF A CONTRACT IS BOUND TO ACCOMPLISH THE WORK.
- E. THIRD PARTY VENDOR OR AGENCY: A VENDOR OR AGENCY ENGAGED SEPARATELY BY THE COMPANY, A&E, OR CONTRACTOR TO PROVIDE MATERIALS OR TO ACCOMPLISH SPECIFIC TASKS RELATED TO BUT NOT INCLUDED IN THE WORK.
- F. OFCI: OWNER FURNISHED, CONTRACTOR INSTALLED EQUIPMENT
- G. CONSTRUCTION MANAGER ALL PROJECTS RELATED COMMUNICATION TO FLOW THROUGH SPRINT REPRESENTATIVE IN CHARGE OF PROJECT...

- 1.6 SITE FAMILIARITY: CONTRACTOR SHALL BE RESPONSIBLE FOR FAMILIARIZING HIMSELF WITH ALL CONTRACT DOCUMENTS, FIELD CONDITIONS AND DIMENSIONS PRIOR TO PROCEEDING WITH CONSTRUCTION. ANY DISCREPANCIES SHALL BE BROUGHT TO THE ATTENTION OF THE SPRINT CONSTRUCTION MANAGER PRIOR TO THE COMMENCEMENT OF WORK. NO COMPENSATION WILL BE AWARDED BASED ON CLAIM OF LACK OF KNOWLEDGE OR FIELD CONDITIONS.
- 1.7 POINT OF CONTACT: COMMUNICATION BETWEEN SPRINT AND THE CONTRACTOR SHALL FLOW THROUGH THE SINGLE SPRINT CONSTRUCTION MANAGER APPOINTED TO MANAGE THE PROJECT FOR SPRINT.
- 1.8 ON—SITE SUPERVISION: THE CONTRACTOR SHALL SUPERVISE AND DIRECT THE WORK AND SHALL BE RESPONSIBLE FOR CONSTRUCTION MEANS, METHODS, TECHNIQUES, SEQUENCES, AND PROCEDURES IN ACCORDANCE WITH THE CONTRACT DOCUMENTS. THE CONTRACT DOCUMENTS. THE MATTENDANCE AT THE SITE AT ALL TIMES DURING PERFORMANCE OF THE WORK.
- 1.9 DRAWINGS, SPECIFICATIONS AND DETAILS REQUIRED AT JOBSITE: THE CONSTRUCTION CONTRACTOR SHALL MAINTAIN A FULL SET OF THE CONSTRUCTION DRAWINGS, STANDARD CONSTRUCTION DETAILS FOR WIRELESS SITES AND THE STANDARD CONSTRUCTION SPECIFICATIONS FOR WIRELESS SITES AT THE JOBSITE FROM MOBILIZATION THROUGH CONSTRUCTION COMPLETION.
  - A. THE JOBSITE DRAWINGS, SPECIFICATIONS AND DETAILS SHALL BE CLEARLY MARKED DAILY IN RED PENCIL WITH ANY CHANGES IN CONSTRUCTION OVER WHAT IS DEPICTED IN THE DOCUMENTS. AT CONSTRUCTION COMPLETION, THIS JOBSITE MARKUP SET SHALL BE DELIVERED TO THE COMPANY OR COMPANY'S DESIGNATED REPRESENTATIVE TO BE FORWARDED TO THE COMPANY'S A&E VENDOR FOR PRODUCTION OF "AS-BUILT" DRAWINGS.
- B. DETAILS ARE INTENDED TO SHOW DESIGN INTENT. MODIFICATIONS MAY BE REQUIRED TO SUIT JOB DIMENSIONS OR CONDITIONS, AND SUCH MODIFICATIONS SHALL BE INCLUDED AS PART OF THE WORK. CONTRACTOR SHALL NOTIFY SPRINT CONSTRUCTION MANAGER OF ANY VARIATIONS PRIOR TO PROCEEDING WITH THE WORK.
- C. DIMENSIONS SHOWN ARE TO FINISH SURFACES UNLESS NOTED OTHERWISE.
  SPACING BETWEEN EQUIPMENT IS THE REQUIRED CLEARANCE. SHOULD THERE BE
  ANY QUESTIONS REGARDING THE CONTRACT DOCUMENTS, EXISTING CONDITIONS
  AND/OR DESIGN INTENT, THE CONTRACTOR SHALL BE RESPONSIBLE FOR OBTAINING
  A CLARIFICATION FROM THE SPRINT CONSTRUCTION MANAGER PRIOR TO
  PROCEEDING WITH THE WORK.
- 1.10 USE OF JOB SITE: THE CONTRACTOR SHALL CONFINE ALL CONSTRUCTION AND RELATED OPERATIONS INCLUDING STAGING AND STORAGE OF MATERIALS AND EQUIPMENT, PARKING, TEMPORARY FACILITIES, AND WASTE STORAGE TO THE LEASE PARCEL UNLESS OTHERWISE PERMITTED BY THE CONTRACT DOCUMENTS.
- 1.11 UTILITIES SERVICES: WHERE NECESSARY TO CUT EXISTING PIPES, ELECTRICAL WIRES, CONDUITS, CABLES, ETC., OF UTILITY SERVICES, OR OF FIRE PROTECTION OR COMMUNICATIONS SYSTEMS, THEY SHALL BE CUT AND CAPPED AT SUITABLE PLACES OR WHERE SHOWN. ALL SUCH ACTIONS SHALL BE COORDINATED WITH THE UTILITY COMPANY INVOLVED:
- 1.12 PERMITS / FEES: WHEN REQUIRED THAT A PERMIT OR CONNECTION FEE BE PAID TO A PUBLIC UTILITY PROVIDER FOR NEW SERVICE TO THE CONSTRUCTION PROJECT, PAYMENT OF SUCH FEE SHALL BE THE RESPONSIBILITY OF THE CONTRACTOR.
- 1.13 CONTRACTOR SHALL TAKE ALL MEASURES AND PROVIDE ALL MATERIAL NECESSARY FOR PROTECTING EXISTING EQUIPMENT AND PROPERTY.
- 1.14 METHODS OF PROCEDURE (MOPS) FOR CONSTRUCTION: CONTRACTOR SHALL PERFORM WORK AS DESCRIBED IN THE FOLLOWING INSTALLATION AND COMMISSIONING MOPS.

NOTE: IN SHORT-FORM SPECIFICATIONS ON THE DRAWINGS, A/E TO INSERT LIST OF APPLICABLE MOPS INCLUDING EN-2012-001, EN-2013-002, EL-0568, AND TS-0193

1.15 USE OF ELECTRONIC PROJECT MANAGEMENT SYSTEMS:

PART 2 - PRODUCTS (NOT USED)

#### PART 3 - EXECUTION

- 3.1 TEMPORARY UTILITIES AND FACILITIES: THE CONTRACTOR SHALL BE RESPONSIBLE FOR ALL TEMPORARY UTILITIES AND FACILITIES NECESSARY EXCEPT AS OTHERWISE INDICATED IN THE CONSTRUCTION DOCUMENTS. TEMPORARY UTILITIES AND FACILITIES INCLUDE POTABLE WATER, HEAT, HVAC, ELECTRICITY, SANITARY FACILITIES, WASTE DISPOSAL FACILITIES, AND TELEPHONE/COMMUNICATION SERVICES. PROVIDE TEMPORARY UTILITIES AND FACILITIES IN ACCORDANCE WITH 05HA AND THE AUTHORITY HAVING JURISDICTION. CONTRACTOR MAY UTILIZE THE COMPANY ELECTRICAL SERVICE IN THE COMPLETION OF THE WORK WHEN IT BECOMES AVAILABLE. USE OF THE LESSORS OR SITE OWNER'S UTILITIES OR FACILITIES IS EXPRESSLY FORBIDDEN EXCEPT AS OTHERWISE ALLOWED IN THE CONTRACT DOCUMENTS.
- 3.2 ACCESS TO WORK: THE CONTRACTOR SHALL PROVIDE ACCESS TO THE JOB SITE FOR AUTHORIZED COMPANY PERSONNEL AND AUTHORIZED REPRESENTATIVES OF THE ARCHITECT/ENGINEER DURING ALL PHASES OF THE WORK.
- 3.3 TESTING: REQUIREMENTS FOR TESTING BY THIS CONTRACTOR SHALL BE AS INDICATED HEREWITH, ON THE CONSTRUCTION DRAWINGS, AND IN THE INDIVIDUAL SECTIONS OF THESE SPECIFICATIONS. SHOULD COMPANY CHOOSE TO ENGAGE ANY THIRD—PARTY TO CONDUCT ADDITIONAL TESTING, THE CONTRACTOR SHALL COOPERATE WITH AND PROVIDE A WORK AREA FOR COMPANY'S TEST AGENCY.
- 3.4 DIMENSIONS: VERIFY DIMENSIONS INDICATED ON DRAWINGS WITH FIELD DIMENSIONS BEFORE FABRICATION OR ORDERING OF MATERIALS. DO NOT SCALE DRAWINGS.

3.5 EXISTING CONDITIONS: NOTIFY THE SPRINT CONSTRUCTION MANAGER OF EXISTING CONDITIONS DIFFERING FROM THOSE INDICATED ON THE DRAWINGS. DO NOT REMOVE OR ALTER STRUCTURAL COMPONENTS WITHOUT PRIOR WRITTEN APPROVAL FROM THE ARCHITECT AND ENGINEER.

# SECTION 01 200 - COMPANY FURNISHED MATERIAL AND EQUIPMENT PART 1 - GENERAL

- 1.1 THE WORK: THESE STANDARD CONSTRUCTION SPECIFICATIONS IN CONJUNCTION WITH THE OTHER CONTRACT DOCUMENTS AND THE CONSTRUCTION DRAWINGS DESCRIBE THE WORK TO BE PERFORMED BY THE CONTRACTOR.
- 1.2 RELATED DOCUMENTS:
- A. THE REQUIREMENTS OF THIS SECTION APPLY TO ALL SECTIONS IN THIS SPECIFICATION.
- B. SPRINT "STANDARD CONSTRUCTION DETAILS FOR WIRELESS SITES" ARE INCLUDED IN AND MADE A PART OF THESE SPECIFICATIONS HEREWITH.

PART 2 - PRODUCTS (NOT USED)
PART 3 - EXECUTION

#### 3.1 RECEIPT OF MATERIAL AND EQUIPMENT:

- A COMPANY FURNISHED MATERIAL AND EQUIPMENT IS IDENTIFIED ON THE RF DATA SHEET IN THE CONSTRUCTION DOCUMENTS.
- B. THE CONTRACTOR IS RESPONSIBLE FOR SPRINT PROVIDED MATERIAL AND EQUIPMENT AND UPON RECEIPT SHALL:
- 1 ACCEPT DELIVERIES AS SHIPPED AND TAKE RECEIPT.
- 2. VERIFY COMPLETENESS AND CONDITION OF ALL DELIVERIES.
- 3. TAKE RESPONSIBILITY FOR EQUIPMENT AND PROVIDE INSURANCE PROTECTION AS REQUIRED IN AGREEMENT.
- RECORD ANY DEFECTS OR DAMAGES AND WITHIN TWENTY—FOUR HOURS AFTER RECEIPT, REPORT TO SPRINT OR ITS DESIGNATED PROJECT REPRESENTATIVE OF SUCH.
- 5. PROVIDE SECURE AND NECESSARY WEATHER PROTECTED WAREHOUSING.
- COORDINATE SAFE AND SECURE TRANSPORTATION OF MATERIAL AND EQUIPMENT, DELIVERING AND OFF-LOADING FROM CONTRACTOR'S WAREHOUSE TO SITE.

#### 3.2 DELIVERABLES:

- A. COMPLETE SHIPPING AND RECEIPT DOCUMENTATION IN ACCORDANCE WITH COMPANY PRACTICE.
- B. IF APPLICABLE, COMPLETE LOST/STOLEN/DAMAGED DOCUMENTATION REPORT AS NECESSARY IN ACCORDANCE WITH COMPANY PRACTICE, AND AS DIRECTED BY COMPANY.
- C. UPLOAD DOCUMENTATION INTO SPRINT SITE MANAGEMENT SYSTEM (SMS) AND/OR PROVIDE HARD COPY DOCUMENTATION AS REQUESTED.

# SECTION 01 300 - CELL SITE CONSTRUCTION CO. PART 1 - GENERAL

1.1 THE WORK: THESE STANDARD CONSTRUCTION SPECIFICATIONS IN CONJUNCTION WITH THE OTHER CONTRACT DOCUMENTS AND THE CONSTRUCTION DRAWINGS DESCRIBE THE WORK TO BE PERFORMED BY THE CONTRACTOR.

#### 1.2 RELATED DOCUMENTS:

- A. THE REQUIREMENTS OF THIS SECTION APPLY TO ALL SECTIONS IN THIS SPECIFICATION.
- B. SPRINT "STANDARD CONSTRUCTION DETAILS FOR WIRELESS SITES" ARE INCLUDED IN AND MADE A PART OF THESE SPECIFICATIONS HEREWITH.

#### 1.3 NOTICE TO PROCEED

- A. NO WORK SHALL COMMENCE PRIOR TO COMPANY'S WRITTEN NOTICE TO PROCEED AND THE ISSUANCE OF THE WORK ORDER.
- B. UPON RECEIVING NOTICE TO PROCEED, CONTRACTOR SHALL FULLY PERFORM ALL WORK NECESSARY TO PROVIDE SPRINT WITH AN OPERATIONAL WIRELESS FACILITY.

PART 2 - PRODUCTS (NOT USED)
PART 3 - EXECUTION

#### 3.1 FUNCTIONAL REQUIREMENTS:

- A. THE ACTIVITIES DESCRIBED IN THIS PARAGRAPH REPRESENT MINIMUM ACTIONS AND PROCESSES REQUIRED TO SUCCESSFULLY COMPLETE THE WORK. THE ACTIVITIES DESCRIBED ARE NOT EXHAUSTIVE, AND CONTRACTOR SHALL TAKE ANY AND ALL ACTIONS AS NECESSARY TO SUCCESSFULLY COMPLETE THE CONSTRUCTION OF A FULLY FUNCTIONING WIRELESS FACILITY AT THE SITE IN ACCORDANCE WITH COMPANY PROCESSES.
- B. SUBMIT SPECIFIC DOCUMENTATION AS INDICATED HEREIN, AND OBTAIN REQUIRED APPROVALS WHILE THE WORK IS BEING PERFORMED.
- C. MANAGE AND CONDUCT ALL FIELD CONSTRUCTION SERVICE RELATED ACTIVITIES
- D. PROVIDE CONSTRUCTION ACTIVITIES TO THE EXTENT REQUIRED BY THE CONTRACT DOCUMENTS, INCLUDING BUT NOT LIMITED TO THE FOLLOWING:

Spr

LANS PREPARED FOR:



PLANS PREPARED BY:

INFINITY

FROM ZERO TO INFINITY

the solutions are endiess

D33 Watervilet Shaker Rd | Albany, NY 1220 Phone: 518-690-0790 | Fax: 518-690-0793 www.loffinlgy.com JOB NUMBER 526-104

AIROSMITH DEVELOPMENT

32 CLINTON ST

SARATOGA SPRINGS, NY 12866 OFFICE#. (518) 306-3740



- DRAWING NOTICE:

THESE DOCUMENTS ARE CONFIDENTIAL AND ARE
THE SOLE PROPERTY OF SPRINT AND MAY NOT BE
REPRODUCED, DISSEMINATED OR REDISTRIBUTED
WITHOUT THE EXPRESS WRITTEN CONSENT OF
SPRINT.

REVISIONS:			
DESCRIPTION	DATE	BY	REV
		$\vdash$	H
ISSUED FOR REVIEW	01/25/18	SKB	0

SITE NAME: -

N. MADISON/ VOL. FIRE DEPT.

SITE NUMBER

CT03XC164

SITE ADDRESS

864 OPENING HILL RD. MADISON, CT 06443

SHEET DESCRIPTION: -

SPRINT SPECIFICATIONS

MERRO ....

SP-1

#### CONTINUE FROM SP-1

- 1. PERFORM ANY REQUIRED SITE ENVIRONMENTAL MITIGATION.
- PREPARE GROUND SITES; PROVIDE DE—GRUBBING; AND ROUGH AND FINAL GRADING, AND COMPOUND SURFACE TREATMENTS.
- MANAGE AND CONDUCT ALL ACTIVITIES FOR INSTALLATION OF UTILITIES INCLUDING ELECTRICAL AND TELCO BACKHAUL.
- 4. INSTALL UNDERGROUND FACILITIES INCLUDING UNDERGROUND POWER AND COMMUNICATIONS CONDUITS, AND UNDERGROUND GROUNDING SYSTEM.
- 5. INSTALL ABOVE GROUND GROUNDING SYSTEMS.
- 6. PROVIDE NEW HVAC INSTALLATIONS AND MODIFICATIONS.
- 7. INSTALL "H-FRAMES", CABINETS AND SHELTERS AS INDICATED.
- 8. INSTALL ROADS, ACCESS WAYS, CURBS AND DRAINS AS INDICATED.
- 9. ACCOMPLISH REQUIRED MODIFICATION OF EXISTING FACILITIES.
- 10. PROVIDE ANTENNA SUPPORT STRUCTURE FOUNDATIONS.
- 11. PROVIDE SLABS AND EQUIPMENT PLATFORMS.
- INSTALL COMPOUND FENCING, SIGHT SHIELDING, LANDSCAPING AND ACCESS BARRIERS.
- 13. PERFORM INSPECTION AND MATERIAL TESTING AS REQUIRED HEREINAFTER.
- 14. CONDUCT SITE RESISTANCE TO EARTH TESTING AS REQUIRED HEREINAFTER
- 15. INSTALL FIXED GENERATOR SETS AND OTHER STANDBY POWER SOLUTIONS.
- 16. INSTALL TOWERS, ANTENNA SUPPORT STRUCTURES AND PLATFORMS ON EXISTING TOWERS AS REQUIRED.
- 17. INSTALL CELL SITE RADIOS, MICROWAVE, GPS, COAXIAL MAINLINE, ANTENNAS, CROSS BAND COUPLERS, TOWER TOP AMPLIFIERS, LOW NOISE AMPLIFIERS AND RELATED EQUIPMENT.
- PERFORM, DOCUMENT, AND CLOSE OUT ANY CONSTRUCTION CONTROL DOCUMENTS THAT MAY BE REQUIRED BY GOVERNMENT AGENCIES AND LANDLORDS.
- PERFORM ANTENNAL AND COAX SWEEP TESTING AND MAKE ANY AND ALL NECESSARY CORRECTIONS.
- 20. REMAIN ON SITE MOBILIZED THROUGHOUT HAND-OFF AND INTEGRATION TO ASSIST AS NEEDED UNTIL SITE IS DEEMED SUBSTANTIALLY COMPLETE AND PLACED "ON AIR."

#### 3.2 GENERAL REQUIREMENTS FOR CIVIL CONSTRUCTION:

- A. CONTRACTOR SHALL KEEP THE SITE FREE FROM ACCUMULATING WASTE MATERIAL, DEBRIS, AND TRASH. AT THE COMPLETION OF THE WORK, CONTRACTOR SHALL REMOVE FROM THE SITE ALL REMAINING RUBBISH, IMPLEMENTS, TEMPORARY FACILITIES, AND SURPLUS MATERIALS.
- B. EQUIPMENT ROOMS SHALL AT ALL TIMES BE MAINTAINED "BROOM CLEAN" AND CLEAR OF DEBRIS.
- C. CONTRACTOR SHALL TAKE ALL REASONABLE PRECAUTIONS TO DISCOVER AND LOCATE ANY HAZARDOUS CONDITION.
- 1. IN THE EVENT CONTRACTOR ENCOUNTERS ANY HAZARDOUS CONDITION WHICH HAS NOT BEEN ABATED OR OTHERWISE MITIGATED, CONTRACTOR AND ALL OTHER PERSONS SHALL IMMEDIATELY STOP WORK IN THE AFFECTED AREA AND NOTIFY COMPANY IN WRITING. THE WORK IN THE AFFECTED AREA SHALL NOT BE RESUMED EXCEPT BY WRITTEN NOTIFICATION BY COMPANY.
- CONTRACTOR AGREES TO USE CARE WHILE ON THE SITE AND SHALL NOT TAKE ANY ACTION THAT WILL OR MAY RESULT IN OR CAUSE THE HAZARDOUS CONDITION TO BE FURTHER RELEASED IN THE ENVIRONMENT, OR TO FURTHER EXPOSE INDIMIDUALS TO THE HAZARD.
- D. CONTRACTOR'S ACTIVITIES SHALL BE RESTRICTED TO THE PROJECT LIMITS. SHOULD AREAS OUTSIDE THE PROJECT LIMITS BE AFFECTED BY CONTRACTOR'S ACTIVITIES, CONTRACTOR SHALL IMMEDIATELY RETURN THEM TO ORIGINAL CONDITION
- E. CONDUCT TESTING AS REQUIRED HEREIN.

#### 3.3 DELIVERABLES:

- A. CONTRACTOR SHALL REVIEW, APPROVE, AND SUBMIT TO SPRINT SHOP DRAWINGS, PRODUCT DATA, SAMPLES, AND SIMILAR SUBMITTALS AS REQUIRED HEREINAFTER
- B. PROVIDE DOCUMENTATION INCLUDING, BUT NOT LIMITED TO, THE FOLLOWING, DOCUMENTATION SHALL BE FORWARDED IN ORIGINAL FORMAT AND/OR UPLOADED INTO SMS.
- 1. ALL CORRESPONDENCE AND PRELIMINARY CONSTRUCTION REPORTS.
- 2. PROJECT PROGRESS REPORTS.
- CML CONSTRUCTION START DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- ELECTRICAL SERVICE COMPLETION DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).

- LINES AND ANTENNA INSTALL DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- POWER INSTALL DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- TELCO READY DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- PPC (OR SHELTER) INSTALL DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- TOWER CONSTRUCTION START DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- TOWER CONSTRUCTION COMPLETE DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- BTS AND RADIO EQUIPMENT DELIVERED AT SITE DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- 12. NETWORK OPERATIONS HANDOFF CHECKLIST (HOC WALK) COMPLETE (UPLOAD FORM IN SMS)
- CIVIL CONSTRUCTION COMPLETE DATE (POPULATE FIELD IN SMS AND/OR FORWARD NOTIFICATION).
- 14. SITE CONSTRUCTION PROGRESS PHOTOS UNLOADED INTO SMS.

## SECTION 01 400 - SUBMITTALS & TESTS

#### PART 1 - GENERAL

1.1 THE WORK: THESE STANDARD CONSTRUCTION SPECIFICATIONS IN CONJUNCTION WITH THE OTHER CONTRACT DOCUMENTS AND THE CONSTRUCTION DRAWINGS DESCRIBE THE WORK TO BE PERFORMED BY THE CONTRACTOR.

#### 1.2 RELATED DOCUMENTS:

- A. THE REQUIREMENTS OF THIS SECTION APPLY TO ALL SECTIONS IN THIS SPECIFICATION.
- B. SPRINT "STANDARD CONSTRUCTION DETAILS FOR WIRELESS SITES" ARE INCLUDED IN AND MADE A PART OF THESE SPECIFICATIONS HEREWITH.

#### 1.3 SUBMITTALS:

- A. THE WORK IN ALL ASPECTS SHALL COMPLY WITH THE CONSTRUCTION DRAWINGS AND THESE SPECIFICATIONS.
- B. SUBMIT THE FOLLOWING TO COMPANY REPRESENTATIVE FOR APPROVAL.
  - CONCRETE MIX—DESIGNS FOR TOWER FOUNDATIONS, ANCHORS PIERS, AND CONCRETE PAVING.
  - 2. CONCRETE BREAK TESTS AS SPECIFIED HEREIN.
  - SPECIAL FINISHES FOR INTERIOR SPACES, IF ANY.
  - ALL EQUIPMENT AND MATERIALS SO IDENTIFIED ON THE CONSTRUCTION DRAWINGS.
  - 5. CHEMICAL GROUNDING DESIGN
- D. ALTERNATES: AT THE COMPANY'S REQUEST, ANY ALTERNATIVES TO THE MATERIALS OR METHODS SPECIFIED SHALL BE SUBMITTED TO SPRINT'S CONSTRUCTION MANAGER FOR APPROVAL PRIOR TO BEING SHIPPED TO SITE. SPRINT WILL REVIEW AND APPROVE ONLY THOSE REQUESTS MADE IN WRITING. NO VERBAL APPROVALS WILL BE CONSIDERED. SUBMITTAL FOR APPROVAL SHALL INCLUDE A STATEMENT OF COST REDUCTION PROPOSED FOR USE OF ALTERNATE PRODUCT.

#### 1.4 TESTS AND INSPECTIONS:

- A. THE CONTRACTOR SHALL BE RESPONSIBLE FOR ALL CONSTRUCTION TESTS, INSPECTIONS AND PROJECT DOCUMENTATION.
- B. CONTRACTOR SHALL ACCOMPLISH TESTING INCLUDING BUT NOT LIMITED TO THE FOLLOWING:
- COAX SWEEPS AND FIBER TESTS PER TS-0200 REV 4 ANTENNA LINE ACCEPTANCE STANDARDS.
- 2. AGL, AZIMUTH AND DOWNTILT USING ELECTRONIC COMMERCIAL MADE-FOR-THE-PURPOSE ANTENNA ALIGNMENT TOOL.
- CONTRACTOR SHALL BE RESPONSIBLE FOR ANY AND ALL CORRECTIONS TO ANY WORK IDENTIFIED AS UNACCEPTABLE IN SITE INSPECTION ACTIVITIES AND/OR AS A RESULT OF TESTING.
- C. REQUIRED CLOSEOUT DOCUMENTATION INCLUDES, BUT IS NOT LIMITED TO THE FOLLOWING;
- AZIMUTH, DOWNTILT, AGL UPLOAD REPORT FROM ANTENNA ALIGNMENT TOOL TO SITERRA TASK 485. INSTALLED AZIMUTH, DOWNTILT, AND AGL MUST CONFORM TO THE RF DATA SHEETS. SWEEP AND FIBER TESTS
- SCANABLE BARCODE PHOTOGRAPHS OF TOWER TOP AND INACCESSIBLE SERIALIZED EQUIPMENT
- 3. ALL AVAILABLE JURISDICTIONAL INFORMATION
- 4. PDF SCAN OF REDLINES PRODUCED IN FIELD

5. ELECTRONIC AS—BUILT DRAWINGS IN AUTOCAD AND PDF FORMATS. ANY FIELD CHANGE MUST BE REFLECTED BY MODIFYING THE PLANS, ELEVATIONS, AND DETAILS IN THE DRAWING SETS. GENERAL NOTES INDICATING MODIFICATIONS WILL NOT BE ACCEPTED. CHANGES SHALL BE HIGHLIGHTED AS "CLOUDS" IDENTIFIED AS THE "AS—BUILT" CONDITION.

- 6. LIEN WAIVERS
- 7. FINAL PAYMENT APPLICATION
- 8. REQUIRED FINAL CONSTRUCTION PHOTOS
- 9 . CONSTRUCTION AND COMMISSIONING CHECKLIST COMPLETE WITH NO DEFICIENT ITEMS
- ALL POST NTP TASKS INCLUDING DOCUMENT UPLOADS COMPLETED IN SITERRA (SPRINTS DOCUMENT REPOSITORY OF RECORD).
- 1.5 COMMISSIONING: PERFORM ALL COMMISSIONING AS REQUIRED BY APPLICABLE MOPS
- 1.6 INTEGRATION: PERFORM ALL INTEGRATION ACTIVITIES AS REQUIRED BY APPLICABLE MOPS

PART 2 - PRODUCTS (NOT USED)

PART 3 - EXECUTION

- 3.1 REQUIREMENTS FOR TESTING:
- A. THIRD PARTY TESTING AGENCY:
- WHEN THE USE OF A THIRD PARTY INDEPENDENT TESTING AGENCY IS REQUIRED, THE AGENCY THAT IS SELECTED MUST PERFORM SUCH WORK ON A REGULAR BASIS IN THE STATE WHERE THE PROJECT IS LOCATED AND HAVE A THOROUGH UNDERSTANDING OF LOCAL AVAILABLE MATERIALS, INCLUDING THE SOIL, ROCK, AND GROUNDWATER CONDITIONS.
- THE THIRD PARTY TESTING AGENCY IS TO BE FAMILIAR WITH THE APPLICABLE REQUIREMENTS FOR THE TESTS TO BE DONE, EQUIPMENT TO BE USED, AND ASSOCIATED HEALTH AND SAFETY ISSUES.
- 3. EXPERIENCE IN SOILS, CONCRETE, MASONRY, AGGREGATE, AND ASPHALT TESTING USING ASTM, AASJTO, AND OTHER METHODS IS NEEDED.
- 4. EXPERIENCE IN SOILS, CONCRETE, MASONRY, AGGREGATE, AND ASPHALT TESTING USING ASTM, AASJTO, AND OTHER METHODS IS NEEDED.

#### 3.2 REQUIRED TESTS:

- A. CONTRACTOR SHALL ACCOMPLISH TESTING INCLUDING BUT NOT LIMITED TO THE FOLLOWING:
- CONCRETE CYLINDER BREAK TESTS FOR THE TOWER AND ANCHOR FOUNDATIONS AS SPECIFIED IN SECTION: PORTLAND CEMENT CONCRETE PAVING.
- ASPHALT ROADWAY COMPACTED THICKNESS, SURFACE SMOOTHNESS, AND COMPACTED DENSITY TESTING AS SPECIFIED IN SECTION: HOT MIX ASPHALT PAVING.
- FIELD QUALITY CONTROL TESTING AS SPECIFIED IN SECTION: PORTLAND CEMENT CONCRETE PAYING.
- TESTING REQUIRED UNDER SECTION: AGGREGATE BASE FOR ACCESS ROADS, PADS AND ANCHOR LOCATIONS
- 5. STRUCTURAL BACKFILL COMPACTION TESTS FOR THE TOWER FOUNDATION.
- 6. SITE RESISTANCE TO EARTH TESTING PER EXHIBIT: CELL SITE GROUNDING SYSTEM DESIGN.
- ANTENNA AND COAX SWEEP TESTS PER EXHIBIT: ANTENNA TRANSMISSION LINE ACCEPTANCE STANDARDS.
- 8. GROUNDING AT ANTENNA MASTS FOR GPS AND ANTENNAS
- 9. ALL OTHER TESTS REQUIRED BY COMPANY OR JURISDICTION.

#### 3.3 REQUIRED INSPECTIONS

- A. SCHEDULE INSPECTIONS WITH COMPANY REPRESENTATIVE.
- B. CONDUCT INSPECTIONS INCLUDING BUT NOT LIMITED TO THE FOLLOWING:
- GROUNDING SYSTEM INSTALLATION PRIOR TO EARTH CONCEALMENT DOCUMENTED WITH DIGITAL PHOTOGRAPHS BY CONTRACTOR, APPROVED BY A&E OR SPRINT REPRESENTATIVE.
- FORMING FOR CONCRETE AND REBAR PLACEMENT PRIOR TO POUR DOCUMENTED WITH DIGITAL PHOTOGRAPHS BY CONTRACTOR, APPROVED BY A&E OR SPRINT REPRESENTATIVE.
- COMPACTION OF BACKFILL MATERIALS; AGGREGATE BASE FOR ROADS, PADS, AND ANCHORS; ASPHALT PAVING; AND SHAFT BACKFILL FOR CONCRETE AND WOOD POLES, BY INDEPENDENT THIRD PARTY AGENCY.
- 4. PRE— AND POST—CONSTRUCTION ROOFTOP AND STRUCTURAL INSPECTIONS ON EXISTING FACILITIES.
- 5. TOWER ERECTION SECTION STACKING AND PLATFORM ATTACHMENT DOCUMENTED BY DIGITAL PHOTOGRAPHS BY THIRD PARTY AGENCY.
- ANTENNA AZIMUTH, DOWN TILT AND PER SUNLIGHT TOOL SUNSIGHT INSTRUMENTS — ANTENNALIGN ALIGNMENT TOOL (AAT)

Sprint

PLANS PREPARED FOR: \*

FROM ZERO TO INFINIGY
the solutions are endless

033 Waterviiet Shaker Rd | Albany, NY 1220

Phone: 518-690-0790 | Fax: 518-690-0793

www.Infinigy.com
JOB NUMBER 525-104

PROJECT MANAGER:

32 CLINTON ST. SARATOGA SPRINGS, NY 12866 OFFICE#. (518) 306-3740



P DRAWING NOTICE:

THESE DOCUMENTS ARE CONFIDENTIAL AND ARE THE SOLE PROPERTY OF SPRINT AND MAY NOT BE REPRODUCED, DISSEMINATED OR REDISTRIBUTED WITHOUT THE EXPRESS WRITTEN CONSENT OF SPRINT.

DATE	BY	REV
-		
01/25/18	SKB	0
		DATE BY

SITE NAME:

N. MADISON/ VOL. FIRE DEPT.

CT03XC164

MADISON, CT 06443

- SITE NUMBER: -

864 OPENING HILL RD.

SHEET DESCRIPTION:

- SHEET NUMBER

SPRINT SPECIFICATIONS

OD O

SP-2

#### CONTINUE FROM SP-2

- VERIFICATION DOCUMENTED WITH THE ANTENNA CHECKLIST REPORT, BY A&E, SITE DEVELOPMENT REP, OR RF REP.
- FINAL INSPECTION CHECKLIST AND HANDOFF WALK (HOC.). SIGNED FORM SHOWING ACCEPTANCE BY FIELD OPS IS TO BE UPLOADED INTO SMS.
- 9. COAX SWEEP AND FIBER TESTING DOCUMENTS SUBMITTED VIA SMS FOR RF
- 10. SCAN-ABLE BARCODE PHOTOGRAPHS OF TOWER TOP AND INACCESSIBLE SERIALIZED EQUIPMENT
- 11. ALL AVAILABLE JURISDICTIONAL INFORMATION
- 12. PDF SCAN OF REDLINES PRODUCED IN FIELD
- C. THE CONTRACTOR SHALL BE RESPONSIBLE FOR ANY AND ALL CORRECTIONS TO ANY WORK IDENTIFIED AS UNACCEPTABLE IN SITE INSPECTION ACTIVITIES AND/OR AS A RESULT OF TESTING.
- D. CONSTRUCTION INSPECTIONS AND CORRECTIVE MEASURES SHALL BE DOCUMENTED BY THE CONTRACTOR WITH WRITTEN REPORTS AND PHOTOGRAPHS. PHOTOGRAPHS MUST BE DIGITAL AND OF SUFFICIENT QUALITY TO CLEARLY SHOW THE SITE CONSTRUCTION. PHOTOGRAPHS MUST CLEARLY IDENTIFY THE PHOTOGRAPHED ITEM AND BE LABELED WITH THE SITE CASCADE NUMBER, SITE NAME, DESCRIPTION, AND
- 3.4 DELIVERABLES: TEST AND INSPECTION REPORTS AND CLOSEOUT DOCUMENTATION SHALL BE UPLOADED TO THE SMS AND/OR FORWARDED TO SPRINT FOR INCLUSION INTO THE PERMANENT SITE FILES.
  - A. THE FOLLOWING TEST AND INSPECTION REPORTS SHALL BE PROVIDED AS
  - 1. CONCRETE MIX AND CYLINDER BREAK REPORTS.
  - 2. STRUCTURAL BACKFILL COMPACTION REPORTS.
  - 3. SITE RESISTANCE TO EARTH TEST.
  - 4. ANTENNA AZIMUTH AND DOWN TILT VERIFICATION
  - 5. TOWER ERECTION INSPECTIONS AND MEASUREMENTS DOCUMENTING TOWER INSTALLED PER SUPPLIER'S REQUIREMENTS AND THE APPLICABLE SECTIONS
  - 6. COAX CABLE SWEEP TESTS PER COMPANY'S "ANTENNA LINE ACCEPTANCE STANDARDS"
- REQUIRED CLOSEOUT DOCUMENTATION INCLUDES THE FOLLOWING;
  - TEST WELLS AND TRENCHES: PHOTOGRAPHS OF ALL TEST WELLS; PHOTOGRAPHS SHOWING ALL OPEN EXCAVATIONS AND TRENCHING PRIOR TO BACKFILLING SHOWING A TAPE MEASURE VISIBLE IN THE EXCAVATIONS
- 2. CONDUITS, CONDUCTORS AND GROUNDING: PHOTOGRAPHS SHOWING TYPICAL INSTALLATION OF CONDUCTORS AND CONNECTORS; PHOTOGRAPHS SHOWING TYPICAL BEND RADIUS OF INSTALLED GROUND WIRES AND GROUND ROD
- 3. CONCRETE FORMS AND REINFORCING: CONCRETE FORMING AT TOWER AND EQUIPMENT/SHELTER PAD/FOUNDATIONS — PHOTOGRAPHS SHOWING ALL REINFORCING STEEL, UTILITY AND CONDUIT STUB OUTS: PHOTOGRAPHS SHOWING CONCRETE POUR OF SHELTER SLAB/FOUNDATION, TOWER FOUNDATION AND GUY ANCHORS WITH VIBRATOR IN USE; PHOTOGRAPHS SHOWING EACH ANCHOR ON GUYED TOWERS, BEFORE CONCRETE POUR.
- 4. TOWER, ANTENNAS AND MAINLINE: INSPECTION AND PHOTOGRAPHS OF SECTION STACKING; INSPECTION AND PHOTOGRAPHS OF PLATFORM COMPONENT ATTACHMENT POINTS; PHOTOGRAPHS OF TOWER TOP GROUNDING; PHOTOS OF TOWER COAX LINE COLOR CODING AT THE TOP AND AT GROUND LEVEL; INSPECTION AND PHOTOGRAPHS OF OPERATIONAL OF TOWER LIGHTING, AND PLACEMENT OF FAA REGISTRATION SIGN; PHOTOGRAPHS SHOWING ADDITIONAL GROUNDING POINTS FOR TOWERS GREATER THAN 200 FEET.; PHOTOS OF GROUNDING POINTS FOR TOWERS GREATER THAN 200 FEET.; PHOTOS OF ANTENNA GROUND BAR, EQUIPMENT GROUND BAR, AND MASTER GROUND BAR; PHOTOS OF GPS ANTENNA(S); PHOTOS OF EACH SECTOR OF ANTENNAS; ONE PHOTOGRAPH LOOKING AT THE SECTOR AND ONE FROM BEHIND SHOWING THE PROJECTED COVERAGE AREA; PHOTOS OF COAX WEATHERPROOFING — TOP AND BOTTOM; PHOTOS OF COAX GROUNDING—TOP AND BOTTOM; PHOTOS OF COAX GROUNDING; PHOTOS OF COAX CABLE ENTRY INTO SHELTER; PHOTOS OF PLATFORM MECHANICAL CONNECTIONS TO TOWER/MONOPOLE.
- 5. ROOF TOPS: PRE-CONSTRUCTION AND POST-CONSTRUCTION VISUAL INSPECTION AND PHOTOGRAPHS OF THE ROOF AND INTERIOR TO DETERMINE AND DOCUMENT CONDITIONS; ROOF TOP CONSTRUCTION INSPECTIONS AS REQUIRED BY THE JURISDICTION; PHOTOGRAPHS OF CABLE TRAY AND/OR ICE BRIDGE; PHOTOGRAPHS OF DOGHOUSE/CABLE EXIT FROM ROOF;
- SITE LAYOUT PHOTOGRAPHS OF THE OVERALL COMPOUND, INCLUDING EQUIPMENT PLATFORM FROM ALL FOUR CORNERS.
- 7. FINISHED UTILITIES: CLOSE-UP PHOTOGRAPHS OF THE PPC BREAKER PANEL: CLOSE-UP PHOTOGRAPH OF THE INSIDE OF THE TELCO PANEL AND NIU; CLOSE-UP PHOTOGRAPH OF THE POWER METER AND DISCONNECT; PHOTOS OF POWER AND TELCO ENTRANCE TO COMPANY ENCLOSURE; PHOTOGRAPHS AT METER BOX AND/OR FACILITY DISTRIBUTION PANEL
- 8. REQUIRED MATERIALS CERTIFICATIONS: CONCRETE MIX DESIGNS: MILL CERTIFICATION FOR ALL REINFORCING AND STRUCTURAL STEEL; AND ASPHALT PAVING MIX DESIGN.
- 9. ANY AND ALL SUBMITTALS BY THE JURISDICTION OR COMPANY.

## SECTION 01 400 - SUBMITTALS & TESTS

#### PART 1 - GENERAL

1.1 THE WORK: THESE STANDARD CONSTRUCTION SPECIFICATIONS IN CONJUNCTION WITH THE OTHER CONTRACT DOCUMENTS AND THE CONSTRUCTION DRAWINGS DESCRIBE THE WORK TO BE PERFORMED BY THE CONTRACTOR.

#### 1.2 RELATED DOCUMENTS:

- A. THE REQUIREMENTS OF THIS SECTION APPLY TO ALL SECTIONS IN THIS
- B. SPRINT "STANDARD CONSTRUCTION DETAILS FOR WIRELESS SITES" ARE INCLUDED IN AND MADE A PART OF THESE SPECIFICATIONS HEREWITH.

#### PART 2 - PRODUCTS (NOT USED)

#### PART 3 - EXECUTION

#### 3.1 WEEKLY REPORTS:

- CONTRACTOR SHALL PROVIDE SPRINT WITH WEEKLY REPORTS SHOWING PROJECT STATUS. THIS STATUS REPORT FORMAT WILL BE PROVIDED TO THE CONTRACTOR BY SPRINT. THE REPORT WILL CONTAIN SITE ID NUMBER, THE MILESTONES FOR EACH SITE, INCLUDING THE BASELINE DATE, ESTIMATED COMPLETION DATE AND ACTUAL
- B. REPORT INFORMATION WILL BE TRANSMITTED TO SPRINT VIA ELECTRONIC MEANS AS REQUIRED, THIS INFORMATION WILL PROVIDE A BASIS FOR PROGRESS MONITORING

#### 3.2 PROJECT CONFERENCE CALLS:

A. SPRINT MAY HOLD WEEKLY PROJECT CONFERENCE CALLS. CONTRACTOR WILL BE REQUIRED TO COMMUNICATE SITE STATUS, MILESTONE COMPLETIONS AND UPCOMING MILESTONE PROJECTIONS, AND ANSWER ANY OTHER SITE STATUS QUESTIONS AS

#### 3.3 PROJECT TRACKING IN SMS:

A. CONTRACTOR SHALL PROVIDE SCHEDULE UPDATES AND PROJECTIONS IN THE SMS SYSTEM ON A WEEKLY BASIS.

#### 3.4 ADDITIONAL REPORTING:

A. ADDITIONAL OR ALTERNATE REPORTING REQUIREMENTS MAY BE ADDED TO THE REPORT AS DETERMINED TO BE REASONABLY NECESSARY BY COMPANY.

#### 3.5 PROJECT PHOTOGRAPHS:

- A. FILE DIGITAL PHOTOGRAPHS OF COMPLETED SITE IN JPEG FORMAT IN THE SMS PHOTO LIBRARY FOR THE RESPECTIVE SITE. PHOTOGRAPHS SHALL BE CLEARLY LABELED WITH SITE NUMBER, NAME AND DESCRIPTION, AND SHALL INCLUDE AT A MINIMUM THE FOLLOWING AS APPLICABLE:
- 1. 1SHELTER AND TOWER OVERVIEW.
- 2. TOWER FOUNDATION(S) FORMS AND STEEL BEFORE POUR (EACH ANCHOR ON GUYED TOWERS).
- 3. TOWER FOUNDATION(S) POUR WITH VIBRATOR IN USE (EACH ANCHOR ON GUYED TOWERS).
- 4. TOWER STEEL AS BEING INSTALLED INTO HOLE (SHOW ANCHOR STEEL ON GUYED TOWERS).
- 5. PHOTOS OF TOWER SECTION STACKING.
- 6. CONCRETE TESTING / SAMPLES.
- 7. PLACING OF ANCHOR BOLTS IN TOWER FOUNDATION.
- 8. BUILDING/WATER TANK FROM ROAD FOR TENANT IMPROVEMENTS OR COMMENTS.
- 9. SHELTER FOUNDATION -- FORMS AND STEEL BEFORE POURING.
- 10. SHELTER FOUNDATION POUR WITH VIBRATOR IN USE.
- 11. COAX CABLE ENTRY INTO SHELTER
- 12. PLATFORM MECHANICAL CONNECTIONS TO TOWER/MONOPOLE.
- 13. ROOFTOP PRE AND POST CONSTRUCTION PHOTOS TO INCLUDE PENETRATIONS AND INTERIOR CEILING.
- 14. PHOTOS OF TOWER TOP COAX LINE COLOR CODING AND COLOR CODING AT
- 15. PHOTOS OF ALL APPROPRIATE COMPANY OR REGULATORY SIGNAGE.
- 16. PHOTOS OF EQUIPMENT BOLT DOWN INSIDE SHELTER.
- 17. POWER AND TELCO ENTRANCE TO COMPANY ENCLOSURE AND POWER AND TELCO SUPPLY LOCATIONS INCLUDING METER/DISCONNECT.
- 18. ELECTRICAL TRENCH(S) WITH ELECTRICAL / CONDUIT BEFORE BACKFILL.
- 19. ELECTRICAL TRENCH(S) WITH FOIL-BACKED TAPE BEFORE FURTHER BACKFILL.
- 20. TELCO TRENCH WITH TELEPHONE / CONDUIT BEFORE BACKFILL
- 21. TELCO TRENCH WITH FOIL-BACKED TAPE BEFORE FURTHER BACKFILL.
- 22. SHELTER GROUND-RING TRENCH WITH GROUND-WIRE BEFORE BACKFILL (SHOW ALL CAD WELDS AND BEND RADII).
- 23. TOWER GROUND-RING TRENCH WITH GROUND-WIRE BEFORE BACKFILL (SHOW ALL CAD WELDS AND BEND RADII).

- 24. FENCE GROUND-RING TRENCH WITH GROUND-WIRE BEFORE BACKFILL (SHOW ALL CAD WELDS AND BEND RADII).
- 25. ALL BTS GROUND CONNECTIONS.
- 26. ALL GROUND TEST WELLS.
- 27. ANTENNA GROUND BAR AND EQUIPMENT GROUND BAR.
- 28. ADDITIONAL GROUNDING POINTS ON TOWERS ABOVE 200'.
- 29. HVAC UNITS INCLUDING CONDENSERS ON SPLIT SYSTEMS.
- 30. GPS ANTENNAS
- 31. CABLE TRAY AND/OR WAVEGUIDE BRIDGE.
- 32. DOGHOUSE/CABLE EXIT FROM ROOF.
- 33. EACH SECTOR OF ANTENNAS; ONE PHOTOGRAPH LOOKING AT THE SECTOR AND ONE FROM BEHIND SHOWING THE PROJECTED COVERAGE AREA.
- 34. MASTER BUS BAR,
- 35. TELCO BOARD AND NIU.
- 36. ELECTRICAL DISTRIBUTION WALL.
- 37. CABLE ENTRY WITH SURGE SUPPRESSION.
- 38. ENTRANCE TO EQUIPMENT ROOM.
- 39. COAX WEATHERPROOFING-TOP AND BOTTOM OF TOWER.
- 40. COAX GROUNDING -TOP AND BOTTOM OF TOWER.
- 41. ANTENNA AND MAST GROUNDING.
- 42. LANDSCAPING WHERE APPLICABLE.
- 3.6 FINAL PROJECT ACCEPTANCE: COMPLETE ALL REQUIRED REPORTING TASKS PER CONTRACT, CONTRACT DOCUMENTS OR THE SPRINT INTEGRATED CONSTRUCTION STANDARDS FOR WIRELESS SITES AND UPLOAD INTO SITERRA.

LANS PREPARED FOR:



the solutions are endless 033 Watervilet Shaker Rd | Albany, NY 1220

Phone: 518-690-0790 | Fax: 518-690-0793 www.lnfinigy.com



- ENGINEERING LICENSE: HINE CONNE OF CONNEC

THESE DOCUMENTS ARE CONFIDENTIAL AND ARE THE SOLE PROPERTY OF SPRINT AND MAY NOT BE

REPRODUCED, DISSEMINATED OR REDISTRIBUTED WITHOUT THE EXPRESS WRITTEN CONSENT OF

DESCRIPTION	DATE	BY	REV.
		H	
ISSUED FOR REVIEW	01/25/18	SKB	0

N. MADISON/ VOL. FIRE DEPT.

CT03XC164


864 OPENING HILL RD. MADISON, CT 06443


SHEET DESCRIPTION: =

SPRINT SPECIFICATIONS

SHEET NUMBER

SP-3





**TOWER ELEVATION** 

				SITE	LO/	4 <i>DING</i>	CHART			
SECTOR	EXISTING/ PROPOSED	ANTENNA MODEL #	VENDOR	AZIMUTH	QTY.	REMAIN/ REMOVED	RRH (QTY/MODEL)	CABLE	CABLE LENGTH	RAD
	PROPOSED	APXVTM14-ALU-I20	KMW	290°	1	-	(1) 800 MHZ 2X50W RRH W/ FILTER	SEE SHEET A-5 DETAIL 1		
ALPHA	EXISTING	APXVSPP18-C-A20	RPS	290°	1	REMAIN		EXISTING HYBRID		±150' AG
						775	(1) 1900 MHz 4X45 RRH		1	
	PROPOSED	APXVTM14-ALU-I20	KMW	10°	1	-	(1) 800 MHZ 2X50W RRH W/ FILTER	SEE SHEET A-5 DETAIL 1		
BETA	EXISTING	APXVSPP18-C-A20	RPS	10°	1	REMAIN	141	EXISTING HYBRID	±190'*	±150' AG
	-		is <del>aa</del>				(1) 1900 MHz 4X45 RRH		1 !	
	PROPOSED	APXVTM14-ALU-120	KMW	170	1	_	(1) 800 MHZ 2X50W RRH W/ FILTER	SEE SHEET A-5 DETAIL 1	1	
GAMMA	EXISTING	APXVSPP18-C-A20	RPS	170*	1	REMAIN		EXISTING HYBRID		±150' AG
						1	(1) 1900 MHz 4X45 RRH		( I	

PROPOSED CABLE LENGTH WAS DETERMINED USING THE SUM OF THE RAD CENTER OF ANTENNAS, AND DISTANCE FROM EXISTING EQUIPMENT AREA TO TOWER BASE WITH AN ADDITIONAL 20' BUFFER, LENGTH TO BE VERIFIED IN FIELD PRIOR TO ORDERING MATERIALS.

SITE LOADING CHART

**DETAIL NOT USED** 

INSTALL: (3) PANEL ANTENNAS AND (3) RRH'S

NO SCALE

NO SCALE

Sprint 🎾

PLANS PREPARED FOR:

PLANS PREPARED BY: -

INFINIGY& FROM ZERO TO INFINIGY

the solutions are endiess

1033 Waterviiet Shaker Rd | Albany, NY 12205
Phone: 518-690-0790 | Fax: 518-690-0793
www.infinigy.com
408 NUMBER 526-104

JECT MANAGER:



32 CLINTON ST. SARATOGA SPRINGS, NY 12868 OFFICE#. (518) 308-3740

COMPAND AND THE PROPERTY OF TH

- DRAWING NOTICE: -

THESE DOCUMENTS ARE CONFIDENTIAL AND ARE THE SOLE PROPERTY OF SPRINT AND MAY NOT BE REPRODUCED, DISSEMINATED OR REDISTRIBUTED WITHOUT THE EXPRESS WRITTEN CONSENT OF SPRINT.

DESCRIPTION	DATE	BY	REV.
ISSUED FOR REVIEW	01/25/18	SKB	0

SITE NAME:

N. MADISON/ VOL. FIRE DEPT.

SITE NUMBER: -

CT03XC164

SITE ADDRESS:

864 OPENING HILL RD. MADISON, CT 06443

SHEET DESCRIPTION: -

TOWER ELEVATION


SHEET NUMBER:


A-2


O MHz ER LEG DR OO MHz R LEG DR		


GROUND LEVEL

NO SCALE











RRH Per HYBRIFLEX Jumpers Sector 6 pr MM Fiber Power from existing Network Vision HYBRIFLEX Medusa with outdoor rated terminations HYBRIFLEX Riser Per Site 18 pr MM Fiber RFS 2500MHz ALU SCENARIO 1

ALU 2500MHz ALU SCENARIO 1






PLANS PREPARED FOR:

FROM ZERO TO INFINIGY the solutions are endless

1033 Watervilet Shaker Rd | Albany, NY 12205 Phone: 518-690-0790 | Fax: 518-690-0793 www.infinigy.com JOB NUMBER 528-104

32 CLINTON ST. SARATOGA SPRINGS, NY 12866 OFFICE#. (518) 306-3740



THESE DOCUMENTS ARE CONFIDENTIAL AND ARE THE SOLE PROPERTY OF SPRINT AND MAY NOT BE REPRODUCED, DISSEMINATED OR REDISTRIBUTED WITHOUT THE EXPRESS WRITTEN CONSENT OF SPRINT.

DESCRIPTION	DATE	BY	REV	
ISSUED FOR REVIEW	01/25/18	SKB	0	

N. MADISON/ VOL. FIRE DEPT.

CT03XC164

- SITE ADDRESS: -


864 OPENING HILL RD. MADISON, CT 06443

- SHEET DESCRIPTION: -

PLUMBING DIAGRAM

SHEET NUMBER: -

A-6



**LEGEND:** 

BOND INSTALL ANTENNA TO SECTOR GROUND BAR PER

EXISTING SPRINT TOWER GROUND BAR (CONTRACTOR TO VERIFY)-

> BOND RRH's TO SECTOR BAR PER MANUFACTURER'S SPECIFICATIONS-

> > TYPICAL ANTENNA GROUNDING PLAN

MANUFACTURER'S SPECIFICATIONS-

EXISTING GROUND RING

CADWELD CONNECTION


(EXOTHERMIC WELD) MECHANICAL CONNECTION

CABLE GROUND KIT

2

NO SCALE

GROUND ROD



TYPICAL EQUIPMENT GROUNDING PLAN (ELEVATION)

PLANS PREPARED FOR:

FROM ZERO TO INFINIGY


the solutions are endless

1033 Waterviiet Shaker Rd | Albany, NY 12205 Phone: 518-690-0790 | Fax: 518-690-0793 www.infinigy.com JOB NUMBER 526-104

PROJECT MANAGER:



32 CLINTON ST. SARATOGA SPRINGS, NY 12866 OFFICE#. (518) 306-3740



- DRAWING NOTICE: -

THESE DOCUMENTS ARE CONFIDENTIAL AND ARE
THE SOLE PROPERTY OF SPRINT AND MAY NOT BE
REPRODUCED, DISSEMINATED OR REDISTRIBUTED
WITHOUT THE EXPRESS WRITTEN CONSENT OF

DESCRIPTION	DATE	BY	REV.
ISSUED FOR REVIEW	01/25/18	SKB	0

N. MADISON/ VOL. FIRE DEPT.

- SITE NUMBER: -

CT03XC164

864 OPENING HILL RD. MADISON, CT 06443

- SHEET DESCRIPTION: -

**ELECTRICAL & GROUNDING PLAN** 

3

NO SCALE

E-1

